

POPULAR SCIENCE

FOUNDED MONTHLY 1872

FEBRUARY 1931

25 CENTS

SM

TRACTOR MOTORCYCLE
GOES ANYWHERE *see PAGE 70*

UNCLE SAM EXPOSES FAKE CURES

HOW WILD OIL WELLS
ARE TAMED

OUTDOOR COLD MAY HEAT HOUSES

BUILD AN ICE SCOOTER FOR WINTER
SPORT



EVEREADY PACKAGED ELECTRICITY



LIGHT Little cylinders that carry loads and loads of bright, silvery light. Ready to serve in all emergencies—patterned to fit any make of flashlight. Long-lasting, faithful servants. A long, bright time for a thin bright dime—that's Eveready.

POWER Eveready Dry Cells deliver the goods . . . sparks hot as a streak of lightning . . . sparks with a kick that spurts energy where electrical energy is wanted. For doorbell circuits, buzzers, stationary engines—for reliable, unfailing ignition.

RADIO If you have a battery-operated radio, you need an Eveready Layerbilt. These batteries furnish the purest kind of direct current. Built of flat, laminated cells. (An exclusive Eveready principle.) Last longer—are more economical.



Evereadys are dated—your guarantee of fresh, full-powered batteries.

Manufactured and guaranteed by NATIONAL CARBON COMPANY, INC.

General Offices: New York, N. Y.

UNIT OF UNION CARBIDE AND CARBON CORPORATION



© This seal on an advertisement in POPULAR SCIENCE MONTHLY signifies the approval of the INSTITUTE OF STANDARDS. See page 8.



THE FINAL GUARANTEE OF CADILLAC-LA SALLE EXCELLENCE . . .



Because of the unvarying dependability of Cadillac and La Salle cars, it has been possible to place back of them one of the most unique service programs ever offered to the motoring public. In fact, through the terms of the Cadillac-La Salle Standard Service Contract, your Cadillac dealer will assume complete responsibility for servicing your car for an entire year, or for 12,000 miles of driving—whichever occurs first in point of time.

By the terms of this Contract, the dealer agrees

—for a moderate pre-determined sum—to maintain your car at maximum operating efficiency for the period specified. This agreement covers all lubrication, all oils and greases, periodic inspection, and all necessary adjustments and repairs—including both parts and labor.

And no matter where you purchased your Contract, its full provisions will be carried out by *any* authorized Cadillac-La Salle dealer—giving complete protection *wherever* you drive your car.

The Service Contract, of course, applies only to those who wish to handle their service on this basis. But every purchaser of a new Cadillac or La Salle enjoys the protection of the Cadillac Standard Service Policy—with its many liberal provisions and its exceptional touring benefits.

There could be no finer guarantee of Cadillac-La Salle excellence than this liberal policy—for it is obvious that only a car of the highest quality could be backed by such a definite, all-inclusive Service Contract.

Advantages of Cadillac's Standard Service Contract



- You know, in advance, what your service costs will be for the entire year.
- Because of the careful, periodic inspection given your car, the necessity for major repair operations is forestalled.
- You have the satisfaction of knowing that your car is always at the peak of its operating efficiency—and that you are safeguarding your investment to the fullest possible degree.
- You do not have to explain what you want done when you take your car in for service.
- You save money on your routine service needs—such as adjustments and lubrication.

CADILLAC - LA SALLE

CADILLAC MOTOR CAR COMPANY, Division of General Motors

Detroit, Michigan

Oshawa, Canada

25 Cents a Copy
\$2.50 a Year

POPULAR SCIENCE MONTHLY

381 Fourth Avenue
New York, N. Y.

Table of Contents for February, 1931

LEADING ARTICLES

How Wild Oil Wells Are Tamed	By Jesse F. Gelders	19
Thrilling adventures in capping unruly gushers		
Winter Air May Heat Homes		22
How a special refrigerating plant may be run in reverse		
Car Dial Warns of Deadly Gas	By Alden P. Armagnac	23
Will a new meter end poison peril in cities?		
World's Biggest Airship to Fly in May	By Walter E. Burton	24
Fascinating details of the U. S. Navy's new dirigible		
Uncle Sam Exposes Fake Cures	By Edwin W. Teale	26
How medical quacks prey upon the unwary		
Calls Our Sun Huge Electric Light	By Robert E. Martin	28
Amazing new facts about solar mysteries		
Pernicious Anemia Cure Wins \$10,000 Award		30
An outstanding scientific achievement rewarded		
New Dogs for Frozen North	By James W. Booth	40
How thrilling races produce improved animals for sledges		
Can Men Pilot Rocket Planes at 5,000 Miles an Hour?	By George Lee Dowd, Jr.	42
New facts in the search for the human speed limit		
Ancient Armor Copied for Modern Warriors	By Fairfax Downey	44
Bringing oldtime coats of mail up to date		
Government Tests Roasts	By H. C. Davis	50
How experts are learning to breed cattle for meat		
Mysteries of Oyster's Secret Life Are Solved	By John E. Lodge	52
Probing a bivalve's personal habits for science		
When Airships Were Death Traps	By Captain Horace B. Wild	59
Hairbreadth escapes of an air pioneer		

SPECIAL FEATURES

Cover Design	By Edgar F. Wittmack	4
Financial Page		12
Popular Science Institute Page		14
Our Readers Say—		14
Winners of November "What's Wrong?" Contest		17
Design Your House to Fit Its Site	By W. L. Risley	78
Improved Tools to Make Housework Easy		80
Editorials		82
Radio Programs Now Recorded at Home	By John Carr	83
Old Circuit Comes Back	By Alfred P. Lane	84
Useful Hints for Radio Fans		85
Heat Your Car but Don't Burn It!	By Martin Hann	86
The Home Workshop		87
New Ideas to Help Auto Workers		98

ASTRONOMY

Does the Moon Go Round the Earth?	33
Photos Show Neptune Has Sixteen-Hour Day	52
New Star Found by German Stage Star	52

AUTOMOBILES

Radio Opens Garage Doors	32
Auto Turntable Saves Hacking	32
Valve for Crank Case Easily Drains Oil	33
Front Roller on Truck Prevents Accidents	53
Weather Strips Keep Engine Warm	64
How Cars Kill	64
Shackle Lubricator	66
Hand Painted Figures Now Decorate Autos	70
Loadspeaker in Car Warns Pedestrians	72
Great Highway Bridge Is Speed Demon's Delight	74
Match Scratcher Hooks to Steering Wheel	75

AVIATION

Plane Tests Checked by Instrument on Ground	35
Airplanes of Future May Look like This	35
New Airship Must Lose Tail Swing with Wind	35
Seek Airports in Arctic Ice	36
Raiding Planes in Mimic War Deceived by Army "Ears"	49
Propeller May Lift Plane Straight Up	54
Air Mail to Europe, 1932	54
Adjustable Wing Aids Plane in Landing	54
Open Passenger Line, New York to Chicago	54
Blimp Moored to Mast on Top of Big Bus	54
New Air Mail Flag Soon to Fly at Airports	54
Italian Helicopter Rises, Hovers, Flies	58
Parachute Jumping Now Taught on the Ground	55
Claim Vertical Flight for Box Car Plane	55
Airplane Motors Now Tested on a Truck	55
First Rocket Airdrome Opened near Berlin	56
Mail Now Carried in Airplane's Wings	56
Tailless German Plane Seems to Fly Backward	56
Old Planes Destroyed by Bombs from Air	56

February, 1931, Vol. 114, No. 2. Popular Science Monthly is published monthly at 381 Fourth Avenue, New York, N. Y., by the Popular Science Publishing Co., Inc. Entered as second-class matter Dec. 28, 1928, at the Post Office at New York, N. Y., under the act of March 3, 1879; additional entry as second-class matter at Dallas, Ohio, entered as second-class matter at the Post Office Department, Canada, printed in U. S. A. Copyright, 1930, by the Popular Science Publishing Co., Inc. Single copy, 25 cents. Nine months' subscription, \$2. Yearly subscriptions to United States, its possessions, and Canada, \$2.50; foreign countries, \$3. The contents of this mag-

azine must not be reprinted without permission. The editors are not responsible for unsolicited contributions, and cannot guarantee the return of such material or insure against its loss. In presenting numerous studies of the new products of applied science, Popular Science Monthly does not underwrite the business methods of the individuals or concerns producing them. The use of Popular Science Monthly articles for stock-selling purposes is never authorized. A. L. Cole, President and Treasurer; H. C. Wilson, Vice-President; John Nichols, Vice-President; F. W. Briggs, Secretary.

Popular Science Monthly for February, 1931

Robot Handles Plane in Flight	63
Keeping 400 Navy Airplanes Ready to Fly	69

ENGINEERING

Use Aluminum Paint to Keep Water Pipes Cool	39
Electric Water Power Plant Crowded Steam	48
New Inland Canal Rivals Panama	62
Test Chicago Soil for New Subway	63
World's Biggest "Wye" Feeds Two Turbines	64
Rivers Built in Laboratory	71
Ten-Ten Statue Is Raised 400 Feet	72
New Engines Use Old Two-Pressure Boiler	74

HEALTH AND HYGIENE

Analysis of Blood Wins Nobel Prize	39
Tiny Detector Reveals Health Ray "Pinhole" in Metal May Harbor Germs	73
Boosts V-Shaped Bed	73

MODELS

Arming Our Destroyer Model	90
Planking Ship Models	96
Boxing Models for Shipment	109
Readers Build Amazing Ship-in-Bottle Models	112
Better Ways to Build Wings for Model Planes	116
Covered Wagon Models Popular	127
How to Install a Block Signal System on Your Model Railway	128
Red-Hot Needle Useful in Ship Model Work	131

NEW PROCESSES AND INVENTIONS

Screw Cap Connects Electric Wires	33
Squirrel Cage Truck Collects Ash Cans	34
Folding Nine-Inch Rule Is Part of New Knife	34
Army Gets Talking Gas Mask	38
Two Extra Wheels on Motorcycle for Towing	38
Has Plot Writing Robot	38
Measures Salt in Water	39
Machine Mixes Plaster and Puts It on Walls	39
New Silencers Stop Window Noise but Let In Air	46
Pocket Projector Shows 250 Pictures	48
Score Card on Putter	48
1,000 Film Books on a Shelf	49
New Microscope Uses Invisible Light	57
Send Writing by Phone	63
Dual Control Cycles for Tyro Drivers	65
Both Sides of Phone Talk Can Now Be Recorded	64
Water Spray in Chimney Cleans Smoke	65
New Fish Line Weight Dissolves in Water	65
Bowed Steel Strips on Casters Hold Carboys	65
New Vanner Glue	66
Machine Wrings Hay Dry	66
Outboard Motor Runs Under Water	67

Tractor Cycle for Rough Ground	70
Pockets in New T-Shirt Hold Photographs	72
Balance in Shop Tells Moisture in Lumber	73
New Lamp Reflector Imitates Daylight	74
Universal File Handle	76
Portable Fire Engine	76
Machine Digs Up Old Road, Lays New One	77
Lopsided Golf Ball Picked Out by Gage	77

RADIO

Telescope Reads Radio Meters	48
Pup Cured by Radio	82

UNUSUAL FACTS AND IDEAS

Flute, 20,000 Years Old, Found in Nevada Cave	33
Uncle Sam Has Railway in Alaska and Panama	33
Biggest Roller Bearing	33
"Ski Hopping" Is Stunt for Experts	34
Makes Million Clay Balls a Minute in Rotary Kilo	34
Treasure Seekers Still Active	35
Aluminum Stronger in Great Cold	35
Cows Go to Pasture through a Subway	38
May String Violin Bow with Silver Threads	38
Makes Hard Coal in Few Hours	38
Research Tries to Find Cause of Gray Hair	38
Flue Gas in Oil Tank Checks Fire Hazard	39
80,000 Pullman Tickets Used Each Day	46
Sailors in U. S. Navy to See Sound Pictures	48
Thrilling Stories Stop Beat of Child's Heart	48
Weird Beasts Pose before the Camera	51
Enlarges Tiny Plants in Pictures	52
Effort Now Being Made to Solve Mystery of Northern Lights	53
Snow Mosquitoes Sleep through the Winter	53
Fire Engine Draws Life-Saving Boat	63
Crews of Submarines Get Toast for Bread	65
Name Wanted for New "Lemon-Grapefruit"	64
Lumber in One Tree Is Enough for 500 Homes	64
Plane without Wings Is Speedy Ice Boat	64
203 Four Leaf Clovers Found in Four Hours	65
Home No Longer Safe, Accident List Shows	65
Asbestos Sun Saves Acid Worker	66
America's Highest and Lowest in California	67
War Now Declared on Book Bugs	67
Home Weatherproofed with Automobile Taps	67
Big Hole in Atlantic Aids Sailors in Fog	67
Diesel Engines in India Meet Hot Competition	67
Strange Life of a Big Ship That Never Goes Anywhere	68
Diet Fats Fight in Brook Trout	76

New Process Extracts Rubber from Milkweed	72
Develops Giant Sugar Cane	73
Men Ride Engine Front to Study Power	73
New Auto Toy Gives Child Chance to Drive	73
Locomotive Wheels Drop Off in Repair Shop	74
Mine Mule Now Wears Headlight	75
Three Railway Trucks Rise One above Another	75
World's Only Fish Hospital	75
Bad Smells Now Warn Miner of Danger	75
Trees Unharmed by Drought	76
Finds Ball of Cold Fire in Deadly Gas	76
Despised Weed Aids Farm Land	76
Fruit Flavor Probed	77
Everybody Is Happy, Psychologist Finds	77
Siberian Wolves May Howl in Microphones	77
Ice Box Gale Tests Warmth of Cloth	77

FOR THE HOME OWNER

Automatic Control for Damper	119
Using Old Newspapers Instead of Kindling	120
Filling Corner Cracks	120

CRAFTWORK

Making a Leather Photo Frame	94
Parrot to Hold Reading Lamp	106
How to Cut Laces for Leather Craft Work	132
Painting Fabric Rugs	132

WOODWORKING

Easily Built Scooter Skims Ice at Mile-a-Minute Clip	87
Your Guests Will Like This Luggage Rack	96
Barrel Stave Toboggan	97

IDEAS FOR THE HANDY MAN

An Illuminated Ice Mountain	93
Cutting Circles on a Band Saw	110
Old-Style Phonograph Cabinet Converted into a Lowboy	111
Tool Handle Ferrules	111
Blueprints for Home Workshop	113
Safety Goggles Protect Eyes while Sawing	114
Pipe Fitting Make Lumber Rack	115
Doctor Builds Band Saw	121
Cuts—and Short Cuts—on a Motorized Joiner	124

HINTS FOR THE MECHANIC

Quenching Steel Is an Art	100
A Minute or Two with Old Bill	100
Hints on Use of Taps	102
Data Simplifies Thread Cutting	102
Locating Holes in Small Work	104
What to Do When the Drill Runs	103
Depth Gage Tests Circle Radius	104
Slicing Leather Belting	104
Boring Odd-Shaped Holes in a Lathe	104
Removing End Play in Grinder	104
Sandpaper Holder for Commutator Work	109

Retire in 15 years

on your Present living Budget

by investing in safe 6½%
First Mortgage Bonds

Follow the plan given in the new edition of this famous book, and win financial independence. The plan works just as surely whether you are now earning \$1,000 or \$100,000 a year.

The way is definite—each step plainly indicated and independent of luck, business genius or speculation.

Every fact has been harvested out of the 49 years' experience of Cochran & McCluer in the first mortgage investment banking business.

The plan is so simple any one can understand it—so practical and certain that anyone may follow it to success.

In addition to the Financial Independence Plan and the unique budget schedule, the book gives suggestions that enable you to enjoy more of the good things of life, both while building your independent fortune and after you have attained it.

We invite the most skeptical to read this plain, straightforward, interesting book. Phone, call or send coupon. We employ no salesmen, therefore none will call.

MAIL THIS FOR

NEW EDITION

6½%
62

Cochran & McCluer Co. ESTD 1881
46 N. Dearborn St., Chicago

Please send me, without obligation, a copy of the new edition of your famous book, "How to Retire in 15 Years." (No salesman will call.)

Name

Street


City State

Cochran & McCluer Co.

Established 1881

46 North Dearborn St., Chicago, Ill.

**This Book Has Helped
Thousands to Success
The Real Estate Educator**



The New Revised Edition, contains Questions and Answers; Brokers' License Law; Dictionary of Words and Phrases in Real Estate and Construction; How to Appraise Property; Law of Real Estate; How to Advertise Real Estate; Legal Forms; Commissions to Agents; "Don'ts" in Contracts, etc. 288 pages. Cloth. Postpaid \$2.00.

The Popular Science Monthly

381 - 4th Ave.

New York

I Have \$7,000 in the Savings Bank— WHAT SHALL I DO?

By LEON MEADOW, Financial Editor

A LETTER received in the Financial Department the other day, seemed so well timed in the light of present market conditions that we think our readers will benefit by reading both the letter and our reply to it. In view of the personal nature of this letter's contents, we naturally refrain from revealing the writer's identity.

Mr. Leon Meadow, Financial Editor
Popular Science Monthly, New York City

Dear Mr. Meadow:

As a constant reader of Popular Science Monthly and a close follower of the financial articles, I would appreciate your advice on a situation now confronting me.

I am thirty-seven years old, married, and the father of two children—a boy of twelve and a girl of ten. While I have always looked forward to investing my hard earned savings, the first year I was married—thirteen years ago—I promised myself to resist the temptation until I could invest with absolute safety—until I had enough money left in the savings bank, after withdrawal for investments, to give me something to fall back on in case of unforeseen financial emergencies.

At the present writing I have lived up to my word and have accumulated about \$7000, deposited in various savings banks in this city. What I would like to know is this: Would I be acting wisely and safely in withdrawing \$5000 of this amount for investment—and, if so, into what would you suggest that I put this money?

Realizing that market and business conditions are very bad, I hesitate strongly . . . but, at the same time, I need every penny that comes my way, and could very easily use the extra income over bank interest that the right kind of investments would bring me. If I am not asking too much, I would like your sincere opinion—and your suggestions in this matter.

Here is the main content of our reply to the above letter:

The investment problem now confronting you is one which a great many men face at different times. It must be remembered that the suggestions we offer in solution are applicable principally to present day conditions. And, as you yourself put it, these conditions—both in finance and industry—are undoubtedly poor at present. That does not imply that this is a bad time for investing. On the contrary, were you a man of exceptional wealth or independence, the common stock market today offers you some of the finest buys that have been seen in years. But of course common stocks are out of the

question for any man who is thinking of investing with funds drawn out of his savings account, or any money which must produce financial security. Fortunately, the question of investing does not end with common stocks—which can never be genuine investments for the buyer of limited means—but goes on, and points definitely to one answer: Bonds, good sound bonds. We believe that if you will bear in mind certain fundamental but important points, you will be safe in taking out of your savings bank any sum up to \$5,000 and investing it in gilt-edge bond issues. This would leave you with \$2,000 in the bank, and that should be an ample reserve for emergencies.

Generally speaking, good bonds are fairly high in price at the present writing, because the demand for such issues is rather large. In all periods of unsettled and unstable market conditions such as we are now witnessing, the bond market attracts the attention of a great many investors. Working on the law of supply and demand, the increased desire for bonds sends them up in price and accordingly forces down their effective interest yield. (For example: the bond that pays 5% at 100 par only pays 4.6% at 110.) Before us is a statistical chart showing that sixty of the very finest bonds available in the different industrial groups are yielding between 4½ and 5%.

We have no pessimistic desire to look at the darkest side of the situation, but nevertheless we have seen no definite and continuous indication of the stock market reaching a stabilized level as yet. And certainly business will not return to normal over night. The reconstruction process is more likely to be a long, steady pull up-grade. In the meantime, as the stock market feels its way to a steadier level, the demand for bonds will continue to grow larger—because good bonds are always safe investments—and likewise, their prices will continue to rise.

In other words, if you buy bonds now, in all probability you will realize an advance in their value. And taking the matter from the point of interest yield, bonds still seem to be an attractive buy at their current prices. A glance at the same statistical chart reveals the fact that even at the height of the 1929 stock boom, when bonds were relatively cheap because the demand was small—even then, their average interest yield did not touch 5%. Right now, with a definitely strong bond market—there are a number of secure issues that will yield 5%. So that from the standpoint of interest—this is also a good time to buy bonds.

However, to be conservative, we should place the average bond yield now at 4¾%. If you (Continued on page 5)

I HAVE \$7,000 IN THE SAVINGS BANK— WHAT SHALL I DO?

(Continued from page 4)

withdraw \$5000 from banks paying 4% or approximately \$210 a year in compound interest—and use that money to buy \$5000 worth of bond securities yielding 4½%—or \$237.50 a year interest you are gaining \$27.50.

Now, if there were any question about the insecurity of even the finest bonds—as against the safety of bank deposits—we would naturally say that it would be unwise for you to risk any portion of your \$5000 for the sake of gaining an extra \$27.50.

But that is not the case. Among the industrial, rail and utility groups, you will find attractive bonds, issued by the world's leading companies. Their tremendous financial assets and structures are enough to insure the safety of your investments as firmly as any savings bank can. Because of this absolute security and because of your need for any extra income you might obtain, we believe that the right bond investments will help solve your particular problem.

In connection with the purchase of bonds, there are one or two points on which we should like to advise you. If you find yourself in a situation where you have to choose between a bond yielding 4% on a par \$100 value—but now priced at 90, so that its effective rate of interest is roughly 4½%—and a bond paying 5% on a par of \$100—but yielding only 4½% because it is now quoted at 110—in all cases pick the lower priced bond. That is, of course, if all other things—such as date of maturity, company earnings, etc.—are equal or offset each other. Reasons for this are as follows:


Most bonds are callable before maturity at par (100) or slightly above par. So that, in case of earlier redemption there would be a decided advantage to you in purchasing your bonds below par, whereas, in the opposite case, a loss might easily result. Perhaps this point can be made clearer to you if it is illustrated with two examples like these:

Let us consider a bond that matures in 1946 at a par value of 100—but is callable any time before then at 102½. Supposing you buy that bond today at 95. In 1933 the company decides to redeem it—at 102½. Your gain is then 7½ points in 2 years—or 3¾ points per year—as against 3 points in 15 years, or 1/3 of a point per year, should the company let the bond run until maturity and then redeem it at par (100).

Now take exactly the same bond and suppose you were to purchase it today for 105. In 1933 it is called for redemption at 102½—meaning a loss to you of 2½ points in 2 years—or, if the bond is not called until maturity, a loss of 5 points in 15 years.

Incidentally, there is another moral to be drawn from this example. That is, always investigate thoroughly all conditions, terms, and reservations with which the bond you contemplate purchasing is being offered upon the market. Take maturity dates, (Continued on page 6)

How you can retire on \$200 a month



THIS new Retirement Income Plan enables you to provide for yourself a guaranteed income for life.

The income begins at any age you say—55, 60 or 65. It can be any amount you wish—\$100 a month, \$200, \$300, or more.

This life income is unconditionally guaranteed to you by the Phoenix Mutual, a 79-year-old company with assets of over 135 million dollars.

A business man recently asked us questions about the Plan. Here are his questions and our answers: "A Retirement Income takes care of me, but suppose my wife outlives me. How can I be sure she will not be without money?"

"That can be taken care of. The income can be made to continue as long as either you or your wife lives."

"Suppose I should be killed suddenly by some accidental means."

"Your wife would receive double the amount of cash or double the income received in the event of natural death."

"Suppose serious illness or accident should destroy my earning power while I was still young. Where would I get money to live on?"

"Shortly after you became totally and permanently disabled, the company would pay you a monthly income. This income would continue as long as your disability lasted."

Retirement Income Plan

Here is what a \$200 a month Retirement Income, payable at age 60, will do for you.

It guarantees when you are 60
A Monthly Income for life of \$200, which assures a return of at least \$20,000, and perhaps much more, depending upon how long you live, or, if you prefer, a Cash Settlement of \$27,000.

It guarantees upon death from any cause before age 60
A Cash Payment to your beneficiary of \$20,000. Or a monthly income for life.

It guarantees upon death from accidental means before age 60
A Cash Payment to your beneficiary of \$40,000. Or a monthly income for life.

It guarantees in event of permanent total disability before age 60
A Monthly Income of \$200. Plans for women or for retirement at age 55 or 65 are also available.

"How much does a Retirement Income cost?"

"That depends upon your present age and upon the amount of income you want to retire on. A Retirement Income does not have to be paid for all at once. It is purchased on the installment plan. The payments are usually spread out over a period of years. This makes the payments comparatively small."

Send for the Facts

An interesting 28-page book tells how you can provide a Retirement Income for yourself—how you can provide money to send your son to college—money to leave your home free of debt—money for other needs. Send for your copy now. No cost. No obligation.



**PHOENIX MUTUAL
LIFE INSURANCE COMPANY**

Home Office: Hartford, Conn.

First Policy issued 1851



PHOENIX MUTUAL LIFE INSURANCE CO., 566 Elm St., Hartford, Conn.

Send me by mail, without obligation, your new book,

"HOW TO GET THE THINGS YOU WANT."

Name _____ Date of Birth _____

Business Address _____

Home Address _____



A man knows when he's found his RIGHT SMOKE

MEN who have not found their right smoke are discontented, uncertain—but when a man does find his right smoke he knows it!

If you're not a pipe smoker, maybe you should be. Get a good pipe and some good tobacco, and taste the real satisfaction of pipe smoking.

If you are a pipe smoker, maybe the tobacco you're using fails to give you full-bodied, all-round satisfaction.

Many men have found that a pipeful of Edgeworth is the right smoke for them. Edgeworth is a blend of fine old burleys, and its "eleventh process" gives a flavor and a coolness that have pleased thousands of smokers. Maybe Edgeworth is your right smoke.

You can buy Edgeworth wherever good tobacco is sold. Or just send coupon for a generous packet of Edgeworth—free.

EDGEWORTH SMOKING TOBACCO

Edgeworth is a blend of fine old burleys, with its natural savor enhanced by Edgeworth's distinctive eleventh process. Buy Edgeworth anywhere in two forms—"Ready-Rubbed" and "Plug Slice." All sizes—15¢ packet package to pound humidifier tin.



LARUS & BRO. CO., 100 S. 22d St.
Richmond, Va.

I'll try your Edgeworth. And I'll try it in a good pipe.

Name _____

Street address _____

City and state _____

I HAVE \$7,000 IN THE SAVINGS BANK— WHAT SHALL I DO?

(Continued from page 5)

for instance. Some bonds are non-callable—that is, the company cannot redeem them before maturity. But most bonds can be called or redeemed before maturity. In such cases, it is usual for the company to pay the holder a premium above par, although there are some few instances where bonds are callable before maturity at their par value. But, if a premium is to be paid, it may range anywhere from 1 to 10% of the bond's par value. Very often a sliding scale is assumed, in which the premium decreases as time elapses.

Concerning the maturity date itself, for a person of your means and purposes it is perhaps wise, when all other things are equal, to purchase bonds with comparatively short maturity dates. Long term securities are bought mostly by large trust funds, banks, insurance companies, and other big financial interests because they must arrive at a fixed income over a long period of years—and because expiration of short term maturity dates would involve sale and reinvestment on such a large scale that the commission and other necessary transactions would cause a decrease in the total income.

To get back to the average investor—the shorter maturity dates, the sooner you realize your profits in points, if you follow the previous suggestions when purchasing bonds. And it is also wise to remember that the shorter the term, the more profit per year for you. Time is a factor which must be considered in all investments where the profit comes from interest or rise in value or both.

Now let us briefly summarize the whole thing, and keep in mind at the same time that all this applies not only to yourself but also to every man in similar circumstances. Absolutely safe, gilt-edge bonds are now available in the industrial, rail and utility groups that will yield very close to 5% on their present market prices. In view of general, prevailing conditions as we have outlined them, and remembering always the intrinsic value of bonds themselves,—proper purchases along the lines indicated should prove not only just as safe for you as savings bank deposits, but more profitable in the long run.

To Help You Get Ahead

THE booklets listed below will help every family in laying out a financial plan. They will be sent on request.

"The Provident Provider" is a booklet describing a new savings plan which provides a regular retirement income for a man and insurance protection for his family. A copy will be mailed on request by Provident Mutual Life Insurance Company, Philadelphia, Pennsylvania.

The House Behind the Bonds reminds the investor of the importance, not only of study-



MONEY FOR A WORLD CRUISE

As little as \$16.25 invested monthly delivers you \$2500 cash in exactly 120 months—ample for an all-expense world cruise!

Return this advertisement with your address for booklet "Enjoy Money," explaining our 36-year-old Plan.

200,000 INVESTORS

INVESTORS SYNDICATE

FOUNDED 1894

MINNEAPOLIS

BOSTON

LOS ANGELES

OFFICES IN 21 PRINCIPAL CITIES

ing the investment, but of checking up the banker who offers it. Address: Fidelity Bond & Mortgage Co., 1188 New York Life Building, Chicago, Ill.

How to Get the Things You Want tells how you can use insurance as an active part of your program for getting ahead financially. Phoenix Mutual Life Insurance Company, 328 Elm Street, Hartford, Conn., will send you this booklet on request.

Enjoy Money shows how the regular investment of comparatively small sums under the Investors Syndicate plan, with annual compounding of 3½% interest, builds a permanent income producing estate, a financial reserve for a business, or a fund for university education or foreign travel. Write for this booklet to Investors Syndicate, Investors Syndicate Building, Minneapolis, Minnesota.

How to Retire in Fifteen Years is the story of a safe, sure and definite method of establishing an estate and building an independent income which will support you the rest of your life on the basis of your present living budget. Write for the booklet to Cochran & McCluer Company, 46 North Dearborn St., Chicago, Ill.

See How Easy It Is tells how it is possible to start off with a definite plan for creating an immediate estate leading to future financial security. Get your copy of this booklet by writing to Postal Life Insurance Company, 311 Fifth Avenue, New York City.



THE FIFTH OF A SERIES OF ADVERTISEMENTS DEALING WITH ULTRA-VIOLET RADIATION IN THE HOME.



When children enjoy a G. E. Sunlight Mazda Lamp They Enjoy . .

Sounder teeth, resistance to disease,
 straighter limbs, glowing health

THOUGH it was discovered less than a decade ago, Vitamin D might be called the mother's vitamin because of the important part it plays during the prenatal and growth years of life. Every mother is tremendously interested in the influence this vitamin has on her children.

First, in bone building. What mother does not want her youngsters to grow up strong and straight of limb? Vitamin D tends to regulate the absorption by the body of several necessary mineral elements, especially calcium. In this way it controls the growth of bone and tissue and frees children of bowlegs and other rachitic deformities.

Second, in developing sound teeth. Teeth, perfectly constructed, are much less subject to decay than defective teeth. Numerous tests which have been made, both in the United States and abroad, support the theory that poor structure is a cause of tooth decay and that the presence of Vitamin D is essential not only for the original development of the teeth but for their protection later in life. For example, the teeth of a mother do not suffer as they otherwise would when her supply of calcium is drawn upon by a nursing child.

Third, in building up resistance to disease. The maintenance of youthful health is the primary concern of every mother. The sunshine vitamin not only builds strong bones but helps to build strong constitutions. This is of especial concern to mothers during the winter months, when the sunlight contains only a very small amount of the normal beneficial ultra-violet found in summer sunlight.

For these three reasons every mother is vitally interested in Vitamin D. "How



The pool of free mercury in the bulb of every General Electric Sunlight Mazda Lamp is the vital element which makes possible the effective ultra-violet rays not found in ordinary Mazda lamps. When the lamp filament is lighted a portion of this mercury is evaporated and an arc is formed above the V of the filament. This mercury arc furnishes the ultra-violet radiation. Remember, NO incandescent lamp, without this pool of mercury, is a G. E. Mazda Sunlight Lamp. Remember, no Sunlight lamp without this pool of mercury is a G. E. Mazda lamp.

best to provide my children and myself with this sunshine vitamin?" is her first question.

Because Vitamin D, as far as is known, only originates under the influence of ultra-violet radiation—MAZDA research in developing the General Electric Sunlight MAZDA lamp, brought a safe, simple and economical means of supplying the apparent source of this health-giving vitamin, as it is supplied by nature, through summer sunlight.

The G. E. Sunlight MAZDA Lamp is a great advance over all other methods of simulating sunshine—especially for children—because it does not frighten them. It operates without noise, fuss or mechanism. Children play, dress and read under its light just as they would under any other light in the home. To them it is just a new and wonderful "incandescent lamp."

Manufacturers, including General Electric, who make fixtures and standards utilizing this new lamp, have further developed this same idea. Fixtures and standards look like beautiful bridge or floor lamps and have no "treatment" aspect to make children apprehensive of their use. Special fixtures are necessary because the G. E. Sunlight MAZDA Lamp will not operate in the ordinary bridge lamp or fixture.

From the standpoint of mothers,

another angle is of vital interest. *Safety.* To insure this, Mazda research has used in the making of the bulb of the G. E. Sunlight MAZDA Lamp a special glass which filters out practically all of the "short" or harsh ultra-violet rays not found in sunlight. In nature these are screened out by atmosphere before reaching the earth. Therefore, in using the G. E. Sunlight MAZDA Lamp it is only necessary to observe the same sensible precautions every mother would observe in bright midday midsummer sunshine—namely, prevent over-exposure and staring at the source of light.

Busy mothers will appreciate the simplicity of this new lamp. It operates like any other MAZDA lamp in the home, at a touch of the switch. Keen home managers will be impressed by the economy of the G. E. Sunlight MAZDA Lamp—it costs, at the average price of current, less than three cents an hour to operate. Three children can get all the benefit of sunlight at less than one cent per exposure!

Best of all, this boon to health-maintenance is a development of Mazda research and possesses that high quality you expect in all General Electric products. And is sold in accordance with the requirements of the Council of Physical Therapy of the American Medical Association. Insist on G. E. Sunlight when seeking sunlight for your children.

THE INCANDESCENT LAMP DEPARTMENT
 OF GENERAL ELECTRIC COMPANY
 NELA PARK, CLEVELAND, OHIO

Please send me, without obligation, full information about the G. E. Sunlight MAZDA Lamp.

Name _____

Address _____

City _____

PSM 2-31

GENERAL ELECTRIC
SUNLIGHT MAZDA LAMP

INDEX

Guaranteed Advertisements

Automobiles and Accessories

	Page
Cadillac Motor Car Co.	1
Chevrolet Motor Co.	11
Ethyl Gasoline Corp.	152

Aviation

American School of Aviation	141
Lincoln Airplane School	134

Books

Audel & Company, Theo.	149
Book League of America, The	9
Denison Company, T. S.	141
McGraw-Hill Book Co.	150
Merriam Co., G. & C.	140
Nelson & Sons, Thomas	111
Quilvie Publishing Co.	148

Building Materials

Craftsman Wood Service Co.	122
International Mill & Timber Co.	122
Masonite Corporation	18
The Insulite Company	13

Business Opportunities

Central States Manufacturing Co.	142
Fate-Root-Heath Co., The	147
Food Display Machine Corporation	138
Metallic Letter Co.	149
Newcomer Associates	141
Pioneer Tailoring Co.	141
Rollo Specialty Co., The	118

General

American Telephone & Telegraph Co.	17
Incandescent Lamp Dept. of G. E. Co.	7
National Carbon Company, Inc.	2d Cover

Hardware Supplies

Casain Mfg. Company, The	122
Plastic Wood	114
Smooth-On Mfg. Co.	118
Three-In-One Oil Co.	124

Industrial Equipment

American Screw Co.	116
Norton Company	Insert
S. K. F. Industries, Incorporated	95

Investments

Cochran & McCluer Co.	4
Investors Syndicate	6
Phoenix Mutual Life Insurance Co.	5

Miscellaneous

Bernard & Heller	144
Burpee Co., W. Allen	125
B. & L. Engineering Co.	125
Crescent Tool Co., The	144
Crown Cork & Seal Co.	131
Heiss Hotels	151
Kelsey Co.	131
Landon & Warner	136
Wrigley's	122
York Tires & Rubber Co.	141

Musical Instruments

Conn. Ltd., C. G.	125
Deagan, Inc., J. C.	127
Hobart, Inc., M.	123

Patent Attorneys

Chartered Institute of American Inventors	144
---	-----

	Page
Dieterich, Albert	145
Evans Co., Victor J.	145
Fisher Mfg. Co., Adam	145
Greene, W. T.	145
Hartley's Reliable Patent Agency	144
Lacey & Lacey	144
Lancaster & Allwine	145
McCaithron, Irving L.	145
O'Brien, Clarence A.	143
Randolph & Company	145

Radio Apparatus

High Frequency Laboratories	151
-----------------------------	-----

Razors, Toilet Articles, Etc.

Lambert Pharmacal Co.	15
Lever Brothers Co.	131
Proctor & Gamble	127
Williams Co., The J. B.	99

Popular Science GUARANTEE

POPULAR SCIENCE MONTHLY guarantees every article of merchandise advertised in its columns. Readers who buy products advertised in POPULAR SCIENCE MONTHLY may expect them to give absolute satisfaction under normal and proper use.

Tools, Radio Apparatus, Oil Burners and Refrigerators advertised in POPULAR SCIENCE MONTHLY have been tested or investigated by the Popular Science Institute of Standards and each advertisement carries the insignia indicating approval.

However, other products advertised in the magazine not subject to test carry the same guarantee to readers as products tested.

THE PUBLISHERS

Schools

American School	136-151
Blackstone Inst.	141
Bliss Electrical School	142
Boone, Benjamin N.	149
Borne School of Wrestling	141
Columbian Correspondence College	149
Coyne Electrical School	133-135
Detroit School of Lettering	151
Dobe, Engineer	138
Dodge Institute	149
Federal School of Illustrating	137
Feuchtinger, Prof. E.	151
Finley Engineering College	141
Franklin Institute	147-151
International Correspondence Schools	134-144
Landon School of Cartooning	149

	Page
La Salle Extension University	141-148-151
Lederer School of Drawing, The	148
Lewis Hotel Training Schools	148
McCarrie School of Mech. Dentistry	142
National Electrical School	149
National Radio Inst.	139
New York Electrical School, The	149
New York Inst. of Photography	149
Northwestern School of Taxidermy	149
Perfect Voice Institute	142
RCA Institutes, Inc.	146
Standard Business Training Inst.	144
Tamblyn, F. W.	141
Tri-State College	141
U. S. School of Music	151
Universal Plumbing School	147
University of Chicago	142

Smoking Materials

Dill Company, J. G.	Insert
Larus & Brother Company	6
Lucky Strike	Back Cover

Sporting Goods and Toys

Harley Davidson Motor Co.	120
Mead Cycle Co.	122
Porter Chemical Co., The	132
Thompson Bros. Boat Mfg. Co.	127

Things to Make

American Chime Clock Co.	122
Bierbauer, C. J.	129
Fisher, A. J.	131
Ideal Aeroplane & Supply Co., Inc.	132
Miniature Ship Models	127
Model Ship Supply Co.	132
Schiercke, Henry C.	122

Tools and Shop Equipment

Arkograf Pen Co.	129
Atkins & Company, E. C.	113
Boice, W. B. & J. E.	117
Brown & Sharpe Mfg. Co.	105
Carborundum Company, The	121
Chicago Gear Works	131
Delta Specialty Co.	125
Gerold Company, The	131
Gerstner & Sons, H.	131
Gilson Slide Rule Co.	131
Goodell-Pratt Co.	112
Heston & Anderson	127
Hinsdale Mfg. Co.	129
Jennings Mfg. Co., The Russell	131
LeBlond Machine Tool Co., R. K.	105
Lufkin Rule Co., The	3d Cover
Nicholson File Co.	115
North Bros. Mfg. Co.	109
Parks Woodworking Machine Co., The	131
Simonds Saw and Steel Co.	107
South Bend Lathe Works	126
Starrett Co., The L. S.	101
Stanley Rule & Level Plant, The	119-132
Wallace Co., The J. D.	122-129

Typewriters, Writing Materials, Etc.

International Typewriter Exchange	150
-----------------------------------	-----

Eugene
O'NeillAlice Roosevelt
LongworthEdwin Arlington
RobinsonGamaliel
BaileyRichard
Burton

This Famous Board of Editors Selects for You 2 Books Each Month

One of the Best New Books-AND-One of the Greatest Classics

Here is the perfect book club plan. Think of receiving one of the best new books each month AND ALSO one of the greatest of the famous classic novels—TWO books each month, the best of the new and the best of the old, both selected by a distinguished Board of Editors and both supplied in the handsome library cloth binding designed exclusively for Book League members. This is the Book League—Balanced Reading Plan which doubles the entertainment and cultural value of your reading and enables you to build up a balanced library containing the cream of the world's literature both new and old.

THE BOOK LEAGUE OF AMERICA

Supplies These Two Books Each Month at 1/3 of the Usual Cost!

The Biggest Buy in the Book World Today

The Book League Plan has six main features which combine to give you the best and most for your money:

1. A Distinguished Editorial Board to select the best books for you.
2. A Balanced Reading Plan giving you the cream of the world's literature both new and old.
3. One of The Best NEW BOOKS each month in a handsome library cloth edition exclusively for members.
4. A Famous Classic selected each month and prepared in a handsome and exclusive cloth edition for League members only.
5. Extraordinary Savings giving League members their books at one third of their usual cost.
6. The Book League Monthly—a highly interesting magazine devoted to books and authors, sent free each month.

The rapidly growing number of Book League members testifies that the League plan is best and the League values greatest. We want to prove that fact to you before you assume any risk whatever. Without risk or obligation you may

Judge for Yourself Get the Two Current Books for FREE EXAMINATION

Without paying a cent, you may enter your subscription and receive for free examination the two January selections: The new book is Sylvia Thompson's *PORTRAIT BY CAROLINE*. The famous author of "Hounds of Spring" gives us her most brilliant novel—a vivid picture of modern English society and the intimate story of four fascinating characters who seem outwitted by the choices they own ways of life. But the author takes us behind the scenes to see the forces and passions that decide their destinies.

The famous classic for January is Cervantes' *DOM QUIXOTE*—the immortal romance of 17th century Spain that has been a best seller for over 300 years and one of the best loved books in all literature. This special Book League edition is complete and unabridged in 936 pages.

These books are representative of the two splendid selections which will be sent you, as a regular subscriber, each month. If you are not delighted with these books, you may return them, cancel your subscription, and owe nothing. This is your opportunity to become familiar with the service of The Book League—the club which gives you the best and most for your money.

Send No Money

Simply fill in and mail the coupon below. We will send you the two current books. Within one week you may return them and owe nothing. Otherwise keep them and you will be a regular member of the Book League for two years at the rate of \$3.00 a year, select one each month and all other membership privileges. You then will receive a bill for the full \$6.00 and six months' payment, but after 60 days a total of only \$2.00 for 72 splendid library volumes and the full service of the League.

Mail This Coupon

THE BOOK LEAGUE OF AMERICA,
Dept. 159, 100 Fifth Avenue, New York, N. Y.

Enroll me as a member of the League at the earliest moment and send me the two January selections. Without any work I may return the books you will send me within one week and I will owe nothing. (Otherwise I will remit \$3.00 a month for seven months.) I will receive the two League selections each month for twelve months and all other membership privileges.

Name _____

Address _____

City _____ State _____

All
League Books
Are
Artistically
Bound in
Cloth and
Specially
Designed by
Frank Peets

The Book League
of America
Is the Only Book
Club That Gives
You A Balanced
Reading Program

These great classic novels that have stood the test of time—the works of Shakespeare, Tolstoy, Flaubert, Melville, Virginia Woolf, and a host of others—have us at all times a part in your reading program as the new books, whether you read for entertainment or culture or both. Therefore the Book League serves for its members both the best of the new and the best of the old. It is the only book club which meets this important requirement.





INTO THIS one brilliant book of 280 pages have been condensed the outstanding facts that scientists have discovered since Aristotle, the father of science, dissected a frog to see what made its heart beat.

How often have you wanted to know about the wonderful discoveries in science that have so changed the world we live in . . . the secret of radium . . . the romance of the atom . . . the origin of the earth!

Or you may have wanted to know why glass is transparent . . . how fireflies produce light . . . why the grass is green . . . if radio waves move in a straight line?

All of these questions, and hundreds of others, have now been answered, for the first time, in one book—**THE POCKET GUIDE TO SCIENCE.**

All that you probably will ever want to know about science is told in this one book that will fit in your pocket or grace a library table. The curiosity-satisfying facts about the world we live in are made instantly available to you in simple question-and-answer form in **THE POCKET GUIDE TO SCIENCE.**

Your Name in Gold —on this Wonderful Book

YOU are assured of the accuracy of the answers in **THE POCKET GUIDE TO SCIENCE** because it has been edited by Dr. F. J. Free, the distinguished author of "The Story of Man and His Work." Dr. Free has a remarkable genius for condensing the known facts about scientific questions into a vivid, easily remembered presentation.

SPECIAL OFFER

THE POCKET GUIDE TO SCIENCE is not for sale. It is offered to you without one penny extra cost, with a 14 months' subscription to **POPULAR SCIENCE MONTHLY.**

In **THE POCKET GUIDE TO SCIENCE** you get full information of all that the scientists have discovered up to the summer of 1934.

POPULAR SCIENCE MONTHLY "comes out" where **THE POCKET GUIDE TO SCIENCE** comes off. **THE POCKET GUIDE** gives you all the information up to right now. **POPULAR SCIENCE MONTHLY** will give you all the important, interesting and new discoveries of science for the next 14 months.

In every issue of **POPULAR SCIENCE MONTHLY** are a dozen or more important articles that explain and picture the most fascinating and significant new developments, discoveries, and undertakings in exploration,

in engineering, in health, in electricity, in medicine, and in every branch of science.

And there are also, in every issue, a hundred or more articles describing the important new inventions in every branch of

mechanical activity—page after page filled with photographs and descriptions that show you how you can save money in the shop, around your car, in your office, office and home.

But all this is only part of the contents of one issue of the amazing **POPULAR SCIENCE MONTHLY.** It takes over 300 articles and pictures every month to tell the readers of **POPULAR SCIENCE MONTHLY** all that has happened in the scientific, radio, mechanical, and automotive fields.

Your Name in Gold

We will stamp your name in 23-carat gold on the cover of **THE POCKET GUIDE TO SCIENCE** at no extra cost to you if you use the coupon below immediately.

You are offered a 14 months' subscription to **POPULAR SCIENCE MONTHLY** regular price thought by the publisher would be \$3.50, with **THE POCKET GUIDE TO SCIENCE**—all for \$2.00, plus the few cents' postage. If you are already a subscriber to **POPULAR SCIENCE MONTHLY** we will be glad to extend your subscription 14 months if you accept this offer.

In using the coupon please **PRINT** your name

A Few of the Hundreds of Questions Answered in the POCKET GUIDE TO SCIENCE

Why does static interfere with radio receivers?
What gland makes people grow tall or keeps them short?
Why do we grow old?
What is the safest stimulant?
What is the function of the liver?
Why are tears salty?
Can you see behind a mirror?
Why can you taste oil placed in a container?
How does a washing machine work?
Why does an electric fan blow?
How can a microscope magnify?
What is a vacuum?
How does a vacuum pump work?
Why do the stars twinkle?
How do we know what the stars are made of?
Is the inside of the earth molten?
What is an electric spark?
What makes the ocean a barrier?

POPULAR SCIENCE MONTHLY, 381 Fourth Ave., New York

SEND No MONEY

Send no money, just the coupon. If within 10 days after you receive the book and magazine you decide that you are not satisfied in every particular you may return them and your entire payment will be refunded promptly and without question. Could any offer be fairer?

POPULAR SCIENCE MONTHLY
381 Fourth Avenue, New York

I enclose your order of **THE POCKET GUIDE TO SCIENCE** and a 14 months' subscription to **POPULAR SCIENCE MONTHLY.** I will pay the amount \$2.00, plus the few cents' postage when he delivers the **POCKET GUIDE** and the first issue of **POPULAR SCIENCE MONTHLY.** If the book and magazine are not fully satisfactory to me I will return them within ten days and you are to promptly refund my full payment. Please stamp my name in gold.

Name _____
Address _____
City _____ State _____



THE GREAT AMERICAN VALUE

***A new and improved six-cylinder car—
yet lower in price than ever***



The New Chevrolet Sport Coupe

In the bigger and better Chevrolet Six, Chevrolet and General Motors have combined their resources to set a new standard of value for the American motor car. You will find smart and distinctive new lines—roomier, more luxurious Fisher bodies, which include many pleasing refinements—easier riding, easier steering and easier gear-shifting—numerous chassis advancements—and a remarkably smooth, quiet, six-cylinder engine. In fact, wherever finer materials and advanced design could add to the pride, satisfaction and economy of Chevrolet ownership, improvement has been made. Yet this fine six is as economical to own and operate as any car you can buy. And it sells at new low prices that stamp it as *the Great American Value*.

Chevrolet prices range from \$475 to \$650. f. o. b. Flint, Michigan. Special equipment extra
CHEVROLET MOTOR COMPANY, DETROIT, MICHIGAN. Division of General Motors Corporation

NEW CHEVROLET SIX

It's wise to choose a Six



This Research Service for You

EVERY day you can read about the millions spent for research by big concern and that, always, they are big successful firms that make a practice of watching every cent and getting full return on investments. Research must pay.

Instead of taking a chance when they buy, these great industrial organizations go to all kinds of expense to investigate equipment so that not a dollar may be wasted on anything inferior. The same applies to the various departments of the U. S. Government that likewise have found they cannot afford to gamble. So what they do is to determine, first, what they require of a product in order to get satisfaction and, second, find out what particular products meet such requirements. It is a costly procedure involving expensive tests, but they consider the information cheap at any price.

GAMBLING OR RESEARCH

The small buyer is no better fixed to gamble with his money and he is often up against the problem of buying equipment of a type with which he has had no experience, the sort of purchase that is made once or twice in a lifetime. Ordinarily the one avenue of research open in such a case is to find out from friends what results they have had with this or that product, but the information thus gathered is too limited and partial to be of much value.

So, to help out the consumer in the field of certain semiscientific products, POPULAR SCIENCE MONTHLY inaugurated a testing service that provides the small buyer of radio equipment, tools, and oil burners with information of the sort that big business gets through expensive private research. It was back in 1924 that this service was started, and since then it apparently has been of real help to many thousands of readers, judging from the number who come back for further advice every time they buy equipment within the classification of products covered by the

POPULAR SCIENCE INSTITUTE's investigations. The INSTITUTE is glad to have so many readers taking advantage of its service, and the purpose of this article is to set forth for the benefit of new readers the exact nature of the aid at their disposal.

THE INSTITUTE'S WORK

This service consists of general information on various types of products supplied through the editorial columns of POPULAR SCIENCE MONTHLY, and specific information on particular makes of products supplied by mail to readers of the magazine on their request. It is the POPULAR SCIENCE INSTITUTE's job to keep up with new standards and developments, to know what equipment represents good value at this particular period, and to separate generally the good from the mediocre and poor.

The products that it investigates are, as stated before, in the three classifications of radio, tool, and oil heating equipment. What the INSTITUTE does is to determine which makes are reliable and deserving of being termed the "cream" of their class, considering both price and performance. Products found to be up to requirements are put on the approved lists issued by POPULAR SCIENCE INSTITUTE, and they can be purchased with the assurance that

they will satisfactorily perform the service for which they are intended.

A RELIABLE AID

Of course, to make this service worth while, the investigations leading to approval must be thorough and the decisions impartial. To insure both, the INSTITUTE was put under the direction of Prof. Collins P. Bliss, Dean of the College of Engineering at New York University. As Director of the INSTITUTE, Dean Bliss' work attracted the attention of Government officials, who specially visited the laboratory and witnessed tests in progress. He was then added to the staff of the U. S. Bureau of Standards as consulting mechanical engineer.

The tests of POPULAR SCIENCE INSTITUTE are made by a staff of experts in the Sage Research Laboratory, New York University, where more than \$300,000 worth of testing equipment is available. In every case, these tests are sufficiently thorough and accurate definitely to bring out the worth of a product; and it is Dean Bliss who, personally, decides whether approval is merited after he has gone over the data submitted by the engineer in charge of tests.

Equipment is approved solely on the basis of test and investigation findings and there is no relation whatever between the advertising in POPULAR SCIENCE MONTHLY and the INSTITUTE's approvals. However, to such tools, radio products, and oil burners as lack the approval of the INSTITUTE, the advertising columns of POPULAR SCIENCE MONTHLY are closed.

The INSTITUTE will supply readers, free of charge, with lists of the products it has investigated and found to possess particular merit. The element of chance is eliminated in buying products that are mentioned on these lists, for they may be relied upon as safe guides in making a selection. To secure such lists, address POPULAR SCIENCE INSTITUTE, 381 Fourth Ave., New York, N. Y.

INSTITUTE BULLETINS
Refrigeration for the Home*
Heating and Ventilating*
Insulation in Building
Construction*

List of Approved Tools
List of Approved Radio Sets
List of Approved Oil Burners
Advice on Installing Oil Heat

*Starred bulletins 25 cents



WHAT ABOUT THAT Mortgage


When it's time to renew?

MORTGAGE loan companies make more liberal loans on homes that are insulated . . . modern homes that are easy and economical to heat.

If you contemplate remodeling, or building . . . will you be able to show, after your home is completed, how thoroughly it is insulated. Remember, insulation is a concealed product, built into the walls.

This is the reason for the Insulite Metal Plaque permanently affixed in an inconspicuous place in your home. It is "enduring evidence of enduring insulation" It shows how thoroughly and efficiently your home is insulated with Insulite.

**EFFICIENCY! 3,000,000
WOOD-LOCKED
AIR CELLS TO
THE SQUARE
FOOT . . .**



Thermal insulation materials achieve their efficiency to a great extent through tiny dead

air cells which act as non-conductors of heat, cold, and sound. Insulite contains 3,000,000 wood-locked air cells to the square foot . . . 3,000,000

tiny barriers holding in your furnace heat, cutting your fuel bills, making your home more comfortable.

Insulite is a full half inch thick, all wood-fiber insulating board, chemically treated to resist fire, moisture, vermin and rodents—it is not subject to rot or disintegration. This means Insulite gives permanent, lasting insulation throughout the life of the building.

INSULITE INSULATION PAYS FOR ITSELF

And remember, when you use Insulite, either in building or in remodeling, it is not an expensive "extra", but takes the place of non-insulating building materials. As sheathing, Insulite has several times the bracing strength of lumber horizontally applied. As plaster base, Insulite guards against unsightly streaks and cracks, and grips plaster with more than twice the strength of wood lath.

Insulite, light cream color in appearance, can also be attractively and economically used as wall-board. Insulite is easy to handle, easy to use, and pays dividends in increased comfort and fuel savings through all the years to come.

Your architect can tell you about Insulite. He knows its strength, quality, efficiency, and economy. Your lumber dealer can supply you with Insulite.



ENDURING EVIDENCE OF ENDURING INSULATION

The Insulite Plaque pictured above is your visible proof of the efficient insulation built into your home. The Plaque is made of durable metal and is permanently affixed to the wall. Cut into the metal is the address of the house, and the amount of insulation used.

THE INSULITE CO

(A Backus-Brooks Industry)
1800 Golden Exchange, Dept. 43B
Minneapolis, Minnesota
Offices in All Principal Cities

Send me a sample of Insulite and a copy of your free booklet "Increasing Home Efficiency."

Name _____

Address _____

City _____

State _____

For Efficiency
and Economy
be sure your
Refrigerator is
Insulated with
INSULITE

INSULITE

the Wood-Fiber Insulating Board

For Efficiency
and Economy
be sure your
Refrigerator is
Insulated with
INSULITE

Our Readers Say

Takes Rap at Our Critical Friends

HAVING missed but one number of POPULAR SCIENCE MONTHLY in five years, I believe I'm entitled to a word in "Our Readers Say" column. In the first place let me congratulate you on your success in keeping your publication interesting.

Personally I am interested chiefly in the ship model and home workshop section, but I believe your policy of variety is sound and above criticism. Now for the knocks. Why do you waste valuable space on the fellows who say your magazine should be barred from the mails because of articles on the Patent Office?

These "patriots" are trying to violate one of our fundamental rights, that of free speech and, if they don't like progress, cut off their water main, electricity, papers, and radio and see how they like that! Another type of fellow I should like to see barred from your columns is the one who pook-pooks science because his horse sense shows that science is wrong! Such people do not display horse sense but only ignorance and unjustified cockiness. Why waste space on them?—P. K., St. Louis, Mo.

But Everyone Isn't a Dr. Steinmetz

THE problem proposed by J. E. N., of Durango, Colo., is an old one. The story is told that a couple of engineers spent considerable time on it and finally put it up to the late Dr. Steinmetz, who after thinking for a few minutes, gave them the correct answer, which is 5.313 cubic inches. The problem is really an easy one. It can be solved by calculus, but it isn't necessary to use that process. Any person capable of visualizing the solid left by the two-inch drill, and dividing it into elements of volume, can perform the operation in his head. The volume of the hole bears the same ratio to the volume of a two-inch diameter sphere as the area of a two-inch square to the inscribed circle.—J. J. R., Kearny, N. J.

There's a Catch Here If Your Bait's Right

HERE is a problem that has been worrying me for some time. A dough is put into a sealed glass bowl in which there is nothing but water. After the fish breathes the oxygen out of the water there obviously will not be enough molecules of oxygen to make water. What then will be the nature of the compound in the bowl? Will it be hydrogen, oxygen, water, or what?—H. G., Plaquemine, La.



Finds Lost Inch With Perfect Ease

Isn't it odd how long pure dumb carelessness can perpetuate an obvious fake? I see the old sixty-four-inch square and sixty-five-inch rectangle wheeze has bobbed up again. It lasts only because people cut an inaccurate square from thin paper and fit the pieces together loosely in only an approximate rectangle. Absolutely accurate pieces, cut from bristol board or thin wood, will not fit together, and will reveal instantly that the rectangle has a rhomboidal hole of exactly one square inch area. The error may also be demonstrated mathematically by several methods.—J. G. H. Duncanson, Fla.

Hats Off While Grammarian Passes By

As you are always ready to print anything in the way of a correction, I am sending you this about faulty diction. First, in the caption, "Try and Drill Your Way Through This One." Some people try and really do a thing but we generally try "to" do. Second, on editorial page in article "Who Owns the Air?" in fourth paragraph, "And there is no doubt but what he has committed actual trespass." "But what" should not be used for the conjunctive expression. "But that," is correct. There are cases in which "but what" can be used correctly, as "I know nothing but what you have told me." However, POPULAR SCIENCE MONTHLY is the best ever.—H. E. D. Sturgeon Bay, Wisconsin



Readers Like You Are Our Best Advertisement

IF your magazine is superior to every other, how could I live fifteen years in the country and know your magazine by name only? The only solution I can offer is that you don't advertise your magazine sufficiently. The reading matter and illustrations are so interesting that anybody who knew of your magazine's contents would buy it.—O. H., Nashville, Tenn.

Five-Year Trial Proves We're Good

I HAVE been a reader of POPULAR SCIENCE MONTHLY for the past five years and I wish to compliment you and your staff on your December, 1930, issue. I enjoyed the article on miniature trains by Frederick D. Ryder, Jr. I have a very large miniature railroad myself and I look forward to his articles with keen interest. I have nearly all my copies of your magazine on file, for they contain much valuable information. I have

a workshop in my attic with a powered saw, jointer and wood lathe. I like wood turning and I hope you will put articles of this sort in your publication.—E. T., Durham, N. C.

Lands Squarely on "Too Much Aviation"

OF course we know that everyone cannot be satisfied, but we think that you are printing entirely too many articles about aviation. In your last issue there were five aviation articles in the fourteen others of general interest, including Home Workshop articles. How about other forms of transportation such as railways, buses, and boats? We, personally, are interested in railways more than the others but would like to see articles concerning all methods of transportation.—C. C. and R. G., Cincinnati, Ohio.



Couldn't Show Photo of Every Oven


IN a recent issue you show several pictures bearing the title "How the Staff of Life Is Made Here and in Foreign Countries." I should like to criticize those pictures very severely. The pictures you show of two are merely the methods used by the natives for the manufacture of bread while the bakers in those countries have some very fine bakeries. Take Canada, for instance. You have shown a small outdoor oven for family use while in the cities in Canada one may find some of the most modern bakeries in the world. In the picture representing the United States you show a large high speed dough mixer which you say shapes the loaf. This is wrong as the mixer merely mixes the dough.—A. J. G., Billings, Mont.

L. E. R. Takes One on the Button

IN the November issue of POPULAR SCIENCE MONTHLY L. E. R., of Louisiana, asks for more ship model construction articles and says that there are only a few people who care to build furniture. L. E. R. should inform himself better in the future. I have traveled in every state west of the Mississippi and in three Canadian provinces and every where have found people who not only enjoy furniture building but who are actually building it. I have seen hundreds of pieces of furniture patterned after the plans given in POPULAR SCIENCE MONTHLY, and I have heard many of them say that they



Wet feet breed SORE THROAT



gargle with Listerine— reduces mouth germs 98%

WET feet, sudden changes of temperature, over exposure, fatigue, all are predisposing causes of colds, grippe, sore throat and kindred infections.

They weaken body resistance so that germs in the mouth get the upper hand.

Reduces mouth germs 98%

As an aid in guarding against these troubles, medical authorities recommend the morning and night gargle with full strength Listerine, the safe, healing antiseptic and germicide.*

Listerine actually reduces germs in the mouth 98%. Kills them by millions, outright! Repeated tests following the methods used at famous

universities and laboratories of international repute prove its amazing germicidal power.

Gargle every 2 hours

Under ordinary conditions of health, the night and morning gargle is sufficient. But when you feel a cold or sore throat coming, or are already in the grip of either, increase the frequency of the gargle. Every two hours, authorities urge. Hold the liquid in the mouth as long as possible so that it reaches germ-ridden surfaces.

Such frequent gargling aids your body, weakened by the cold or

sore throat, to overcome millions of disease-producing organisms in the oral cavity.

Intelligent men and women everywhere use Listerine as both a precaution against and a treatment for colds, sore throat and allied infections. Keep a bottle handy in home and office and use it at the first symptom of trouble. Lambert Pharmacal Co., St. Louis, Mo., U. S. A.

Gargle every 2 hours



*Listerine though safe and healing in action is one of the most active germicides known. It kills even *Staphylococcus Aureus* (pus) and *Bacillus Typhosus* (typhoid) in counts ranging to 200,000,000 in 15 seconds (fastest killing time accurately recorded).

THE SAFE
ANTISEPTIC

LISTERINE

KILLS 200,000,000
GERMS IN 15 SECONDS

wished your magazine would publish more articles on furniture building. Please give us more on this line for there are literally thousands of us who are not like L. E. R.—H. A. E., Lone Tree, N. D.

Success of Others Perks Him Up

JUST a line to show my appreciation of our POPULAR SCIENCE MONTHLY. I say "our" because it has become as vital to me as to its editor and publisher. I keep four or five copies handy at all times, which I read and reread several times between editions. I read everything between its covers and find nothing that I would be content to leave out. When tired and discouraged I pick up POPULAR SCIENCE MONTHLY and read of other people's achievements, then think of the numerous failures and disappointments surmounted before each new creation. I forget my own troubles and glory in their spunk and success. I find things directly applicable to my own business (as all mechanics can in a book like this), which makes lighter and speedier work and stimulates the making of quick and correct decisions. All I say is, give us more of what we have, and anything else that is good.—O. B. H., San Luis Obispo, Calif.



Yazoo Delta Pleads for Fuse Plug Levee

IN A recent issue of POPULAR SCIENCE MONTHLY, I note an article on Mississippi flood control by General Jackson. Naturally this article caught my attention because I am an active sufferer from the periodic floods in the Yazoo Delta. After a careful reading of General Jackson's words, I can find nothing that holds out hope for the people of this region. To build our levees higher is suicidal, as we have not the foundation upon which to rest them. The 1928 act of Congress promised us Fuse Plug Levee at Cypress Creek on the Arkansas River. This Fuse Plug Levee is about to be denied us in favor of reservoirs. These are untimed defenses and will not give us any relief for a generation or more. Something must be done to lower the water line to the main river and so take the pressure off the levees. Our safety and future depend on the immediate opening of the Cypress Creek spillway and the widening of the river at Natchez and Vicksburg.—D. H., Fallala, Miss.

Sharpens Her Knife to Defend Lindbergh

IN spite of your article, "Air Progress from Lindbergh to Coste," I still think that Lindbergh's flight is the greatest in all the history of aviation. Lindbergh flew alone. His flight fired the imagination of the world, while Coste's flight did nothing of the sort. I insist that personalities win for aviation and Lindbergh has the personality. Most people do not know or care about the danger of flying the ocean. It was the twenty-five-year-old boy with the kid attitude who reserves to himself and plane as "we," who is responsible for our air-mindedness. Let's have more of Lindy in your magazine.—Mrs. M. B., Rochester, N. Y.



Has Flexible Stone from North Carolina

IN AN article in the December number of your magazine is the description of a piece of flexible stone. The article also states that "it is believed that a similar stone may be found in North Carolina." I have a piece of that flexible stone on the desk beside me. It was given to me by a jeweler about two years ago. He said it came from North Carolina. For three years I have had a subscription to the POPULAR SCIENCE MONTHLY and I surely was glad when you made two pages of "Our Readers Say." Can't you make it three just to please your fan?—J. M. W., Braddock, Pa.

Where We Would Be Without Railroads

I read in your "Our Readers Say" a letter signed W. J. M., of Macon, Ga. He states that when you say that railroads operate at sixty miles an hour you seem to overlook the fact that it takes a lot of force to hold a 300-ton train on the rails at that speed around curves. You say that railroads operate at this speed and over only because they have skilled operators and safety devices. You are perfectly right. If he does not agree I will let him know that the Union Pacific Railway has large, powerful, mountain-type locomotives that can do one hundred miles an hour if necessary, with a train of from ten to twelve heavy steel cars, and I have never known one of these engines to meet with an accident caused by excessive speed. I also see many others knocking the railroads, and giving aviation the highest praise. The railroads have for a century given the country invaluable service, and if they should stop operating, even the most earnest aviation enthusiast will have to admit that the country would be thrown into a state of chaos. Food would soon give out, automobiles and airplanes could not get gasoline, little or no freight could be transported, and business in the cities would be paralyzed.—S. P. B., Brooklyn, N. Y.



Gets Money's Worth Just As It Is

I HAVE noticed considerable criticism of POPULAR SCIENCE MONTHLY on "Our Readers Say" page. In general these critics tell you what you should cut out and what you should add to the magazine. Now in my opinion if you dealt only with one or two subjects you would not have a POPULAR SCIENCE MONTHLY but you would have more of a trade paper and then what would your circulation be? There are several parts that I do not read as I am not interested in the subjects treated and there are other parts that I would like to see more of but I would not ask for them unless I were in a position to pay extra for them. My hobby is models and small caltwork including freework and I can honestly say that I get good value from the magazine as it is.—P. M. D., Lussland, Canada.

Your Nut Problem Has Many Answers

YOUR correspondent, C. W., in POPULAR SCIENCE MONTHLY for December, 1930, is mistaken in thinking his African nut problem has only one solution. It has an infinite

number of solutions of the form $N-3125n-4$ where N is the original number of nuts and n is any positive integer. The smallest value of n is given by $n = 1, N = 3129$.—L. B. F., Washington, D. C.

Untrue and Ridiculous—Anything Else Wrong?

I find the article "America to Save King of Horses" in your November issue absurd and untrue. The subtitle, "Few Survivors of Fleet Arab Steed Left—Plans are Laid to Rescue Breed from Extinction," is ridiculous in the extreme. Do you know that here at Blida, Algeria, the French government has a remount station of over one hundred pure-blooded Arab stallions and that every spring these horses are placed all over northern Africa for the service of the Bedouin tribes and Europeans who care to use them? The French government also has several hundred pure-blooded mares loaned out to those who promise to raise a colt each year. The one thing in the article mentioned that stirred me up more than anything else was the statement that France is a monarchic hate-messed country. As I wish is that we Americans were as well organized as the French.—R. I. McC., Sohma, Nevada.



No Horse Sense but Answer Is Right

IN THE November issue of POPULAR SCIENCE MONTHLY T. R. W., Pittsburgh, Pa., said that horse sense, not algebra, was needed to solve the problem about how fast a stream flowed. By means of elementary algebra I proved that the stream flowed three miles an hour. No other method of solving would work and I should like to know how it is done by "horse sense." Probably I am dumb but I cannot see how horse sense would help in this case. Please publish some more problems.—R. D., Barrytown, N. Y.


Wants to Build Model of the Bremen

I HAVE made quite a few models from your plans, particularly airplane models. Looking over some old copies of POPULAR SCIENCE MONTHLY I ran across a drawing of the German steamship Bremen made especially for your magazine by H. G. Seidelstad, in your October issue of 1929, page twenty-two. I thought it would be an ideal model to build. If you could publish plans I think it would be a great piece of art work.—J. A. G., Ottawa, Can.

Why Does Rock Lose Weight in Water?

HERE is a question I should like to ask M. J. K., of Chicago, Ill. Is it the upward pressure of water that causes a rock to lose weight when it is submerged? My professor in physics said yes, but I always disagreed with him and he was never able to show where I was wrong though he had all the books on physics to back him up. If I am wrong I should like to be shown where I have made a mistake.—E. A. D., Garbham, N. H.





THE STEADY SCIENTIFIC PROGRESS OF THE BELL LABORATORIES SHOWS IN THE EVER INCREASING QUALITY AND SCOPE OF YOUR TELEPHONE SERVICE

To clear all barriers for the human voice

An Advertisement of the American Telephone and Telegraph Company

BELL TELEPHONE LABORATORIES, Incorporated, is the scene of a progressive conquest of natural forces that aims to let you speak clearly, quickly and cheaply to any one, anywhere in the land and even to distant countries. More than 5000 scientists and assistants are busy there and elsewhere in the Bell System studying the problems of sound transmission. Its work is the growing foundation of the telephone art; and it has, besides, helped to make possible the radio, sound pictures and special apparatus for the medical profession.

Among its achievements are the underground cables which make city telephone service possible, better and faster long distance service, service to ships at sea, and to millions of telephones beyond the seas. The steady

scientific progress of the Bell Laboratories shows in the ever-increasing quality and scope of your telephone service. Its new developments in every type of equipment clarify and speed up your telephone talks and give you more and better service at low rates. Every advance it makes is available throughout the Bell System.

The Bell System is an American institution owned by more than 500,000 stockholders. It places before you the benefits of its technical achievements and the co-ordinated efforts of more than 400,000 trained workers. It accepts its responsibility to further the development and welfare of the nation by furnishing the public the best of telephone service at the least cost consistent with financial safety.



Make it out of PRESIDWOOD

*this grainless
all-wood board
will serve you well*

FURNITURE

OUTDOOR SIGNS

KITCHEN CABINETS

TRUNKS-TOYS

INCUBATORS

RADIO CABINETS

TRUCK BODIES

AND 80 OTHER USES

VERIFIED Premium Quality is what you get when you use the grainless, board-like material with the smooth surface and uniform texture better known as Masonite. It's the only wood product that will serve you well in every use.

For example, in the home, it's ideal for making a sturdy, long-lasting cabinet or wardrobe. It's also perfect for making a sturdy, long-lasting outdoor sign. It's also perfect for making a sturdy, long-lasting kitchen cabinet. And it's also perfect for making a sturdy, long-lasting truck body.

In construction projects, Masonite is the ideal material for making a sturdy, long-lasting wall panel or ceiling panel. It's also perfect for making a sturdy, long-lasting floor panel. And it's also perfect for making a sturdy, long-lasting roof panel.

So, for every use, there's a Masonite product that will serve you well. And it's the only wood product that will serve you well in every use.


Masonite

VERIFIED PREMIUM QUALITY
MASONITE CORPORATION
MASONITE DIVISION

Increase home comfort—insulate your attic with Masonite Structural Insulation. For more facts, write to: Masonite Corporation, 10000 N. 10th St., Minneapolis, Minn. 55412. Or write to: K. J. Masonite, 10000 N. 10th St., Minneapolis, Minn. 55412. For more facts, write to: K. J. Masonite, 10000 N. 10th St., Minneapolis, Minn. 55412.

Send for
Free Booklet
Name _____
Address _____
City _____
State _____
Zip _____

Also, for more facts, write to: Masonite Corporation, 10000 N. 10th St., Minneapolis, Minn. 55412. Or write to: K. J. Masonite, 10000 N. 10th St., Minneapolis, Minn. 55412. For more facts, write to: K. J. Masonite, 10000 N. 10th St., Minneapolis, Minn. 55412.



Great oil well fire at Signal Hill, Long Beach, Calif. In the oil fields of this name state one of the record disasters of the industry occurred when firemen fought a burning well for 26 days before capping it.

How Wild Oil Wells Are Tamed

By JESSE F. GELDERS

MILLIONS of dollars may be lost when a gusher throws its oil and gas into the air, and efforts to choke it may take their toll of human life. To prevent these disasters now is the aim of all engineers connected with the hazardous work of oil drilling. This remarkable article tells why wells go on a rampage, what damage they then do, and the means employed to subdue these mad underground giants.

A NATIONAL Guardsman runs up to the door of a bungalow and taps imperiously.

"No fires here!"

Inside a man faces him, protesting. "But my wife is just cooking supper. It'll spoil. We've got to cook it."

"Sorry. No fire," the Guardsman repeats firmly. "Do you want to blow yourself up? And everybody else in this end of town? Put it out. Quick!"

The fire is extinguished. The Guards-

man hurries down the street. Five hundred other Guardsmen, firemen, police, and deputy sheriffs are busy in the threatened district, laboring without rest in a determined effort to save lives.

It is the southeastern sector of Oklahoma City late last fall. A little over a mile away, an oil well has gone wild. It is bombarding the sky with 60,000 barrels of oil and 100,000,000 cubic feet of gas a day.

The rusty black torrent shoots upward

Car Dial Warns of Deadly Gas

Attachment for auto shows presence of poisonous carbon monoxide which can be eliminated by adjusting carburetor—Use of device, inventor says, would stop waste of billion dollars a year for gas that, unburned, goes out into the air with exhaust.

By ALDEN
P. ARMAGNAC

A SIMPLE device that can be attached to any automobile in a few minutes may recently avert the peril of poison gas. Dr. Miller Reese Hutchinson, New York inventor and former chief engineer for Thomas Edison, announces that after two years' work he has perfected a "monoxide meter" for cars. It will warn a driver when his car's exhaust is belching fumes of the deadly carbon monoxide gas. Also, it will help him to get more miles to the gallon of gasoline.

The device is hailed as one of the most important contributions to automotive engineering in recent years. It comes from an engineer already noted for his inventions. If a motor horn baits you as you cross a street, the chances are good that it is one of a type that Hutchinson patented. Business men owe him a debt for the invention of a dictating machine. He has aided the deaf with more than one device to improve their hearing. Now this energetic, gray-haired man, at fifty-four, gives a new proof of his versatility.

Carbon monoxide, the evil fought by the new invention, is the gas that kills motorists who run their cars' engines in closed garages. A pall of it drifted by air hangs




Dr. Miller Reese Hutchinson of New York City demonstrating a model that tested the value of his monoxide meter.



The dial warns of deadly gas.

near the surface of city streets. Though the passerby might not notice it, the gas is thick enough to imperil the health of traffic officers and others who must stand in the street for hours at a time.

The gas is properly called "poison gas" because it is so deadly.



a mixture of gasoline and air. A perfectly-tuned car will not produce carbon monoxide. It is always a sign of imperfect combustion in the car's motor.

Two parts make up the "monoxide meter" which Dr. Hutchinson has invented. All that the motorist sees is a dial on his instrument board, a little larger than a watch, labeled "Combustion Indicator." Its little black needle fluctuates across a scale marked off in brightly colored divisions from "zero" to "fifty" and lettered "Percent of Fuel Wasted." When the needle swings toward the "fifty" side, it means that the exhaust is pouring carbon monoxide into the air. The motorist then can correct the trouble by readjusting his carburetor.

Unseen by the motorist but really the brains of the device is a little brass tube a few inches long clamped upon the exhaust pipe. It might be called a mechanical chemist. Constantly it samples and analyzes the gas rushing out through the exhaust.




Diagram makes clear how dial pointer is actuated.


who has seen a certain style of lighter for gas ranges in which a coil of "sponge" platinum thread a porous form of the metal glows when held over flowing gas, will understand at once how it works. This is of platinum, specially-treated in the process of making it glow.

The "catalytic" or uniting action of the platinum in both cases promotes a chemical process resembling combustion between the gas and air, and the platinum glows with the heat resulting.

In the gas-analyzing tube, the platinum strips are connected in an electrical circuit with (Continued on page 151)



The dial warns of deadly gas.



enough to hold the National Capitol with room for a White House or two in addition—and of the airship, which will hold 6,500,000 cubic feet of helium.

Probably few of those who are not privileged to walk from one end of the dock to the other and inspect the vessel at close range obtain a truly accurate impression of size. For instance, from the floor the airship looks as if it were almost scraping the roof girders of the dock. But, if you were to ride up the catwalk elevator that goes sidewise as well as up and down, you would find, upon viewing the busy scene from the catwalk 200 feet above the floor, that the top of the hull is actually several stories below your feet.

AT FREQUENT intervals on the busiest visiting days, a police officer turned orator tells the spectators about some of the features of the dock and the airship.

Someone inquires about the wires that look like the web of a giant spider. These wires are everywhere—lacing together the framework of duralumin girders that looks like a lacework of larger threads.

YOU could play a symphony on the bracing wires of the ship. The various lengths, diameters, and tensions employed cover a considerable portion of the musical scale. Steel piano wire, treated to make it corrosion-proof, is used throughout because it provides the greatest strength for a given weight. There will be between 1,250 and 1,500 miles of this wire in the completed ship.


Nine different diameters, ranging from .047 to .135 inch, can be counted. The wire is all put under a tension that varies from fifty to two hundred pounds. As a result the framework of the Zeppelin will have a rigidity and strength for all practical purposes as great as

if it were made in a single solid piece.

The largest wires are employed in the making of bulkheads—the network that separates adjacent gas cells. At the circumference of the huge, almost circular frames inclosing these cells, the bulkheads are attached to resiliency devices. These correspond to shock absorbers on an automobile. If a gas cell loses some of its helium the adjacent cells will have a tendency to expand and fill up some of the space. The resiliency devices will serve to keep such expansion under control yet permit an equalization of pressure.

Perhaps you would ask if you were visiting the dock, how the girders are fastened together. The answer is rivets—6,500,000 of them. It is a coincidence that there is almost exactly one rivet for every cubic foot of helium lifting gas the Akron will carry.

There is a little story behind those rivets. For one (Continued on page 118)



A view of the interior of the Goodyear Airship Dock in Akron. Above three stages of evolution of lighter-than-air craft. A Zeppelin is seen in the background, and a smaller airship is visible in the foreground.

Uncle Sam *Exposes* Fake Cures

Swindle Remedies, Tried in Government's Laboratory, Prove Worthless—Invalids, Seeking Health, Bunked Out of Millions

By EDWIN W. TEALE



Hanging yourself up by this phony device was guaranteed to increase your stature.

LESS than a dozen blocks from the White House, in Washington, D. C., a small group of men working in a laboratory saved American citizens \$20,000,000 in the last two years by exposing medical and mechanical frauds through scientific tests.

Known as "Collaborative Investigations," the laboratory is operated jointly by the United States Department of Agriculture and the Post Office Department to examine devices and concoctions which are sold through the mail on claims that are believed to be fraudulent.

More than 400 such frauds, calculated to extract money from the pockets of the gullible, were tested last year. They ranged from "Radium Glasses," promised to make the stone blind see, to "Infra-Red Ray Skullcaps," guaranteed to grow hair on a head as bald as an egg.

One of the weirdest of these fake devices was a "Height Halter," the use of which, it was promised, would add from two to six inches to the height of the buyer. It consisted of a collar arrangement, fitting around the neck, to which was attached two lengths of rope cable ending in handles. These cables were hung through loops from a bar or beam and the user pulled down on the handles, thus lifting himself up by the neck.

This was supposed to lengthen the spine and make giants out of pygmies. The funny part of it was that when the pro-

moter of the fraud was arrested, he proved to be only five feet four inches tall. His explanation was that he had been so busy selling his device to other people that he had never had time to use it himself.

As each new discovery of science is announced, the crooked quack proclaims it a cure-all and reaps a harvest from the sick and the gullible, unless he is stopped by the investigations in the Washington labora-

tory. was to throw the pipe in a fish bowl, attach one of the wires to his wrist and the other to his ankle, and sit and rock in a rocking-chair.

THE beneficial electric current which was supposed to be generated inside the pipe would flow through his system with its wonderful healing and curative powers and rid him of everything from rheumatism to cross-eyes. When the laboratory scientists examined the glorified gas pipe, it was found that the only way to see what was inside was to saw the pipe in two. When they did this, they found it was filled with gravel and sand.

Another device was more elaborate. It



Current from this handy little electrical device is controlled by the lever; only there is no current to control. The bottle was found to contain sulphur and graphite.

tory. At the present time, the catchwords most frequently used by the quacks are "electricity," "radium" and "infra-red rays." To the ignorant person these are vague, miracle-working terms from the world of science which suggest infinite possibilities.

"Electricity" is the "come-on" word most frequently employed. Not long ago, the laboratory examined a device selling for \$35. It was a small section of polished gas pipe with wires coming out of welded-in plugs at each end. All the user had to do



Here is the infra-red cap, advertised to cure baldness and incidentally stop all toothache.

was a bottle-like metal cylinder with a lever at the top that could be moved over a series of metal disks numbered from one to nine. Two wires coming from the apparatus were held in either hand.

The amount of the healing current that entered the system depended upon which of the disks the lever touched, the directions stated. When the lever touched nine, the maximum amount of electricity entered the body—which was exactly none. For, when laboratory workers broke into the cylinder by boring a row of holes up the side and sawing across it, they found that the main element in the mixture inside the device was dirt.

THE fact that alternating copper and zinc plates are used in batteries to produce electricity is frequently employed by quacks as a selling point for worthless devices "guaranteed" to work wonders.

The simplest of these frauds, which sold like hot cakes, was uncovered not long ago by the laboratory. It consisted of a copper plate to be worn in the right shoe and a zinc plate, to be worn in the left. The result, the promoter promised, would be a constant electric current running through the body "invigorating the nerves, toning up the system, and absolutely eradicating rheumatism."

Conter another crooked advertiser promised, could be cured quickly by wearing a string of "electric beads." Between each of some two dozen amber beads was a tiny zinc plate, and the whole was strung on a copper wire. The electricity, which was supposed to be generated


by the copper and zinc coming in contact, was expected to stimulate mysterious glands in the neck and cause the goiter to disappear.

The most elaborate of the devices based upon this form of deception was an outfit known as "Heart Batteries." Strapped to the front of the body, just over the heart, was a large copper plate. On the left side of the back, a zinc plate was held in place by similar straps. The electric current was said to pass through the body from one plate to the other, purifying the blood as it entered the heart and preventing hardening of the arteries.

Even in examining such self-evident frauds as "Electro-Chemical Rings" guaranteed to extract acid from the blood, the laboratory



At top, the magic churn that was said to turn one pound of butter into two. At bottom, was used a pound of good butter. Immediately above the "cure" for tuberculosis. It held nothing but charcoal, sulphur, and oil.



In center, the sex tester—a little red peg that was supposed to tell the sex of the unhatched chick. In circle, the fat reducer—a vacuum cup to draw off surplus flesh.

must make searching tests. Often one of the workers will follow the directions for the use of the fake electric device while a sensitive galvanometer shows if any current is passing through his body—which, of course, there isn't.

No matter how wild the claims, the laboratory, to obtain a conviction, must have absolute proof that they are fraudulent. The promoter is considered innocent until he is proved guilty. So there must be no loophole left for the wily crook to slip through.


WHEN a complaint reaches the Chief Post Office Inspector from someone who has been duped by a curative fraud, he sets into motion the wheels of an official investigation. Evidence is first obtained that the mails were used in selling the worthless device or compound.

After that, the Collaborative Investigations laboratory begins its examination and makes its report. Then the Solicitor for the Post Office Department hands down a decision as to whether the law has been violated and the defendant is given a hearing.

If he is convicted the Postmaster General issues a "Fraud Order." This bars the promoter's advertising from the mail and returns all letters addressed to him to the senders stamped "Fraudulent." Those who are cheated by such frauds can best help in catching the crooks by

(Continued on page 14)

Calls Our Sun Huge Electric Light



Measuring the sun's heat at Smithsonian Observatory, Table Mountain, Calif. Coelostat, at right, reflects rays to bolometer which records millionths of degree.

Government astronomer advances amazing new theory as to cause of solar activity—Power generated there so vast human mind cannot imagine it—What observers learned from eclipse

By ROBERT E. MARTIN

OUR sun is a huge electric light. All the stars, suns more or less like ours, are twinkling electric lights each with a filament a hundred thousand miles in length.

This is the startling new theory of the nature of the sun and of the universe advanced recently by Dr. Ross Gunn, of the United States Naval Research Laboratory, Washington, D. C. Dr. Gunn says that electricity runs the sun and that it glows exactly as a man-made incandescent electric lamp glows.

Millions of volts of electricity, he told me, turn the solar atmosphere into a vast incandescent filament that furnishes our light and heat. So great is this flow of power that he estimates, if it were paid for at present rates, the entire wealth of the United States would be required to keep this celestial lamp shining for one millionth of a second.

For more than four years, Dr. Gunn has been working upon the intricate mathematical calculations which have led him to his revolutionary conclusion. Astronomers at Mount Wilson Observatory, California, have made careful measurements of the strength of the magnetism around the sun.

These studies showed that the sun is a magnetic field similar to that of the earth. Starting with these observed facts, Dr. Gunn began his calculations and built up his theory that explains several of the hitherto baffling puzzles about the hub of our universe.

From the surface of this giant star, he assumes, there are streaming into outer space ions charged with negative electricity. In passing through the solar atmosphere, which consists of the reversing layer nearest the sun, the chromosphere above it and the shooting, flaring corona at the outer limits, the electrified particles meet resistance. As a result they heat the gases to incandescence, just as does the electric current passing through the filament of an ordinary bulb.


For nearly a century, astronomers have noted a perplexing fact about the rotation of the sun. Instead of spinning like an ordinary sphere, different parts rotate at different speeds. By timing the reappearance of sun spots, watchers found that at the sun's equator a revolution took twenty-five days. Halfway to the poles there was a lag of two days, while at the poles a complete turn requires six days longer than at the equator.

More than this, the speed with which the sun revolves is not constant. The flaming ball speeds up and slows down. Over a period of five or six years, the

pace at which it rotates may alter as much as seven percent.

Dr. Gunn's theory suggests a solution for these mysteries. The action of the electricity in the upper reaches of the reversing layer and the chromosphere, he says, produces a wind in the solar atmosphere. This "electrical wind" reaches a speed of about 1,200 miles an hour at the equator, but blows slowly at the poles.

"Since an astronomer on earth can see only the atmosphere of the sun," Dr. Gunn points out, "he sees this high wind superimposed upon the ordinary rotation of the sun proper and he naturally reports that points on the equator rotate faster than points near the poles. Variation in the speed of rotation may be due to the variation in the strength of the electrical wind."



Above, at right, is the 2,500-pound Einstein camera, carried to "Tin Can Island" and mounted on concrete pillars. In circle is picture of eclipse showing corona.




Dr. Ross Gunn, right, explains his theory of electric energy in our sun.

which have puzzled astronomers.

A solution for another mystery of the sun is offered by the new theory. Many of the observations made at Mount Wilson indicated that the sun is a uniformly magnetized sphere like the earth, but in one respect it is strangely different. This is in the suddenness with which its magnetic force decreases as it leaves the region of the star.

If you hold a common horseshoe magnet close to a tack,



This drawing shows the activity and peculiar behavior of the sun. Dr. Gunn's theory explains these phenomena.

the tack will leap across the intervening space and stick to the ends of the magnetized metal. But when you move the magnet farther away, the force of its magnetic attraction becomes less and less. In the case of a uniformly magnetized sphere the strength of its pull decreases at a known rate as the distance from the surface of the sphere grows greater. By mathematical calculations, this reduction in pulling power can be determined for 100 miles, 1,000 miles, or a million miles out in space.

Such computations have been made for the sun. But, when observatory spectroscopes were trained on points a known distance from the sun, during eclipses the result was a surprise. The shift in the lines of the spectrum showed that the magnetic force dropped off 7,000 times as rapidly as the computations indicated it should. Why? Dr. Gunn's theory

magnetic field as revealed by the spectroscope.

The size of the current that leaves the surface of the sun and the voltage necessary to force this tremendous stream of power through the solar atmosphere have been computed by Dr. Gunn. He places the total power in kilowatts at four hundred thousand billion (four followed by twenty-three ciphers)—a display so vast that the output of all the generators in America, working at top speed, would compare to it as a drop of dew compares to the Atlantic.


Where does this tremendous electric current originate? What is the power house that has kept this electric light of the heavens burning for more than a million million years?

The answer to these questions, Dr. Gunn says, is to be found in subatomic conversion, (Continued on page 136)

Streamers of flaming gas thrown from sun's surface may reach a height of 100,000 miles, as in latest eclipse.

offers an ingenious answer.

The electrified particles that stream into the thin solar atmosphere, he suggests, spiral many times before they collide with other particles. These whirling charges of electricity produce the same effect as a current traveling in a circle. They form a great many billion of invisible electromagnets which are so arranged in direction as to produce an "opposing magnetic field," a great "network" of spinning electromagnets holding in or reducing the strength of the magnetic force below. This accounts, Dr. Gunn believes, for the unexplained drop in the strength of the



Pernicious Anemia Cure Wins Our \$10,000 Annual Award

POPULAR SCIENCE MONTHLY'S Committee Selects as the Outstanding Scientific Achievement the Discovery of a Successful Treatment for a Fatal Disease made by Drs. George H. Whipple of Rochester University and George R. Minot, Professor of Medicine at Harvard.

FIRST bestowal of the POPULAR SCIENCE MONTHLY Annual Award of \$10,000 for the current achievement in science of greatest benefit to the public was made on December 18 at a brilliant gathering of the country's foremost scientists and business and industrial leaders in the University Club, New York City.

The achievement singled out for the distinction was the discovery of a cure for pernicious anemia, the fatal and mysterious malady which has baffled physicians for generations and hitherto was considered incurable. The selection was made by twenty-one outstanding men of science constituting the Committee of Award.

The prize was conferred jointly upon Dr. George Hoyt Whipple, dean and professor of pathology of the School of Medicine and Dentistry in the University of Rochester, who discovered the principle of the cure and Dr. George Richards Minot, professor of medicine in the Medical School of Harvard University, who perfected its application to human beings.

Dr. Whipple and Dr. Minot each was presented with \$5,000 and a gold medal commemorating the Award.

The selection of the prize-winning accomplishment was a prodigious task. In its efforts to find the current scientific achieve-

ment of greatest benefit to humanity, the Committee of Award thoroughly covered the entire American field of scientific endeavor.

Shortly after the creation of the Award, the Committee secured the cooperation of every university and college in the country, all of the scientific societies, every industrial research organization and various departments of the United States Government. In all, communication was established with nearly 1,800 organizations.

THESE bodies were asked to appraise the Committee of any outstanding accomplishment they deemed deserving of the Award within their own or any other field. Soon, nominations representing virtually every department of scientific endeavor began to pour in. The names of hundreds of candidates were submitted, and their number was further increased by numerous suggestions from individuals, among whom were many readers of POPULAR SCIENCE MONTHLY.

The Committee now was faced with the task of investigating the merits of each claim. This was done with the utmost care until the number of contenders was reduced to 117. It was from this number that the final choice was made.

Like many other important discoveries, that of Dr. Minot and Dr. Whipple es-

entially is very simple. Fundamentally, it is that a diet of liver will cure a sufferer from anemia and pernicious anemia. Working independently of each other, they both found that the organs of certain animals and birds, such as the liver, the kidney, the heart and the walls of the stomach, but especially the liver, contain chemical substances that stimulate the formation of red corpuscles in the circulating blood.

ANEMIA merely means a diminution in the red corpuscles and in the hemoglobin, which is the normal coloring matter that makes them red. It is a very common disease among human beings, and goes back as far as the history of medicine itself.

Broadly speaking, there are two forms of anemia—primary and secondary anemia. Secondary anemia is the kind which accompanies some other disease, such as cancer or tuberculosis, or which is caused by the loss of blood. As a matter of fact, anemia occurs in most chronic diseases and also in several acute ones.

Primary anemia is pernicious anemia. It is in itself a major disease and its essential cause still is one of the unsolved mysteries of medicine. Until Dr. Whipple and Dr. Minot made their discovery, a diagnosis of pernicious anemia in the vast majority of cases amounted to a death warrant for the patient.

It was Dr. Thomas Addison the famous British pathologist, who first noted and studied the disease. Forty years ago, he described its symptoms and progress thus:

The whole surface of the body presents a bronzed, smooth and waxy appearance, the lips gums and tongue areer bloodless . . . appetite fails. Extreme languor



Dr. Frank B. Jewett, Chairman, and Dr. C. G. Abbott, Secretary.

COMMITTEE OF AWARD

DR. FRANK B. JEWETT, CHAIRMAN

DR. C. G. ABBOTT

DR. SAMUEL A. BROWN

Professor of Pathology and Medicine, Harvard Medical School

DR. GEORGE K. BURGESS

Professor of Pathology, Harvard Medical School

DR. WILLIAM W. CAMPBELL

Professor of Pathology, Harvard Medical School

DR. HARVEY N. DAVIS

Professor of Pathology, Harvard Medical School

DR. ARTHUR L. DAY

Professor of Pathology, Harvard Medical School

DR. F. F. FREE

Professor of Pathology

DR. VERNON KELLOR

Professor of Pathology, Harvard Medical School

CHARLES F. KETTERING

Professor of Pathology, Harvard Medical School

DR. ARTHUR D. LITTLE

Professor of Pathology, Harvard Medical School

DR. JOHN C. MERRIAM

Professor of Pathology, Harvard Medical School

DR. ROBERT A. MILLIKAN

Professor of Pathology, Harvard Medical School

PROF. HENRY FAIRFIELD OSBORN

Professor of Pathology, Harvard Medical School

DR. S. W. STRATTON

Professor of Pathology, Harvard Medical School

DR. THURGOOD THOMSON

Professor of Pathology, Harvard Medical School

DR. EDWARD R. WEIDEN

Professor of Pathology, Harvard Medical School

HENRY H. WESTINGHOUSE

Professor of Pathology, Harvard Medical School

DR. ALBERT F. WHITE

Professor of Pathology, Harvard Medical School

DR. WILLIS R. WHITNEY

Professor of Pathology, Harvard Medical School

ORVILLE WRIGHT

Professor of Pathology

years later in 1924 when he was back at the Massachusetts General Hospital in charge of a special clinic after various connections with the Harvard Medical School and the Johns Hopkins Hospital in Baltimore, Md. that he developed his liver treatment.

Dr. Whipple began his experiments thirteen years ago when he was professor of research in



Obverse of gold medal presented to the winners of \$5,000 honor award.



Reverse side of Popular Science Monthly medal with honors inscription.

and fairness supervene breathlessness being produced by the most trying exertion or emotion. The patient can no longer rise from his bed the mind occasionally wanders, he falls into a prostrate and half-torpid state, and at length expires.

And for this dreadful malady there was no known cure. The situation that prevailed from the time Addison wrote his description until Dr. Whipple and Dr. Minot perfected their methods of treatment may be summed up in this terse statement by a New York physician:

"Nothing can be done for a pernicious anemia patient except to make him as comfortable as possible."

Now all this has changed. Today pernicious anemia is curable. By taking it once for all out of the class of incurable diseases, Drs. Minot and Whipple have conferred a boon upon mankind.

Briefly, the problem confronting the medical world was this: What will stimulate an increased formation of red blood cells?

The manner in which these two men set about to solve it constitutes one of those unheralded but thrilling battles with death in which the romance of medicine abounds. They arrived at virtually the same point by traveling widely different roads. Dr. Whipple's investigations were of the experimental or laboratory variety, the work of Dr. Minot, a practicing physician, was clinical and practical.

Dr. Minot first attacked the problem in 1913, when, twenty-seven years old and recently graduated from the Harvard Medical School, he served his internship at the Massachusetts General Hospital in Boston, and began the special study of the diseases of the blood that was to become his life work. But it was not until eleven

years later at the University of California, at Berkeley, California. The results of his work did not become known to the medical world at large until 1922, while those of Dr. Minot's activities were made public only as recently as 1926.

THE first step in Dr. Whipple's experiments was to raise a number of dogs in his laboratory kennels. Dogs have the same blood count as human beings, meaning that a normal dog like a normal man, has from 5,000,000 to 6,000,000 red corpuscles per cubic millimeter of blood. He gradually bled the dogs down to about one third the normal count, thus inducing severe anemia and kept them in that condition for the rest of their lives. Some of the dogs remained anemic "patients" for six years.

In his study the animals reacted sharply to various diets they were fed, offering Dr. Whipple the opportunity to ascertain what kinds of food, if any would cure anemia. A large number of foodstuffs were tested in that way over a number of years.

As a result, Dr. Whipple found that liver was by far the most powerful and quickest factor in stimulating the production of red blood cells. But it must be liver from mammals or birds. Fish liver, the tests showed, contains only a trace of the chemical that restores red blood.

Kidney and chicken gizzard come next, being about three fourths as effective as liver. Sweetbreads are about half as beneficial as kidney. Steak rates low with only half the effect of sweetbreads, or one fifth that of liver.

Brood grains, milk, and cheese were shown to have very little value in fighting anemia. On the other hand certain fruits, such as apricots, peaches and prunes, are surprisingly helpful, possessing about half the potency of liver.

To realize fully the importance of this

Widely Separated Inventors Develop Systems to Open Garage Doors with Radio Impulses

Your garage doors are opened by radio as you drive up when this device invented in Spokane, Wash. is used on the garage.



An Illinois firm developed this system which opens the doors when knob is pulled.



Pressing the button on the instrument board of your car releases impulses to open doors.

WHEN you drive home late at night there is no need to step from the car—a cold wind or a driving rain to open the garage doors. Instead, touch an inconspicuous button on the instrument board of your car—and radio opens the doors for you.


Perfection of the new radio door opener is announced simultaneously by an Illinois manufacturer and by a pair of Spokane, Wash., inventors as another evidence of coincidence in real life.

When the driver pulls out a knob at the left of the cow and lets it go, in the Illinois system, a timer in a small box beneath the instrument board starts to send coded electric signals. Stepped up to high voltage for transmission by a spark coil in a watertight case on the car's frame, they are "broadcast" as a radio message

in code by an antenna—two insulated wires beneath the car.

As if by magic, the doors swing open and the light at the garage door is automatically turned on. The radio signals have been picked up by a second antenna buried in the driveway, and actuate a one-tube receiving set and electric control similar to a device that railroads use for automatic train control. Electric motors open the garage doors, which lock in the open position. When the car is in the garage, another touch of the radio button closes the doors. A person standing inadvertently in the way of the opening or closing doors cannot be hurt, for an "overload release" automatically stops the motors if the doors strike any object, and must be reset by pulling a chain before it will work again.

Closely resembling this system, outwardly, is the radio door opener devised by the Spokane inventors. The control button, at the right of the instrument board, is pressed to operate the doors. The principal difference, however, is the method of protecting cars from possible theft. It depends upon having the receiver tuned to respond only to the particular



Close-up of the safety mechanism that stops doors, when moving, if they strike a person.


wave length broadcast by the spark coil on the car, instead of to coded radio impulses. (Of course with a wave length check, it would be possible to tune through and eventually find the right wave to open the doors. With a code system there would be no chance to activate the control without discovering the right code, a practically impossible task within the time limit that a car thief could give himself.

THIS AUTO TURNTABLE SAVES BACKING

BACKING into and out of garages in small suburban homes may be eliminated by an automobile turntable that swings a car around in its own length, just as locomotives are handled at railway round-houses.

A revolving platform large enough to take standard-sized pleasure cars is controlled either by hand or electric power. When electric drive is used, it is operated by a push button on a cord suspended over the table, just as an electric light is turned on in the house. The driver can operate the table in this manner without getting out of the car. The table makes but one half revolution before stopping.

Should hand operation be desired, the apparatus is so perfectly balanced and according to its inventor turns so easily that a child can operate it. Use of it is said to have solved many problems of garage design where the building has to be placed on small lots.



Backing your car out of a small yard is unnecessary if one of these small turntables is installed. It is operated easily by hand or its mechanism can be hooked up and run by electricity.



FLUTE, 20,000 YEARS OLD, FOUND IN NEVADA CAVE

Who played on a pair of flutes found recently in Gypsum Cave, Nevada? Students of primitive man say these flutes and small darts called "atlatl" found with them, are the most important ethnological discoveries ever made in America. In the opinion of M. R. Harrington, curator of the Southwest Museum, they prove that human beings lived in America 20,000 years ago and had developed even then a distinct culture.

SCREW CAP CONNECTS ELECTRIC WIRES

Joining ends of electric wires without solder or tape may be done with a handy new screw cap made of molded composition with a threaded metal core. Insulation is scraped off the wires, which are held together parallel to each other, and the cap is screwed over them. Threads on the inside of it cut into the soft copper wire, gripping it securely and making contact. It can be put on or taken off as easily as a nut is screwed on or off a bolt.




This insulated cap screw joins electric wire ends quickly by firmly screwing into copper.

UNCLE SAM HAS RAILWAY IN ALASKA AND PANAMA


Of all railways in the United States and its possessions, the one farthest north is in Alaska and the one farthest south is in the Isthmus of Panama, and both are owned by the United States Government.

The Alaska railroad, put in operation in 1925, runs to within 120 miles of the Arctic Circle. Seward and Fairbanks are the terminal points of its 470-mile main line, over which trains make three round trips weekly during the summer season. As yet this railway, which cost its owner \$60,000,000, has not been a financial success.

The Panama railway, forty-seven miles long, was built before the Civil War as a link in the transportation chain between the Atlantic and Pacific coasts. Many "Forty-niners" found it convenient to use this railroad in making the trip to California. The road has always been a financial success. During the first ten years of its existence it carried \$700,000,000 worth of gold and 300,000 bags of mail.



DOES THE MOON GO ROUND THE EARTH?



If our world were stationary in space the moon would travel in a nearly circular path around us. However, both the earth and the moon are rotating around the sun and the actual path of the moon through space is, therefore, a circle made with a wavy line much like the path of a snake traveling around in a circle.

Furthermore, if you plot the orbit of the earth round the sun to a scale which will make it 400 inches (thirty-three and one third feet) in diameter,

the orbit of the moon would be only one inch. At no point would the plotted path of the moon be convex toward the sun.

Speaking in the absolute sense, the moon doesn't revolve around the earth at all. It revolves around the sun in company with the earth.

And if you wish to dig in still deeper, you will find that the sun together with all the planets is traveling through space as a unit at tremendous speed. To an observer on another star the moon's path would appear to be a complicated sort of a spiral. The shape of the spiral would depend on which star the observer chose as an observation point.



BIGGEST ROLLER BEARING WEIGHS 3 1/2 TONS

LARGEST of its kind, this huge roller bearing could carry more load without crushing than a 100-car freight train. It has just been completed along with twenty-seven others like it, for an immense steel mill. The monster three-and-one-half-ton bearing will support rolls that crush steel bars into thin plates, it is claimed by the makers.

By way of contrast, the young woman in the picture holds a standard seven-ounce roller bearing designed for an automobile wheel, thus giving an idea of the size of the giant roller.

VALVES FOR CRANK CASE EASILY DRAIN OIL

DRAINING the oil out of your car is made easy by a new valve that screws in to the hole at the base of the crank case in place of the nut with which most cars are provided. The valve is turned easily with a pair of pliers.

The new valve is sufficiently short to clear any bumps in the road and rugged enough to escape damage from flying pebbles thrown by the wheels. It is made in sizes threaded to fit nearly all makes of cars and is easily installed.



To facilitate the task of draining oil out of your car, this valve fits into the crank case.

"SKI HOPPING" IS STUNT FOR EXPERTS



RUNNING deer expert skiers at St. Moritz, Switzerland, recently gave an exhibition of progress in a series of springy jumps, called "ski hopping." Ordinary travel over open country with skis is difficult but to maintain a speed that enables the user to take off in short successive jumps calls for sking ability of an unusual degree. Only experts can practice the sport of ski hopping. In the photo above, four skiers are in the air.

CRAG LO SKI is a new Alpine sport that only the most expert can hope to enjoy.

SQUIRREL CAGE TRUCK COLLECTS ASH CANS

STRANGE looking trucks have been designed in London, England, for removing ashes and refuse in a quiet and sanitary manner. A rotating framework carries shelves that work like cars on Ferris wheels on which ash cans are stacked. These are of special design having securely fastened covers. When they are filled the cover is closed and fastened and the truck removes the entire can to the dumping grounds, leaving a sterilized "empty" in its place.

Special truck frame.



MAKES MILLION BALLS A MINUTE IN ROTARY KILN

A million hollow clay balls a minute are turned out in a California pottery works that uses what is believed to be the largest rotary kiln in the world. Dr. Knapp




A million clay balls a minute are made in this rotary kiln which is turning out a new kind of brick developed by a Los Angeles engineer.

manufacture of a new style of building brick. The finished bricks are one sixth as heavy as common ones without sacrifice of strength according to Dr. Harding. After baking, the bricks go from the kiln as left above, to the elevator where they are annealed while going up and cooled as they drop from the chute.

FOLDING NINE-INCH RULE IS PART OF NEW KNIFE


A useful pocket "helper" handy men and mechanics is this knife into which a measuring scale has been built. Besides two standard large and small knife blades, it contains leaves that unfold to make together with markings on the knife's back, a nine-inch measuring scale. One side is graduated in inches, the other in centimeters.



This unusual truck for ash cans recently made its appearance in London. The carriage revolves for loading but the cans are always right side up.



Leaves that fold inside the handle of this knife will open up to form a nine-inch measuring gage.



Cine-theodolites trained on plane to take four pictures a second while it is being test-flown

ALUMINUM STRONGER IN GREAT COLD

IN THE bitter cold of high altitudes at which some airplanes operate, aluminum becomes stronger than in warm surroundings. This was the real conclusion reached when samples of the metal, widely used in aircraft construction, were recently tested at seventy-five degrees Fahrenheit and, then at a temperature of 112 degrees below zero, in a Pittsburgh, Pa., metal manufacturer's research laboratory.

One sample of duralumin, an alloy in which aluminum is used, showed an increase in strength of almost three per cent when given the cold test. This means that if it broke under a load of 1,000 pounds at a temperature of seventy-five degrees, at 112 below zero it would stand an additional load of thirty pounds.

Some samples tested showed an increase in strength of eleven percent.

AIRPLANES OF FUTURE MAY LOOK LIKE THIS


WHAT will the airplane of the future look like? When a Los Angeles, Calif. movie engineer was asked to design such

PLANE TESTS CHECKED BY INSTRUMENT ON GROUND

A NOVEL German instrument which combines movies and telescope is now in use in Germany to make a record of every feature of an airplane test flight.

Three of the instruments are set up and kept focused on the plane during the test. Exposures at the rate of four to the second produce a film record that indicates the exact position of the plane during every instant of its flight.

In this way the speed of the plane in flying from one point in the air to another can be accurately determined. Any test evolutions the plane performs can be plotted with equal accuracy as to position, angle, distance, and so on, entirely eliminating any guesswork.



A section of film made by cine-theodolite showing position of plane at various angles

a craft for a scenario, he produced the remarkable model. He visioned a vehicle of a coming age as a craft driven by rockets, of which the tubes may be seen projecting near the bullet-shaped head. The body is streamlined, as if for a high-speed jaunt of a thousand miles an hour through the thin air at outer space several miles above the surface of the earth.

TREASURE SEEKERS STILL ACTIVE

THE glitter of gold sunk on trojic ocean floors centuries ago in Spanish galleons still attracts treasure seekers.


Reports from Spain show that last year alone more than 3,000 people made the trip to old Madrid from all parts of the world for the express purpose of searching old government documents for clues to the possible locations of wrecks of gold ships sunk long ago.



NEW AIRSHIP MAST LETS TAIL SWING WITH WIND

A METHOD of docking large dirigibles by use of two mooring masts is the invention of Dr. Alfred Lee Wilkes, of Los Angeles, Calif. An airship's nose is brought down to a bow mooring mast, while the other mast, to which its tail is secured, moves around it on circular tracks. Automatic control of machinery which actuates the movable mast insures that the airship will be head to wind at all times, while its tail is held from veering wildly in gusty winds. This tendency to veer has caused several near-accidents in the past. The inventor believes smaller ground crews will be able to handle large airships easily by using his equipment.

The illustration above shows how the tail of the dirigible could swing in a circle toward any point of the compass while the nose would remain fixed to a point around which the craft could rotate.



Will airplanes of the future look like this? A Los Angeles engineer made this model to show possible design of high speed rocket driven aircraft.

Seek Airports in Arctic Ice

Flying route to Europe may cross ice fields of Greenland—Dynamite used to blast path as explorers seek site for airplane landing field on frozen plateau



Members of the exploring expedition stopped in the hug of a crevasse in the Kamarujuk glacier.



WILL the first successful air run to Europe cross Greenland ice, as Vilhjalmur Stefansson, famous polar explorer, and many air experts have suggested?

To determine whether an Arctic air line is practicable, a party of German explorers led by Prof. Albert L. Wegener noted geologist, is spending three months on the trackless ice sheet that covers Greenland. They seek to find out how thick it is, how it got there, and whether anyone can live on it, walk on it, and land on it in an airplane. Split in three groups, the expedition is exploring the east coast, the west coast, and the high ice plateau of the interior.

If landing places for planes can be found here, the last-needed link will be added for an airway that can span the Atlantic in jumps of less than 400 miles, as the accompanying map shows. Elsewhere along the route, landing fields are already established.


Besides the investigation of air line prospects, the Wegener expedition is studying the physical nature of the ice cap and its glaciers. Elaborate weather observations are being made with the aid of captive balloons, sent to heights as great as seven miles. These data will be supplemented by records secured by a British surveying expedition, also in the field.

The Germans introduced an innovation in Arctic exploring when they recently put into commission two motor-driven sledges with air propellers, which roar across smooth ice at fifty miles an

At upper right, one of Wegener's parties is hoisted from ship to Greenland's shore. At right, dogs were often used to leap the crevasses, but make travel dangerous on a glacier.

hour. Each, at last reports, had made two dashes to the inland depot, 124 miles from the sea, with loads of 1,000 to 1,200 pounds.

When the going is bad, however, only dog teams and heart-breaking toil can get the supplies through. In order to ascend the treacherous Kamarujuk glacier, on the west coast, it was necessary to blast a path with fifty charges of dynamite. As the ice reflects sunlight, it was sprinkled with snow so it would absorb the sun's warmth, which would melt it.



Map shows proposed America-Europe air line crossing Greenland with 400 miles as longest water jump.



Prof. A. L. Wegener, German explorer and geologist, head of Greenland expedition.



Sledges packed high with food and other necessities were dragged sometimes by the men, into a most inaccessible frozen desert.



In the bitter cold of this wind-swept plateau, everything froze solid, including the flag, as can be seen in this picture. This hut stands on an icy upland that is 8,000 feet high.



Drilling into Greenland's ice. Wegener's expedition is seeking to learn the thickness of the ice cap in this little-explored region.

AMERICAN ARMY GETS TALKING GAS MASK

THE latest development in antigas equipment in the United States Army is a mask through which the wearer can talk. It permits him to use his voice to keep in touch with his comrades instead of muffling him as have all other masks in use up to the present.

A diaphragm carries his voice outside the device while preventing gas from entering it. In testing out the new apparatus wearers carried on telephone conversations easily and distinctly. The masks are expected to prove a benefit to scouting parties which must keep in constant communication by telephone with main bodies of troops in a gas attack.



Wearing the old gas mask, left, a soldier could not talk. With the new one, right, he can carry on conversation in safety.

NEW METHOD MAKES HARD COAL IN FEW HOURS

NATURE requires millions of years to make hard coal, but engineers in Chicago, using an entirely new process, are making it out of soft coal in a few hours. This achievement will make "synthetic" hard coal available for industrial use, which in turn will result in cleaner cities and factory districts, for the new fuel is said to be smokeless. Valuable by-products are extracted and used, instead of escaping up chimneys as waste matter as they do at present.

Soft coal, in the course of this process, is made to part with its moisture and two thirds of its volatile or smoke-forming matter. About 1,400 pounds of "char," the left over material, is obtained from a ton of soft coal. This is ground to a powder, mixed with a petroleum binder to make it stick together, and compressed into briquettes. The plant just put into operation in Chicago is the first of a series to be erected throughout the country.

TWO EXTRA WHEELS ON MOTORCYCLE SO IT CAN BE TOWED

A motorcycle with two small additional wheels that can be lowered, so the machine can be towed behind a motor car is the novel idea of a San Francisco automobile company. The job of calling for and delivering cars is facilitated by its use, for the mechanic delivering a machine tows the motorcycle behind it.


A special frame is fitted to a motorcycle that is standard in other respects. When the small side wheels are dropped for towing they automatically raise the power wheel off the ground.

COWS GO TO PASTURE THROUGH A SUBWAY

Cows in a California dairy get to and from their work by subway. A traffic-crowded highway lay between the dairy buildings and the pastures, constantly endangering the cattle when they crossed it. In order to safeguard the animals a cement-lined tunnel was built under the road for the exclusive use of the cows.



To keep his cows out of highway traffic a dairyman built a subway to their pasture.



towed, is designed to expedite work of mechanics who call for or deliver cars.

SCENARIO WRITER HAS PLOT MAKING ROBOT

A MECHANICAL robot that turns out plots for brain-fagged authors is the invention of Wycliffe A. Hux. Los Angeles scenario writer Christened "Shakespeare's ghost," this device is said to produce a complete outline of a fiction story in twenty minutes, to an accompaniment of whirring gears. It selects background characters and dramatic situations from a series of tapes.

MAY STRING VIOLIN BOW WITH SILVER THREADS

HORSEHAIR, which for hundreds of years has been used for stringing violin bows, may soon give place to another material. A German violinist has been experimenting with bows strung with fine silver wire that has been slightly roughened. Great sensitiveness and brilliance of tone are achieved, it is said, with the new strings.

RESEARCH TRIES TO FIND CAUSE OF GRAY HAIR

Gray hair and baldness recently came in for special attention by scientists.

In New York City sixteen barbers have been enlisted by Dr. Norman Macleason, acting for Columbia University's department of anthropology, to aid in collecting samples of gray hair from their patrons. The object is a survey to find how the graying of the hair is affected by age, sex, and occupation. Barbers receive five cents for each specimen lock shorn from a customer's temple and submitted, with appropriate data, for a microscopic examination.

Meanwhile, a cure for one special type of baldness was reported to the American Chemical Society by Dr. C. N. Myers, of Brooklyn, N. Y. He described a drug known as sulfactol, which had proved efficacious in helping a rare malady in which hair falls out in localized areas.



INSTRUMENT MEASURES SALT IN WATER

SO SENSITIVE that it can measure to within fifty miligrams—about the weight of a postage stamp—the amount of salt in a gallon of sea water, an electrical device developed by the U. S. Bureau of Standards has no equal in the world.

Its practical use is in determining the direction of ocean currents, which may be traced by slight differences in their saltiness. Coast Guard boats on ice patrol, employing the instrument, can tell in which direction icebergs are drifting even when fog prevents actually sighting them. The new instrument does its job by measuring the ability of the water to conduct electricity.

ANALYSIS OF BLOOD WINS NOBEL PRIZE

DOCTOR KARL LANDSTEINER, of the Rockefeller Institute of Medical Research, was awarded the 1930 Nobel Prize in medicine for his studies of human blood. It is upon his discoveries that much of the science of blood transfusions is based. Such operations can only be successful, he found, when blood of the patient and the blood-giver "match." Human beings are divided into four blood-groups, three of which were discovered by Dr. Landsteiner and one by an associate of his. Blood from a person in one group will not mix with that from another.

When Dr. Landsteiner tried to mix blood from two different groups in his test tubes he found that red blood cells often bunched together as if they were glued. When this occurs in human veins

the patient dies. This discovery has also been used in a attempt to prove the parentage of doubtful children.


Dr. Karl Landsteiner in his laboratory examining specimens of human blood. For this work he was given the Nobel Prize.

the patient dies. This discovery has also been used in a attempt to prove the parentage of doubtful children.

Dr. Karl Landsteiner in his laboratory examining specimens of human blood. For this work he was given the Nobel Prize.

MACHINE MIXES PLASTER AND PUTS IT ON WALLS

APPLYING interior or exterior coats of plaster on various building material is now done with an air-operated machine developed in California. The machine mixes and applies the plaster to the walls, but keeps the plastering materials dry until a few seconds before they are applied, thus avoiding, it is claimed, any tendency to "set" before the plaster is on the wall. The trowel is used only to spread the material after it has been applied. The machine, according to its inventor, will handle all grades of plastering from the first coat to the last.



Aluminum paint is sprayed on pipe lines in California to reflect the rays of the hot sun and thus cool the water.

ALUMINUM PAINT KEEPS WATER COOL

KEEPING water cool by covering the pipe with aluminum paint was the idea recently hit upon by engineers of the Oakland, Calif., water department.

Aluminum paint was used because it reflected the sun's rays instead of collecting them as ordinary paint would. It was applied by an air-spraying device mounted on a truck. This is said to be the first time that paint has been used on water pipe lines.

FLUE GAS IN OIL TANK CHECKS FIRE HAZARD

PUMPING flue gas into tanks is one of the latest methods of reducing the ever-present fire hazard in oil-tank steamers, according to a recent announcement of the Petroleum Institute of Chicago. Smoke from the ship's boilers is washed and cooled and the remaining gas is forced into the tanks to displace air. This system

has been successfully applied to storage tanks and refineries ashore.

As oil cargoes are unloaded, air is drawn into tanks through ventilators, forming a highly explosive mixture as it mingles with the oil fumes. When tanks are filled a similar condition exists, as they are never loaded to capacity, space always being left for expansion of cargoes. Such conditions in themselves are not dangerous, but the smallest spark in contact with the vapor would cause an explosion. When a tank vessel is at sea, cargo swishing around in the tanks might generate enough frictional electricity to make such a spark. Filling the tanks with flue gas averts the fire hazard under such circumstances by confining the oil and preventing the possibility of a dangerous heat producing friction.

Oil tank trucks usually drag a length of chain along the roadway to carry off current formed by their contents swishing about, the chain acting as a ground short-circuiting the tank.



Plaster of all grades is mixed and applied to the walls by this machine, recently developed.


New Dogs for frozen North

While airplanes and motor cars invade Arctic waste, dog teams still reign supreme over large areas. This spurs efforts to breed for speed and for strength.

By

JAMES W. BOOTH

James W. Booth
is a well-known
author who has
written many
times about racing
the \$10,000 Alaskan
dog sleds.
He is now
in the States.
James W. Booth



Mushing through the white wastes of the North with a team of eighteen dogs harnessed to one sled. This is an unusually large team, but so well trained are these animals that in go strings of them tend to business and cause little trouble.

SWIFT, stout-hearted husky teams from far away as northwestern Canada will meet in a test of speed and endurance at Quebec next month, when the Eastern International Dog Sled and Derby Race is run for the championship of the world.

Even if a blinding blizzard should change the country into a trackless white waste around Washington's Birthday, the furry four-footed trail blazers of the frozen North will streak across the snows to win the gold cup and money prizes for their mushing masters. For three days they will dash over the 120-mile course in three heats of forty miles each.

This international event is the most important in a series of contests to be staged from the middle of January until the beginning of March over a far-flung territory stretching from Maine to northern California and from New York State to Manitoba.

The fact that races will be run at such widely separated places as Lake Placid, N. Y.; Pound Springs, Me.; Laramie, N. H.; Ottawa, Ontario; Le Pas, Manitoba; Ashton, Idaho, and Truckee, in the Lake Tahoe region of California, indicates a general revival of interest in one of winter's most thrilling sports—the dog derby.



Meat Murns and John, two of the imported thoroughbred Siberians at the Seppala-Ricker kennels.

Once strictly Alaskan, it was adopted by Canada and now has stirred the imagination of dog lovers throughout the United States.

These spectacular, exciting races, however, are far more than mere sporting events. In their staging, science and sport are cooperating to perpetuate and improve existing breeds and to originate new ones.

WHILE the railroad and the airplane, constantly pushing further in toward the Arctic Circle, are minimizing the importance of the dog sled as a means of transportation, the husky's usefulness both in scientific and commercial endeavor is by no means at an end.

His return from the Antarctic, Admiral Byrd declared that, without his dogs, he could not have accomplished his work of exploration. Airplane flights proved invaluable for survey purposes, he said, but it was the dogs that paved the way for all detailed observation. The late Nansen and Amundsen, greatest of Norwegian explorers, each expressed the opinion that the sled dog is indispensable for any prolonged observation in the Arctic and Antarctic regions.

So far as industry is concerned power-generating machinery has found its way north of fifty-



The musher and his dog team are the mainstay of the frontier.

The musher and his dog team are the mainstay of the frontier.

of square miles stretching the outposts of civilization, and the rough work falls to his lot.

The dog can haul a load where a horse is useless. As a matter of fact, the Quebec races are financed by a group of men who control vast lumber interests in the far Canadian Northwest, where timber still is hauled exclusively by dog teams.

THESE and other sponsors of the sport have injected a new spirit into dog racing. In the old days, the drivers' incentives were pride in their teams, the joy of competition, and the chance of pocketing a substantial prize. Today, the chief objective is to find a strain of dogs that combines the important qualifications of speed, endurance, and intelligence.

This change in viewpoint is clearly reflected in the way dog derbies now are conducted. While the thrill by no means has been taken out of the sport, the races have become comparatively conservative affairs. In the days of the All-Alaska Sweepstakes, the great dog racing classic that was abandoned in 1917, dogs and men often fought death and each other over a course of 408 miles.

Nowadays, the races are run over shorter courses, ranging from twenty-five miles at Poland Springs, Me., and Lake Placid, N. Y., to 200 miles at Le Pas, Manitoba Championship in the All-Alaska Sweep-

stakes earned with it a purse of \$10,000. Today, a gold cup and \$1,000 are awarded the winner at Quebec and a like amount in other important derbies.

To encourage the breeding of a real northern dog, a "condition prize" of \$500 is given at Quebec and Lacoma, N. H., to the driver of the dogs that reach the finish line in best condition. This prize is awarded only for those dogs which, in an inspection made previous to the races

prove to possess the necessary thick, warm coats, and well-furred feet with good, strong pads.

Attempts to breed a northern dog characterized by speed, endurance, and intelligence date from the time when the white man first began to penetrate the northern wastes. What probably happened was explained to

(Continued on page 142)



Ice and frozen pieces of snow are hard on the feet of the dogs and at top end of the team is getting first aid treatment for a sore paw. Above, the gee pole is used like a wagon tongue to guide the sled.


Can Men Pilot Rocket Planes at 5,000 Miles an Hour?



The fastest craft in the world. This Supermarine seaplane has been driven up to the amazing speed of over 300 miles a minute—300 miles an hour. Flight at twelve times the speed of sound.



This graphic drawing shows clearly what happens when centrifugal force holds blood away from brain by overcoming the heart's action.



Cracking the pylons at great speed in air races throws an enormous centrifugal force upon the pilot. It was thus Capt. Arthur Page was killed.

Flying in Straight Line Is No Strain, but Turns at High Speed Stop the Heart

By GEORGE LEE DOWD, JR.

FROM New York to San Francisco in thirty minutes, from San Francisco to Hongkong in an hour and a half, the world in five hours!

The incredible airplane for a dozen years in Opel, famous German engineer and the first man in the world to ride a rocket plane. Man-made meteors, capable of 5,000-mile-an-hour speeds, will be common in 1942, he says.

At the present moment, there is under construction in a closely guarded secret the Junkers factory in Germany an engine-driven craft designed to fly 700 miles an hour or faster (P S M Jan. 31 p. 33). Racing


across the sky seven miles up, it is expected to carry passengers in a streamlined sealed cabin from Berlin to New York in approximately six hours.

Aerial travel at breath-taking speeds is an actuality. Captain Frank M. Hawks has flown his Mystery monoplane from coast to coast at more than three miles a minute. In racing planes, four miles a minute is slow. The British pilot, Captain A. H. Orlebar, has rocketed by the Isle of Wight on his Supermarine seaplane at more than six miles a minute.


Louis Bleriot, the first man to fly across the English Channel, forecasts 700 miles an hour speeds within ten years, and F. H. R. Folland, designer of Orlebar's machine, sees no reason why racing ships cannot attain 1,000 miles an hour within



Another view of the fastest machine yet built by man. In its closed cockpit, the pilot feels no discomfort when moving six miles a minute in a straight line. Only the turn bothers him.



When a car is traveling at the speed attained by Major Segrave, 231 miles an hour, the outward pull on each tire is equal to four tons.



When buckets of water are whirled at the ends of a rope centrifugal force keeps water from spilling out.

the next twenty years or perhaps sooner.

These figures are given for engine-driven planes. The success of huge rocket-propelled machines, such as are foreseen by Von Opel and others, would open up an entirely new realm of speed possibilities.

Even conservative aeronautical engineers admit that the era of speed, which has lifted the record from about 170 miles an hour in 1920 to more than 360 miles an hour in 1930, has just begun. Where will it end? What will determine the limit—the weakness of machines or men?

Not long ago, a well-known engineer wrote an article in which he declared that a plane going more than 500 miles an hour would become heated by the friction of the atmosphere so that it might actually melt in the air!

The answer given to this objection is that the high-speed planes of the future are planned to race along the speedways of the stratosphere—the thin air many miles above the earth. They would climb at relatively low speeds through the denser atmosphere near the earth's surface to levels where the friction would be slight.

It is interesting to note that calculations indicate that at a height of 740 miles, a speed of a little more than six miles a second would allow a plane to break away from gravity and escape into space.

But the fact that future speed planes will use the upper air levels presents other problems to the designers. Ordinary machines lose speed as they go higher because of the inefficiency of their propellers, which cannot grip the thin air. The Junkers plane, now under construction, is to have a variable pitch propeller to overcome this difficulty. It can be adjusted during flight to take a greater "bite" as the air becomes thinner. Rocket planes would not have this difficulty and would be just as efficient high in the air as near the earth's surface.

Nor would they be affected, as engine-driven craft are, by the lack of oxygen and the extreme cold of the upper reaches. High-flying speed planes, powered by motors, will have to be equipped with superchargers to feed oxygen to the engine and heating equipment to keep it warm. At such levels, the air is too thin and too cold to support life and the pilot and passengers must ride in sealed cabins in which the pressure, temperature, and oxygen-con-

tent of the air is automatically maintained.

All of these problems, designers believe, can be solved. Tremendous speeds are mechanically possible, they declare, especially if the rocket form of propulsion proves to be practicable. As far as machines go, there appears to be no speed limit yet in sight.

But what of the man and passengers? Will the human body be able to stand the terrific pace of future planes? For uncounted centuries have been crawling slowly over the face of the earth. The fastest sprinter on a cinder track never reaches twenty-five miles an hour for the hundred-yard dash. The greatest speed attained by muscle-power is made by the gazelle, a fleet-footed animal which can run sixty miles an hour.

With the coming of the machine age, the speed records increased by hundreds. The *Rapier*, the fastest ocean liner, crosses the sea at a rate of approximately thirty-two miles an hour, and Gar Wood's racing hydroplane has skinned the surface of a lake at nearly 100 miles an hour. Steam locomotives have run at 120 miles an hour.

The fastest thing on rails is the Opel rocket car, which attained a speed of 156 miles an hour in tests near Hanover, Germany. The highest speed ever attained over ground is 231 miles an hour.

(Continued on page 134)




When a car is traveling at the speed attained by Major Segrave, 231 miles an hour, the outward pull on each tire is equal to four tons.

When buckets of water are whirled at the ends of a rope centrifugal force keeps water from spilling out.

Ancient Armor Copied for Modern Warriors



Polishing armor. Right, helmets of Passadena firemen are copied from those of Middle Ages



By
FAIRFAX DOWNEY

AN ARMORED automobile draws up at the door of a bank and guards who wear steel-plate vests carry in the money bags. Police in armored motorcycles answer a riot call. Machine guns splatter lead against the bullet-proof walls and glass windows of a gangster's limousine.

Soldiers maneuver in helmets, following the great, mobile shields we call tanks. Navy gunners hurl their shells at the armored turrets of retired battleships. Arsenal experiment with the important problem of the armament of airplanes.

Ancestors of all this present-day armor—the iron shells in which the knight of old and his charger were encased—are exhibited in our museums. They are relics of the past, but neither the lead-piping times of peace nor the blasts of modern warfare permit them to be classed as back numbers. The end of armor has been prophesied since the advent of powder and on through

the days of high-velocity firearms. Yet experts went straight to the helmet collections for hints on designing the "tin hats" of the World War; and the plate and chain mail of past centuries served as models for sniper's breastplates.

The collection of armor in the Metropolitan Museum of Art, New York City, is regarded as of technical, historical, and artistic interest. It comprised 4,700 pieces before the recent addition of the late Bashford Dean's collection, one of the three most important private armories in the world. The Museum is a counterpart of the arsenals maintained by

kings and princes in the age of iron men. Like them it has its armorers and its armorer's workshop for restorations, repairs, and cleaning.

If you inquired at the Museum for its armorer's shop, you would be shown that fascinating exhibit that is a duplication of the workroom of an armorer of the Middle Ages. The Museum's own shop, part of its operating department, is not open to the public. In it are hooked forges, bellows, anvils, vises, patterns, shears—all the implements of the craft.

DURING the World War, the Museum put at the disposal of the Government its armorer's shop and the services of its armorers headed by the late Daniel Tachaux. He designed several models of helmets which were copied in proof metal and sent to the helmet board in France.

Tachaux, who brought from his native France many tools of his craft and secrets of the armorer's guild handed down through generations, once wrought a helmet after the ancient

fashion in the Museum shop. It was produced as a restoration of the missing headpiece of a very old and handsome suit of armor.

The armorer hammered the helmet out of a single sheet of steel, using special hammers to shape the heated metal and later employing annealing to make it workable. At all times it was necessary for him to keep in mind not only the next but



Helmets worn by American soldiers during the World War were direct descendants of those that were used by medieval knights



1. Helmet, Paul of A. Museum of Armory, New York. This is a helmet for body and head, as well as a breastplate with a neck guard.



2. Breastplate, Paul of A. Museum of Armory, New York. This is a breastplate with a neck guard.

also the advanced stages of the process.

Now a press can stamp out in a day more helmets than an old-time armorer could forge during his life. But the craft of the old masters never has been exceeded. They could achieve

in iron that the great smiths could surpass. The embossed points and ridges of their mail were not thinner at the top. On the contrary the crest was the weak point of the machine-made helmets worn by the French in the World War.

High technical skill is required not only in the making of armor but in its repair. Even the task of cleaning it demands knowledge and care.

The Museum fights rust as zealously as old-time armorers in the days when king's armor was a flower. Four armorers in the shop do the work that was once done by squires and arsenal servitors. Present methods, barring a few improvements, parallel the old usages.

Extremely rusty armor received at the Museum is soaked with kerosene for from two days to two months, after which the loosened rust yields to a stiff bristle brush. Surfaces are rubbed with various grades of emery cloth moistened with oil. After the kerosene has been removed, the surfaces are cleansed with alcohol and the metal warmed for an even spread of a coating of oil.

Caustic potash, powdered rottenstone, and even a grindstone may be used for rust removal. Yet every piece to be cleaned requires a special diagnosis. The etching of plate armor or the fine pattern



Around the dummy figure breastplate, steel leggings, and helmet are mounted before museum piece is ready.

on a Damascus or Japanese blade can easily be ruined by indiscriminate cleaning.

Armorers used to clean chain mail by putting it in a barrel with sand and vinegar and shaking it. The mail thus received an excellent burnish and at the same time the barrel was well scoured and made ideal for holding ale. Link armor now is soaked in kerosene and placed with sawdust in a tumbling machine.



3. Breastplate, Paul of A. Museum of Armory, New York. This is a breastplate with a neck guard.

When they are given a thin coating of oil. Paint, of course, also would be a preventive but the armor must be in its former state and of its former metal. It is exact. However, the Green Knight and the other figures of the romances who wore it have perpetuation of their precedent in the painted armor of the World War. And another debt is owed to the painted armor of the past, for the bare spots made on it by the blows of weapons oxidized in the air and the marks left suggested the process of etching by acid.

The surviving specimens of the armorer's craft are worthy of especial care and preservation even from the utilitarian standpoint. History has emphatically repeated itself on the subject of armor. Even in this country, so little associated (Continued on page 46)

New Silencers and Mufflers for Your Windows Bar Noise but Let in Fresh Air



Hiram Maxim adapts gun silencer to stop street noise

Now "silencers" and "mufflers" can be applied to the windows of your home or office as easily as to a gun or an auto exhaust. They are the latest advance in the nationwide war against noise.

Recently the "Maxim silencer" for windows, a product of the noted inventor who perfected silencers for firearms and for industrial machinery, was announced at Hartford, Conn. At the same time, installations were being made in San Francisco of another type of "window muffler" designed by the late Prof. J. F. Newsom, at Stanford University.

Prof. Newsom rigged up a tub of mercury, in which he laid a model of a window frame, in order to study the movement of sound waves around it. Ripples in the mercury simulated sound waves.

Further tests of a model "muffler" were made in a unique fashion. A man with a .22-caliber revolver walked away



This window muffler, consisting of a slanting shield and curved hood, was invented by J. F. Newsom, Stanford



MAN FIRES REVOLVER AT VARIOUS DISTANCES FROM OPEN WINDOW

MODEL OF MUFFLER IN PLACE ON OPEN WINDOW

OBSERVER MEASURES AMOUNT OF NOISE THAT PENETRATES WITH MICROPHONE

Diagram of the Newsom muffler showing how tests were made with gun and microphone to gauge noise.

from the open window of the laboratory, firing the revolver at measured distances. An observer, within, measured the intensity of the noise with the aid of a specially-designed microphone. Out of these experiments, checked both with and without the muffler, came the "silencer" which consists of a slanting shield outside the window and a curved hood inside.

To his window silencer, Maxim applied the principle used so effectively in the muffler for guns—a series of baffles to trap sound, but not to obstruct the flow of gas. These he arranged compactly in a flat box, only five inches high, that fits beneath a window shut tightly upon it. To insure a good supply of fresh air he built into his device a reversible fan which blows air into a room or sucks it out.

80,000 PULLMAN TICKETS USED EACH DAY

GETTING an upper or lower berth at a Pullman ticket window may seem a simple operation, but it represents a staggering amount of effort on the part of the sleeping car company. The picture shows one day's supply of tickets, 80,000, boxed and ready for shipment to ticket sellers throughout the country, this number being required to meet the demand.


Clerical work in providing you with a comfortable bed as you speed over the rails does not end here. Each ticket is in three sections, and two of these are returned to the Pullman offices by different means. The agent keeps one part and sends it back with his periodic report. After you have boarded the train, the conductor collects one piece of your ticket and sends it in with his report.

It has been estimated that one year's sale of Pullman tickets, amounting in all to about 29,000,000, if placed end to end would reach from Chicago to Boston with the eastern end sticking out a few miles into the sea.



Want a Pullman ticket? Here are 80,000 of them stacked up in boxes ready to be sent out to meet the demands of one day's business. About 29,000,000 of them are used each year.

Winners in the November "What's Wrong?" Contest



He won a prize in Popular Science Monthly's "What's Wrong?" Contest and all the family shared his joy.

FIRST PRIZE 500 DOLLARS

Charles T. Sharpe, Los Angeles, Calif.

SECOND PRIZE 100 DOLLARS

W. V. Chambers, Swarthmore, Pa.

THIRD PRIZE 50 DOLLARS: Frederick E. Beaumont, New Bedford, Mass.

TEN PRIZES OF TEN DOLLARS EACH

Elmer B. Benson, Rock Island, Ill.
Leonidas W. Ellis, Cherrydale, Va.
Albert R. Getchel, Boston, Mass.

John Hackett, Centerville, Wash.
Andrew J. Kelly, Utica, N. Y.
E. A. Matthews, Gibsonburg, Ohio
Marion Trevathan, Michigan Center, Mich.

Harold W. Braden, Anderson, Ind.
Derrick P. Rusoch, Providence, R. I.
Russell G. Young, Washington, D. C.

FIFTY PRIZES OF FIVE DOLLARS EACH

Ernest Arnold, El Paso, Tex.
B. H. Bell, Rapid City, S. D.
Joseph A. Bieker, Detroit, Mich.
James Bolton, Regina, Sask.
Le Roy W. Boughton, Berwyn, Md.
Joseph Brockman, Cincinnati, Ohio
Andrew S. Burnett, Hannibal, Mo.
G. W. Buzw, U. S. S. Crestal
A. R. Chesney, Mannington, W. Va.
Elmer H. Cousins, Northeast Harbor, Me.
Robert C. Forbes, Somers, Conn.
Avin H. Fox, Brackton, Mass.
W. M. Furlow, Albany, Ga.
Mrs. Guy A. Garrett, Clarksburg, W. Va.
Charles A. Garverich, Harrisburg, Pa.
Wm. E. Geer, Pueblo, Colo.
Sister Agnes Gonzaga, Tipton, Kans.

Bessie M. Hahn, Wilkesburg, Pa.
Edgar W. Hall, Catskill, N. Y.
Herbert C. Haller, Lawrence, Mass.
A. E. Heatherington, Orlando, Fla.
Walter Heins, Appleton, Wis.
William Herrmann, Jr., Hartford, Conn.
M. H. H. Hoxa, Steubenville, Ohio
W. F. Jensen, Tipppecahoe City, Ohio
John M. Keating, Beacon, N. Y.
J. E. Lapp, Orono, Me.
G. H. Leaverton, Baltimore, Md.
Ben Lewis, Venice, Calif.
Clifford K. Loder, Syracuse, N. Y.
William G. Lownds, Brooklyn, N. Y.
Chas. A. Merritt, Racine, Wis.
Bertha W. Miller, Ravenna, Ohio.
A. W. Mitchell, Portland, Me.

Oscar L. Morris, Salisbury, Md.
Franklin F. Murdoch, Washington, D. C.
Chas. Pister, Kenton, Ohio
F. W. Rabner, Anniston, Ala.
J. O. Ritter, Clarksburg, W. Va.
Joseph F. Siler, Yonkers, N. Y.
Clyde W. Sisson, Cobleskill, N. Y.
W. O. Spoon, Portland, Ore.
R. V. Stevenson, Mayvern, Ark.
D. W. Sutherland, Sioux Falls, S. D.
P. C. Swan, Arcu, Ga.
R. H. Swartzwelder, Hartford, Conn.
S. Wallwork, Athol, Mass.
Mrs. E. R. Webster, Denver, Colo.
Andrew H. Young, Boston, Mass.
A. D. Zimmerman, Blue Mound, Ill.

STILL TIME TO WIN A BIG CASH PRIZE!

THE FINAL "What's Wrong?" Contest, which appeared in POPULAR SCIENCE MONTHLY last month does not close till January 31. Therefore you still have time to get into this big contest in which you may win the \$500 first prize or one of the other sixty-two cash prizes.

The "What's Wrong?" Contest

pictures appeared on pages twenty-eight and twenty-nine of the January number.

To enter the contest all you have to do is to figure out what George is doing wrong and the four photographic errors in each picture, write or typewrite your answer and mail to POPULAR SCIENCE MONTHLY by January 31.

And if you get busy right away, you have just as good a chance to win as anyone! You don't even have to dig up your copy of POPULAR SCIENCE MONTHLY for January. Look over this copy of the magazine in any public library or office of POPULAR SCIENCE MONTHLY. Rules are on page thirty-one of that issue.

POCKET PROJECTOR SHOWS 250 PICTURES



This pocket projector, weighing less than two pounds, is used to demonstrate an Edison's goods.

A SMALL picture projecting machine that can be carried in a sportsman's coat pocket will help him demonstrate his product and its uses to prospective customers. About the size of a pocket camera, it will operate on ordinary house circuits. It can be plugged into any light socket, after which it is only necessary to turn a knob to flash each picture, in succession, on any convenient blank wall.

The machine weighs but a pound and three quarters and uses standard film. It has a capacity of 250 different pictures. Illumination from a fifty-watt lamp with a coiled filament concentrates the light at the focus of the projection lenses.

TELESCOPE IS USED TO READ RADIO METERS

RADIO experts took on the appearance of star-gazers at Whippany, N. J., when the antenna of a large experimental radio station was decked with electric meters recently. Two young engineers of the Bell Telephone Laboratories, copying a

scheme worked out by radio amateurs, made the rounds, measuring antenna currents, with a telescope.

One of them sighted through the eyepiece and called off the figures. The other jotted them down in his notebook. Thus the radio station solved a knotty problem, for the meters could not be lowered to earth to be read, and there was no way to get up to them.

ELECTRIC WATER POWER PLANT CROWDED STEAM

A few months after Thomas A. Edison opened his first electric generating station on Pearl Street, New York City, in 1882, the first electric water power plant was put in operation at Appleton, Wis. It was a crane plant, handling but 250 lamps and using the same type of dynamos that were installed in the first Edison plant.

They were driven by bevel gears and belting from the water wheel, which had a vertical shaft like the vertical-spindle water turbines that drive generators in present-day hydroelectric plants.

SAILORS IN U. S. NAVY TO SEE SOUND PICTURES

TALKING picture apparatus will be installed in all United States warships, according to a recent announcement by the Navy Department. A contract for 200 talking moving picture machines, each of which will be installed in a different vessel, has been awarded. Arrangements were also made with producers to supply the talking films.

SCORE CARD ON PUTTER NEW GOLF NOVELTY

WHEN a player has finished playing a hole with this golf club, he need only lift it to record his score. The back of the head of the putter holds a removable score card, on which the number of strokes is marked with a pencil. When not in use, the pencil is carried in a clip on the shaft of the club.



A golfer has no excuse for failing to keep his score: he has a putter with card on its head.

THRILLING STORIES STOP BEAT OF CHILD'S HEART

THAT some fairy stories really do make a child's heart stand still momentarily while reading them has been proved by tests made at Harvard University, Cambridge, Mass. A special amplifier, sensitive to electric impulses emanating from the heart but insensitive to other muscle currents, has been developed.

The children tested wore two small metal buttons strapped to their chests and connected to the amplifier and recorder. Through this apparatus each successive heartbeat was marked on a record tape, together with time signals which enabled the rapidity of the beats to be noted.

The children's hearts distinctly sped up or slowed down during emotional passages from fairy stories that were read to them. Return to the normal heartbeat was more delayed, it was noticed, when the story was one with which the child was familiar. This was taken to indicate that familiar songs or stories have a stronger and more lasting emotional appeal than new ones.




Meters strung on the antenna of a radio station to measure the current could not be read until two engineers used a telescope to make the figures visible.

Raiding Planes in Mimic War Defeated by "Ears"

CAMOUFLAGED "ears" defeated a raiding air fleet not long ago, when a squadron of "Red" planes swooped toward Los Angeles in a mimic air war staged by the Army. Listeners swept the air with huge horn like devices and caught the magnified sound of the distant airplanes' motors. A telephone call to a nearby air field followed, and a powerful defending fleet of "Blue" aircraft roared into the air to repel the invaders.

The mock battle gave Army men a chance to test under war conditions their latest equipment, including the sound detectors and huge 2,000-pound "demolition bombs. The detectors are mounted for mobility on a four-wheeled chassis, and at the first warning of a coming air attack they can be rushed to the scene to listen for the invaders. Two observers man the apparatus, one to manipulate controls that turn it in any direction and the other to listen through hose like speaking tubes. Tree branches hang over the horns disguise the listening device from the air.

Air bombs are carried beneath the fuselage of the plane, between the wheels of the landing gear. They are released by a trigger from the pilot's cockpit.



The remarkable photograph at left shows an Army plane one of the fleet used in the war game attack on Los Angeles, just as it has released a 2,000-pound demolition bomb which is caught beneath fuselage and trapped on lockpit.



This camouflaged "mechanical ear" is the Army's latest device to detect the sound of approaching enemy planes. Tried out on the Pac. Sc. Coast it gave satisfactory results. At left while one observer aims his horn at various parts of the sky another listens through tubes for warning hum.

1,000 FILM BOOKS ON A SHELF


Storing a thousand books upon a five-foot shelf is the apparent miracle made possible by a camera recently placed in service at the Library of Congress, Washington, D. C. It photographs a book page by page upon a narrow strip of film with microscopic sharpness. The film requires small space for storage. When the celluloid copy of the book is to be examined the film is placed in a special projector and thrown on a screen enlarged to normal size.

The camera is a European invention. Dr. Thomas P. Martin, of the library staff, became interested in its possibilities while engaged in securing copies of documents in foreign libraries and official archives. He developed the projector that he uses with it.

Important practical applications are seen for the filming system. Newspapers, the most perishable of any form of public records, may be preserved for future gen-

erations in film libraries. An ordinary-sized newspaper is reduced by the process to a three foot roll of film that can be slipped in a vest pocket.

In addition, the new process makes it possible for a newspaper publisher to send unlimited copies of the paper to distant points by airplane, at no greater expense than the dispatch of ordinary air mail letters. Dwellers in city apartments may also use the device. In a limited space, booklovers will now be able to have as large a library of volumes at their disposal as they desire.



Dr. Thomas P. Martin, of the Library of Congress, demonstrates a European camera to film books to save shelf room.

Government Tests *Roasts* to Find Best *Meat Cattle*

By H. C. DAVIS



A
insures a uniform cooking heat.

PRODIGEED roasts, scientifically cooked in a special Government kitchen in Washington, D. C., play an important part in the latest attempt to improve the livestock of America. With each roast that comes to the ovens of this meat-testing laboratory, here is a complete history of the breeding, age, sex, and feeding of the animal that produced it.

Twenty-five state experiment stations and other meat and livestock agencies are cooperating with the U. S. Department of Agriculture in this study of the factors which govern the palatability of meat.

Under the direction of Lucy M. Alexander, in charge of the experimental kitchen, more than 2,000 legs of lamb, nearly 1,000 rib roasts of beef, and about 400 cuts of pork have been cooked. In order to be sure that differences found in the cooked meats are due to the animals and not to the cooking, all roasts are prepared in the same way.

Careful records of oven temperatures and cooking periods are kept. This insures that the meat sent in from the experimental farms year after year from animals fed under identical conditions will be cooked in exactly the same manner.

Besides the oven thermometers which indicate the heat within each of the eight roasting compartments, meat thermometers are thrust into the center of the roasts to record internal temperatures and show when the meat is done. These instruments are marked "rare," "medium," "well done."

THE average temperature for rare roasts is 140 degrees Fahrenheit, for medium, 160 degrees, and for well done, 180 degrees. Such thermometers, taking the guesswork out of roasting meats, have recently been put upon the market for use in the home kitchen.

Besides keeping a record of the oven temperatures and time of cooking, the shrinkage of the meat is determined by weighing the roast before it is placed in



Getting roasts ready for the oven in the Government experimental kitchen, Washington, D. C.



Here the final decision is made. These expert tasters sample a bit from each of the eight roasts and make record of its quality.

the cooking oven and after it is taken out.

At three o'clock in the afternoon, a jury of five expert "meat-tasters," selected from various bureaus of the Department of Agriculture, assemble to sample the roasts and decide upon their merits.

One at a time the roasts are sampled. Five slices are cut from each and the judges take a bite or two from the same part of their slices so they will all be examining the meat under similar conditions. They record their opinions on printed grading charts, giving their estimate of the intensity and desirability of the aroma, the flavor of the fat, the flavor of the lean, the texture, the tenderness and the juiciness of each piece of meat.

There are seven gradings for each item. For instance, a judge may encircle any of the following after "Quality of Juice": Very juicy, Juicy, Moderately Juicy, Slightly dry, Dry, Very Dry, Extremely dry. At the bottom of the chart, he checks the color of the lean, which ranges from light red to dark brown, and the color of the fat, which begins with white and ends with amber.

AN ADDITIONAL check upon the tenderness of the meat is obtained by the use of a mechanical tester, devised not long ago by the U. S. Bureau of Standards (P. S. M., Aug. '30, p. 48). It records the force necessary to cut through a given piece of meat when it is raw and again when it is cooked.

The work of the experimental kitchen, which is being continued over a number of years, is the first attempt to trace the effect of an animal's history upon the meat it produces by keeping records that start with its birth and end with the meat fully prepared for the table.


By use of the kitchen and expert judges, it is believed accurate information about the effect of various feeds upon the palatability of meat will be obtained to aid in raising superior meat-producing animals.



NOT AS BAD AS IT LOOKS

It is a very old fossil, and is a very good specimen of the kind. It is a very old fossil, and is a very good specimen of the kind. It is a very old fossil, and is a very good specimen of the kind.

It is a very old fossil, and is a very good specimen of the kind. It is a very old fossil, and is a very good specimen of the kind. It is a very old fossil, and is a very good specimen of the kind.



A GOOD SPECIMEN

It is a very old fossil, and is a very good specimen of the kind. It is a very old fossil, and is a very good specimen of the kind. It is a very old fossil, and is a very good specimen of the kind.

Weird Beasts Pose Before Camera



GROWS ITS OWN COLLAR. This strangely frilled lizard is a native of Australia, where the animals have developed along their own lines. The specimen shown here is in the Sydney Museum.




NOT AS BAD AS IT LOOKS



SNAPPED IN A MOMENT OF SURPRISE. When a sea elephant is startled, it snaps its trunk. This is one of the strange animals encountered was the sea elephant. These beasts, striking their notes above an ice floe, would stare in astonishment at the queer two-legged strangers.

ENLARGES TINY PLANTS IN PICTURES



With his botany et
styles of minute plants. With I
San Francisco Cal
likes them. H
photographing the result

First he obtained a standard laboratory
microscope such as is used in science
classes. He tilted it to a horizontal posi-
tion and fitted its eyepiece into a card-
board collar that was substituted for the
lens of an ordinary view camera. A
stereopticon furnished the light. Focusing
was done on the regular ground glass panel
of the camera.


PHOTOS SHOW NEPTUNE HAS SIXTEEN-HOUR DAY

ASTRONOMERS at the Lick Observatory,
Mount Hamilton, Calif., recently learned
that the planet Neptune rotates in the
same direction as the earth and has a day
about sixteen hours long. They made the

discovery by holding a camera trained
on the equator of the planet for hours and
studying the light on each side of its
center with a spectroscope. The study
showed that one side was approaching,
while the other was receding, and further
observations determined the speed of
rotation.

The magnitude of the task is appre-
ciated when it is realized that even in a
large telescope Neptune appears as a pin
point of light, and the scientists had to
photograph but a minute strip of its sur-
face. The camera was mounted on a
telescope that was spotted on the target
2,800,000,000 miles away and held there
unwaveringly by intricate machinery.

NO FIRE IS NEAR AS RADIO POPS CORN



This corn, between glass jars packed with ice, was popped by
radio waves from a "fever machine" which heated it internally.

POPPING corn by
radio was demonstrated
in New York the other
day by General Elec-
tric engineers. A glass-
ful of popcorn, crack-
ling and bursting with
no stove near, popped
in two minutes. Not a
kernel was charred.

On each side of the
popcorn was an electric
wire in a glass with ice
cubes to prove it was
cold. Short radio waves
passed between the
wires and induced elec-
tric currents in the corn,
heating it internally.
The wires were con-
nected to a radio arti-
ficial "fever machine"
developed several
months ago (P. S. M.,
Sept. '30, p. 32) to com-
bat disease by heating
a patient's blood in-
ternally just as it
popped the corn.

NEW STAR FOUND BY GERMAN STAGE STAR

A "STAR" of the stage found a new
star in the heavens at Berlin, Germany,
the other night. While Heinrich George,
noted German actor and author was
scanning the sky from his private observ-
atory, he chanced upon a pin point of
light that his star map failed to indicate.
He reported his discovery to the German
Astronomical Society. That body con-
firmed the fact that George's star was a
new one to astronomers.



Heinrich George, German actor-author, in
his observatory where he found a new star.


NEW MICROSCOPE USES INVISIBLE LIGHT

A new way to take photomicrographs
by invisible ultra-violet rays, developed
by a Rochester, N. Y., camera firm and
an optical manufacturer of the same city,
makes it possible to use ordinary glass
lenses in the microscope.

Photomicrography with ultra-violet
rays is not new. The most highly mag-
nified photographs in the world are made
with these invisible rays, and pictures
taken at the Bell Telephone Laboratories,
where the process was originally perfected,
have been made with magnifications of
5,000 diameters. Hitherto, however, ex-
pensive quartz lenses have been needed.

Now the Rochester experimenters have
found a way to use ultra-violet rays so
nearly resembling visible light that they
will pass through glass. Tests showed
that pictures could be made magnified a
fifth again as much as those taken with
ordinary light. One of the most success-
ful pictures showed a grain of hollyhock
pollen so enlarged that a vague gray ring
around it, as seen by visible light, became
a clear circle of spines. One specimen of
a worm could not be photographed in the
new way because its body contained a
layer that stopped ultra-violet rays.

Effort Now Being Made to Solve Mystery of Northern Lights



TRUMSO OBSERVATORY IN THE WORLD.

WHEN the northern lights flame up into the sky, they come a gets busy and on its plates are pictured streamers like this.

...observatory in the world.

On a bank half a mile from the town of Tromsø, Norway, a concrete platform has been raised with the aid of American contributions and funds from the Norwegian government. Strange looking instruments roll out upon it at the approach of an auroral display, and are manned by men under the direction of Prof. Lars Vegard, noted Norwegian physicist.

They have a grandstand seat at one of Nature's most gorgeous spectacles. For every one display of northern lights that is visible as far south as the middle of the United States, these observers see ten.

White or yellow auroras are most com-



When the northern lights flame up into the sky, they come a gets busy and on its plates are pictured streamers like this.

mon. Rose, however, is more unusual, and one brilliant aurora of this kind was mistaken for a conflagration not long ago and called out a fire brigade in Svalbard, Austria. When green or red rays shoot across the sky, compasses become agitated, revealing the strange magnetic disturbances that disrupt telegraph and radio service. Blue or violet lights, seen by some observers in auroras, are extremely rare even in the very high latitudes.

One man at the Tromsø observatory works the spectroscope, a bulky box that



...in communication by telegraph with another observer taking notes from a high peak, several miles away, so that the height can be found by the method familiarly known as 'triangulation'.

From such observations it is already known that most auroras are sixty to seventy miles above the earth. Some of their streamers may extend as high as 600 miles or more. There are a very few cases, seemingly authentic, when auroras have been seen close to the earth.


Such observations are unexplained by the theory that auroras are the glow of rarefied gases in the upper air, bombarded by electrons from the sun.

FRONT ROLLER ON TRUCK PREVENTS ACCIDENTS


Destined to prevent pedestrians from being run over, a British motor truck has a large roller before its front wheels which rotates in the opposite direction to the wheels. If a person is knocked down the tires cannot touch him, since the roller's reverse rotation throws him away from the vehicle. It thus has time to stop before doing him serious injury.

SNOW MOSQUITOES SLEEP THROUGH THE WINTER

Mosquitoes that sleep all winter inhabit the northern ranges of the Rocky Mountains in Montana. They pack out homes under rocks and logs and doze through the cold weather, buzzing out on the first warm day of spring. They are called "snow mosquitoes," and grow large, having spotted wings. During the summer they store up fat, on which they subsist during winter. When they come out in the spring, they are lean and hungry.



A roller in front of this truck revolves in the opposite direction to that of the wheels and thus tosses a human body out of the way and gives the driver a chance to stop his car.



PROPELLER MAY LIFT PLANE STRAIGHT UP


MOUNTED on a vertical shaft, a huge propeller may lift a strange looking aircraft straight up in the air, according to its inventor, who hopes to try out his machine soon. An ordinary airplane engine supplies power for driving both this device and the usual airplane propeller mounted on the nose of the ship. The large "helicopter" propeller is driven by "friction disks," two wheels with smooth surfaces, one turning the other by being pressed against it. One is mounted on the engine's horizontal shaft and the other on

the vertical shaft, forming a right-angle drive. Similar drives were used on motor cars in the early days of the automobile before shifting gears came into fashion.

AIR MAIL TO EUROPE, 1932

UNITED STATES air mail to Europe may start in 1932, by way of Bermuda and the Azores. By the time this issue of the magazine appears, the Post Office Department will have asked for bids for an all-American route across the Atlantic.

Service as far as Bermuda would begin, according to the plan, next June first.



ADJUSTABLE WING AIDS PLANE LANDING

A NEW airplane wing developed in Los Angeles by H. D. Rocheville has been tested successfully in flight. The pilot can, by turning a crank in the cockpit, regulate its shape to suit flying conditions. For slow landing speeds and quick take-offs he can "thicken" the wing, automatically increasing its angle and lifting capacity. For high speed flight he can, by the same means, flatten the wing, decreasing its lifting capacity but increasing its speed by reducing wind resistance. In either shape of wing the plane handles easily, and the adjustable wing helps in sudden storms.

Rocheville, who designed the new wing and is seen above pointing to the bulge

that is supposed to make the plane safer and more easily managed, has been identified with aviation since 1917.

OPEN PASSENGER AIR LINE, NEW YORK TO CHICAGO

RECENTLY the first regular passenger line between New York and Chicago was opened. Hitherto considered a dangerous line section mail planes have carried passengers only by special arrangement. The new line's tri-motored, all-metal monoplanes cover the distance in six and a half hours.

BLIMP MOORED TO MAST ON TOP OF BIG BUS

FOR what is believed to be the first time in history, a lighter-than-air flying machine has been moored to a motor car. Officials of the Goodyear Rubber Company experimenting with portable mooring devices for their blimps, rigged a small tripod mast on top of a bus. When their airship *Paritan* arrived at Washington recently they succeeded in mooring it to this traveling landing device. When not in use the mooring mast can be folded up on top of the bus so that it will in no way interfere with the normal operation of the car. The bus can be anchored if its weight is not sufficient to hold securely the gas-filled airship above it.



For the first time in history an airship was moored recently to a mast on top of a bus.

NEW AIR MAIL FLAG SOON TO FLY AT AIRPORTS

AN OFFICIAL air mail flag, recently adopted by postal authorities, soon will be hoisted over all airports at which United States mail is handled. Red, white, and blue stripes at its top and bottom edges resemble the markings on air mail envelopes.

On a central field of white, a device worked in gold represents a globe bearing the words "U. S. Air Mail," flanked by two wings. Colonel L. H. Brittin, of Northwest Airways, designed the flag, which was dedicated by Assistant Postmaster General Glover.



This new air mail flag, with red, white, and blue stripes, will fly at U. S. Mail fields.

ITALIAN HELICOPTER RISES, HOVERS, FLIES

IN A recent issue of this magazine was illustrated a one-ton, ninety-horsepower Italian helicopter said to be capable of flying straight up (P. S. M., Oct. '30, p. 53). It was ordered by the Italian government in 1927, and completed last year. Now word comes from Italy that it accomplished the following record feats at the Ciampino airport, near Rome. Ascended to a height of sixteen feet and hovered stationary for one minute, climbed to an altitude of fifty-eight feet and returned to a starting point indicated by a circle on the ground, and flew cross-country for nearly three fourths of a mile.



A plane looking like a carpet sweeper and no wider than an auto is designed to rise in vertical flight.




This Italian helicopter rises vertically, hovers stationary in air, and lights on a spot indicated by a circle on the ground. A super machine of same design was ordered by the government.

PARACHUTE JUMPING NOW TAUGHT ON THE GROUND

INSTRUCTORS at a California air school rigged up a portable airplane propeller driven by an electric motor, to aid in teaching the technique of parachute jumping. Standing in its air blast with chute pack made up on his back, the student is shown how to pull the rip cord and what to do after the chute opens out. Most conditions of an actual jump are imitated

by the machine without submitting green students to the risk of leaping from actual planes in flight. Having mastered the technique of pulling the cord and keeping their heads, the danger incident to a real jump is greatly reduced.



Learning to pull the rip cord of a parachute is no longer dangerous, as a blast of air from a propeller imitates the chute and suggests actual conditions of jumping.



Compact and massive-looking, a strange aircraft model with which Glendale, Calif., plane designers are experimenting in no way resembles the graceful planes now in use. Thus "flying carpet sweeper," so called from its unusual appearance, is said to be able to alight on and take off from water or land and be capable of vertical flight or hovering motionless in mid air. Since its width is no greater than a motor truck it is believed to be able to operate on public highways. The plans from which the model was built were for a freight plane.



AIRPLANE MOTORS NOW TESTED ON A TRUCK

A STAND for testing airplane motors, recently completed in Portland, Ore., resembles a queer-looking aerial propeller driven vehicle. A steel framework is built at one end of a truck, the other end of which is occupied by a small house in which the operator works.

After an overhaul, airplane engines are given a twenty-hour shop test by running them in the plane. This wear and tear of the plane will be eliminated by use of the new testing stand.

FIRST ROCKET AIRDROME OPENED NEAR BERLIN



Evidence of the serious
ness with which German aer-
onauts are taking

work is shown by the

construction of the

new rocket airdrome

near Berlin. The

land is one and a half square

and equipped with laboratories

and workshops. Engineers are

experimenting with a means

of flight with which they hope

ultimately to shoot mail to

America in six hours.



TAILLESS GERMAN PLANE SEEMS TO FLY BACKWARD

A new German plane is without the
ordinary tail. A small wing equipped with
ailerons is attached to an extension of the
fuselage ahead of the main wing. In this
it looks as if it were flying backward.
The auxiliary wing gives its nose the
position of the tail on airplanes of
standard design.

It is a racer, much like those of
other planes, mounted close behind.

It is placed under the main wing on either
side of the fuselage. The machine is a
win-engine cabin type craft. Early
Curtiss and Wright airplanes were fitted
with a bow extension for stabilizers and



OLD PLANES DESTROYED BY BOMBS FROM AIR

Old planes have been used recently by

the Germans to destroy

them during recent maneuvers near

Camp Stanley, Texas.

Modern bombers swept over the field

and their

of the ground. One

were hit but

of the ground. One

were hit but

of the ground. One

were hit but

of the ground. One

were hit but

of the ground. One

were hit but

of the ground. One

were hit but

of the ground. One

were hit but

of the ground. One

were hit but

of the ground. One

were hit but

of the ground. One

were hit but

of the ground. One

were hit but

of the ground. One

were hit but

of the ground. One

were hit but

of the ground. One

were hit but

of the ground. One

were hit but

of the ground. One

were hit but

of the ground. One

were hit but

of the ground. One

were hit but

of the ground. One

were hit but


of the ground. One

were hit but


MAIL NOW CARRIED IN AIRPLANE'S WINGS

How can more space be found in an
airplane for mail bags? That question has
been raised by the fact that the air mail
volume has enormously increased during
the past few months. As one answer, Post
Office officials have suggested that mail
bags can be carried in the wings of a plane.
As a result of this proposal, the Ford all-
metal plane, at right, has been developed
with a hinged section between the ribs on
the underside of the wings. It is raised
and lowered by cables that work on a wind-
ing drum, which in turn is operated by a
portable crank handle resembling, in
appearance, a carpenter's long brace, and
giving sufficient leverage to move the sec-
tion even when it is loaded.

A mail truck can back up to the plane
and the sacks can be loaded directly into
the wing space. As planes are constantly
being built larger and larger, with a con-
sequent increased depth of wing, designers
are tending more and more to make use
of the inside of the wings as passenger and
freight space.



All-metal Ford plane developed with hinged section in each wing into which
mail bags can be packed. Increased volume makes necessary more space for mail.



Mysteries of Oyster's Secret Life Are Solved

AN OYSTER INVESTIGATION
LABORATORY
AT THE U. S. BUREAU OF FISHERIES
WASHINGTON, D. C.

By

JOHN E. LODGE

For an army of 35,000 persons.
The revelation of the oyster's
secret life with the
...
... Seeking ...
... in for ...
Dr. Galtsoff undertook a thor-
ough study of the oyster and
its ways. In general the life
history of the oyster was
... But that history fairly
... with question marks

IT WAS early in the morning
that the female oyster
... directly into the sea, as the
male does its sperm, and that
hazardous fertilization takes
place in the water. The Euro-
pean oyster, and it is believed,
some species on the Pacific

coast of America, can change sex, at one
time being male and at another female.

In five or six hours, the fertilized eggs
develop into microscopic free-swimming
larvae that in twenty-four hours grow thin
bivalve shells and soon afterwards settle
upon objects in the water and cement
themselves in place.

These young oysters are known as



Dr. Paul S. Galtsoff in the oyster investigation laboratory and,
upper left, ready to go down in a diving bell to study bivalves


THE LIFE OF THE
OYSTER WAS KNOWN
AS A SECRET

Recently, many new facts
have been uncovered about its
curious manner of reproduction
and the strange, almost plantlike existence
it leads. Laboratory tests show that it
stays "awake" about eighteen hours a day
that the female may lay 500,000,000 eggs
a year, and that, deprived of locomotion,
hearing, and sight, the oyster possesses a
sense of taste four times as efficient as
that of man.

Much of this work of discovery has

been done under the direction of Dr. Paul
S. Galtsoff in charge of the oyster investi-
gation division of the U. S. Bureau of
Fisheries, Washington, D. C. For more
than four years, he has been devoting all
his time to the study of the habits and
problems of this marine animal that, in
America alone, produces \$25,000,000
worth of food a year and supplies work

Experimental oysters are arranged in storage tank for future use.



things about this life cycle remained unknown. How many eggs does a female oyster produce in a year? What is the effect of changes of water temperature? How much sea water does an adult oyster

Thirteen tests were made. The smallest number of eggs discharged by one oyster was 11,000,000. The largest number was 114,800,000. As one female may spawn from five to six times in a season, Dr. Galtsoff estimates that a single oyster may produce 500,000,000 eggs a year. If every oyster egg produced an adult oyster the cumulative process would cover the globe miles deep with oyster shells in the span of a human life.

But the mortality of larvae and spat is high. Small fish gobble them up, Starfish, marine horers, and jellyfish prey upon them. Also it has been discovered lately that the temperature of the sea water has



In this laboratory investigation brings to light the tiny oyster parasites that may be disease spreaders.

"spat," and the settling process is called a "spatfall." The spatfall takes place usually on the muddy flats between high and low tide marks where the tiny mollusks cover every solid object like swarming bees.

TO PROVIDE suitable resting places for the spat, oyster men scatter "cultch"—clean shells, stones, and branches—in the water. As many as 15,000 spat have been known to cement themselves to a half bushel of shells. Recently, the Bureau of Fisheries demonstrated that shells inclosed in chicken wire, so that they form masses that look like logs, allow from ten to a hundred times as many young oysters to grow on the same area of bottom.

The spat soon develop adult organs and then begin filtering sea water, straining out the microscopic plants and animals which form their food, growing into "seed oysters" that are planted in beds to be fattened for the market later on.

While these facts were known, many

filter through its body to obtain its food? Can an oyster detect different chemicals in the water? How many hours a day does an oyster "work"? These questions Dr. Galtsoff and his associates set out to clear up. And ingenious were the methods by which they were answered.

To obtain an accurate estimate of the number of eggs a female oyster discharges, Dr. Galtsoff placed several specimens with their bodies full of eggs, in tanks of sea water. By raising the temperature, he induced them to spawn. An instrument, attached to the oyster, recorded on a graph the rhythmic muscular contractions that accompany each discharge of eggs.


AS SOON as the device showed that the spawning had ceased, Dr. Galtsoff stirred the water in the tank vigorously in order to distribute the eggs uniformly through it. Then a sample was taken and the eggs filtered out and then counted.

are bearing upon whether there will be a good or a bad spatfall. If the water is exceptionally cold during the spring months, it can be definitely predicted that the spatfall for the year will not be as good as when the water is warmer.

ANOTHER example of the important part the temperature of the sea water plays in the life of the oyster was discovered by the experimenters. It was found that spawning never begins until the temperature rises to sixty-eight or seventy degrees Fahrenheit. The main reason oysters are sold only in "R" months is that in warm weather, when they are breeding the taste is poor. A new process of freezing, recently announced by the Bureau of Fisheries, may make possible all-year-round consumption of this favorite seafood.


One of the most important events in the life cycle of an oyster is when the spat begins to cement itself to some solid object. Inability to set properly is a condition often encountered in northern waters. Recently, H. F. Prytherch, one of Dr. Galtsoff's associates, made a startling discovery which may have far-reaching effect. He found that a minute amount of copper added to the sea water increases the ability of the microscopic larvae to set. This amount is so small that dangling a copper penny in a tank for a minute, it was told, will increase the cementing power of the larvae. Settings have been induced in water that had as little as one part copper to fifty million parts water.

However, larger amounts of copper in sea water are distinctly harmful to oysters. In Long Island Sound, of late years oysters have been reported with green oysters—specimens of a dark hue and unpleasant taste. (Continued on page 60.)



Keeping oyster larvae free of disease germs is a problem that the Government experimenters have attacked. Into these jars go the larvae over whose growth careful watch is kept.

When Airships Were Death Traps



As the airship got caught fire, I leaped, landing on a swan in a lagoon. I was black and blue all over when rescued.



Concluding the Thrilling Story of

"My Forty Years of Flying"

By CAPTAIN HORACE B. WILD

MY MOST thrilling thirty seconds in the air was experienced at Tampa, Florida, in February 1907. I was flying a "rubber cow" as we called the early dirigibles, at 200 feet when a gasoline connection broke, the fuel ignited, and flames shot toward the gas bag, filled with 10,000 cubic feet of hydrogen which when mixed with air is as dangerous as T. N. T.

I was riding on a frail wood and wire framework along beneath the balloon. Sliding toward the engine, I tried to smother the blaze. My gloves and cap caught fire, burning my hands. The gasoline pipe, swinging from side to side, spouted flame like a blowtorch. Overhead, blisters were puffing out on the brown silk of the gas bag. The explosion was a matter of seconds.

While hydrogen must be mixed with air to burn, the envelope leaked sufficiently to be surrounded with a ring of igniting mixture. A circle of fire shot up the bag. In a flash, the envelope was a mass of roaring, shooting flames. I leaped out into space, 200 feet from the ground. As I jumped, the hooks on one of my high-topped shoes caught in the netting. For a split second I dangled head downward

RIDING in dirigibles above big crowds twenty-three years ago, Captain Wild and other daring aviators made America air-minded with their stunting done at the risk of life and limb.



Absolutely blind, I flew a dirigible guided only by a siren on a wagon.

before I kicked myself free and somersaulted through the air.


The dirigible was flying over a park when the connection broke. When I jumped, it was directly above a lagoon in which a score of big white swans floated.

As I fell, I heard a terrific detonation and saw flames shooting in all directions


above me. Then I struck. I landed in a sitting position directly on top of one of the swans, and an instant later struck the mud at the bottom of the pond. Just as I bobbed to the surface, the heavy motor and the flaming center section of the framework crashed into the lagoon not twenty feet away. When I was pulled out I was black and blue from my ears to my heels but without a bone broken. I ate my meals standing up for months afterwards. The miracle of being above that tiny pond saved my life.

CARRIED by the wind, pieces of the flaming gas bag fell among the barns of a large race track near by, starting a fire in which twenty horses perished. When I finished paying the bills, I was cleared out. I had come to Tampa in a private car, with \$22,000 in the bank. I left with my wife, baby, and a gripsack, thankful to be alive.


Fire was a menace that pilots constantly dreaded on the early airships. The sputtering, backfiring gasoline engines of 1907 were a continual source of danger. Explosive hydrogen was the only lifting gas we had. Helium, now used, cost from \$1,700 to \$2,000 a cubic foot before the




Buffeted about in a Chicago blizzard, the framework of *The Comet* struck a roof and tobogganed down into a vacant lot next door.



At right, Captain Wood starting in the dirigible race at St. Louis, 1907. His magnocow was jacked nose and his ship drifted away, landing in a distant field.



At Sioux City, Iowa, in 1907, Wood raced his *Comet* against the great racer, Dan Patch, who won easily. Dan Patch is seen blanketed in front of stand.



Young Dixon's mother, following flight in 1907, found him in Illinois.

war. Large supplies recently discovered in Texas and Kansas have reduced the price per cubic foot to three cents, and last year 8,000,000 cubic feet were produced for dirigible use. It will require 6,500,000 cubic feet of this gas for one filling of the gigantic containers of the *Akron*, the U. S. Navy's big airship now being completed in Ohio.

Little did I dream, when I was barnstorming through this state in 1906-7, that less than a quarter of a century later the world's biggest building would be erected on the outskirts of Akron to shelter an airship 650 times as big as the dirigible I flew.

Cronwell Dixon, 13, built his own dirigible and powered it with bicycle pedals attached to a tin propeller. He flew at St. Louis meet. in 1927.

At the banquet held in New York to celebrate the *Graf Zeppelin's* round-the-world flight last year, Dr. Hugo Eckener, the commander, with whom I had flown long before the war, told me that it is only a matter of a few years until sky-liners will leave for distant parts with the regularity of ocean steamboats. His fondest dream, which he predicts will become a reality in 1945, is a Zeppelin holding 20,000,000 cubic feet of helium, carrying 1,000 passengers and propelled by motors totaling 25,000 horsepower.

ANOTHER flight, almost as nerve-straining as the one at Tampa, took place at Anderson, N. C., on August 6, 1910. I was just recovering from injuries sustained in an airplane crash at Galesburg, Ill., when I received an offer of \$2,000 to fly a dirigible over the southern city. I jumped at the chance and wired

On the train down there, I was looking out the window when everything turned black. I had gone blind as a result of the nervous shock. For months, I couldn't see my hand before my face. The committee at Anderson asked me what I was going to do. I said I was going to fly the dirigible. And I did fly it without ever seeing the ground, piloting the "rubber cow" with my ears.

An assistant mounted a fire siren on a buggy and drove from the ball park where the airship was filled, across the center of town, around the outskirts, and back to the starting point, keeping the siren going all the time. With the dirigible at about 500 feet, I followed the sound. When I got back to the ball park, I circled around the point where the siren was screaming, coming lower and lower. When I was within 100 feet of the ground, the siren stopped and the assistant called:

Throw down your dragrope. I dropped the long rope overboard. It was caught and I was hauled safely to earth.



Captain Wild, center, and his crew with *The Conqueror* at the Indiana State Fair in 1908. At right the big tanks in which sulphuric acid from batteries and water were mixed to generate hydrogen.

That was the first guided "blind" flight of history. Last month I rode from New York to Chicago with a night air mail pilot who flew most of the way guided by invisible radio waves. As we roared through the darkness at two miles a minute, I recalled how I had groped my way at ten miles an hour following the sound of a siren twenty years before.

In 1908 newspapers all over the country printed, as a "startling prophecy," my statement that twenty years from that date mail would be transported from coast to coast in airplanes. On July 1, 1924, four years previous to the time set by me sixteen years before the prophecy came true.

On another occasion when I made a "blind" dirigible flight, the difficulty was that I could see too well. I took off at Terre Haute, Ind. late in the afternoon. We usually gave our exhibitions between five and six, when the air was perfectly calm. When we flew at fairs, the programs always announced: "Dirigible Flight at Favorable Hour!"

THIS time, I was circling over the Wabash River when the engine gave a sneeze or two and went dead. I drifted like a balloon and landed on the roof of a junkyard shed. It was after dark when I got the balky motor in good humor and started back for the fair grounds. All the street lamps were lit. The thousand glittering points of light confused me. I started in the wrong direction, got lost, landed again.

My manager drove up. He always followed me in a wagon to haul the airship home if the gas leaked out. We decided on a plan. He drove off with red flares sputtering at the rear of the wagon. From the air I followed this one-man torchlight



procession through the heart of town to the starting point. Just as we arrived, the propeller struck the top of a tree and snapped off.

Snapping "props" was a common experience with the pilot of a "rubber cow." These early propellers were made of canvas stretched over frames of Oregon spruce. Half a dozen of these "whirling rags" were always on hand. We also took along at least four spare rudders, folded up like Army cots. The rudder was the last thing over an obstruction, so it frequently got tangled with telephone wires, trees, and roof tops. When one broke off I shut down the motor and landed. An assistant would unfold one of the collapsed frames, attach it, and off I would go again.

TWO ropes, like reins, turned the rudders. Several times these ropes broke in the air. The most exciting experience I ever had with a disabled rudder was during a flight in a blizzard over Chicago in 1906.

I started from the foot of Chicago Avenue. I had hardly taken off when snow began to fall and the wind rose. The swirling flakes and smoke were so dense that I could barely see the ground from 1,000 feet. The wind was hurrying the big bag over the city in a northeasterly direction. Gusts struck it,

rocking the framework.

Over Ohio and Robey Streets, I tried to turn back into the wind. A blast struck the rudder. One of the controlling ropes snapped. The rudder flapped back and forth, useless. Out of control, the big bag swung from side to side like an angry elephant. I cut off the motor and began the battle to land.

I descended to 200 feet and threw out the dragrope. (Continued on page 142)



Lincoln Beachey starting race at St. Louis, 1907, which he won, making the circuit in less than five minutes. Notice the bags of ballast hanging from the ship's framework just behind the pilot. In center, the demonstration following Wild's record flight of five hours.

New Inland Canal Rivals Panama

Welland ship waterway made possible by brilliant feats of engineering that are unsurpassed even on Isthmus—Opening soon, it has world's longest lock

RIVALING the Panama Canal in many respects surpassing in magnitude, the Welland Ship Canal, most stupendous ever built to join two fresh-water soon will be open for shipping. Water on Lake Ontario to Port Colborne on Lake Erie, thus providing a deep-water link between these two huge inland

An idea of the proportions of this Canadian engineering project may be gained from the fact that the dirt which had to be dug to construct it is equivalent to that which would have to be dug in digging a seven-foot tunnel New York clear through the earth.

The greatest single lift in a lock on the Panama Canal is thirty-one feet. On the new Welland, the single lift is forty-six and a half feet. The total lift on the Panama is eighty-five feet. The total lift on the Welland is 326.5 feet. The longest lock on the Panama is a little more than 1,000 feet. One of the locks on the Welland is the longest canal lock in the world, measuring 1,380 feet in length.

Amazing feats of engineering, had to be accomplished. A whole river had to be buried in a tunnel seventy-five feet underground at one point and moved out of its course as much as he could possibly. And all of these things had to be done without interrupting the flow of traffic on the old system, which he now operates.

Cana's hosts in the longest oak in the world is the Walsby oak and it is 120 feet long. Upper right: huge gates weighing 40 tons each.


canal in the north reaches is 310

Links are eighty feet wide and have a side length of 820 feet.

Each rail of the steel gages at the lower end of each of the 111 bunks is eighty-two feet high, forty-eight feet wide, six feet long and weighs 405 lb.

Any of the locks can be filed in right-hand or left-hand patterns, which means that they will raise or lower the injured vessel, but can —

Apparently, with the law channel march-establishe in a heroic proportion



FIRE ENGINE DRAWS LIFE-SAVING BOAT

SEVERAL drownings in near-by ponds and lakes, with no rescue craft available within miles, aroused the inland town of Nauck, Mass. So its brush-fire wagon now dashes out on emergency calls, towing on its trailer a twenty-foot rowboat complete with oars, grappling irons, and a lung motor to resuscitate a half-drowned person.

SEND WRITING BY PHONE

GERMAN telephone engineers are experimenting with an attachment by means of

which written words may be sent over the line in addition to sound. The listener, using the German device, switches it on whenever he has difficulty in understanding a word. The speaker then spells it out and it appears before the listener in writing.


German long distance lines, it is expected, will be the first to use the attachment. Its inventors say it will popularize long distance telephone use in that country, where the transmission is seldom so good as it is on American long distance lines.

DUAL CONTROL CYCLE FOR TYRO RIDERS

IN ORDER that beginners in the sport of motorcycling may safely take driving lessons, a Berlin, Germany, motorist has perfected a dual control machine.

A special side car is fitted with duplicate controls for the motorcycle to which it is attached. Even the steering gear is duplicated, so there is no danger of green students losing control of the machine in an emergency.

This method of instruction has been used in autos and airplanes for some time, but this is believed to be the first instance of its application to the teaching of motorcycling.



With a motorcycle with two sets of controls, it is possible to teach a beginner to ride with little chance of accident.

ROBOT HANDLES PLANE IN FLIGHT

THE GROTESQUE "mechanical man" in the rear cockpit of this dual-control plane piloted the craft in a recent flight over a Brighton, England, airfield. His creator, Prof. J. Poppe, in the front seat, took the plane aloft and then turned over the controls to the queer-looking robot, who manipulated them in straight flight without a hitch. The "dummy" was a dressed-up version of the latest in automatic controls for aircraft, which can fly the plane on an even keel by means of gyroscopes.



The queer figure in the rear cockpit is a robot, made by Prof. J. Poppe, in front. Recently it guided this English plane safely.

TEST CHICAGO SOIL FOR NEW SUBWAY ROUTE

RESIDENTS of Chicago were interested recently to see men going about the city with well-drilling equipment which they set up at various points, sinking holes in the ground and then moving on to the next location. Few of them realized that the men were doing the first preliminary work on the projected Chicago subway. Before excavation starts, engineers must know what kind of earth the tunnels will pass through. In order to find this out, drilling gangs are sent about the city with instructions to bore down to bedrock at various locations.

They use ordinary well-drilling equipment mounted on a portable frame and driven by gasoline motor. Samples of the soil at various depths are taken and studied to see if the tunnels could be driven through them safely and efficiently. The same method is followed before the foundation of large buildings or bridge piers are laid.




These "well drillers" are getting samples of Chicago soil to help engineers on new subway.

CREWS OF SUBMARINES GET TOAST FOR BREAD

IN CONSIDERING the diet for a submarine crew for a cruise of more than five or six days, naval authorities found that the one article difficult to furnish was bread. After much experiment they have discovered that dry toast is the most satisfactory substitute. Bread is baked ashore and loaves are sliced and dried in slow heat. The slices are then wrapped and packed in cartons protected by a covering of waxed paper.

Fresh bread from the shore will keep only five or six days. It is not baked on board, because when fresh it is indigestible unless the eater is getting plenty of exercise. Officers and men like the dry or "dehydrated" toast they are getting now and find it an improvement over bread substitutes previously used.




NAME WANTED FOR NEW "LEMON-GRAPEFRUIT"

WHAT would you call a fruit that has the dimensions of a grapefruit and the color, taste, and appearance of a lemon? Botanists of the University of Washington's pharmacy school are seeking a name for this strange hybrid which they have grown. It is a by-product of their constant search for new plants useful in the manufacture of drugs.

The plant department of the pharmacy school specializes in all sorts of strange horticultural freaks which have resulted from the experimental work done in cross fertilization and grafting. The "lemon-grapefruit" is a result of one of these experiments, many of which are made in efforts to develop medicinal plants.

DESIGNED to supply water for two huge turbines, what is said to be the world's biggest "wye," recently constructed at Seattle, Wash., was shipped in parts to the hydroelectric development on the Skagit River. The branch pipes are fifteen feet in diameter and the main pipe is nineteen and one half feet in diameter. The "wye" is thirty-three feet long.

It is made of three-quarter-inch steel plates which are braced with steel angles and bars. Water from the dam divides at the "wye" into two swift-running fifteen-foot streams each of which will run a 95,000-horsepower turbine.



This "wye," biggest in the world, will carry water to turbines at Skagit River power plant.



WEATHER STRIPS KEEP CAR ENGINE WARM

New insulation boards shield a car's motor from wintry blasts. They are made of heat-insulating material and are fitted with clips which secure them inside the hood against the ventilation slits, preventing cold air from getting at the engine.

Heat from the motor is thus kept under the hood of the automobile.

LUMBER IN ONE TREE IS ENOUGH FOR 500 HOMES

CLAIMING a world's record for size and age, one specimen of a California Sequoia tree recently observed could furnish timber sufficient for about 500 five-room houses. Its age has been estimated at 4,000 years, and it is still hale and hearty. The Sequoias, world's largest trees, have an average height of about 275 feet, with an average diameter of twenty-five feet.

PLANE WITHOUT WINGS IS SPEEDY ICE BOAT

Looking like an airplane without wings, an ice boat built by several St. Joseph, Mo., boys whisks them over frozen lakes at a dizzy pace. Its body, resembling an airplane fuselage, seats two passengers and at the forward end is mounted on old sled runners. A two-cylinder air-cooled motorcycle engine and airplane propeller drive it. The vehicle is steered by swiveling the runner under the rear end of the machine.

BOTH SIDES OF PHONE TALK CAN NOW BE RECORDED


A TELEPHONE with a dictaphone attachment, recently exhibited in Chicago, makes it possible to obtain a permanent record of a conversation. Wax cylinders record the remarks of both parties and may be played back afterward like ordinary dictaphone records. By using this apparatus contracts can be drawn up and legally "signed" over the telephone.

HOW CARS KILL

NOT all fatal motor accidents occur while cars are running at reckless speeds, a state bureau of safety recently announced. A six-month survey showed that many mishaps occur while cars were being moved slowly in backing or parking in crowded places. Out of 1,142 such accidents, twenty-six resulted in fatalities.



This home-built ice boat is powered with motorcycle engine, which drives a propeller.






Demonstrating the new machine that records a telephone talk and can reproduce it at will.

WATER SPRAY IN CHIMNEY CLEANS SMOKE

WASHING smoke and gases from chimneys before they escape into the atmosphere has been accomplished by means of a water-spraying smoke-stack top recently developed. This device resembles a huge dish pan set on top of the chimney. A conical-shaped hood with rings of perforated water pipes inside it creates a curtain of spray falling into the "dish pan." Smoke and gases must pass through the wet curtain to find their way to the outer air.

For larger chimneys where combustion is less nearly perfect, a second curtain of spray is added to insure satisfactory operation. The mechanism does not interfere with the draft, as the cooling spray lowers the temperature of the gases, thus causing a shrinkage, which in turn creates a partial vacuum and thus actually increases the draft. The device, it is claimed, is applicable to all kinds of fuel burners.

Besides removing soot and ashes from chimney gases, the running water carries away tarry vapors and sulphurous fumes, which, although invisible, are injurious to plant and animal life. In tall office buildings, the washer keeps soot from blowing into upper story windows.



BOWED STEEL STRIPS ON CASTERS HOLD CARBOYS

Acid carboys, large glass jars in which chemicals are transported, may be easily handled by a new device. At one end several strips of steel are bent into bows and mounted on four casters. This is rolled under the container and hooked to its wooden casing, after which it may be rolled about plants or factories on the casters, or tipped over on the bowed side of the carrier for emptying. This device also is made in larger sizes for handling barrels of paint and drums of oil.

203 FOUR-LEAF-CLOVERS FOUND IN FOUR HOURS

SHOWING her keenness of eyesight, Miss Dorothy Schwarze, of Milwaukee, Wis., picked 250 clover stalks, each of which had more than the usual three leaves, in a search lasting four hours, setting what is perhaps a world's record.

In her collection were 203 with four leaves, fifty-four with five leaves, and two with six leaves. Superstition associates good luck with the four-leaf clover, bad luck with five leaves, and death with six.



Proving her keenness of eyes, Dorothy Schwarze set a new four-leaf-clover record.



NEW FISH LINE WEIGHT DISSOLVES IN WATER

A fishing line weight which dissolves on striking the water solves one of the most difficult problems connected with casting with rod and reel when live minnows are used as bait. It is made of sea sand mixed with a suitable soluble binder, so that it is hard as a rock when dried out. A new weight is used for each cast. The weight is attached by passing the line through the weight's lengthwise groove and bending the small wire seen in the photo around the line.

As soon as it strikes the water it dissolves, allowing the live bait to dart about to the limit of the line. This is impossible with lead weights as they drag the bait to the bottom where it is usually lost among snags and mud. Casting weights weighing as much as six ounces have been used in surf fishing from beaches, permitting the bait to swing with the waves.

HOME NO LONGER SAFE, ACCIDENT LIST SHOWS

"SAFE at home" is an expression with little meaning, according to a report on accidents recently issued by an insurance company. It cited the following unusual accidents:

One policy holder lost his front teeth when his baby broke them with a milk bottle. Another swallowed a tack, which he was holding in his mouth when someone slapped him on the back. A third man swallowed his false teeth while he was asleep. One farmer broke his foot when he kicked a pig.

A hot-water bottle got too full of steam and blew up, scalding another man. One individual broke his hand while he was pounding on his desk. Another man's glass eye broke, cutting his face. Two men suffered broken ribs from being hugged by girls.

Another man was dancing with a girl when one of her hairpins slipped into his ear and pierced his ear drum. A man and his wife noticed their dog about to steal a chicken from their kitchen. They both reached for the dog, the wife with a carving knife in her hand, and the husband lost a finger.

One of the strangest of the home accidents described in the company's records was that of a man who, receiving a sharp electric shock while in his bathtub, fell out of the window.

ASBESTOS SUIT SAVES WORKER FROM ACID

WORKERS in chemical factories or other places where acids, scalding water, or sparks might injure them dress for safety rather than appearance. An asbestos suit to protect acid workers was recently exhibited at an industrial exposition in Belgium. A hooded cape covers the head, the eyes being shielded by thick goggles.

The body of the suit is large enough to cover a man completely from neck to heel with specially-designed asbestos boots. Large mittens protect his hands, while a loose "skirt" of asbestos is draped along his right side. The protective suit is said not to interfere with the user's motions.



Suit of asbestos designed to protect the face, hands, arms, and legs of worker with acids.

NEW VENEER GLUE HOLDS WITHOUT CRACKING

A dry glue perfected by T. R. Truax, of the United States Forest Products Laboratory, may end troubles now experienced in making plywood or veneers. It is made in sheets, cut to the size of wood panels, laid between them, and held under pressure until it sets. This glue has held wood together even when tested by soaking in water. Its principal ingredients are dried black blood albumen and sugar syrup, the latter being used to retain enough moisture for adhesion after the bulk of water used in mixing it has been evaporated.

Before gluing, veneer is thoroughly dried but glues now in use contain so much water that it is necessary to dry them after they are glued. This causes checks and cracks to appear in the material, resulting in considerable waste.

TINY DETECTOR REVEALS HEALTH RAY




WITH the aid of a telltale detector that looks like a pocket microscope anyone can check up for himself whether his health lamp or special windowpane is supplying him with ultra-violet light.

Even a child can easily use the three-inch device. When held in sunlight or in the illumination of a good health lamp, a bright blue glow is seen in the indicating the presence of ultra-violet rays. The fact that ordinary window glass shuts out these invisible rays is demonstrated when a sheet of the glass is held in front of the instrument, causing the blue glow to darken.

The interior of the device, developed by the General Electric Company, is coated with a substance that

glows or "fluoresces" when ultra-violet light enters through a slit and strikes it, much as the luminous paint used on watch dials glows under the bombardment of radium or other radioactive material that it contains.


The detector should prove useful to seekers of sun tan by showing the strength of the sun's ultra-violet rays.



SHACKLE LUBRICATOR GETS GREASE HOME

ONE of the most difficult places to lubricate effectively on a car is the spring shackles, and standard fittings are not always built to withstand the pressure which is necessary.

A new lubricator, developed for one popular make of automobile, clamps over the regular fittings. It provides two connections to which a high-pressure grease gun may be applied. Then grease can be forced infallibly into the most inaccessible cranny. With this attachment it is possible to force the grease so thoroughly into the points that are the source of most of the objectionable squeaks, which are apt to destroy the pleasure of a



MACHINE WRINGS HAY DRY FOR BALING

A MACHINE that squeezes water out of hay while cutting it has proved a benefit to farmers. The motor-driven implement passes the cut crop through rollers, under 2,000 pounds pressure, wringing it dry enough to bale.

This machine literally "makes hay while the sun shines," for by its use it is possible to cut and bale a hay crop on the same day, instead of leaving it lie as cut to dry before putting in its stacks to "cure" as was necessary under the old way before it could be baled. It is claimed that better hay is produced by the new method, which means more vitamins for livestock, less work for the farmer, and a quicker harvesting of his crop.



When hay is cut it is no longer necessary to let it lie on the ground and dry before baling. This machine cuts it and subjects it to such pressure as to wring it dry.

WAR NOW DECLARED ON BOOK BUGS

THE silverfish, a queer insect that eats the covers off books, is being studied by the U. S. Department of Agriculture in an effort to eradicate it. The experiments have shown that the silverfish has a "sweet tooth" for starch. It is the starch in the paste used in making the books that the insect is after when it begins its destructive work.

Strips of cardboard coated with flour-and-water paste, to which is added small amounts of arsenic, are being prepared in the Home Economics Bureau to destroy the insects. They are scattered about the library to attract the silverfish in their search for starch, and kill them.

The silverfish is so called from the silvery glitter of the scales covering it.



BIG HOLE IN ATLANTIC AIDS SAILORS IN FOG

DISCOVERY of a new valley in the Atlantic's floor off the New England coast recently announced by the United States Coast and Geodetic Survey, will help fog-blinded seamen to know their whereabouts. It is two miles wide and eight miles long, sinking 1,800 feet below the normal bottom.

When heavenly bodies are obscured by weather conditions, mariners fix their position on the sea's surface by "dead reckoning." This consists in finding their rate of speed in a known direction from a given point, or finding the depth of water and character of the bottom over which they are sailing. These are found by taking "soundings." When this shows that a ship is over the great submarine valley her exact position will be known.

HOME WEATHERPROOFED WITH AUTOMOBILE TAGS

JEROME K. BARTLETT, of Boise, Idaho, solved the problem of weatherproofing his new home by completely covering it with automobile license plates. As they are coated with durable enamel, it will in many years before his house will need painting.

The builder got the idea for his novel home when he learned that an oversupply of plates was about to be junked by the state authorities at Boise. They gave him permission to cart the plates away.



Above, painting license plate "shingles" to the walls of a house built entirely of unadorned materials by a Boise, Idaho, man.

At right, Jerome K. Bartlett, who covered his house with left-over auto license tags.




NEW OUTBOARD MOTOR RUNS UNDER WATER

AN ENGINE that runs under water is the latest novelty for outboard motorboats. Motor, propeller, and rudder are mounted on one shaft, and the boat is steered by turning all three at once.

When designers wanted more space than inboard motors afforded within a boat, they tried putting the motor in the stern and driving the propeller through an L-shaped drive with gears. The new design goes a step farther, and shoves the motor completely out of sight and under water.

The motor is cranked by a handle atop the steering post. The exhaust is under water. Cooling the motor is simple, as its submerged position makes it "water-cooled" in more than the usual sense of the word.



This outboard motor is dropped beneath water line and acts as power and rudder for boat.

DIESEL ENGINES IN INDIA MEET BUS COMPETITION

AMERICAN railways are not the only ones that have had to improve their service and equipment in order to meet the inroads made on their traffic by motor bus competition. From England comes the news that even in far-off India railways are facing the same competitive situation and are taking steps to speed up their service, especially on short runs.

Two Diesel-electric locomotives have recently been built there to the order of the Indian State Railways as a measure for providing cheap, rapid transportation on short hauls on both the main and the branch lines of the North-Western Railway of India.

These locomotives will haul a three-car train weighing 100 tons at a speed of forty-seven miles an hour on a level track. They recently have been loaned to a Scottish railway, which will test them on its own regular runs to see that they are in condition before they are shipped for use on the far-away roads of India.

AMERICA'S HIGHEST AND LOWEST IN CALIFORNIA

WITHIN only eighty-six miles of each other are the highest and lowest points of dry land in the United States, according to the Geological Survey, Department of the Interior. A point in Death Valley, California, is the lowest spot, being two hundred and seventy-six feet below sea level, about the height of a fifteen-story building. Mount Whitney, also in California, is the highest point, 14,496 feet above sea level, nearly three miles high.

Strange Life of a Big Ship That Never Goes Anywhere



The compressed air siren, known as a "diaphone," just aft of the vessel's stack.

LIGHTSHIP No. 114, the new lightship, built to withstand the constant buffeting of ocean winds and waves, guards the shoals outside New York's harbor. She may remain at anchor for fifty years. Notice the compressed air siren, known as a "diaphone," just aft of the vessel's stack.




On her stumpy masts, Lightship No. 114 carries two 16,000-candlepower beacons. One is shown above. On clear nights they can be seen for thirty miles.



The new lightship, built to withstand the constant buffeting of ocean winds and waves, guards the shoals outside New York's harbor. She may remain at anchor for fifty years. Notice the compressed air siren, known as a "diaphone," just aft of the vessel's stack.

On her stumpy masts, Lightship No. 114 carries two 16,000-candlepower beacons. One is shown above. On clear nights they can be seen for thirty miles.

Keeping 400 Navy Airplanes Ready to Fly




INTO THE AIR AGAIN. A few of the Navy's 400 biplanes are shown here.

IT TAKES more than a lot of money to keep these planes in the best of shape. The Navy has 400 biplanes in its fleet, and it takes a lot of money to keep them in the best of shape.



THAT IT CAN'T OR TEST? A few of the Navy's 400 biplanes are shown here.



THEY TAKE 5 M. AN HOUR TO REPAIR. A few of the Navy's 400 biplanes are shown here.



FINISHING UP THE FUSELAGE. When a plane comes into the shop the fuselage is sandblasted down to clean metal and every wing is examined. When all fittings are perfect a new covering is put on and dope is applied, as above, to tighten and preserve it.



ABSOLUTE PRECISION NEEDED. After a propeller has been taken apart, completely refitted, and then assembled, the matter of balance and angle must be attended to. The blades are balanced to hair's breadth and set at required angle. At the left, a machinist is testing a blade.

Rivers Built in Strange Laboratory

ENGINEERS at the University of Iowa are studying flood control in a four-story hydraulic laboratory, where scale working models of rivers are constructed so that they may be observed under the closest possible approximation of conditions in the actual streams.

A ten-by-fifty-foot canal 100 feet long carries river water from a nearby dam at Iowa City to the laboratory basement. From here it is pumped to the top floor where a constant-level tank maintains an even flow of water to all parts of the building in which tests are being conducted. Large-size river models are constructed on this floor in a ten-by-forty-three-foot trough. It is mounted on jacks so actual slopes of river beds can be obtained.

Twenty miles of the Mississippi River were recently built to scale in the laboratory, showing the stream between Hastings and St. Paul in Minnesota. The object was to determine what effect the river would have on a dam being planned at Hastings, which is designed to maintain a constant level in the river above that point.

In order to do this it will have gates that permit surplus flood water to flow past the dam from above. But the Mississippi does not like gates in its path, and when its current is forced through their narrow openings it scours out the bottom at those points. These conditions cannot be



Above, hydraulic laboratory at University of Iowa and, left, model of Des Moines River.

calculated by mathematical formula, but observation of water running through actual gates in the model showed engineers how to build their dams to withstand the scouring action of the river's current.

In constructing these models, every detail of the real river is studied and reproduced to scale. Depths of water on straight lines across the stream are measured at frequent intervals. Strips of tin are then cut to contours shown by these figures. The strips are placed upright at correct intervals along the model trough and the river bed is modeled to their high and low points.


Where cement is used to represent river bottoms, it is rilled to imitate the effect of currents on soft ground. Sand and gravel are used at points where the current is rapid, to show how much the river will dig out its bottom in a given time.

After working models of the river have been used for several hours, water is drained off and the bottom laid bare for study. By this means several efficient methods of flood control have been devised. In one instance engineers not only reproduced the river bed, but they made a working model of an entire flood!

Other parts of the building are used for studying the effect of bridge piers,


railway trestles, and piling on river currents. These also cause a scouring effect on the bottom when placed in swift currents, sometimes with disastrous results to themselves. This can be avoided by study of models that show the best manner of placing foundations for such structures.

Models of river beds have for several years been studied in foreign hydraulic laboratories, at Cornell University, Ithaca, N. Y., and at Worcester Polytechnic Institute, Massachusetts. The one at Iowa City is believed to be one of the largest in which river beds have been studied.



Using a ten-inch model channel, an effort is being made in the center picture to determine, by means of Pitot tubes, the velocity of spread in an eighteen-degree bend. Directly above is a small scale model of the dam at Gray's Mills, showing the power plants around which sediment collects.

TEN-TON STATUE IS RAISED 400 FEET



POCKETS IN NEW ALBUM HOLD PHOTOGRAPHS

SOMETHING new in the line of photograph albums was recently placed on the market by a New York firm. It is designed on much the same principle as a large pocketbook. Pictures are held in pockets, which vary in size to accommodate different-sized photos.

It is not necessary to paste them in, and they may be removed and passed about for examination. The simplicity of inserting the photographs insures that they will be put in place as soon as they come from the finisher, lessening the chance of loss.

NEW PROCESS EXTRACTS RUBBER FROM MILKWEED

Proving that rubber can be made from milkweed, Arthur E. Bergquist, of Lindstrom, Minn., amateur research worker built a model apparatus with which he has made small quantities of rubber. A tall odd-shaped chimney carries a tank and wine-surfaced wheel at its top, the tank being filled with milkweed sap. Heat from a birch bark fire heats tank and wheel.

When these are thoroughly heated the sap is allowed to flow onto the wheel while it is slowly rotated. Solid matter sticks to the wheel, but liquids drop off into the chimney. The solids left on the wheel are raw rubber that is elastic and is said to compare favorably with the best rubber from plantations in Para and India.



With a machine he invented, Arthur E. Bergquist of Lindstrom, Minn., has succeeded in extracting rubber from the lowly milkweed, a sample of which is shown at the right. The hot sap leaves its rubber on the wheel at top of machine illustrated above.

Riggers on the new state capitol building at Lincoln, Nebr., raised a ten-ton statue the other day from street level to the tower top, a distance of 400 feet. The huge bronze figure on its airy perch represents a wheat sower of Biblical times, but onlookers and workmen christened it "Bozo." Twelve picked men were chosen for the task of giving Bozo his dizzy ride and putting him in position on the tower.

His ride took but twelve minutes, and there was no hitch in the proceedings. The hoisting engine that raised him was located so its driver could not see any of the operations, but he performed his share in the task successfully by receiving his orders over a telephone—bell signals not permitting such positive control.



This ten-ton statue of a symbolic wheat sower is seen hooked to tackle for 400-foot ride.

of the hoist as instructions by the human voice. An ordinary telephone headset was clamped over his ears during the lifting of the statue to its place.



From the ground to the top of the Nebraska State capitol the statue was raised safely.

LOUDSPEAKER IN CAR WARNS PEDESTRIANS

A BRITISH motor car has just appeared that has no horn, but is fitted with a loudspeaker instead. A microphone, attached to the steering wheel, is connected to a dynamic speaker under the hood. By using this device the driver can warn pedestrians, telling them what he is about to do, or notify drivers of other machines when he is about to turn or stop.

This is believed to be the first instance of the use of a loudspeaker in a private car. Machines have been so equipped for the purpose of making public announcements, but hitherto they have not been used as a means of warning pedestrians.

As shown below, the microphone is strapped to the steering wheel at a height convenient to the driver's mouth.



A microphone on wheel and a loudspeaker under hood enables driver to shout warnings.



GOVERNMENT DEVELOPS GIANT SUGAR CANE

A new sugar cane that yields three bags of sugar where the best commercial varieties produce but two, has now been made available to planters by the United States Department of Agriculture. In addition to giving more sugar this plant is highly resistant to mosaic disease, which did much damage to Louisiana cane fields before it was checked by plants brought from Java.

For the last three years experimental fields at Canal Point, in the Florida Everglades, have produced nearly three tons of sugar an acre, double the average yield.

NEW AUTO TOY GIVES CHILD CHANCE TO DRIVE

SO THAT children may "drive" when they go automobiling with their parents, a new toy has recently been placed on the market. A U-shaped tube, one end attached to the child carries a small steering wheel on its other end. With this the child can turn the wheel and toot a horn.



Wheel and horn attached to child give him the thrill of driving when riding in auto.

"PINHOLE" IN METAL MAY HARBOR MANY GERMS

METAL parts of machines such as fruit juice extractors and soda fountain equipment must have an absolutely smooth surface and be free from imperfections or any imperfections in castings and welds. Users of this machinery have found that one such pinhole may house millions of germs. Consequently, one maker gives his welders efficiency tests. A man who makes only one pinhole in a weld scores ninety percent, and none at all counts 100 percent.

BOOSTS V-SHAPED BED AS BETTER FOR REST


AN UNUSUAL looking bed insures better rest and relaxation, according to its inventor, Joseph H. Pilates, former physical director of the German police force. It is made in two sections, in the shape of a "V." This shape, Pilates says, supports the body perfectly at every point no matter what position the sleeper may assume. A lever raises the bed to the conventional horizontal position whenever desired. Models have been designed for household, beach, and camping use. Pilates plans to manufacture the bed in this country.



MEN RIDE ENGINE FRONT TO STUDY POWER

How much horsepower does a locomotive develop under actual operating conditions out on the road, drawing a heavy train? This is the question that men behind this odd-looking shield on the front of a British passenger locomotive are seeking to answer. While the engine is speeding over its run they will make "pictures" of the work done by steam in its cylinders using for the purpose a little instrument known as an "indicator."

It is mounted on top of the locomotive's cylinder, steam from which enters it through a connecting pipe. In response to the fluctuation of steam pressure in the engine's cylinder, the indicator charts a record on a paper card. This is taken back to the railway offices and analyzed, the results often enabling engineers to make adjustments in an engine's mechanism that materially improve its efficiency.




When a piece of bone dry

BALANCE IN SHOP TELLS MOISTURE IN LUMBER

NOW a woodworker can tell by the condition of the air in his shop how moist or dry his material is. A balance developed by the U. S. Forest Products Laboratory weighs the amount of moisture that the wood is likely to pick up from the air, just as if it were so many pounds of peas on a grocer's scale.

A standard piece of wood, hung on one arm of the balance is cut to weigh when bone-dry exactly one hundred units of any one hundred quantity. Therefore, when the air is dry the balance swings perfectly. But if six units, say, must be added to the weights to maintain balance, the sample is known to have absorbed six percent of its weight as moisture from the air.



An observation box on the front of English locomotive used in getting data as to actual horsepower.

NEW LAMP REFLECTOR IMITATES DAYLIGHT

A new reflector that can be slipped onto any lamp adds to lighting comfort by imitating daylight. Its blue-glass mirrors distribute a soft white light, said to be easier on the eyes than the glare of ordinary bulbs and pleasanter to read by, as it filters out the bulb's yellow rays.

A spring holder quickly and easily fastens the reflector to a bulb, no screws or other devices being required. Unsilvered transparent rings of glass in the reflector allow the light to shine sideways through the shade of a lamp, as well as downward, for reading. Fifty- or sixty-watt lamps are said to work best with this daylight device. The reflector, designed especially for use with a bridge or reading lamp, may be used to advantage on ceiling or wall lights as well.



NEW ENGINES USE OLD TWO-PRESSURE BOILER

GERMAN railway engineers have found that the principle of the "two-pressure" boiler, developed by Jacob Perkins, an American engineer, in 1832, can be applied to modern locomotives with great efficiency as a result. Experimental engines built in this way have, they claim, hauled trains at lower cost than is possible with the most modern central station electric power generating system.


The water tube boiler, which consists of a small upper cylindrical portion connected to pipes that line the fire box, produces steam at 1,800 pounds pressure after the steam has passed through superheaters also located in the fire box. This steam supplies two high-pressure cylinders and then exhausts into the second boiler, which is of the ordinary fire tube type. Steam from this boiler operates a low-pressure cylinder of much larger diameter. Thus more of the heat developed by the burning coal is turned into usable power.

LOCOMOTIVE WHEELS DROP OFF IN REPAIR SHOP



shown in the picture and above.

Then the whole elevator shifts sideways on a subterranean pair of rails, the motors are reversed, and the locomotive wheels reappear on the same level as the engine. They may be rolled away then over the shop floor into the repair room. The husky electric elevator, recently developed by a Muskegon, Mich., firm, can handle loads up to fifty tons.



On one of world's longest auto bridges, crossing James River, Virginia, drivers are told to go forty miles an hour—or faster.



At top, engine wheels being lowered for repair; above, the wheels seen in elevator.

GREAT HIGHWAY BRIDGE SPEED DEMON'S DELIGHT

TRAFFIC officers have no difficulty in enforcing the forty-mile-an-hour minimum speed limit on the James River bridge connecting Newport News and Norfolk, Va. This makes the four-and-a-half-mile concrete span one place where motorists can step on it to their hearts' content. While there is a speed below which you are not allowed to drive over this bridge, you can go as much faster as you care to or your car will go. The new ruling is said to have speeded up traffic satisfactorily on this link in the southern highway system, which is one of the longest highway bridges.

The photograph at the right shows traffic officer E. Hogue, stationed on the bridge, telling a puzzled motorist to "step on it" to avoid congestion.

MINE MULE NOW WEARS HEADLIGHT ON COLLAR

MULES wear headlights, just as miners do, in a Pottsville, Pa., coal mine. An electric flashlamp, suspended from the collar of the animal's harness, enables it to see its way when it plods through a dark underground shaft towing a coal car. The mules show their appreciation by the increased efficiency of their work. This is only one indication of the sweeping changes that the use of the electric light has brought to the mines of the world. It is a far cry from the safety lamp invented by Humphry Davy and Michael Faraday, a century ago, to the brilliant headlight now worn by a mule in a mine, every part of which can be thoroughly lighted with little danger of fire or explosion.



No longer groping in darkness, the mine mule now carries a headlight on collar.



THREE RAILWAY TRACKS RISE ONE ABOVE ANOTHER

AN L V T street railroad crossing is located at Seventeenth and Dock Streets, Richmond, Virginia. Tracks of three large trunk line railways cross each other at this point, one on the ground level, and the others at different heights on steel trestles. As Richmond is a busy railway center, trains are passing this point on one or another of these three levels almost constantly during the day and night.



MATCH SCRATCHER HOOKS TO STEERING WHEEL

For the driver who smokes, a new match scratcher that can be mounted on the steering wheel has just appeared. It carries a small oblong of abrasive material, and is held in place by a rubber tab that buttons tightly to one of the spokes. The device removes temptation to strike a match on the wheel or instrument board.

WORLD'S ONE FISH HOSPITAL KEPT BUSY

THE only fish hospital in the world is that run by James Pamer, of the Walker House Hotel Aquarium at Toronto, Canada. Patients are brought to it from all parts of Canada and the United States. They suffer from many of the ailments common to human beings such as eye inflammation and consumption. The most common fish disease, however, is fungus, which is caused by changing the water too often.

In the hospital each sick pet is placed in an individual tank. Like cots in a human hospital ward, each has the patient's record on a chart hanging over it.

Operations are also performed on the fish. In one case, after all known methods of diagnosing fish ailments had failed, an X-ray was used on the patient, showing a stone lodged in its stomach. This was removed and the patient rapidly recovered.

Dieting forms an important part of the treatment of patients in the fish hospital. The invalids are fed on dried shrimp, calves' liver, whole-wheat bread, beef, codfish, and eggs.



An X-ray picture of a pet goldfish made in the world's only fish hospital at Toronto. At top, performing a life-saving operation on a patient.

BAD SMELLS NOW WARN MINERS OF DANGER

WHEN a miner notices a particularly bad smell in the air of the shaft, and sees the electric lights flash nine times, he knows that it is time to get out—quickly. That is the new danger signal recently adopted by the American Standards Association that will be used in metal mines in case of fire.

The United States Bureau of Mines, which tried out the scheme, first experimented with pleasant smells as a warning but found bad ones more effective. The odors, used in liquid form, are sprayed into the ventilating shafts of the mine and shot underground along with fresh air at the rate of thousands of feet a minute. Odors found effective are butyl and ethyl mercaptan, which have the smell of decayed cabbage; butyric acid, suggestive of rancid butter, and banana oil, whose pungent aroma is like nothing else.

BIG TREES UNHARMED BY LAST YEAR'S DROUGHT

LAST year's dry spell did not damage trees as much as might be imagined, says the American Forestry Association. Since that body has not as yet received notice of many large trees being harmed, it is believed that small trees were the principal sufferers.

Among those hit hardest were the Ben Davis apple tree and dogwood in Pennsylvania, Maryland, and Virginia. This apple tree is considered one of the hardest of its kind, but its high death rate was due to the unusually heavy crop that probably left it in a weakened condition. The dogwood died in great quantities because it grows in shady places, with its roots seeking to live in soil near the surface from which the larger trees had already extracted much of the nourishment.

The Forestry Association believes that those trees whose leaves withered and fell early in the fall were unaffected by the dry spell and will be green again this spring. The Association's report says, however, that those trees whose leaves turned at an early date, but did not drop off until well into the winter months, are almost all dead.



UNIVERSAL FILE HANDLE SCREWS ONTO SHANK

A NEW convenience for home workshoppers is this file handle that screws on the shank of any file. In the screwing end is a die that cuts a thread on the metal shank. The result is a handle that can be detached at will, but which cannot come loose even when used in hard service.

FINDS BALL OF COLD FIRE IN DEADLY GAS




Jack C. Cotton, Columbus, Ohio, watching the ball of cold fire caused by a rapidly alternating current of electricity passing through metal tubing wound around the glass globe.

A STRANGE ball of cold fire, confined in a glass globe, is the plaything of Jack C. Cotton, of Columbus, O. While preparing for his master's degree in science at Ohio State University, he rigged up the apparatus shown in the picture. When he passes an electric current alternating 400,000 times a second through the spiral of metal tubing, a cold but firelike light glows within the globe. The vessel is filled with poisonous carbon monoxide gas.

There is no metallic connection between the coil and the gas. The phenomenon is called an "electrodeless ring discharge" by Cotton.



PORTABLE PUMP IS REAL FIRE ENGINE



This new portable pump, motor driven, so light that two women can carry it, makes a powerful fire engine.

A LITTLE motor-driven portable pump developed in Germany makes a handy fire extinguisher or emergency pumping apparatus for farms, factories, or construction works. So light that two women can easily carry it, it will handle as much as 20,000 gallons of water an hour. Its three-and-one-half horsepower two-cycle water-cooled engine is so simple that no mechanic is needed to keep it in operation.

The motor runs on low grade fuel at from 1,400 to 1,600 revolutions per minute. It has a wide field of use in positions where permanent pumping installations are not available.

DESPISED WEED ADDS VALUE TO FARM LAND

FARMERS of the Imperial Valley, in California, have found wild hemp, a familiar weed, will in two or three months replenish exhausted soil as thoroughly as alfalfa and do the job more quickly. Wild hemp grows abundantly from the Atlantic to the Pacific Coast, and from the Mason-Dixon line south to an undetermined point in Central America. In a few weeks it towers seven to ten feet high and is of jungle thickness. According to D. E. Creighton, assistant farm adviser of Imperial County, discovery of its ability to enrich soil may prove the greatest advance in farming since water was brought in to irrigate the American Desert.


During the months when the soil is "resting" the depleted land is plowed and seeded with wild hemp. Tractor machinery then plows under the luxuriant crop, stalks and all. The formerly-despised weed is now said to be adding from ten to twenty-five percent to the \$12,000,000 crops of the Imperial Valley.

FRUIT FLAVOR PROBED IN VACUUM STILL

WHAT makes a cherry taste like a cherry and a peach like a peach? To find answers to these questions, E. K. Nelson, of the Chemistry Bureau of the Department of Agriculture, is making experiments with a new type of still, recently imported from Germany. The new apparatus is being used to isolate and study the essential oils of different fruits and determine their exact chemical composition.

The new still makes use of the fact that as air pressure decreases, the boiling point lowers. Within the vacuum chamber of the new still the liquid comes to a boil quickly at comparatively low temperatures.

Discovery of what gives a fruit its taste would



With this vacuum still, chemists in the Department of Agriculture are searching for the secret of flavoring in fruits.

LOPSIDED GOLF BALL PICKED OUT BY GAGE

BECAUSE a lopsided golf ball may spoil a player's game, a midwestern firm has devised a "golf ball gage" to test its trueness. A good ball should pass freely through one of the circular openings. Two apertures, of 1.62 and 1.68 inch diameter, permit both the old and the new standard golf balls to be tested. The tester is small enough to be carried in the golfer's pocket or in the ball compartment of the golf bag.




Golf ball gage which tests both new and old size balls and shows if they are lopsided.

SIBERIAN WOLVES MAY HOWL IN MICROPHONE

PACKS of wolves that infest the plains of Siberia will announce their presence through microphones, in a plan proposed recently by scientists of Soviet Russia. At intervals throughout the country, microphones like those used by radio broadcasters would be hung on trees and posts and connected by wire with a central telephone exchange or listening-post.

When the operator at the wolf center heard the howls of a pack, he could locate it at once with the aid of a map showing the position of the microphone, and dispatch rangers or volunteer hunters to exterminate the animals. The scheme is being urged in an effort to conquer the wolf menace, which has made travel dangerous in large areas of Siberia.



MACHINE DIGS UP OLD ROAD, LAYS NEW ONE

Old grave roads go into one end of this strange machine, coming out at its other end in the form of new ones. It moves along over highways breaking up the surface, picking up the chunks, mixing them with a "bituminous binder"—a tarlike by-product of soft coal—and re-laying it in the form of a new road.

The machine, developed in Cedar Rapids, Iowa, travels under its own power, and it is claimed will do the work of several road gangs and save much time.

EVERYBODY IS HAPPY, PSYCHOLOGIST FINDS

MOST people like to call themselves happy, according to Dr. Randolph Sailer, psychologist at Yenching University, China. Only sixty workers out of 300 whom he questioned admitted that they were less happy than the average mortal. None was a complete pessimist.

Money, jobs, and education seem to have nothing to do with happiness, Dr. Sailer and his coworkers have found. Smokers and nonsmokers are both happy. Men are happier as a rule when married.

ICE BOX GALE TESTS WARMTH OF CLOTH

A NEW YORK department store finds out how warm overcoats are by testing material in this apparatus which measures the amount of heat that can escape through the fabric. The heating element around which the cloth is wrapped is maintained at 98.6 degrees Fahrenheit by electricity. It is placed over the opening in the electric refrigerator on which it stands, and a fan blows cold air over it in imitation of a severe winter gale.

The cloth's resistance to cold shows on dials on top of the apparatus. Ephraim Freedman, who designed it, has found Alaska seal to be the warmest garment material he has tested on it.



Cloth wrapped around heating element is exposed to icy blast from refrigerator to test cold resisting quality.

The Architect Builds His Own Home—A Series Design Your House to Fit Its Site



Before the fireplace in the living room of the Risley home in Los Angeles, Calif. This room has windows on four sides but in spite of that the arrangement gives large wall space.

By

W. L. RISLEY

Los Angeles architect, who built dwelling on unusual shaped lot and won honor award, describes it for you



A NUMBER of interesting conditions were to be met when the house shown in the accompanying photographs and plans was designed and built. The lot was sixty by 140 feet in size, with the street end facing to the west. The lot rose and rose about twenty feet from front to rear, giving a grade of approximately one in eight, and necessitating, for such a small lot, numerous retaining walls, terraces, and different levels.

Since the soil is adobe and expands when wet, special precautions were taken to insure each level being properly drained. Inasmuch as large trees are not as plentiful in Los Angeles as in the East, the five quite large eucalypti, in scattered locations, were to be kept, and the house built.

To obtain the fine view of the wood Hills on the north, to deprive the home of the sunlight from the other compass, an L-shaped plan was adopted.

These conditions combined with the designing of this place from that of the usual city small home on a level lot. The frank acceptance of unusual locations generally results in homes that seem to fit their sites.

Local zoning ordinances fixed the exact distance of the front of the building from the street. After the number of rooms and their general size was determined, the next step was the locating of the main garden, with a view to the accessibility



and the continued rise from street end to rear, it was necessary to build a high retaining wall



Interior of the office, showing fireplace and the battery of windows, with built-in drawers below, overlooking patio.

which, as shown in the photograph, was stepped down to follow the gradient of the street, giving continually increasing impressions of size to the garden. This condition also permitted rather unusual treatment on the entrance steps, which lead up to the main entry by way of several terraces, overcoming without effort the rise of the lane.


At the foot of the steps, an electric light is set behind frosted glass, flush with the wall and about waist high. Over and around this grows English ivy, so that when the light is turned on, the appearance of an ever-changing pattern is given. Steps and terrace are flanked by hedges and foliage plants.

Owing to the steepness of the slope at the front there is no lawn. Instead, the planting is arranged to give privacy and block out the street so that, as one looks from the windows of the first floor across the garden and in unbroken vision to the gardens of the homes across the street, there is no apparent intrusion of any thoroughfare.

All the trees, hedges, foliage plants and so on were carefully planned and placed to enhance the architecture of the house. A complete sprinkler system, with the sprinkler heads adjustable in height, makes watering an easy task.

From the front, the house gives little evidence of having two full stories, yet there are two bedrooms, bath, and attic on the second floor. The main entrance was inspired by an old Cotswold doorway, and a stone tablet over the doorway carries the initials of the owners and the date the house was built. In a way, this seems to indicate that the structure was erected as a permanent home and not as a transitory dwelling-place or one "built for sale."

The garden. This plan well as that in the front and rear ensures privacy. But not and the planting it is a see into the first-floor rooms either from the street or the two sides. Such planting also adds to the beauty of the garden establishment as a whole.



Tradesmen's entrance. This door and the path that leads to it are blocked off and cannot be seen from rest of house.



Exterior view of the Roney home. The house, in spite of its low elevation, is full two stories in height and was designed to blend perfectly with its surrounding trees and foliage.

makes glimpses of the house more alluring than landscaping where the front of the building is left open to view.

The living room, dining room, kitchen and two upstairs bedrooms all face east thus enjoying not only morning sunshine but all the privacy and quiet beauty of the garden. Off the living room is a small terrace, flanked by a large eucalyptus tree and surrounded by potted plants forming a pleasant spot for the serving of meals out-of-doors. It was necessary to cut back the roof at the eave to permit this fine tree to remain where it was.



convenient place to water the plants and to keep the upper garden wall opposite a fountain with a border of Mexican tiles in soft blues and yellows.

Study of the plans will reveal that our

house is most compact, with little space for halls. It contains downstairs, a living room, small dining room paneled in Oregon pine, kitchen, back porch, and small bedroom so designed that it may be used as a guest room, study or man's room, as needed. A bathroom attached to his bedroom also connects with the back porch. Upstairs are the master's bedroom, a guest room, and bath.

Floors, with the exception of those in the bathrooms, hall, and kitchen, are select oak stained almost black. Kitchen and screen porch have linoleum flooring, while red quarry tile is used in the bathrooms. The tiling in the hall was found in the "junk pile" of a tile yard, and ranges from red to tawny yellow. It is quite rough in texture, undoubtedly the reason for being discarded. Yet it blends beautifully with the Oriental rugs in the living room and wears well.

Woodwork of the entire house, with the exception of the kitchen and bathrooms, is finished in silver gray. The wood was first stained dark with acid and then waxed. Rottensone was added to the wax to give it a gray color. Walls are of steel-troweled

a warm neutral color. Windows are steel cottage casements, with operating rolling screens. Electrical and gas furnaces supply heat.

Curtains in the living and dining rooms are Spanish homespun wool, of a warm parchment shade. Old Oriental rugs and some fine Chinese Khassas give color and warmth to the interior. An effort was made to so design and finish the interior of this home as to make it a background for furnishings.

An unusual feature of the living room is that it has four exposures and yet has considerable wall space. There are no fixed electric

(Continued on page 14)

Improved Tools to Make *Housework Easy*



MAKE ICE BOX COOKIES. Ripening dough in a refrigerator is a method used by the best bakers. A new set of cookie molds in which dough is packed makes it easy for any housewife to do the same.



MINIATURE DRY CLEANER. Small articles can be dry cleaned at home now in a jar containing cleaning fluid. The articles are swished up and down in the jar.



PAO COOKING. A new device is

placed on the market. It should prove useful to the housewife who follows broadcast cooking directions of which she wants to make sure.

AREA CLT FLOWER. Placing a console area heat heater in a room is an instant source of warm air outlet of the room so well heated that fresh flowers are without waiting.



SPRAY TO COOL BOTTLES. When the rubber ring is slipped over a bottle and the tube connected to the faucet a chilling spray pours around the bottle.



A BUILT-IN STRAINER. A new style cook pot has a strainer that arches halfway over its top, permanently attached to it. When vegetables are cooked the water is poured off through the sieve. Handles at the sides make a firm grasp possible. Tongs for removing vegetables are unnecessary.



PAN & GLASS CEREAL PACKAGE. Less messy and more convenient than the original packages are glass containers that nest in a compact group. Sloping fronts with close fitting airtight tops keep the jar tightly closed, preventing the cereal from getting stale.



ALUMINUM MIXING STICKS. These new "swirler sticks" can be twisted rapidly by rubbing them between the palms of the hand. The small size fits cup or glass; the larger is used with bowl or pitcher.



**TEA CART AND BRIDGE TABLE COM-
BINATION** By ROBERT
BANKS
This new
table is
designed
for use
as a
bridge
table or
tea cart.
It is
made of
metal and
wood.



**TEA CART AND BRIDGE TABLE COM-
BINATION** By ROBERT
BANKS
This new
table is
designed
for use
as a
bridge
table or
tea cart.
It is
made of
metal and
wood.



**TEA CART AND BRIDGE TABLE COM-
BINATION** By ROBERT
BANKS
This new
table is
designed
for use
as a
bridge
table or
tea cart.
It is
made of
metal and
wood.



HOLDER FOR STOVE RINGS An added con-
venience for coal ranges is this rack for the
various sized rings. When several of them are
removed and using the size of the opening to
the pot to be used, they may be hung for ready
use, and get out of the way, on these small arms.



MILK BOTTLE SEAL
When a bottle of milk has
been opened, it can be
sealed in a sanitary man-
ner with one of these new
paper seals which success-
fully closes it against dust,
flies, and household pets.
The brown paper disk folds
down around the bottle and
a gummed paper tab en-
sures the neck to hold the
seal securely in position.

POPULAR SCIENCE MONTHLY



RAYMOND J. BROWN, Editor
ARTHUR WAKELING, Home Workshop Editor
ALFRED P. LANE, Technical Editor
ISRAEL DOKROW, Art Editor

Published Monthly by Popular Science Publishing Company,
Inc., 201 Fourth Avenue, New York City. Single Copies Twenty-
Five Cents. In the United States and Its Possessions and in
Canada, \$2.50 the Year. In All Other Countries, \$3.00 the Year.

America's Healthiest Year

ACCORDING to the mass of statistics compiled by one of our largest life insurance companies, the people of the United States and Canada enjoyed better health during 1930 than in any previous year.

However, before we start patting ourselves on the back perhaps we had better see whether we are really entitled to any credit for this fine showing.

According to the figures, there is a general falling off in the number of deaths from communicable diseases such as typhoid, diphtheria, influenza, tuberculosis, and so on. But there has been an increase in the number of deaths caused by suicides, homicides, and automobile accidents.

It seems that the doctors, by keeping eternally at it, have literally forced us to take the precautions that will prevent the spread of infectious diseases. They have, indeed, forced us to reduce deaths from these diseases more than enough to counterbalance suicides, murders and highway accidents over which the doctors, unfortunately, have no control.

It seems fitting therefore that POPULAR SCIENCE MONTHLY'S \$10,000 award for scientific achievement should go to the medical profession.

Are Business Leaders All Dead?

BUSINESS has slowed down. Millions of men who want work can't get it. Their families are in want, and relief plans are flourishing everywhere. Economists say the cause is overproduction and speculation, and everybody is waiting for a "turn" in business.

This is not the whole story. It is difficult to picture the industrial leaders of America waiting like gamblers for their luck to change; and yet, in the existing crisis, business does seem to be suffering from a conspicuous lack of courage and brains.

The business man who discharges employees because he feels that he has to cut expenses actually is admitting that with all his money, all his credit, all his brains, and all his experience he is unable to think of a way to use labor to produce something that can be traded to somebody else for what it cost plus a fair profit.

Most business men apparently aren't thinking very hard or they would find a thousand things that people want and are willing to pay for but cannot get. Neither, in general, are our statesmen and political leaders, for the undertaking of needed

public work would do much to relieve the present depression.

For example, there are undoubtedly thousands of people in the vicinity of New York City who would gladly pay for the privilege of driving their automobiles through a tunnel under the East River to Long Island. Such a tunnel was completed under the Hudson river between New York and New Jersey three years ago. It cost \$50,000,000 and between 5,000 and 7,000 men worked on it for seven years. It will pay for itself within ten years, meanwhile paying from eight to nine percent on the investment. Already another tunnel twice as large is needed at the same place. Only two of the great railroad systems have terminals in New York. The rest dump their passengers off on the New Jersey shore, letting them find their way to New York by ferry or tube, as they can. Present-day conditions demand that these roads construct a union terminal in New York with a connecting tube under the Hudson river.

These projects would not solve the unemployment problem, even for New York City, but, if they were attempted now, they might serve as a spur to business, for they would indicate that some of those to whom we look for leadership possess brains enough to seek a remedy for an evil condition and courage enough to prosecute difficult work in face of the cry of "hard times."

Deeds Rather Than Words

PUBLIC SAFETY, an interesting little magazine published by the National Safety Council, has been conducting what it calls a "national word hunt," seeking a short synonym for "motor vehicle fatality," which it regards as a "cumbersome term."

Public Safety's own candidate is "autocide." Various readers of the magazine have put forward "motorcide," "highway-cide," "carrocide," "motorhate," and "M. V. F." (the initial letters of "motor vehicle fatality") as substitutes for the cumbersome term.

Now of course any student of English will tell you that the "cumbersome term" itself is pretty bad. "Fatality" becomes a synonym for "death" only in its secondary meaning. But the efforts of *Public Safety* and its readers thus far seem to us only to have made a bad thing worse.

It would not be a bad idea for *Public Safety* and its readers to get out their grammars and read the section on eymology which gives the rules of the game they are trying to play. If "regicide" for example means the killing of a king, or the killing of a king, and "parricide" means the killing of a near relative, or the killing of a near relative, then "motorcide," "highwayside," and the others obviously cannot mean anything but the killing or killing of a motor, a highway, and so on.

Meanwhile, we might suggest that those whom the phrase "motor vehicle fatality" offends would be performing a more useful work if, instead of seeking a substitute, they sought to remove the necessity for its use by preaching careful driving.

Changing Jobs to Work Harder

HAROLD K. PATTERSON whose remarkable success in concocting "plant pills" was described last month has written us a very interesting letter. He states that the recording of his experiments in cold type has inspired him to apply for a position with a large fertilizer manufacturer.

The chances are that Patterson will be a success at his new occupation, not simply because he made a shift, but because of the reasons back of that shift.

To begin with, he is going into the fertilizer business not as a soft snap that will bring him lots of money for little work. He isn't looking at it that way at all. He wants to work and work hard and he thinks that with the particular type of brain with which nature has endowed him, he can work harder and more effectively in the fertilizer business than he could at selling furniture.

The world, unfortunately, is full of misfits—men doing jobs for which they have no natural ability and no instinctive liking. To the misfits, Patterson's experience will stand out as a light house in a fog of uncertainty.

If such a man can only discover what it is that he can learn to do well and then put his heart and soul into acquiring the necessary knowledge and skill, he may follow Patterson's footsteps with high hopes.

It may be well to point out, however, that the lazy, indolent chap who is merely looking for an easy berth had better stay where he is. It takes less work to keep on with your present occupation than it does to take up a new one.

Radio Programs Now Recorded at Home

Grooved Blank Disk with Special Steel Needle Makes It Easy for You to "Can" All Music or Speech at Will

By
JOHN CARR



Placing the pick-up on blank record and holding microphone ready to make the record.

RECENT developments make possible the home recording of radio programs on disk records that can be played again on any type of phonograph that will handle the conventional type of disk record.

This new form of home entertainment will find many uses. The children's voices may be "canned" for future reference. Personal greetings by voice can be sent to friends and relatives who live far away. Excellent radio programs can be pre-

graphed with a bit of home talent comedy is obvious.

Home recording has been made practical by the production of a pre-grooved blank record capable of taking an impression from a special steel needle. This pre-grooved record blank eliminated all the complicated apparatus used in commercial recording studios to guide the needle so that it would form the spiral groove as it recorded the sound

the electrical playing of phonograph records of the disk type.

If you wish only to record the music or speech heard over the radio, you need no additional apparatus beyond a supply of the blank records and a couple of recording needles. These can be obtained from a dealer in phonographic supplies. If you also wish to record speech or home music, a microphone is needed in addition to a microphone or some substitute to pick up the voices or music.



The one indispensable part of a home recording set-up is the audio amplifier. The illustrations in Fig. 1 show how the audio amplifier always is used whether you are receiving radio on the loudspeaker, recording a radio program on a record, recording voice or music, or electrically playing records of either the homemade or "store" variety.

In your radio receiver the function of the audio amplifier is to take the weak electrical equivalent of the sound impulses from the detector tube and amplify them

where they will operate a loudspeaker. In any of the operations above mentioned, the function of the audio amplifier is exactly the same—to take the weak electrical impulses and turn them into powerful ones.

The procedure in recording radio programs is the simplest of all. You merely connect the phonograph pick-up to the output of the set, use a recording needle in place of the one with which you play records, and put one of the blank records on the turntable.

It is well to add a little extra weight to the phonograph pick-up so it will press the recording needle more tightly against the record. The amount of extra weight can be determined by experiment. It will be only a few ounces at most, and is governed by the weight. (Continued on page 139)



The microphone is connected to the audio amplifier.

that home recording by such simple means does not require special periods.

record. The last step is to place the record on the turntable and operate the apparatus available. If the recorded speech, however, is clear and understandable and the reproduction of music under such conditions is all that could be desired.

Home recording now can be done by any radio fan who has a radio receiver that embodies at least two stages of audio amplification and who also possesses any one of the standard electric pick-ups designed for

Fig. 1. Drawings above show how audio amplifier always is used in radio reception or in making or playing a record.

Old Circuit Comes Back

Superheterodyne Vastly Improved by Use of Recent Radio Developments

By ALFRED P. LANE



One of the new superheterodyne receiving sets is being examined in the laboratory of Popular Science magazine.

THE superheterodyne radio receiving circuit, which still remains an unsolved mystery to most radio enthusiasts, has been rejuvenated. Its bad features have been removed and its good features greatly improved.

This remarkable circuit was a war baby, an emergency solution of the problem of intercepting the enemy's extremely weak radio signals. While Edwin H. Armstrong, the inventor, is better known to old-time radio fans in connection with the regenerative circuit, it is the super which catches him to lasting fame.

When the radio vacuum tube was first introduced, attempts were made to design circuits that would amplify a radio frequency. The early tubes were so satisfactory in such circuits only when the frequency was relatively low. The higher the frequency, the poorer the amplification that was obtained, so that while fair results could be secured on the frequencies we now use for broadcasting, the still higher frequencies gave virtually negative results.

The superheterodyne circuit got around this trouble by converting the high frequency of the incoming radio wave to a lower frequency wave and then amplifying at this lower frequency.

THE method used to obtain the lower frequency is most ingenious. In the original "super" design, the incoming radio signal was fed directly into an ordinary detector tube circuit.

Another tube, called the oscillator because its only function was to produce a continuous stream of radio-frequency oscillations, was controlled by a separate knob so that it could be made to work at any frequency within the range of the detector tuning circuit.

The radio wave as reproduced by the detector and the high frequency electrical oscillations of the oscillator tube were fed into the same electrical circuit. If the oscillator happened to be set to produce

exactly the same frequency as that of the incoming radio wave, the two frequencies would, figuratively speaking, drop into step with each other and travel along through the rest of the circuit in the most friendly fashion. The result from a reception standpoint would be nil.

But if the oscillator were set for

a frequency differing from that of the incoming wave, the two couldn't keep step continuously—first they would be in step, then out of step, then in step. The same thing happens when two men with different strides walk together.

OBVIOUSLY, if the incoming radio wave had a frequency of, say, 1,500,000 cycles and the oscillator produced a frequency of 1,375,000 cycles, they would go through the in-step, out-of-step cycle at the rate of 175,000 cycles a second, a much lower and more easily amplified frequency. The rest of the circuit design of the original superheterodyne was simple. Armstrong built a special amplifier that would work on this one frequency and no other. He called it the intermediate frequency amplifier and that designation is still used. To obtain strong results from a weak incoming radio signal he set his oscillator so as to obtain the 175,000 in-step, out-of-step cycle difference.

Right here hobbled up one of the most serious defects of the original superheterodyne circuit—a defect that troubled owners of early types of receivers using this circuit. You could obtain the difference of 175,000 cycles whether you tuned the oscillator that number of cycles above that of the incoming wave or the same amount below it. In either case you got the station.


THAT wasn't so bad when there were only a few stations broadcasting and there was plenty of room on the dial for two points for each station, but under modern conditions it would be pretty hopeless. The lower point for one station would be almost certain to coincide with the upper point of some other station and the result would be hash.

Engineers tried various schemes to overcome this defect of the superheterodyne. Almost every possible intermediate frequency was tried but that only cleared part of the dial.

In the meantime the introduction of screen grid tubes and other new developments improved the ordinary tuned radio-frequency circuits until it seemed that the superheterodyne might have to take a back seat.

But the improvement in tuned radio-frequency amplification has also provided a way to eliminate double point tuning in the superheterodyne. Modern radio-frequency amplifier and preselector circuits were grafted onto the front end of the super circuit and the screen grid tube was used in the intermediate stages. Then the oscillator frequency changing condenser was hitched to the tuning dial.

It is easy. (Continued on page 119)



The above picture shows the arrangements of the various tubes in the most highly developed superheterodyne sets, in which the many advantages of this circuit are brought out.

USEFUL HINTS FOR RADIO FANS

Latest Sets Can Use Light Socket Aerials

THE extreme sensitiveness of the modern radio receiver has renewed interest in the idea of using the electric light wiring as an antenna. Under on many conditions, the light socket antenna does not bring in signals as well as does a properly constructed outdoor antenna. But with the modern set, the strength of signal picked up from the light lines usually is ample for all ordinary reception.

The illustration of Fig. 4 shows what an attractive form the light socket antenna may take. In this case a model stagecoach lamp designed to be placed on top of the radio cabinet looks and acts like any other decorative lighting fixture. There is the usual cord to be plugged into the wall socket and in addition a single wire to be connected to the antenna binding post of the radio set. Any table lamp could be used for the same purpose.

Electrically a light socket antenna, no matter what its appearance or size, consists of nothing but a small fixed capacity mica condenser, one terminal of which is connected to the light wiring. The other terminal is connected to the antenna binding post of the set. The diagram of Fig. 2 shows the circuit.

SIMPLE CHOKE COILS

Radio beginners often are confused by the technical terms used to designate relatively simple radio apparatus. The term "radio-frequency choke coil" is a case in point. Anything with a name like that ought to be quite complicated and

restrain the current in which it is placed and yet allow the low-frequency audible currents to get by unimpeded. It is, in a way, like a fence high enough to stop small animals yet low enough so that a big animal can walk over it.

High-frequency current, such as the wave from a broadcasting station, seems to have a special aversion to being whirled around and around in the turns of a coil of wire unless the number of




Fig. 2. This diagram shows a simple hook-up by means of which electric wiring serves as antenna.

turns makes the coil tune to the particular frequency of the current.

Consequently the design of an R. F. choke coil is not exact as far as the number of turns of wire is concerned. It is only necessary to make sure that you have enough turns to make the natural tuning of the coil beyond the range of the broad-



Fig. 4. Your electric light socket antenna can take this attractive form and stand on radio cabinet.

cast waves. It takes about five or six hundred turns to do this if the coil is as big around as an ordinary thread spool.

To get so many turns into such a small space it is necessary to use fine wire such as No. 32.

Figure 3 shows how to wind your own radio-frequency choke coils using thread spools for forms and No. 32 double covered wire for the winding. The hand drill can be clamped into the bench vise and used to rotate the spool, as shown. A drill or a metal or wood rod can be used as a mandrel.

Strange as it may seem, the more careless you are with the winding, the more effective the coil as a radio-frequency choke. The worst thing you can do is to wind the wire in smooth and even layers. Wind it back and forth at random as shown in the circle, Fig. 3.

The most common use of the R. F. coil is to isolate radio-frequency amplifier plate circuits from each other where there would otherwise be interaction by way of the common B supply. Figure 1 shows a radio-frequency choke coil installed in a B circuit with, of course, the by-pass condenser that is necessary to provide a return path for the radio-frequency current.

Another use is in the plate circuit of the detector tube to prevent radio-frequency current from passing along into the audio amplifier and causing mysterious overloading troubles.

When a choke coil is used, a by-pass condenser is also required to complete circuit.




Fig. 1. A radio-frequency choke coil installed in a B circuit with condenser.

elaborate. Actually it isn't. A radio-frequency choke coil—often abbreviated to R. F. choke—is nothing but a small spool of fine wire wound in such a way that the electrical capacity or condenser effect between the turns of wire in the coil is at a minimum.

The function of a radio-frequency choke is to block the flow of high-frequency cur-



Fig. 3. Wind your own radio-frequency choke coils as shown above, letting the wire go back and forth at random as demonstrated in the photo at right.

Heat Your Car but Don't Burn It!

By
MARTIN BUNN



JOE CLARK, pencil in hand, was checking the day's gasoline total at the pump outside the Model Garage when a sedan drew up.

"Fill her up," the driver called. "Got a long trip ahead of us tomorrow." He stepped out and came around to watch.

Joe casually glanced at the attractive woman seated in the car as he ground the crank. She was leaning forward, apparently searching for something on the floor. Then suddenly she sat up with a jerk and yelled "Fire!" at the top of her lungs.

Joe stopped cranking and took up the call. Gus Wilson, his partner, came charging out of the garage with a fat and sleek fire extinguisher.

The owner of the car with one sweep dragged out the lap robe and with it the smoldering remains of a newspaper. The woman immediately hopped out and the men searched for the cause of the fire.

"What's that gadget there?" Gus asked, pointing to a piece of pipe placed crosswise on the floor boards just back of the front seat.

"That's a new car heater I built myself," the owner replied. He placed his fingers on the pipe and instantly jerked them away again. "Ouch!" he howled, shaking his hand. "That pipe sure is hot!"

"I guess we don't have to look any further," said Gus. "The newspaper must have been on the pipe and the robe kept the heat in till it got nearly red hot."

THE owner bent over to examine the pipe. "I certainly am disgusted," he said "after all the work I put into building that heater."

"You did a good job—as far as you went," reported Gus after checking up on the whole installation. "You got every thing tight so no exhaust gas could leak out into the body of the car. But you didn't insulate the pipe from the wood of the floor boards well enough. There ought to be plenty of asbestos separating every part of the outfit from anything that can burn. And you didn't put any guard over it."

"I had no idea the pipe would get so

Gus Says—

THERE'S one sure way to tell a beginner from an experienced auto driver. Watch him when he passes another car. The beginner swerves way out in the road to pass and cuts back too soon. The experienced driver gets by without swinging out too far and never cuts back again too soon.

But confessed the owner. "I felt of the exhaust tail pipe and it seemed to be just the right heat for a car heater."

GUS smiled. "You forgot that the exhaust gases cool a lot in the muffler. You're taking them out of the exhaust line right back of the motor where they're hottest. Anyhow plenty of heat certainly isn't a fault in a car heater. If you just insulate it properly and fit a strong wire screen over the pipe on the floor, so nothing can get nearer than an inch or two to it everything will be fine and dandy."

But the owner's wife cut into the conversation.

"Charlie Green!" she exclaimed. "If you don't have the man take that thing out of the car this minute you'll make the rest of the trip alone! I'd rather freeze to death than be fried to a crisp!"

Green shrugged his shoulders and yielded. "All right," he agreed. "I'll take you down to the hotel and then bring the car back here."

They drove off with Mrs. Green warily eyeing the pipe as though she expected it to blow up.

When the car returned, Gus set to work at once while Green gloomily watched the destruction of his handiwork.

"I suppose you've got to satisfy the

Gus checked up with a fire extinguisher as the owner dragged the robe out of the car.

women." Gus grunted. "Still, Mr. Green, you don't have to go without a heater just because your wife is afraid of this one. I'll install a good one if you say so."

Green's face brightened at once. "That's an idea," he said. "What kind of a heater do you sell?"

"We do a few different ones," Gus smiled. "I can give you any one of three different kinds. Properly installed, you get fine results out of any of them."

"Why do you carry three makes if they're all equally good?" Green inquired.

"Come in the stock room and I'll show you," Gus offered. "Now," he said as he pulled three bulky packages off the shelf,

"in an automobile you've got heat going to waste in two places. One is out of the exhaust pipe and the other through the fins of the radiator. That means you can heat the car either with hot gases or with hot water. The difference between them is almost the same as steam and hot water in house heating."

THE steam is much quicker and harder to control to get even heat. Also it's likely to make a 'hot spot' in the car because there's so much heat in such a little space. Hot water heat, either in your home or in your car, is much slower to get going and a lot more steady. Also the hot water can't get hotter than boiling so there's no possible chance of scorching anything.

"Also," Gus continued, "there's the matter of ventilation. You can't take long trips with every window shut tight without the air in the car getting kind of stuffy. Heating and ventilation are really twin parts of the job of keeping comfortable in winter driving. You've got to figure on one as well as the other."

"Here's a heater that works from the exhaust gases." (Continued on page 147.)

THE HOME WORKSHOP



BETTER SHOP METHODS
NEW IDEAS FOR
THE HANDY MAN
HOME WORKSHOP
CHEMISTRY
MODEL MAKING
BLUEPRINTS
SHIP SHAPE
HOME



Easily Built SCOOTER

Skims Ice at Mile-a-Minute Clip

By EDWIN T. HAMILTON

IN THESE days of speed, when fast flying airplanes cut the clouds at death-defying velocities, we are apt to look with scorn on anything as slow as seventy miles an hour. And yet this speed will make your hair stand on end if you happen to be seated behind a spread of sail on runners. No windshield, no banked turns, no easy-riding springs, no comforting heat from an engine; just a wild dash on the wings of an icy gale, with but 3 in. between you and the ice!

They are doing just this on the Great South Bay off Long Island. Boys and men from fifteen to seventy-five, all members of the South Bay Scooter Club, which is the only club of its kind, are on the ice right now getting the "kick" of a lifetime. You, too, can have the same sport for a relatively small outlay.

A scooter is primarily a boat that has been fitted with runners for use on ice. Its improvement over the ordinary ice boat and its great safety lie in the fact that it takes to open water quite as readily as to ice. In thirty years of scootering, no one has had a serious accident. Is there any other vehicle in which one can travel seventy miles an hour with safety?

Captain Charles J. Bason, Commodore of the South Bay Scooter Club, to which the writer owes his thanks for the data presented in this article, has beaten some of the fastest of racing ice boats and is



Captain Bason displaying a few of his trophies on the deck of his speedy ice scooter.

now looking for new worlds to conquer. His only complaint is that there are none. At his home in 1924, the first and only scooter club was formed with fifteen members, and today we find a club of close to 300.

The growth has been solely due to the fact that this is an inexpensive, safe, and thrilling sport. It has been estimated that a scooter like the one to be described will not cost more than fifty dollars to build. As they are usually sailed by two or three men, why not get a companion to help you and for twenty-five dollars apiece buy yourselves many winters of fine sport?

In cross section, the shape of the scooter on both top and bottom, as the drawings indicate, is that of a large arc. The side-to-side bottom ribs have their ends raised 4 in. off level when nailed to the $\frac{1}{2}$ by 3 in. side formers. The side-to-side top ribs drop 3 in. at each end to meet these same side formers. If the shape is studied in the side view, it will be seen that the deck curves downward toward each end, the bow and stern both being 3 in. lower than the highest point amidships. The bottom, conversely, curves up 4 in. at each end.

The top and bottom ribs are cut from oak on a hand saw. On stock $1\frac{1}{4}$ in. thick, 5 ft. long, and as wide as is obtainable lay out the fifteen necessary bottom formers. Cut them $1\frac{1}{4}$ in. square and the full



The scouter has no rudder, the steering being done with the jib sail.

length of 5 ft. Remember that the bottom ribs curve up 4 in. at their ends, but the top ribs only 3 in. While only one top and bottom rib of the full 5-ft. length is used, it is found easier to cut the others to the proper lengths after the shape of the boat has been determined.

Obtain a wagon felloe (rim of a wagon wheel), plane it to size, and cut as shown. Then attach two lengths of $\frac{1}{2}$ by 3 in. oak (the side formers) to the joint made in the felloe. The center bottom rib is now nailed between these at a point 6 ft. 6 in. from the outer edge of the felloe.



Above: A file is used to sharpen the angle. Then runners are put in place.

Bring the two side formers together 14 ft. from the same point, bevel to fit, and nail them together. A solid oak block is now cut in the triangular form shown and inserted between the side formers at their point of contact, then the side formers are nailed to it with six-penny nails.

The long bottom fore-and-aft former is now attached. This consists of an oak plank $\frac{1}{2}$ by 3 in. Its length is determined after nailing it to the center of the felloe and bringing it over the center bottom former. It is cut to the proper length for

nauling to the bottom edge of the side formers where they meet at the bow. Nail this bottom former to the center bottom rib. Cut two side braces as shown, and assemble the center top rib. A long fore-and-aft top center former is now applied in the same manner as was the bottom former. It is the same size stock although it may be pine, if preferred. When the decking and bottom planking are applied later, these long top and bottom formers become a part of them.


The general form of the boat is now completed. Continue applying the other bottom ribs, and then those for

the top. Run the top ribs across the cockpit and cut them after the decking has been applied. The bottom planking should now be nailed in place. It will be found best to start this from the edge and work in, so that a narrow strip, if needed, will not come at the edge.

The decking is ordinarily considered a part of the trim of a boat, but if expense is a consideration, I suggest the use of common pine covered with 8 oz. duck. Both bottom planking and decking should run fore and aft, and should be nailed to all cross ribs.

The top formers are cut to form the cockpit, and the combing is applied. This is constructed of two pieces only. The aft piece, which is straight, is nailed in place on the decking edge, the horseshoe part is steamed, bent, and nailed in the same way. The stock for this is $\frac{1}{2}$ in. thick and 4 $\frac{1}{2}$ in. wide.

The mast hole, which is $3\frac{3}{8}$ in. in diameter, is



Top view of the hull. The decking is applied and the opening for the cockpit cut later.

now located and cut. It is 3 in. ahead of the combing and in the exact center. Next, the step is nailed into place, after a $3\frac{3}{8}$ -in. hole has been cut into it 1 in. deep. When nailing the step to the cross ribs, make sure that the hole in the deck and the recess in the step are exactly in line. Place a strengthening block of wood between the step and the deck.

The wooden runners are now shaped as shown and attached to the bottom by countersunk bolts through the bottom cross ribs. This is done before the angle-iron runner shoes are prepared. Note that the angle iron must be bent to conform to the runners. They are drilled and countersunk for the 1-in. wood screws which are used to fasten them to the wooden runners.

If pine has been used for the deck, it should be covered with duck. Dampen the duck and nail it over the sides 2 in.; then apply the side trim, which will cover the edges of the cloth. This trim is $\frac{1}{2}$ -in. stock 4 in. wide. It extends around the boat over

Bottom view of the completed hull showing the planking and four runners.

Detail showing one of the runners. The angle-iron shoe is fastened to the wooden runner with screws. The runners are bent to conform to the shape of the bottom.



be 3-in. siding and covers the joints between the siding and the top and bottom planking. Over the joint where this trim meets the deck, a $\frac{1}{2}$ in. wide molaug, named as shown. No nailing is required in any of the joints. It is customary to fill the boat with water to cause the wood to swell so that the joints will be watertight.

All spurs are made of either hr or spruce. Great care should be taken to follow the measurements given on the drawings.



can be made of 8-oz. canvas without much difficulty. Note that the scooter has no ~~runner~~ the jib serves this purpose. After a few trials, the hunter will find this arrangement most efficient.

Paint the boat any color desired, varnish all the spars, and grease the pulleys. Then put on your heavy clothes, hoist your sail, and let'er go.


If you have any specific questions to ask concerning this craft, the writer will gladly



7	10	15	20	25	30	35	40	45	50	55	60	65	70	75	80	85	90	95	100
1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20

The pulley's chain plates are necessary rigging as shown. The runners should be tied as sharp as possible at this time.

The writer recommends that the sails be ordered from a sailmaker, if the binder is inexperienced in this work, although they




Detail showing the construction of the main beam jaw. The gill jaw is the same size.

The job down is a way as to

in care of the Home Workshop Department
POPULAR SCIENCE MONTHLY

Readers who wish to work from larger plans than those given below may obtain a large blueprint of the original drawings by sending fifty cents to the Blueprint Service Department.



Demonstrated views of the hull, keels, boom, jib boom, gaff and mast sectional views showing the construction of the ribs, formers, and braces and struts. Views showing the first step in constructing the hull and how the upper and lower ribs are laid out on 1/2 in. planks.



Arming *Our* Destroyer Model

Captain E. Armitage McCann tells how to construct and place the funnels, guns, and small deck fittings of the U. S. S. "Preston"

WITH the superstructure of our model of the United States destroyer *Preston* in place, we are now ready to arrange and assemble the smaller deck fittings that will make her more realistic looking and rather more like a real ship.

As we left our model last month, we were just about to place the skylights under the fire control platform. These are shown as 24 in the deck plan below.


In order to assist readers who wish to build the *Preston*, either as a working or as a decorative model, three blueprints

Side elevation and deck plan of the model. These appear in colors on Blueprints Nos. 123, 124, and 127 (see list, page 112).

BE TWO STAFFS
ONLY IF DECK IS TO BE REMOVED

SIDE ELEVATION

DECK PLAN




have been prepared. These blueprints, which have met with unanimous approval from a large number of model makers, contain full size drawings for a 3 1/4-in. model. They may be obtained by sending seventy-five cents for Blueprints Nos. 125, 126, and 127 (see page 113).

In placing the smaller deck fittings, start at the forward end of the model and work aft. On the stem there is a circular cleat for a towrope. This consists of a section of thin brass tubing soldered to a brass base and having a little socket soldered above it to take the jack staff. This cleat is nailed to the deck with $\frac{3}{8}$ -in. bank pins. In this and in all other nailings, be sure to drill small holes first.

At the extreme stern there is another cleat similar to the bow cleat except that the flagstaff socket slopes aft a trifle (see side elevation).

About 1 in. abaft the bow towing cleat are the cleats for the anchor cables marked 2. These are loops of wire soldered to plates bent to a right angle as shown.

Between the anchor cable cleats is an even water-tight scuttle or hatch. Hereafter these small hatches and scuttles will



He was made from sheet metal and was

as they are merely small bits

as indicated on the deck plan.

tion scuttles, blower trunks, and a rucks. Nine are just pieces of cardboard cut to size and glued with rubber solder, the pieces underneath to the



the deck is cut down at the sides, and small triangular pieces of cardboard are glued on to form the sloping platform for the anchors. The anchors are of the loose stock type and can be made from brass or lead with wire stocks at the ends of which are set small drops of solder. The anchors are fastened down to a slip bar and staples with small chains. I also put a pin staple over mine, which looks like a lashing and serves to hold them in place on the platforms.

On a line with the anchor platform is the crane for lifting the anchors to the deck. I made this by soldering wires to a sheet metal plate of the right shape as shown in

5. The blocks are made by soldering a brass disk on each end of a short piece of tubing. A piece of cork should be tacked through holes to represent the valves.

Aft the crane is on ton plate 5 and the double spurling gates on road 3 boxes that lead to the chain maker and the capstan 8. The lower

part of the capstan is a gyrost to heave
in the anchor cable, and above is an
extending arm for rope.

order to form a combination way.

Since all of the 4-in. rapid-fire guns are practically the same we shall describe them together. Detail 8 (page 92) shows the construction of the plain guns and also the one having a protecting shield, which is placed forward of the bridge-house. As the guns are to be painted

They may be made of wood. They can be turned from a dowel stick, leaving the part in the middle large; this part is then cut to leave three small round portions.



to represent the two recoil cylinders underneath and the sighting tube on top. If preferred, the guns can be turned to shape and these small details glued in place later. The bases also can be turned. The square part of the base is a piece of cardboard glued to the deck. To mount the guns, a hole is bored up into the base and a pin shank is inserted, this is then driven into the deck.

The forward gun requires a shield. Metal is the best for this, but cardboard will serve. This should be bent to shape and glued to the gun mounting before the gun is placed.

In the well deck, there is a lift-up skylight and a small hatch. These are shown in the detail of the well deck.

A ventilator, fan, and motor are also placed in the well deck as shown. The ventilator should stand high enough to allow its cowl to extend over the end of the bridge rail.

Four wide sloping ladders 10 and five narrow upright ones 10A




Few tools are needed in constructing the funnels and smaller deck fittings.

are required. The sloping ladders in reality are flat iron plates about 5 in. wide, slightly bulbed on both edges and with two iron bars riveted to them for each step. After several failures to make these on so small a scale, I hit on the following method which is easy and neat: I flattened some No. 22 wire slightly, turned it with solder, clamped two pieces parallel in a small hand vise, and placed this in such a way in a large bench vise that the wires were horizontal. After soldering two pieces of smaller diameter wire together and cutting them into lengths equal to the width of the ladders, I spaced these evenly along the length of the two uprights and soldered or "sweated" them in place using a lighted candle for the heat. The ladders can be secured by inserting the lower ends of the uprights in holes bored in the deck and placing staples at the upper ends.

The upright ladders, which are narrower and have only one bar to a step can be made in a similar manner.

The four funnels 23 are best made


from shim (very thin) brass. First, trim a stick to the inside shape of the funnels, making it a trifle larger in diameter at the lower end, this will allow the funnels to slip off after they are shaped. Cut a piece of the sheet brass a little longer than the funnel and about 3.16 in. wider than is actually required to reach all the way around the wooden former. File one edge of this to a bevel, turn the outside of this edge and the inside of the other, wrap the metal around the former and tie it with thread. The two edges are then soldered, and the outer edge of the flap is filed flush with the sides. A ring cut from the bottom edge, about 1.16 in. wide can be soldered to the top of each funnel for appearance and stiffening. Eyebolts for the guys may be soldered on, but I punched holes in the funnels



The guns required on the model. The shield for the forward gun can be of cardboard or metal as desired.

and threaded the guys through with a needle.

When all the funnels are made, cut 14 in. long sections from the stick at the



TWO ANCHOR PLATFORMS

The anchor platforms are placed about the anchor cable cleats. The anchors can be either lead or brass.

correct angle, and glue them in the funnels flush with the bottom; then glue and nail the whole to the deck. Note that the funnel which comes through the galleys


need not be as long as the rest. Be careful to see that the funnels are along the center line of the ship and that their tops are all in the same horizontal line.

On the fore side of the first funnel is the whistle, which can be a thin, round stick inserted in a short piece of brass tubing. The exhaust pipes are sticks inserted in the deck and tied to the funnels with thread. A knot placed between the sticks and the funnels will cause them to stand apart.

If the model is being built to a scale one and one half times as large as that given on the blueprints, it must be remembered that each deck fitting must be made correspondingly larger than shown.

Next month we shall describe the rest of the details and apply the finishing touches to our model.


Small diameter holes can be made in sheet glass by placing a piece of putty on the glass, forming a hole in the putty of the desired diameter down to the glass and pouring molten lead into the well thus prepared. When the hot metal hits the glass, it will crack out a piece equal approximately to the diameter of the well. Be sure that the wall of putty is substantial enough to retain the molten lead.



Detail of the stern towing collar and flagstaff socket (38). The anchor cable cleats (2) are made by soldering a loop of wire to a metal plate.





TWO ANCHOR CABLE CLEATS



A ventilator with its fan and motor and two hatches are placed in the well deck against the after end of the bridge house.

The spurling gates (5) and the capstan (6) are placed just abaft the crane. Detail showing the construction of the bow towing collar (7).



BOW TOWING COLLAR

The latest novelty in party decorations—

An Illuminated Ice Mountain

By

VERNON B. CASE

ONE of the most unusual and brilliant sights enjoyed by guests of the Lake Placid Club, in the heart of the Adirondacks, last winter, was a huge pile of broken ice, 10 ft. high and 20 ft. in diameter and weighing approximately 20 tons, beneath which glowed and flashed dozens of colored electric lamps. Every imaginable color was produced by the prismatic action of the ice.

In carrying out preliminary experimental work, L. C. Porter, who is a member of the engineering department of one of the largest electric companies, found that anyone may enjoy an illuminated ice mountain. Such a decoration may be placed on the lawn in winter or used for adding color and novelty to a summer garden party. Its cost is surprisingly low, the necessary electrical equipment being used over and over, and the only perishable part, the ice, being inexpensive. Three or four 300-lb. cakes of ice, costing 75 cents each in most cities, will suffice for a fair-sized pile. It will last at least one evening, even in hot weather, and in winter it may be expected to remain attractive for almost a week.

In building an ice mountain first obtain a 100-ft. decorative streamer with lamp sockets spaced 2 ft. apart. In selecting this obtain sockets that are as deep as possible so there will be room for a flasher button beneath the lamp base.



A flasher button prevents moisture from getting into the socket.

Insert such a button—flashing one is best—into three sockets out of every four. Place a soft rubber gasket about each lamp base and screw the lamp into the socket. The gasket is necessary to prevent water from getting into the socket. Equip each lamp with a wire guard to prevent its being crushed by the weight of the ice.

Of course all of the sockets in a 100-ft. streamer need not be used. The sockets may be employed. As to the lamps themselves, Mr. Porter found that



A pile of ice, 10 ft. high and 20 ft. in diameter, for the winter months.

alternate red, blue, green, amber, and yellow lamps gave the best results. Yellow and amber lamps that burn steadily should be of the 15-watt size; the others of the 25-watt variety. By having some lamps burn continuously while others flash a smoother action is obtained.

Next break the ice into pieces about 1 ft. in diameter and pile a layer on the ground. Then distribute some of the lamps over this layer, keeping the bulbs


free on another layer, arrange more lamps and continue until the ice mountain has been completed. You are then ready to put into action a light jewel that must be seen to be appreciated.

The ice, of course, will decrease in volume. The ice can be added to compensate for that lost, but eventually the lamps will sink to the bottom of the ice and the effect will not be satisfactory. The heat from the bulbs does not contribute much to the melting action; it was found in the daytime, if a blanket is spread over the pile, melting will be retarded.

The lighted ice pile for the lawn suggests another little stunt: Fill a large tub with cracked ice, bury in it a number of radio dial light bulbs or flashlight lamps carried in suitable sockets that are wired in parallel, and you have a centerpiece of unsurpassed beauty for the table.

If flashlight lamps are used, they can be operated from a number of dry cells giving the proper voltage. For the No. 1 Mazda flashlight bulb, 2.5 volts are required, so that two dry cells in series will serve; or a single storage battery cell may be used. If radio dial lamps are employed, they can be operated from a 6-volt radio or bell transformer or a 6-volt storage battery. Either type of lamp will fit small radio lamp sockets or the miniature "pig-tail" sockets obtainable from electrical stores. A half dozen lamps will be sufficient.

Still another attraction worked out by Mr. Porter and other engineers at Lake Placid was a star outlined with lamps frozen in the ice of the skating rink.



The lamps should be distributed evenly throughout the pile of ice. Wire guards protect the bulbs from being crushed.

Making a Photo Frame in Leather

By F. CLARKE HUGHES


THOSE readers of POPULAR SCIENCE MONTHLY who have been following his series of articles on decorative leather work will find that the photograph frame illustrated, while a little more difficult to construct than some of the other projects, is one of the most attractive designs. It is a piece that you will want to keep yourself as well as one that makes a universally acceptable and highly prized gift.

The frame should be constructed of tough cardboard which will bend without breaking. It should be about $\frac{1}{8}$ in. thick. At a printer's or bookbinder's one may obtain a special grade of bookbinding board which serves this purpose admirably. Morocco leather should be used as the facing or covering. It usually may be purchased at a bookbinder's or at any well stocked leather shop.

The first thing is to determine the shape and size of the picture frame and to cut




Mounting the leather on the cardboard sections Nos. 1 and 4. The leather is mitered and folded back over the edge of the oval face drawing G.



TRANSPARENT CELLULOSE

Two types of frames (A and B) at various positions of the cardboard sections (C) and layout of the cardboard and leather (D).



Two methods of obtaining an ellipse (E and F) and how the leather is mounted (G and H).

the patterns. The two types given at A and B can be folded up, however, A also may be made with a simple metal or leather covered easel for the back instead of the folding support shown.

The sections of cardboard are shown at C, all cut and shaped for making a frame similar to type A. These sections are of the sizes shown in the dimensioned drawings D.

Cut two pieces of leather, one for the back exactly the size of part No. 5 (shown at D) and the other, which is for the face sufficiently larger so that it can be lapped around the edge and over the back for about $\frac{1}{4}$ in.

Next, shape and cut the several card-

board sections forming the body of the frame. The oval in section No. 1 may be laid out by either of the two methods shown at E and F. In method E is shown the more familiar plan, that of using two pins or nails and a piece of thread or twine to produce a true ellipse, while F shows a way to fold and cut a paper pattern for an approximate oval.

The oval in part No. 1, the square in

No. 2 and the small slit in No. 3 may be cut with an ordinary knife, but smooth the edges with a bit of sandpaper. A sheet of transparent celluloid is cemented over the opening in part No. 2 as illustrated at D.

Sections Nos. 1 and 4 should be coated with rubber cement on one side. If the cement is spread with a small piece of cardboard, an even layer may be obtained. When the cement has become quite "sticky," these sections (Nos. 1 and 4) should be placed on the rough side of the larger piece of leather as shown at G and rubbed with the tips of the fingers until smooth.

With a sharp knife cut the leather around the oval in the form of a series of flaps as indicated, and cement them down. The outside edges of the leather, however, should not be cemented until the other sections are put into

place as shown in the sectional drawing H. No cement should be used between any of these parts, but when the pieces are all in place, the morocco should be turned over the edges and cemented to the back. The cutting and mitering of the corners as at G will be found an undertaking that requires some careful fitting, it should be done as the work progresses, rather than before you begin to turn up the edges. A good plan would be to experiment with a piece of paper before using the leather.

When this main section or face side is mounted and the edges have been turned, the back piece should be trimmed to a size that will leave a space of about $\frac{1}{8}$ in. between its edge and the edge of the frame. In mounting this thin morocco, be very careful not to apply the cement so thickly that it will show through the material on the face side, thereby causing an unsightly stain. This is a common defect in the work of beginners.

After the leather is mounted and the cement dry, it may be tooled quite easily as at J, page 96. Merely dampen the face a trifle and outline the design with the point of a lead pencil. If a simple vein is to be used, the same methods as have been described in former articles may be followed, however, if the reader cares to



Laying out an ellipse with the aid of two pins, a piece of string, and a lead pencil.



IN THE OIL FIELDS

... Naturally . . . The Demand
in a Bearing is for **PERFORMANCE**

In Any Bearing...Anywhere...Performance Is The Only Thing That Counts

Where derricks throw their gaunt spectres against the sky and drills burrow into Mother Earth for oil . . . where performance instead of price is the factor upon which practically all equipment is sought . . . there you will find wheels turning on **SKF** Bearings in constantly increasing numbers.

SKF is the industrial bearing of the world because it performs — because each **SKF** bearing

type was built to do a specific job—because **SKF** knows it is equipped to do that job before it leaves an **SKF** Laboratory.

Naturally, such a bearing costs more to make and costs more to buy. But more and more each day industry in general is awakening to the obvious fact that you can't judge a bearing by its purchase price. In a bearing, it's always performance. Performance is the only thing that counts. **SKF** Industries, Inc., 40 East 34th St., New York, N. Y.

SKF

Ball and Roller Bearings



One of the many **SKF** equipped machines in the petroleum industry. The Wichita Falls Spindler used for drilling to 4000 feet . . . made by Clark Machine Company, Wichita Falls, Texas.

finish the picture frame with a genuine gold leaf line, it may be done without too much extra work by the following method.

Gold leaf may be obtained in small quantities from a bookbinder or a local sign painter, and it may sometimes be purchased in single sheets from the paint dealer. Being exceedingly thin and fragile it must be kept between the leaves of a book or two sheets of thin paper until ready to use and be handled on the side of a fine flat brush—a special brush is made for the purpose—when placing it in position on the design.


The lines you wish to gild should be coated with a wash of albumen sizing made from the white of an egg beaten to a froth and allowed to stand overnight. Apply the size

with the tip of a small brush as shown at K. Allow it to dry overnight. While a sizing of flour and water is sometimes used for laying gold leaf on leather, it is not as satisfactory as albumen. When you are ready to lay the gold, oil the sized line lightly with a little vaseline and place a narrow strip of the gold leaf in position. The vaseline will retain the leaf tempo-

may be used if the temper is drawn from the wheels and the edge dulled somewhat. These should be kept heated to the temperature of about an ordinary flat iron.



Applying the albumen size to the design with the tip of a small brush.



The design is first tooled on the leather (J), then the albumen size and the gold leaf are applied (K).

The best way to do this is to place them in a pan of sand, which may be heated over any kind of a fire. The hot tools serve to melt the albumen sizing and causes the gold leaf to adhere to the leather.

This method of aluminating the designs on book covers and other leather articles is very old, and some of the old books have

retained their valuable decorations for centuries. The depth of the tooled design protects the gold leaf from most of the wear incident to everyday handling.




Rolling gold leaf into the tooled design.

Your Guests Will Like This Luggage Rack

THIS useful luggage rack not only saves the bed and the floor when your guest packs or unpacks a suit case, but it will also hold a tray in the dining room or sick room. Although usually priced at from \$7 to \$8, this particular rack can be constructed at home from wooden curtain poles or other round rods $1\frac{1}{2}$ in. or a trifle more in diameter. A good height is 27 in. with a 16 by 18 in. spread for the top.

Cut two legs 2 ft. 8 in. long and dowel them into a top round that is 16 in. long—close to its ends. Connect the legs by a small rung set 7 in. up from the bottom. This completes one "gate."

Construct another "gate" exactly like the first in height but make it 3 in. narrower by setting each leg $1\frac{1}{2}$ in. or its own diameter, farther in from the ends.



Two gates, pivoted 18 in. from their lower ends, form this easily built luggage rack.



This luggage holder can also be used in the dining room or sick room to hold a tray.

of the top round. This allows one gate to stand inside the other. Fasten them together 18 in. up from the bottom by inserting a small iron rod through the legs where they cross to act as a pivot.

Connect the two top bars with upholsterer's webbing, or strong tape, in colors the longer the strips the lower the rack will stand. Then cut off the feet of the rack at an angle to fit the floor, and insert polished steel gliders or glue on disks of felt.

Lacquer the rack any desired color, using a black trim for the iron rod and the ends of the top rounds.—A. MAY HOLADAY.


PLANKING SHIP MODELS BY AN EASY METHOD

ALTHOUGH a planked ship model is much more realistic than an ordinary carved model, a built-up hull is so difficult to construct that few model makers attempt it. With a little patience, however, an attractive, full-planked appearance may be produced easily by the following method.

The hull is first carved in the usual manner. Then obtain a Japanese wall pocket which can be bought at almost any variety or notion store. This consists of strips about $\frac{1}{8}$ in. thick and $\frac{1}{4}$ in. wide, which is the right size to represent planks on a model of ordinary proportions.

The strips are glued and laced with very small pins to the carved hull. Because of the difference in girth at various points along the hull, it is necessary to taper the planks where they approach the stem and the sternpost, especially on those close to the keel. Around the stern it may be necessary to soak the strips in hot water for several hours to make them pliable enough to follow the curves of the hull.

For modern steel ship models, pieces of drawing paper cut to represent steel plates may be "riveted" to the hull by means of small pins.—ROGER SCHELL.



Realistic planked effects on ship model hulls can be obtained with strips of thin veneer.



**Look it up
in case you're not sure**

Dill's
SINCE 1848
Best

is America's Best

J. G. DILL COMPANY, RICHMOND, VA





MARINE

The captain commands. Thousands of mechanical devices stir into action, smoothly, quietly . . . the great ocean liner—a city in itself.

Behind countless devices in the assembly of this marvel of oceanic transportation—precision . . . mechanical perfection—the grinding machine and the grinding wheel have been busy.

Modern transports of the sea, toward whose marvelous efficiency the abrasive industry contributes, reciprocate by carrying finished abrasive products of Norton Company, Worcester, Massachusetts, to the ports of the seven seas.

NORTON

Grinding Wheels . . . Abrasives for Polishing
 . . . Pulpstones . . . Floor and Stair Tile . . .
 Grinding and Lapping Machines . . . Refractories
 . . . Porous Plates . . . Abrasive Aggregate . . .

Great Industries
 No. 1

Speedy Toboggan

Besides being a source of endless fun on the hills, this sturdy little snow coaster can be used on hikes and hunting and camping expeditions. It's easy to construct, and as for expense—practically all the parts can be obtained for next to nothing.

BUILDING this barrel-stave toboggan is just the kind of a job in which a "hammer and saw" youth glories. He is certain to make a success of it even though his product may look somewhat rough and ready. The resulting toboggan while not recommended for coasting on extremely high, steep grades, serves admirably for smaller slopes, especially when there is plenty of snow. It is fast, makes an excellent conveyance for use on winter hikes or trapping or camping expeditions, and is light in weight.

From your grocer obtain a large barrel having little curve to the staves—a potato barrel of the rougher type is just about right. Sharply curved staves should be avoided as they make the toboggan too rocker-bottomed.

After taking the barrel apart carefully, plane away the bulge along the middle portion of the staves, making them into parallel-sided boards. Three or four of these side by side will provide a section 15 in. wide by 28 in. long. Nail a batten across the middle of the section driving the nails through the batten and clinching them smoothly on the underside.

Its flexibility allows the toboggan to take the bumps easily.

from

Barrel Staves

By JACK HAZZARD

of the staves. Another batten is nailed at the end of the section, which will be the tail of the toboggan, the tail section being made first.

Now make another section like the first, with a batten across the center. Nail and clinch it firmly to the front end of the first section made, allowing a lap of from 11 to 15 in. A batten is nailed over the center of the lap. The addition of two more of these sections will provide ample length.

The curved prow may be made in one of two ways: short lengths of barrel hoop may be nailed to a batten and then lapped and nailed from 6 to 8 in. under the front of the toboggan, or a piece of a wooden

resting. This is an advantage when it is being used for hauling camp supplies and for similar purposes.


Unloaded or lightly loaded, this toboggan curls up at each end, and travels over rough ground without capsizing in a remarkable manner. Loaded, it flattens out, presenting its whole surface to the snow and bearing the weight easily and evenly. One of the photographs shows how it curls when the writer rides it standing up—a trick he does not recommend for anyone who has not learned to use skis.

Speaking of sports, how would you like to own an 11½ ft. outboard racing boat that is different from all of the rest—a boat thoroughly streamlined to obtain maximum speed and so designed that it is practically uncapsizable? The first of two articles describing the construction of such a boat, together with easily understandable working drawings, is to be published in the March POPULAR SCIENCE MONTHLY.

cheese box may be nailed in place and reinforced with battens. If hoops are used the inside of the lapping ends should be beveled to prevent too prominent a lump at this point.

At each end of each batten is nailed a loop of leather through which is rove a ½-in. rope to serve as a handrail and for use when lashing on a load. The ends of this rope may be extended to act as a towline. An old blanket folded and covered with canvas makes a good pad for use when coasting.

Of course, the staves used for the bottom of the toboggan produce a series of steps, but these, like the steps of a hydroplane, do not oppose the line of motion and do no harm at all, in fact they keep the toboggan from slipping back down a grade on which it may be



Perspective sketch and details showing how the barrel staves are assembled to form the toboggan.



The barrel-stave toboggan and its two proud owners, who declare it's "king of the hill."

New Ideas to Help Auto Workers

POPULAR SCIENCE MONTHLY awards each month a prize of \$10. in addition to regular space rates, for the best idea sent in for motorists. This month's prize goes to Kenneth Murray Sturgis, Mich. (Figure 3). Contributions are requested from all auto mechanics.

IN OLD cars it appears necessary frequently to touch up the breaker points. Many times this trouble is caused by a burning away of the end of the distributor arm which causes a long jump in the distributor. Building out this burned-away portion with solder is a semi-permanent cure for this trouble.




Fig. 1 Shows how to build up with solder the burned away end of distributor arm in an old car and make it run.

LEAKING VALVE

WHEN the exhaust valve is leaking badly a quantity of exhaust gas is drawn back through the valve during the intake stroke. If the motor is allowed to idle at the slowest possible speed, and a piece of paper is held over the end of the exhaust pipe the leaking valve will cause the paper to be sucked against the end of the pipe.




Fig. 2 If a valve is leaking badly, it can be detected at the exhaust pipe.

ACID MAY HELP

IN SOME sections of the country, the water deposits a hard white scale on the interior surface of the radiator. Ordinary cleaning compounds are of no use in such cases. As a last desperate resort try filling the radiator with a ten percent solution of hydrochloric acid. The acid will dissolve the scale but it also attacks the metal of the radiator to some extent. If you are lucky the scale will be removed before the radiator is eaten through.

ICY WINDSHIELDS

OF THE many simple methods of preventing ice from forming on the windshield, one of the simplest is shown in Fig. 4. Take a small bag of ordinary table salt and tie it to the shaft of the wiper so that it will just touch the glass at the upper edge of the path of the rubber squeegee. This will melt the ice.



A heavy scale in the radiator may be removed by ten percent solution of hydrochloric acid.




Fig. 4 A bag of ordinary table salt attached to windshield wiper will keep ice off glass.




Fig. 3 This stop light is made by punching holes in the tire cover and fitting bulb behind it.

NOVEL STOP LIGHT

FIGURE 3 shows how to make a stop light that disappears when not lighted and, because of the large letters, can be seen for a great distance. Punch a series of small perforations in the tire cover to form the letters of the word "stop." Cover on the inside with a sheet of red celluloid. Fit a tin reflector and a powerful headlight bulb back of the letters and connect the bulb to the usual stop light switch. This should make a peculiarly efficient stop signal, as it appears at the most desirable height and directly in front of driver in the rear.

SIMPLE PRIMER

FIGURE 5 shows an easy-to-install priming arrangement that can be applied to almost every car. Remove the fitting that attaches the vacuum line to the windshield wiper and substitute a short length of pipe and priming cup as indicated.




Fig. 5 This simple primer which attaches to vacuum line, is easy to install in most cars.



"All's well" with the Face that's Fit



The world around, millions of men make Face Fitness the first order of the day. The Face Fitness that comes from using Williams Shaving Service. It's a 90-year standard of goodness.

They start their days with Williams lather. Cool as frost. Thick as cream. Quick as quick can be. Natural, all over coolness that won't sting—can't sting. No doubtful dyes in Williams. It's a 90-year standard of goodness.

A dash of water! Then, the crisp briskness of Aqua Velva, dashed freely

over the face, to keep the skin as clear-toned and Fit as the lather leaves it. Vividly fresh. The face that says: "Good Morning" on any man's face or sea.

You men like a shave. Don't you, that a cozy smooth shave? With an after-feel and look of fitness. Casual nicks and cuts cleanly cared for. The natural skin moisture conserved. And, finally, just a lingering hint of heavy fragrance that is good grooming? That's a Williams shave, by Williams Shaving Service. And that's why, everywhere, the big tide is to Williams!

How you treat Williams Shaving Liquid? Very quick, very cool, very new! Ask your dealer.

A COUPON—For the Face that would be Fit!

THE J. B. WILLIAMS COMPANY, Dept. PS-60
Glastonbury, Conn.

Canadian Address: 3532 St. Patrick St., Montreal

Send me Free Trial Sizes of Shaving Cream and Aqua Velva. I will use and observe them.

JUST NOTICE THE FINE SKINS OF MEN WHO USE

Williams

SHAVING CREAM—AQUA VELVA




Upon the workman at the quenching bath depends the final success of the heat treating process.

Quenching Steel Is an Art

By HENRY SIMON

IT LOOKS so simple—just dipping a piece of steel in a tank of brine to cool it—yet Mr. Simon suggested that this article and the one that preceded it last month be called "The Art of Quenching." And art it undoubtedly is, because skill and good judgment are required. It makes all the difference in the world how the work is held and how it is moved about in the bath. The

equipment may be of the finest, but success is principally dependent upon the operator's skill.



THERE is always a crucial moment in quenching steel—the moment when the work is plunged into the bath. Even if everything else is just right and all the little details have been attended to, as suggested in a previous article (P.S.M., Jan. '31, p. 98) there still remains this important operation that requires both skill and judgment.

In innumerable instances, the way in which the work first enters the bath means all the difference between success and failure. A brief moment decides whether the heating shall have been done to good purpose, or to worse than no purpose at all. And very often it settles the question of whether all the previous labor put into the piece and the cost of the steel itself result in gain or loss.

In considering this point, it is convenient, for our purpose, to draw a distinction between symmetrical work and work of approximately even section, and unsymmetrical work and work of greatly varying section. These different conditions are typified by the examples shown at A and B, Fig. 1.

If the work is symmetrical and of about

even section, it is usually best to quench it with its axis vertical. If tongs are used, they should be applied as at B, Fig. 2 where the force of gravity automatically holds tongs and work in the correct position instead of as at A where the work is like a teardrop to be lowered in the wrong position shown by the dotted lines.

Next in importance to the manner of entering the work is the way in which it is moved about in the bath. Jumping about as shown at C, Fig. 2 gives the same result as at A, so far as the cooling effect of the bath is concerned, heat is extracted faster from the side of the work which is

moving forward. The same thing, in another form, is a bath that has been stirred and made to revolve as at D. A brisk, though quiet, water circulation from the bottom of the tank upward, as at E, is excellent, but can be maintained only by a pump and a special piping system such as are found in well-equipped, up-to-date plants like the one in which the photograph above was taken.

Ordinarily, the best way is to lower work into the bath quickly though steadily and move it unburiedly straight up and down, while changing its position gradually, as at F.

In work of varying cross section, the general rule is to cause the thickest portion to enter the quenching liquid first, as at G and H, Fig. 3. This cannot be done with parts like those at C, because air or steam would be trapped by the spaces a, b, as will be seen by studying the diagrams at D and E, which show the right and wrong ways. In some cases it is best to plunge the work as at I. Usually, however, it pays to provide a venthole in such parts as at J, even if there is no other reason for it.

Form tools and similar round parts with a heavy body and a thin flange are best

A Minute or Two in the Shop with Old Bill

ALWAYS plan a blanking die so that the bends in forming will run across the grain of the metal stock.

It is bad practice to take both the side and the end cuts with an end mill.


The use of a spider center when threading pipe will give a truer job, and spider centers are less expensive than pipe centers.

If a drill chatters and leaves radial marks when countersinking, it is a sign that the clearance angle is too large.

When the head of a chisel becomes rough from repeated hammerings, grind off the sharp edges or they may cause serious injury.

Always take up the slack in the lifting screw when adjusting a miller or drill press table.






Combination Square

No. 33—hardened steel blade—graduated in 16ths, 32nds, and 64ths—drop-forged head—eight handy tools in one.




Micrometer

No. 280—out-away frame—lock nut andatchet stop—0 to 1" in thousandths—finest accuracy and feel.



Indicator

No. 198—dial graduated in 1000ths—extremely sensitive—for testing, centering, and truing-up all types of work.



Depth Gage


No. 449—flat blade—like rule—base is hardened, ground and lapped—range 0 to 3"—micrometer accuracy.



Protractor

No. 289—dial lock, blade lock and bar adjustment are all on upper side—vernier reads to 1/12th degree—acute angle attachment.

Close-up of the Stimpson Printer, the machine used by Western Union for sending and receiving telegrams.



Imagine yourself in New York, tapping out a message on a compact little machine with a typewriter keyboard. As you type, the telegram appears before you on a paper ribbon. And the same message appears simultaneously, letter by letter, on an identical machine in a distant office.

Here is a miracle of ingenuity—and accuracy. Asked to build complicated and precise machines like these, skilled machinists use the finest tools they can find—tools like Starrett, that make it easy to be accurate.

In your work, how often have

**Use[®]
Starrett
Tools**

TYPEWRITING BY WIRE

you wished you had better tools? How often have you felt that your skill didn't have a chance to show, simply because your tools were clumsy or inaccurate—or missing? Determine now to own the Starrett Tools you need—the tools that will give you greater pride and pleasure in your work.

Send the coupon for your free copy of the Starrett Catalog No. 25 "W". This book describes and illustrates over 2500 fine Starrett Tools and shows how you can use them to do better work and do it faster.



SEND FOR THIS CATALOG

THE L. S. STARRETT COMPANY
ATHOL, MASSACHUSETTS
Please send me Starrett Catalog No. 25 "W".

Name _____

Address _____

City _____

State _____

HINTS ON USE OF TAPS GIVEN IN LETTER TO OLD BILL

DEAR BILL:

Here are a few pointers on using taps. Considerable breakage can be eliminated by drilling the work to the proper diameter. Only from 62 to 75 percent of the thread depth is needed to supply sufficient strength to cause the average screw to break before the threads are stripped.

Always keep the tap wrench tight on the square end of the tap, and as for lubrication, I prefer lard oil or a mixture of white or red lead and lard oil.

When tapping hard steel use a starting tap, alternating with a stub tap every few threads.

If a tap does break, drop some muriatic acid on the tap and allow it to work down into the threads. This will reduce the diameter of the tap slightly and often will allow it to be backed out with a hammer and punch.

F. J. WILHELM

TABLE FOR CUTTING THREADS IN LATHE

BY SETTING the compound at 30° and feeding the tool in to a depth equal to the number of thousands indicated in the following table opposite the number of threads to be cut per inch, it is a simple matter to cut accurate U. S. S. threads in the lathe.—SAMUEL JAGGER.

Threads per Inch	Depth	Threads per Inch	Depth
2	.00676	14	.007675
2½	.00824	14	.008675
2½	.00900	15	.0050
2½	.00924	16	.004545
3	.00750	18	.0036
3½	.00707	20	.00275
3½	.00747	24	.002225
4	.00625	24	.002125
4½	.00564	26	.00188
5	.00500	27	.00177
5½	.00465	28	.001678
6	.00417	30	.0015
7	.003175	34	.0011725
8	.002609	34	.00207
9	.00212	36	.00208
10	.00180	38	.00197
11	.001625	40	.001875
12	.0015		

quenched as at F, Fig. 3. A good variation of this procedure for work with wide and delicate flanges is that portrayed at G. The work is held on the special hook C, bent from a rod that will easily fit the hole through the work. The thick body is immersed first and held for two or three seconds. The tool is then quickly lifted above the surface of the bath, the hook turned to the second position shown, and the tool quenched. It may be added that such work should always be instantly transferred into boiling water from the quenching bath.

Most of the work that must be hardened in the average shop is handled to advantage with a hook rather than tongs. Such hooks may take hold both outside, as at A, Fig. 4, or in a bore or hole in the part as at B. Where there is no other way, a wire loop may be used, even if it is necessary to provide a small hole in the part, as in the shaft at C.

Small parts with bores through them can be strung on a wire, as at D, Fig. 4, with coil wire spacers between them. The same procedure may be used with flat parts, as at E. Screws, pins, and similar small solid objects can be conveniently suspended in wire cages like that at F, which can be used over and over again. Very small parts may be put up, a number—not too many—at a time in a little bag of ungalvanized steel screening, and thus heated and quenched, as at G.


Many difficulties experienced in quench-

ing very thin and slender work can be avoided by the use of a "steam line" weight described by the writer in a previous article and shown again at A, Fig. 5. Very thin wirelike pieces like the pin at B, may be caused to enter the bath straight by "shooting" them through a narrow tube. Heavier, long, round work, such as shafts and screws may sometimes be handled in quantities by causing it to roll down a 10° to 15° incline as at C. Two or more such inclines may be joined

to give a longer path in the manner shown at D.

It should be remembered that work ought never to be dropped, unless it is certain that it will be thoroughly cooled by the time it strikes bottom. Even then, dropping is a poor habit unless, as in the cases just mentioned, there is some special reason for doing it.

In his next article, Mr. Simon will discuss blanking sheet metal.



Tool Economy!


WHEN you buy a micrometer, rule, or any other accurate measuring tool, you are buying a tool upon which you expect to depend for years of reliable service.

That is one of the important reasons why mechanics consider the purchase of Brown & Sharpe Tools to be real economy. They know from experience that these tools will maintain the same close standard of accuracy year after year.

When you consider tool economy in terms of amount of reliable service per dollar, your choice of tools will invariably be Brown & Sharpe.

Here are a few representative Brown & Sharpe Tools for many different types of work. There are over 2300 others.

Ask your dealer for a copy of our Small Tool Catalog No. 31 listing complete line. If he can't supply you, write to us. Dept. P. S., Brown & Sharpe Mfg. Co., Providence, R. I., U. S. A.



Micrometer Caliper
No. 1183

Range 0 to 1" by thousandths of an inch
Distinctive shape of frame permits measuring over projections or in shallow slots.



Micrometer Caliper
No. 54

Range 0 to 8" by thousandths of an inch
No. 55 Range 2" to 6" by thousandths of an inch—similar to No. 54 but adapted for larger work




Screw Thread Gauge
No. 630

Distinctive shape of blades permits measuring threads of nuts and bolts.




Thickness Gauge
No. 628

Heat-treated blades
Range 1/16" to 1/2"




Inside Micrometer
No. 64

Range 1/8" to 1 1/2" by thousandths of an inch. The frame is made of steel and has a distinctive feature.




Outside and Inside
Spring Calipers
No. 41 and No. 412

Useful tools for general work



Dial Test Indicator
No. 3

A most useful tool for checking and setting up work



Tempered Steel
Rule No. 15

The light band makes it easy to read

Brown & Sharpe Tools


"WORLD'S STANDARD OF ACCURACY"

Locating Holes in Small Work

Boring irregular-shaped recesses in a lathe—Measuring the radius of a segment—How to slice leather belting

TO MOST tool and die makers, the job of locating holes within a tolerance of from .001 to .003 in. does not offer any great difficulty, but the task of staying within the limits of from .0002 to .0003 in. is quite another problem. The following method has been used many times by the writer with uniform success.

The work is first squared up on at least two edges, and two parallels *A* and *B* are then fastened at right angles to each other on the bed of a vertical mill or drill press with clamps *G*. Then the work is placed directly against the parallels and



A MICROMETER depth gage can be used to obtain the radius of a segment of a circle if the proper values are substituted in the following formula:

$$\text{Radius} = \frac{C^2 + 4H^2}{8H}$$




Using a micrometer depth gage to obtain the data necessary for figuring the radius of *B*.

By substituting the value for *C*, which can be measured, and the value of *H*, which can be read directly from the gage, the radius is obtained.—CHARLES KYGLER.

SLICING a length of leather belting in two in order to form two narrower belts can be easily accomplished by the method illustrated.

First, a block of hardwood the same width as the belt is tightly clamped between the jaws of a parallel clamp. The point of a sharp knife blade is then dug into the block with its cutting edge pointing toward the clamp.


Cut a few inches of the belt by hand and pass it between the jaws of the clamp. Next, fasten the cut end of the belt firmly in a vise and holding the belt taut with one hand, and the knife steady in the other, walk away from the vise. With this method it is possible to cut belting just as fast as you are able to walk away from the vise. The jaws of the parallel clamp keep the belt centered on the block, thus insuring an even cut.—HARRY MOORE.



A block of wood, a parallel clamp, and a sharp knife form this simple belt cutter.

THE boring of irregularly shaped holes in a lathe having only a hand feed presents somewhat of a problem, especially when extreme accuracy is required. An ordinary cutter is not usually satisfactory and in cases where the hole to be bored has an undercut cannot be used at all. A simple yet effective method for doing this type of work, which the writer has found to be wholly satisfactory, is outlined in the accompanying illustration.

The work *A* is first strapped in the usual manner to the faceplate. The compound rest is then set at right angles to the cross-



feed as shown, and a layout of the contour of the hole is clamped to the apron as at *F*.

The boring bar is next set at the maximum diameter of the hole and the tracing arm or needle *E* is clamped to the compound rest so that it will move with the tool *B*. It is obvious, of course, that the point of the tracer and the tool should be placed at corresponding points on the layout and the work so that both will be at the same position of the contour at the same time.

Now by manipulating the cross-feed and compound handles so that the tracer will follow the outline on the template, a hole can be accurately bored to the shape desired.

ALMOST every grinding spindle has at least .001 or .002 in. end play, but when accuracy is of utmost importance this allowance on a surface grinder becomes a source of trouble. This end play, however, can be eliminated by the application of a simple kink. A 1/4-in. steel ball is placed in the center hole at the end of the shaft, and a piece of spring steel is clamped to the wheel guard in such a way that its free end is in spring contact with the ball. In cases where only a small amount of pressure is needed, a discarded hack saw blade can be used in place of the spring steel. H. J. CHAMBERLAND.

the hole *H'* drilled and bored. The two blocks *C* and *D* ground in width to the desired dimensions *b* and *f* are next put in place, and the position of *H'* is accurately located.

These spacer blocks *C* and *D* can be made by grinding any suitable soft stock, but the common adjustable parallel is ideal for this purpose.

In spite of its simplicity, this method will produce work to limits of .0002 in. in less than one third the time necessary to do the job by the button method, which at its best will hardly produce results to limits much closer than from .0005 to .001 in.—CLARENCE J. TURCOTTE.

IN CASES where a drill has a tendency to run, as on a slope, or where one cutting edge is in brass while the other is in steel or if the hole is not entirely in the metal, better results can be obtained if a small center hole is drilled first.

If a wad of waste is dropped into a hole that is to be countersunk and the drill brought down on this, the edges will cut through after a few revolutions, and, being supported by the waste, will in most cases leave a smooth countersink.

With any job where the drill is in danger, the shifter should be pulled over or the clutch engaged just enough to pull the load. If anything hangs up, a stalled machine will be the most serious difficulty that can result.—JOHN A. COOK.

Announcing the **LEBLOND** **REGAL LATHE**

A precision lathe with the latest engineering features—8-speed selective geared headstock—quick change geared feed—feed rod (takes the wear off the lead screw)—deep rigid bed of close grained nickel steel alloy iron—built-in motor with V belt drive—furnished with all necessary equipment and ready to operate.



Size:

10' x 3'

\$398.00

*Every Regal Lathe carries
the LeBlond guarantee*

Every Regal Lathe must pass the regular LeBlond tests before shipment and is built in the LeBlond shops.

Jobbers interested in a high-class lathe for the Repair, Maintenance and Light Manufacturing Fields, please write.

Regal Lathes are made in various sizes. The one shown is 10 inches by 3 feet. It sells for the low price of \$398.00. Lathe is shipped to you promptly upon receipt of \$79.60. Balance in monthly payments of \$27.86.

Write for detailed description, sizes and prices of the complete Regal Line.

THE R.K. LEBLOND MACHINE TOOL CO.

**CINCINNATI,
OHIO, U.S.A.**



The R. K. LeBlond Machine Tool Co.,
Regal Division,
Cincinnati, Ohio.

Send me full details of the Regal Line of LeBlond Lathes.

Name _____

Address _____

City _____
200

State _____

Here Is a Parrot to Hold Your Reading Lamp

Not a real, live polly, but a gay wooden bird that anyone can build

By DALE R. VAN HORN



The completed parrot light in use. Either a round or a shield type shade can be used.

AFTER the evening meal, when a man settles down in his favorite chair for an hour with the sporting extra, his enjoyment is made more complete by having a well-placed, attractive looking reading lamp at his side—one that will throw the light just where he wants it. The parrot lamp shown in the accompanying illustrations was designed for this very purpose, and it has the additional advantages of being colorful in appearance and distinctly original in design. You couldn't duplicate this lamp in any store; it is a genuine novelty.

The parrot, cut from wood and brilliantly painted, sits patiently on a perch and holds the light in the best position for reading. What appears to be a feed dish beside the bird can be used as a receptacle for ashes, if desired, although the main purpose is to add to the realistic effect. The perch itself is mounted on a neatly turned standard supported by four shaped legs.

Novel as it is, the parrot lamp is relatively easy to construct, especially if your shop boasts some of the modern motorized equipment now so generally in use.

You should first shop around for a bill of materials about like this:

- 1—2½ by 2½ by 41 in. wood for the upright (walnut or other hardwood preferred)
- 1—1½ by 1½ by 8 in. wood for the perch
- 1—five-ply wood ¾ by 18 by 30 in. for the four legs and the parrot

1—glued-up block 4 by 4 by 2½ in. for the feed dish

1—assembled electric light fixture cord with plug and socket, 50-watt bulb, and appropriate shade


8—5/32 in. diameter roundhead (No. 7)

screws, 2¼ in. long
Glue, putty, several brushes, colored lacquer or paints, etc.

With a band saw, the cutting out of the legs and the bird can be done in ten minutes, but a jig or coping saw will do the work as neatly, although, of course, less rapidly. Smooth the cut edges with sandpaper and inspect them for any holes within the laminated structure. Such holes can be plugged with wood, whittled to shape and coated with glue, or a plastic com-



All band-sawed edges should be thoroughly and carefully sanded.



Drawings of the parts. Full size outlines of the parrot and legs can be obtained by transferring the lines to paper marked off in 8-in. squares.



A genuine novelty in reading lamp design.

position may be used. When one leg has been cut out and sanded, it may be used as a pattern for the other three pieces. A sanding spindle set between the lathe centers and carrying two or three grades of sandpaper will facilitate smoothing the curved surfaces if a drum sander is not available. Give the legs a coat of walnut stain and wipe off the surplus. Then cut out and sandpaper the parrot.

Put the main standard between lathe centers and turn to the shape and size shown. Make what variations you please; your own design is likely to prove more effective than the one shown. See however, that the top end (which must be tapered) has a mean diameter of ¾ in.

Sand the turning smooth, taking care that all tool marks are removed, then stain the wood while still between centers. Start the lathe and wipe off the surplus stain with a rag. Rub down again with fine steel wool held lightly. Stop the motor and rub the steel wool with the grain to take out any traces of sandpaper scratches. Next, apply clear lacquer with a soft brush or rag, allow it to dry for five minutes, and then rub it down with a clean rag. In an hour or two, apply another coat and repeat the rubbing. Give a final finish with wax. This is a quick, simple method, if the wood is to have a natural finish. In

(Continued on page 108)

look for the
RED END

GUIDE TO HACK SAW QUALITY

A Hack Saw is the most important tool in the toolbox of the mechanic. It is the only tool that can be used to cut through the hardest materials. The quality of the blade is of great importance. A good blade will cut easily and without vibration. A bad blade will cut with a great deal of effort and will be very likely to break.

The best Hack Saw blade is one that is made of high quality steel. It should be heat treated to give it the proper hardness. The blade should be ground to a fine edge. The handle should be made of a material that is strong and durable. The handle should be comfortable to hold and should not slip.

SIMONDS SAW AND STEEL CO.

The Edge Saw Mfg. Co.

ESTABLISHED 1832

FITCHBURG, MASS.

Manufacturers of all kinds of saws and files.

SIMONDS

New building
Industry's first
Windowless Factory

RED STREAK
ALL HARD AND HARD EDGE
HACK SAWS

the same manner, finish the legs, and to speed up the rubbing, you can cover a wooden spindle with cloth, set it in the lathe, and run both the flat sides and the curved edges over it. Hold the pieces with a light touch or the lacquer will become heated and may rub off.



Detail showing how the wires are brought out through holes in each side of the bill.

Turn the perch with a 1 3/16-in. ball a little to one side of the center. Taper one end to fit a 1/2-in. hole in the cup or tray. The other end should have half of a 1 in. diameter ball with a sharp shoulder. The central ball should be carefully bored halfway through with a bit; use a small drill first to make a guide hole for the bit screw in order to prevent splitting. Finish the perch as described before, but leave a small area unfinished where the parrot is to sit and along the tapered end.

The cup is turned from a glued-up block of the dimensions shown and is similarly finished. Use only the best quality of liquid, casein, or hide glue to insure satisfactory, permanent joints throughout.

Returning to the parrot, set up a bit in the lathe chuck, fix the table at the proper height, and bore the two holes for the light cord shown by the dotted lines in the



Drilling the holes for the wires. The positions of these are shown in the drawings.

drawings. Both holes start at the same point at the back edge. Small holes, one on each side, are made in the bill at the point indicated; these should meet the end of the larger hole. Through these holes are led the single wires of the cord, which are drawn through far enough to allow the light socket to be wired. The surplus cord is then pulled back through the holes, all the slack taken up, and glue is inserted to hold the cord taut. Putty the holes and space around the wires, or fit plugs to be glued in and sandpaper them off smooth. A groove in the bird's foot serves as an outlet for the electric fixture cord.

Now coat the inside of the foot with glue and wipe glue around the perch and where needed, then set the bird in place. The exact position is optional, but the parrot should tilt far enough forward to permit the light to hang naturally.

Fasten each leg with two 2 1/4-in. No. 2 screws. In making the original lamp, a jig was set up to drill the screw holes in the legs accurately at the points shown; then the jig was readjusted and small holes were drilled on the lower end of the upright to indicate where the screws should enter. It is advisable to sand off the finish from the portions of the upright the legs are to cover, and apply glue here before the screws are turned home. Test the stand on a level floor and sand down the bottom of any leg which

appears to be too long.

The parrot can be painted realistically or sketched with a brush, and the tones easily blended to give a natural effect. However, you have any doubt as to the success of this artistic work and cannot find an artist for assistance, paint in a strictly modernistic fashion with the green, yellow, and red, to suit your own fancy.

While it is desirable to use walnut or mahogany cabinet wood for the perch, legs, and feet, you may, as a suggestion, use softer woods throughout and finish all the parts in opaque paints or lacquers. For example, gray could be used for the body color, with Chinese red for the trim. You can, of course, get the plywood for the parrot and the legs in

facings of walnut, gum, birch, or almost any other wood you might wish, but in case your local dealer does not stock these, you can make the parrot of pine plywood and the legs of solid gum, walnut, or other hardwood for the clear-finish method.

The choice of shade to be used is a matter of personal preference, both the round and shield type being applicable.



The four hand-sawn legs are held in position on the standard with glue and screws.

SANDPAPER HOLDER FOR COMMUTATOR WORK

SANDPAPER is often used to clean motor commutators that have a streak of carbon all the way around which is "shorting" the sections, or to resurface them if they have been worn uneven by the carbon brushes. The open space in the motor housing is generally so small that it is difficult to hold the sandpaper in the fingers, but work of this sort can be done conveniently with a stick shaped as illustrated.

The sandpaper is cut into 1/2-in. strips. The end of one of these is doubled over for about 1/2 in. and fitted into the notch, which holds it firmly. The rest of the sandpaper strip is looped over the end of the stick, and the loose end is held with one of the fingers against the stick.

When the sandpaper is worn down, a short piece is torn off at the notch end of the stick and a fresh portion used.

Quartz sandpaper should always be used, never emery cloth, as the emery is likely to short-circuit the commutator or windings.—C. C. PREIFFER



Cleaning motor commutators becomes less of a problem when a sandpaper stick is used.

The graduate in the making of the parrot.




Applying the colors to the parrot. Blue, red, green, yellow, and white lacquers were used.

BOXING MODELS SAFELY FOR SHIPMENT

AIRPLANE and ship models may be packed in the manner illustrated below with reasonable assurance of safe delivery, barring accidents. Only the hull or fuselage is fastened to the case.

First, measure and make the bottom allowing sufficient clearance for wings, spars, bowsprit, and other parts. Use 1-in. stock for the bottom and the cross cleats at the ends and under the cradles. Set the model on the bottom and locate the position of the cradles. For a ship they should lie about where the turn of the bow and stern begins and at a clear space on the deck for cleats to hold down the model.

Shape the two cradles carefully to fit the bottom of the model and use thick




Methods of packing a model. A peaked roof and handles are desirable for a large case.

enough stock to hold screws well. They may be lined with something soft to prevent chafing. For keel models may be molded down in a board or shelf to about the water line, and the shelf firmly built into the case. Fasten the cradles to the bottom with at least one long screw at each end, driven up through the bottom. A notched block may be fastened at the bow and stern to prevent fore-and-aft slip.

Now set the model on the cradles and measure for the frame of the case. Finish the frame and cover it with thin plywood, wall board, or any thin lumber. Band the lid or cover, which is to be screwed on after the model is fastened.

A light model may be lashed in one cradle with cord passed across the deck and down through the holes in the bottom. Heavy models require cleats across the deck; these must rest on the deck—not on the gunwales—and be screwed to the cradles. Lash down loose anchors, small boats, and the like.

Valuable models or delicate old ones may be packed in two cases, one inside the other, with wadded paper or excelsior around the inner case. Heavy or large cases may have handles on the sides and a peaked roof. Letter the warning "Ship (or Airplane) Model—Fragile" on all sides of the case.—HENRY GEORGE.



First, make a hole for the screw!

USE the "Yankee" Automatic Push Drill, as illustrated. You operate it simply by pushing on the handle. That is the tool the mechanic uses before he drives a screw . . . to make the right size hole for the screw and save splitting the wood.

Drill is revolved by pushing on handle. A spring brings handle back for next push; revolving drill-point backward to clear chips.

Repairing furniture, putting up bathroom fixtures . . . wherever screws are driven, you need this "Yankee" Drill to bore the holes. Any size, from 1/16" to 1 1/4". Eight "Yankee" Drill-points, each tested, carried in magazine in handle.

No. 41.—Used along with "Yankee" Spiral Screwdriver, by mechanics everywhere. Price, \$2.60.

No. 44.—Adjustable Tension regulates pressure to suit kind of wood, size of drill. Price, \$3.15.

Mechanics will tell you "Yankee" tool-making can't be copied . . . look for the name "Yankee" when you buy a push drill.



"YANKEE" TOOLS TO HELP YOU MAKE THINGS



NORTH BROS. MFG. CO., Lehigh Avenue, Philadelphia, U. S. A.

You may send back showing picture of famous "Yankee" tool sets such as: Hammer, Saw, Dr. . . . or a full set of tools. Hammer, Push Drill, Spiral Screwdriver, and a full set of bits. Hammer, Push Drill, and a full set of bits. Hammer, Push Drill, and a full set of bits.


Name _____

Address _____

(ps)

Cutting Circles on a Band Saw

By HERBERT WOOLSEY




No skill is required to cut perfect circles on a band saw equipped with this attachment.

CUTTING circles or circular arcs on a band saw or power-driven jig saw is made an easy task by the use of the simple attachment illustrated.

The device is an auxiliary table that fits over the regular saw table. It is equipped with an adjustable pin to serve as an axis about which the piece being cut is rotated. A perfect circle of any radius within the limits of the attachment can be cut in a minimum of time and without preliminary scribing; and a large number of duplicate cuts, all of the same size, can be made in a short time.

While the attachment illustrated was designed for a 12-in. band saw, it can, of course, be modified to fit a machine of any size. The table requires two 1-in. boards, the length of which is 2 in. greater than the width of the saw table, measured parallel to the blade surface. The width of one board (the left one) is 1 in. greater than the distance from the saw blade to the table edge, measured at right angles to the blade. The other board may be somewhat greater in width than this distance or even several inches wider.



Sectional sketch of the attachment showing how the wood strips are cut and assembled.

The boards are held in place on the table by four 1 by 1 in. cleats on the underside. These cleats pass along the edge of the saw table and also serve to hold the two boards in position, with a space between them equal to about twice the thickness of the saw blade. The cleat along the front edge must be cut in two so that the band saw blade will enter the slot. A locking device consisting of two small right-angle brackets and a bolt and nut holds

beveled, and of a width that will permit them, with the slide, to fill the groove snugly. One of these strips should be the same thickness as the slide; the other, about 1/16 in. thinner to allow for tightening.

Mount the thicker of the side strips solidly at the side of the groove furthest from the operator. Drill three holes in the other—the thinner—side strip to receive small flathead wood screws. Insert the slide, then set the drilled side strip in place and drive the screws, countersinking the heads deeply. The three pieces should fit so that, when the wood screws are loose, the slide can be moved easily, but when they are screwed down, it will be locked in place securely.

You can lubricate the slide with soap, if necessary.

The phonograph needle is cut to a length that will permit its projecting upward about 3/32 in. On the underside of the slide, directly beneath the needle, make a shallow recess and fasten in it a piece of sheet metal, so that pressure on the needle point will not force the other end down into the bottom of the groove.

A block 1/2 in. wide is fastened in the groove at the saw-blade end so that the slide will not be forced into the blade. A scale may be added to facilitate slide adjustment, if desired, the saw blade being at the zero point.




With the stock pivoted on the needle, it is necessary only to revolve the work.

the boards in position and also makes the attachment grip the saw table edges firmly.

The center about which the stock being cut is rotated is a large phonograph needle inserted in a hardwood slide that is adjustable as to its distance from the saw blade. First, cut a groove 2 in. wide and 3/4 in. deep in the outer board of the circle-cutter, using, if possible, a circular saw and dado attachment. Smooth the slot with a wide chisel. The slide, preferably made of maple or birch, is 1 in. wide at the bottom and about 3/4 in. at the top, both edges being beveled equally—to about 15° or 20°. It should be about 2 in. longer than the groove.

After completing the slide, cut two strips, each with one edge similarly



A close-up view of the attachment showing the pivot needle, the guiding strip, and a locking screw.

When soldering tinned copper or tin plate, an otherwise neat looking job is sometimes spoiled by the solder's spattering and sticking to the work. This can be easily prevented by coating the surfaces nearest the seam to be soldered with a heavy mixture of whiting and water. This will effectively keep the solder from sticking.—V. C. DARBY


OLD-STYLE PHONOGRAPH CABINET CONVERTED INTO A LOWBOY



This graceful looking lowboy was once an obsolete and valueless phonograph cabinet.

A DISCARDED phonograph cabinet of the style popular a few years ago can be converted into a presentable lowboy with very little trouble. Remade in this way, the piece is worth far more than an out-of-date phonograph.

How the transformation is effected can be seen from the accompanying photographs. The only puzzling part of the work was to devise a way to conceal the holes where the crank and volume control came out of the end of the case. This was done by carefully fitting in a piece of veneer that had been previously finished in a tone exactly matching the phonograph cabinet. The patching was hardly noticeable, and the remodeled cabinet, when well polished, looked like a new piece of furniture.—M. D. TAYLOR.



Interior view illustrating how the supports and guide strips for the drawers are placed.

TOOL HANDLE FERRULES

FERRULES for tool handles can be made from the small screw caps often used instead of corks on small bottles containing drugs and patent preparations. Punch a hole or cut a slot in the top of the cap and, if you wish, flatten out the rolled threads with a hammer. Two center punch marks will hold the ferrule securely on the handle.—W. G. W.

It is always difficult to keep small dies clean, for filings so minute as to be almost invisible will prevent the clear cutting of fine threads. A solution is to clean the dies before they are started down the rod, with pipe cleaners.—M. E. CRUMB.

The Encyclopaedia for a Lifetime Only NELSON'S Can Give You 1931 Information—Always New— Radio—Television—Aviation The "Talkies"—Business Conditions—New Tariff Covers the World's Entire Knowledge

Nelson's will give you this information when you need it most, when it is new and fresh—long before any other Encyclopaedia could possibly do so—because Nelson's Loose-Leaf system and replacement pages make Nelson's a new encyclopaedia every six months—always ready to meet your needs for the latest information.

NELSON'S LOOSE-LEAF ENCYCLOPAEDIA Can Never Grow Old!



Why NELSON'S is Always New

Renewal Pages come to you every six months containing the latest facts and knowledge gathered from all over the world. You simply unlock the binding, take out the old pages and insert the new ones—a matter of a few moments—and you have an Encyclopaedia that is new, not only accurate and dependable, a Nelson's is the only Encyclopaedia offering the official 1930 Census figures.

THE GREAT AMERICAN ENCYCLOPAEDIA

A Few of 100 Reasons
Why You Should Own NELSON'S
It Is Everyman's University

It is the complete Reference Library—equal to 1000 text books. It is the equivalent of a College education—for all your family. It is your History, Geography, Atlas, your guide in Mechanics, etc. It helps the School Child makes easy the student's studies. It covers the whole Field of Knowledge—over 1,000,000 topics. It makes you familiar with Countries, People, World Travel. It will increase your efficiency, thereby adding to your income. It is beautifully illustrated—over 7,000 illustrations, 500 maps. It will pay you its weight in Gold. Use 15 minutes each day. It should be in every American home because it is THE GREAT AMERICAN ENCYCLOPAEDIA written and edited by Americans, for the American family.

FREE Handsome BOOKCASE

Given to Readers of Popular Science Monthly. This bookcase was especially made for NELSON'S—it is designed especially with leaded glass single door. It is a convenience of holding you set and a handsome piece of furniture as well. It will be yours at no additional cost, if you act promptly.

FREE Question and Answer Service

When you are in need of an answer to any question, old or new you can write to Nelson's Research Bureau and get FREE the latest dependable information.

33 Reading Courses

A Reader's Guide to Nelson's Loose-Leaf Encyclopaedia is given without extra charge to every subscriber. It outlines thirty-three college-grade courses of reading and study.

Send for Illustrated Booklet

We will be glad to send you an interesting illustrated, loose-leaf booklet of sample pages and full information. It tells the whole story of Nelson's Loose-Leaf Encyclopaedia, gives you information about our FREE BOOKCASE offer, describes the free question and answer service of Nelson's Research Bureau and the thirty-three reading courses.

Mail This Coupon

THOMAS NELSON & SONS

301 Fourth Avenue, New York.

Originators of the Loose-Leaf Encyclopaedia
Publishers for Over 140 Years

Please mail me FREE your portfolio of sample pages, all information about the FREE bookcase and how my subscription payment can I obtain Nelson's Loose-Leaf Encyclopaedia with Free Membership in Nelson's Research Library, Service Bureau for Special Information, and Nelson's Readers' Guide Free. (P.S. 31, 2-31)

Name _____

Address _____

City _____ State _____

Here's Your Science Tool Chest!

RADIO New developments in broadcasting—trans-oceanic wireless telephony—ship to shore communication—a new Radio City planned right on Fifth Avenue in New York—radio moves ahead swiftly. NELSON'S keeps you up-to-date on all new developments.

AERONAUTICS New achievements in the aeronautical field—greater speeds—higher altitudes—new safety devices—new navigation aids—more record-breaking flights. All these events are recorded for you by NELSON'S, while they are still new.

INVENTIONS Inventions that revolutionize industry, reduce housework to a minimum, provide new comforts, luxury, safety, economy. NELSON'S records them for your ready reference.

ENGINEERING A new bridge spans the mighty Hudson—steamships make new speed records across the Atlantic—every new triumph of the engineer's skill is faithfully brought to you for quick reference in the renewal pages of NELSON'S.

TELEVISION Already the first commercial receivers are on the market both here and in England, and one bold prophecy sees a television set in every home within 3 years. NELSON'S renewal pages will keep you posted on the progress of television.

And Every Other Science! A new planet is discovered by astronomy! Medicine reports new triumphs over disease! Science marches on, remaking our world at every step! Let NELSON'S keep you informed of every advance of knowledge!

Amazing NEW TOOL VALUE

An Automatic Push Drill
Carrying in the Handle
Eight Sizes of Drill Points

\$1.25

Pick out the size drill you want from the separate numbered compartment. Insert it in the steel jaws. Place drill point where you want hole. Push—push—and presto, you have a smooth clean hole in any wood. It can also be used in plaster. The handiest tool ever invented for household use. Made by one of America's leading makers of fine tools. SHOW THIS AD TO YOUR DEALER AND SECURE A DRILL FOR \$1.25 or if he hasn't a stock yet, mail coupon to us and tool will be sent postpaid C. O. D. \$1.10. Hundreds of household jobs formerly postponed will now be done neatly and easily.



EVERY
HOUSEHOLD
NEEDS ONE

USE THE COUPON TODAY!

Goodell-Pratt Company, Dept. S-2,
Greenfield, Mass.

Please send me a No. 302 Automatic Drill. I
will pay postman \$1.40.

Name _____

Street _____

City _____

State _____

My hardware dealer is _____

Nothing under \$3.00 ever bought such a good tool.



The judges deciding on the winners of the Ship-Model-in-a-Bottle Contest after having narrowed down the competition to twenty of the best models submitted.

Readers Build Amazing Ship-in-Bottle Models

And ten of them win prizes for their work

CRAFTSMANSHIP of an extraordinary character was displayed by many readers who entered our recent Ship-Model-in-a-Bottle Contest. The number of entries was far larger than had been expected, and the general standard of quality was nothing short of amazing.

The judges found it desirable to award four special prizes in addition to the six originally announced and to give honorable mention to six other model makers. The list of winners is as follows:

First prize, \$50—Charles V. Nielsen, Carlsbad, N. J.

Second prize, \$25—Kenneth A. Young, Washington, D. C.

Third prize, \$10—Harold T. Bodkin, Chicago, Ill.

Fourth prize, \$5—Anthony Splich, New York, N. Y.

Fifth prize, \$5—William E. Green, Seattle, Wash.

Sixth prize, \$5—Louis Cochard, Veterans Home, Napa County, Calif.


Four special awards consisting of two years' subscription to POPULAR SCIENCE MONTHLY—Edward W. Roberts, Fort Stanton, N. M.; Bireley Ross, Coleman, Texas; Louis Salu, East Port Chester, Conn.; and Raymond Smith, Lawton, Okla.

Honorable mention—J. R. Campbell, Richmond Hill, N. Y.; William E. Chamberlain, Boston, Mass.; Joseph A. Lindquist, Hempstead, N. Y.; F. F. Mitchell, Phoenix, Ariz.; Charles W. Sheppard, Colwater, Ont., Canada; and William H. Swayne, Piedmont, Calif.

Mr. Nielsen submitted two models of the clipper ship *Flying Cloud*, one with sails, which was awarded the first prize, and the other with standing rigging only. The winning model, which is in a quart bottle with a neck opening of a scant $\frac{3}{4}$ in., is $4\frac{3}{4}$ in. long over all, $2\frac{3}{4}$ in. high from keel to top, and has a hull a scant $\frac{1}{4}$ in. in width and $\frac{3}{8}$ in. in depth amidships (see illustration below).

The second prize model by Mr. Young is the bark *The City of New*

York.



The winner of the first prize, a delicate model of the clipper ship *Flying Cloud* in full sail.

BLUEPRINTS FOR YOUR HOME WORKSHOP

TO ASSIST you in your home workshop, POPULAR SCIENCE MONTHLY offers large blueprints containing working drawings of a number of well-tested projects. Each subject can be obtained for 25 cents with the exception of certain designs that require two or three sheets of blueprints and are accordingly 50 or 75 cents as noted below. The blueprints are each 15 by 22 in.

Popular Science Monthly,
381 Fourth Avenue, New York

Send me the blueprint, or blueprints, I have underlined below, for which I inclose . . .

dollars

cents

Airplane Models

- 50. 36 in. Rise-off Ground Trainer
- 59. Lindbergh's Monoplane (3-ft. by 10-in.)
- 82. 30-in. Single Ship
- 86. 35 in. Twin Pusher
- 87. 30-in. Biplane
- 89-90. Biplane (3-1/2 ft. by 10-in.) 50c
- 102. Morris Biplane (record flight 12 1/2 min.)
- 104. Tractor (record flight 6,024 ft.)

Furniture

- 1. Sewing Table
- 2. Smoking Cabinet
- 3. End Table with Book Trough
- 5. Kitchen Cabinet
- 13. Tea Wagon
- 17. Cedar Chest
- 18. Telephone Table and Stool
- 19. Grandfather Clock
- 20. Flat Top Desk
- 21. Colonial Desk
- 24. Quilting Table
- 31. Sewing Cabinet
- 33. Dining Alcove
- 36. Wash Bottom Chair
- 37. Simple Bookcase
- 38. Sheraton Table
- 39. Chest of Drawers
- 40. Broom Cabinet
- 50. Welsh Dresser
- 58. Magazine Rack Table
- 70-71. Console Radio Cabinet 50c
- 77. Pier Cabinet and Wall Shelves
- 78. Treasure Chest
- 88. Modernistic Stand and Bookcase
- 91. Folding Screens
- 93. Three Modern Lamps
- 100. Modernistic Book Ends, Book Shelf, Low Stand
- 105. Tavern Table and Colonial Mirror

Radio Sets

- 103. One-Tube (battery operated)
- 42. Three Stage Amplifier
- 43. Four Tube (battery operated)
- 54. Five Tube (battery operated)
- 55. Five Tube Details
- 79. Electric
- 80. Electric High Power Unit
- 81. Electric Low Power Unit

- 97. One Tube Electric
- 98. Two Tube Electric
- 99. Four Tube Electric
- 100. Screen-Grid Set

Ship and Coach Models

- 44-45. Pirate Galleon or Frigate, 50c
- 46-47. Spanish Treasure Galleon, 50c
- 48. 20-in. Racing Yacht
- 51. 52-53. Clipper - Sovereign of the Seas, 75c
- 57-58-59. Constitution ("Old Ironsides") 75c
- 61-62. Viking, 50c
- 63-64. 3rd. Toy Motor Boat 50c
- 74-75. 76. Santa Maria (18 in. hull), 75c
- 83-84-85. Mayflower (17 1/2 in. hull) 75c
- 92. Baltimore Clipper (8 in. long)
- 94-95-96. Mississippi Steamboat 75c
- 106-107. 42 in. Racing Yacht, Sea Scout 50c
- 66. Ship Model Weather Vane
- 108. Scenic Half Model of Barque
- 110-111-112. Schooner Bluebonnet 75c
- 115-116-117. Concord Stagecoach, 75c
- 118-119-120. Covered Wagon, 75c
- 121-122. Clipper Ship in a Bottle, 50c
- 123-124. Queen's Sedan Chair 50c
- 125-126-127. U.S. Destroyer (11 1/2 in. hull), 75c

Toys

- 28. Pullman Play Table
- 56. Birds and Animals
- 67. Lindbergh Plane
- 71. Doll's House
- 72. Doll's House Furniture
- 101. Fire Engine or Sprinkler Truck, Tractor
- 113. Lathe, Drill Press, Saw and Jointer
- 114. Airplane Cockpit with Controls

Miscellaneous


- 15. Workbench
- 26. Baby's Crib and Play Pen
- 30. Tool Cabinet, Boring Gage and Bench Hook
- 65. Six Simple Block Puzzles

Price 25 cents each except where otherwise noted

Name _____
(Please print name and address very clearly)

Street _____

City and State _____



This How-to-do-it Book Makes Home-Crafting EASY!

• If you were an craftsman guides you, step by step, as you live up that fascinating hobby. He shows you easier, better ways to do things, and will soon make you an expert.

First, he discusses home-crafting as the ideal hobby, and tells how to have a shop of your own. Then, he advises you about saws, tool and bench machines, and a complete list of equipment suitable for small, medium or larger shops.

Next, he gives you a course in making wood joints, showing you the best ways to cut and fit 24 types. Then come working drawings and directions for making a folding work-table, saw-horse, modern bench, tool chest, and wall cabinet. Also, a "What to Make" reference list of over 200 projects, telling you where to obtain job plans to build them. This is a "gold mine" of ideas!

Finally, he shows you fifty of the famous "Silver Steel" saws and why they are big favorites with home-craftsmen and home-mechanics the world over.

This 42-page book costs only a dime, but you'll say it's worth dollars as soon as you see it. Every month, thousands write for it. Use the coupon to get your copy now.



Cut Out and Mail
This Coupon

E. C. ATKINS

and Company, Est. 1857

428 S. Illinois St., Indianapolis, Ind.

I enclose a dime for the new ATKINS Saw Book. (Please PRINT name, etc., below)

Name _____


Street _____

City _____


State _____

My dealer is _____


Owning a home-workshop means father and son will have good times together.



Selecting GOOD tools saves you time and money, and assures you better results.



Making accurate wood joints is easier with the correct tools. The book gives you



Building a work bench, tool box, or wall cabinet is real fun. The book shows how



Getting plans to build 200 other articles is made easy by a handy reference list.



FREE



BIG 48-Page BOOK of USES

for new kind of wood you
mould with your hands

NEWS! Amazing new kind of wood that handles like putty, hardens into wood, looks like wood...

Plastic Wood you can plane, turn, carve... Plastic Wood that expertly mends a thousand things and makes anything you can make with natural wood or modeling clay... That's its name... **PLASTIC WOOD**. Sold in cans and tubes, in 9 colors, by all paint and hardware stores. Just mail coupon for big 48-page, profusely illustrated book that shows the many uses for this new kind of wood you just mould with your hands. **SENT FREE!**

MAIL THIS COUPON


The A. S. BOYLE CO., Dept. 2-PS-4
Cincinnati, Ohio

Send me—free—Big Book of Uses for Plastic Wood

Name

Street

City State



A model of Rear Admiral Byrd's bark *The City of New York* (at top) won second prize while a beautiful model of the *Sovereign of the Seas* was awarded the third prize

in a quart size bottle with the neck opening $1\frac{1}{4}$ in. in diameter. The length over all is $4\frac{1}{2}$ in. and the mainmast is $2\frac{1}{4}$ in. high. The masts are assembled with cross-trees, trestletrees, and tops, and the details are correct even to such things as the rail on the stern, which is carved from the solid block of the hull.

THE title of Mr. Bodkin's entry, which won third prize, is "*Sovereign of the Seas, Outward Bound*." It is a fine example of minute workmanship, the builder having used a jeweler's glass in shaping many of the extremely small parts. For example, each anchor is about $\frac{1}{8}$ in. long and built up from four separate pieces of celluloid, and the chains are of knitted thread, blackened and then brushed with bronze to represent rusted links.

Mr. Spilich's model is also one of the *Sovereign of the Seas* built to the scale of $\frac{1}{4}$ in. equals 1 ft. Mr. Green submitted a model of the *Canada*, of the old Black Ball line in a gallon size bottle. The model nearly fills the large bottle yet it was inserted through a neck so small that it will not allow a five-cent piece to pass. In fact, Mr. Green had to insert the hull in halves. In addition to this remarkable model, he submitted two models in tiny flat bottles which are only about $\frac{3}{4}$ by $1\frac{1}{4}$ by $2\frac{1}{2}$ in. over all. One of these curious little models has been presented by Mr. Green to Governor Roosevelt of New York, who is an enthusiastic collector of ship models. Mr. Cochard's model, which was built in a half-gallon bottle, is unique in that it is treated decoratively rather than realistically, and the rigging is of gold colored silk.

All these models have to be seen to be appreciated. They would stand out as exceptional examples of craftsmanship in any exhibition of ship models. So perfect

are they in detail that all would be complete and excellent models even if they were enlarged to regular mantelshelf sizes.

While there were some old sailors among the contestants, the majority proved to be men in other lines of work, including advertising and banking. Several models were entered by boys and others by men of great age, the oldest being L. F. Baldwin, of Albany, N. Y., who is in his eighty-third year. One creditable model of a Spanish galleon was submitted by Miss Hazel Way, of Chicago, Ill.

The same general method of construction was used in making all the models; that is, each model was built outside the bottle and then folded into a compact bundle which could be slipped through the neck and reassembled by raising the masts in the manner described when the contest was announced (*P. S. M.*, Aug. '30, p. 71).

The judges of the contest were Capt. E. Armitage McCann, secretary of the Ship Model Makers' Club, and the technical and home workshop editors of *POPULAR SCIENCE MONTHLY*.


SAFETY GOGGLES PROTECT EYES WHILE SAWING

SAFETY goggles with nonshatterable glass should be part of the equipment of every home workshop. I use a pair of metal-framed goggles with a sort of fine screen cup on either side. Once when I was sawing some $\frac{1}{2}$ -in. ebony, the goggles saved the sight of my left eye because the saw, tearing through the hard, brittle wood, drove a tiny splinter with such force that it actually stuck in the nonshatterable glass. Ordinary glass would have broken. Because of this experience, I make a practice of wearing goggles whenever I use either the lathe or the circular saw and, of course, always when using a grinding wheel.—W. F. B.

PIPE FITTINGS USED TO MAKE LUMBER RACK

A STURDY rack for the storage of lumber in the shop can be made from standard pipe fittings. The rack consists of two brackets, which are fastened to the ceiling or wall, and provides a number of horizontal arms on which boards, molding, and similar materials can be stored in the manner shown below.

The brackets illustrated, which are used in a low-ceilinged basement, were



The rack, which consists of two brackets, can be fastened to the ceiling or side wall.

made from $\frac{1}{2}$ -in. fittings, the following materials being required for each bracket: One floor plate six 6-in. nipples, one 5-in. nipple, one 4-in. nipple, two tees, one elbow, two couplings, and three caps.

The top arm consists of two 6-in. nipples, a coupling and a cap. The middle arm includes the 4- and 5-in. nipples and the lower arm a single 6-in. nipple. The hanger can be fastened to the ceiling with heavy bolts or screws. For side mounting, a street elbow should be interposed between the floor plate and the adjacent nipple.—WALTER E. BURTON.



Assembling one of the brackets. The design may be varied to meet the individual need.

IN THAWING a frozen water pipe with a blowtorch, always start at the faucet end and work towards the meter. An electric reflecting heater is a safe and excellent substitute for the blowtorch. The radiant heat given off is easily focused and it quickly warms the frozen pipe.

HE HAS A GOOD JOB



USING NICHOLSON FILES

IN AN AGE when machines reach greedily for work that formerly was done by hand, thousands of mechanics realize that it not only pays to use Nicholson Files but that it also pays to know how to use them.

Filing is one operation that by and large must be done by hand. And the thousands of trained hands which are doing this filing are more than partial to the sharp cutting qualities of Nicholson Files.

Nicholson Files are carried by the great majority of hardware and mill supply dealers in a variety of shapes and sizes for every industrial and home workshop need.

NICHOLSON FILE COMPANY
Providence, R. I., U. S. A.

A FILE FOR EVERY PURPOSE




THE SCREWS that hold the world together



IF you will look around you, whether you are in a house, a boat, an airplane, a church or an office building, you will find that there are hundreds of screws doing hundreds of jobs—they are holding together a "world" of construction.

Famous for length of service, strong bodies and easy driving, are American Screws. For 93 years they have been the standard of quality for the world of industry.

The easiest way to buy American Screws is in "Handy Packs"—you select the size you want from the illustration on the cover. Your dealer can supply you.



WOOD SCREWS MACHINE SCREWS STEEL BOLTS TIE BOLTS

AMERICAN SCREW CO.
PROVIDENCE, R.I., U.S.A.
WESTON DEPOT, 225 WEST HANCOCK ST., CHICAGO, ILL.
"Put It Together With Screws"

Better Ways to Build Wings for Model Airplanes



Builders of model airplanes will do well to lay particular stress on wing design.

Two common types of wing tips, bamboo (Fig. 1) and ordinary thread (Fig. 2).




Fig. 4. The lightest type of wing construction. This design lends itself well to further experimentation.

THE wing of a model airplane being its main supporting surface should be given the builder's utmost care in design and construction. As it is often the lastest part of a model, it must be designed so that its weight will be at a minimum, yet, as it receives a maximum of air pressure its strength must be maintained. Perfection in wing construction requires a combination of strength and light weight.

During the growth of the model airplane many unique and ingenious wing designs have made their appearance. Practically all of these are the result of

fighting the model plane's greatest enemy—weight. Some designs have failed because the designer sacrificed strength in his effort to eliminate weight, but great advances have been made, and model builders should be familiar with them.

Wings for light indoor endurance models, which are usually covered on one side only, can be dismissed with a few words. The usual construction is shown in Fig. 3. Its strength lies in its leading and trailing edges, which consist of two duplicate balsa spars while its ribs are balsa strips of about 1/2 in. square, cambered to suit and cemented to the tops of the spars.

The tissue covering is glued to the ribs as well as the spars. The wing's shape is maintained not only by the tissue covering but also by the wing caps which hold it in place on the motor stick.

In designing and constructing wings for out-




Fig. 3. The plain type of wing that is covered on one side only. Used on indoor models.

door models, whether twin-stick, fuselage or the so-called "flying scale models," three factors have to be considered—strength, weight and form. Such wings, because they are covered on both sides, must be properly formed in respect to air resistance, drag, vacuum, and lift.

Experimentation has proven that the Clark-Y rib form is best for general use on models. All illustrations used in this article, with the exceptions of Figs. 3 and 4 have the general form of this type. It must be understood that the designation "Clark Y" refers to the outside form of a wing from leading to trailing edge, or as the wing looks when covered, and that




Fig 5. This type of wing rib is strong but should be avoided because it is too heavy.

It has nothing to do with the means by which that form has been gained. The wings marked 1, 2, 3, 6, 7, 8, 9, and 10 (and bearing corresponding figure numbers) are all Clark-Y forms. While these various ribs may look different, due to the fact that their excess weight has been removed in varying ways, their outside forms will give the same appearance to the wing when covered.

In the past, ribs were sand, as is shown in Fig. 5. It soon became apparent that such a rib contained an excess of material and in an effort to lighten them, the ribs were cut out in various forms. A razor blade is used for cutting out the straight designs. The circles, however, are punched with the eraser ferrule of a common lead pencil, as shown in Fig. 6. The eraser is removed, and its small, round holder is slowly pressed into the wood.

How the ribs are cut out and their excess wood is removed depends upon the general position of the spars and the type of wing construction. All the wing sections






Fig. 6. An eraser ferrule on a lead pencil can be used to punch holes in balsa ribs.

Very Latest in Bench Machinery



Big Jig Saw

Large massive and heavy
"O" agency. Glutens for
with 12 dia rising
table. Has improved head
down above with 11-12
14-16. 10-12 11-12 12-12

The practical experience gained through twenty continuous and successful years in designing and building bench woodworking machinery is behind the latest improved 1031 BOICE-CRANE line of:

**HANDSAWS . LATHES . JOINTERS
BAND SAWS . JIG SAWS . SHAPER
and HOLLOW CHISEL MORTISER**

[illegible]

New Plan—Shop Pays for Self!

[illegible]

Brand New Shaper



የገንዘብ መመዝገቢያ ስራ የተከናወነው በፊት ተጽእኖ
በሆኑት ዓመታት የገንዘብ ስራ በአጭር ጊዜ ውስጥ
በፊት ተጽእኖ በሆኑት ዓመታት የገንዘብ ስራ በአጭር ጊዜ ውስጥ

549.

New 4" Jointer



\$25

Levin Guard
Nothing on earth
like a graduated
fisher till you
walk long in
his wide robe
and arm

Universal Headliner \$30

Week of year	Week
1st of Jan	1
1st of Feb	5
1st of Mar	12
1st of Apr	16
1st of May	22
1st of Jun	26
1st of Jul	31
1st of Aug	35
1st of Sep	40
1st of Oct	44
1st of Nov	49
1st of Dec	53



Buy
Now
Pay
Later

**Band Saw,
less guards,
\$32.50**

Take this 45 degree
New 4 1/2" thick Orange
ceatings. Very hard finish.
Will prove a valuable aid
in your work. Blanks or
a and metal or compound.

Send for Big FREE Catalog

One of the largest and most complete books ever printed in French woodcutting machinery. Large 8 1/2 x 11" size. 140 color plates & a steel with engraving in the margin. 120 drawings and engravings. The complete list of 1-48451. See Terms with important woodcutting data & answers for the asking. Write today. Send name and address NOW.

W. B. & J. E. BOICE

Dept. P.S.—2G Toledo, Ohio

MAIL COUPON

W. M. & J. E. BOICE
Dept. F. S.—26, Toledo, Ohio

7 Dep. Ch. Comm. Reg. For. Affairs (MIA) Not interested in
'Foreign' - not paid

7 Dep. Ch. Comm. Reg. For. Affairs (MIA) Not interested in
'Foreign' - not paid

Sutton

References

1179

2144

STOP THAT LEAK WITH SMOOTH-ON No. 1

YOU can apply Smooth-On with radiator full or empty, hot or cold, without removal from the car and without putting inside anything that clogs the circulation.

Merely roll the Smooth-On into a stiff putty, press it against and into the leak with your thumb or pack it into the defect with a knife blade or screwdriver, and scrape off the excess. The leak will stop instantly, and the repair is permanent. For a few cents and in a few minutes you will have avoided all the delays and expense of a professional repair job that couldn't be any better.

Cracked water jackets. Water jackets of automobile, stationary or marine gas engines which have developed long or short cracks or have even had pieces broken entirely out from freezing can be made thoroughly and lastingly serviceable by similar repair, or by applying Smooth-On under straps or a plate.

Smooth-On No. 1 can be used in a hundred ways in the household, and it often saves from \$50.00 to \$100.00 on the first job.

Keep a can of Smooth-On No. 1 with your tool kit and some day when caught with a repair job you will thank yourself for your forethought.

SMOOTH-ON MFG. CO.

Dept. 58

574 Communipaw Ave.

Jersey City, N. J.

Get Smooth-On No. 1 in 7 oz., 1 lb., or 5 lb. cans at nearest hardware store or if necessary direct from us.

FREE

This booklet tells how to stop not only water leaks in radiator, cracked water jackets, and all other hose connections, but also how to stop gas leaks from the auto, gasoline lines, and exhaust system, and a leak at gaskets and all cracks in tank or rear axle. It also tells how to make brake fluid joints tight, hub caps and bolts and are in a very light and shows dozens of simple money saving Smooth-On repair jobs. Send for it today to return the coupon.

Do it with SMOOTH-ON

SMOOTH-ON MFG. CO. Dept. 58,
574 Communipaw Ave., Jersey City, N. J.
Please send the free Smooth-On Repair Book.

Name _____

Address _____

2-11

Return this coupon for a
FREE copy of Booklet

have proved successful, and each merits discussion.

5. Disregarding its rib, which was left solid for illustrative purposes only, this is one of the strongest of wing designs. The leading, trailing, and center spar are of the same size. The leading and center spars fit into notches cut into the rib in order that the outer form of the rib will not be changed. The center spar is at right angles with the bottom edge of the rib, while the other spars are parallel to it.

6. This construction has ribs with four holes cut into each for lessening the weight. A trailing spar is cemented parallel to the bottom edge of the ribs, and a center spar of the same size passes through each rib but is at right angles to the bottom edge of the rib. Cement is applied at each rib. The leading spar is the largest. The ribs are cut off at their front end, and the spar rounded to the form of the

9. Two large holes are cut in each rib. The leading and trailing spars are the same size and cemented parallel to the bottom edge of the ribs. Very light balsa center spars are cemented into grooves cut in the top and bottom edges of the ribs. These can be as small as 1/32 in. square. This is a light and strong arrangement.

10. In this well-finished, strong construction, the ribs are cut out as shown, and the trailing and center spars, each of the same size, are cemented to each rib. The front end of each rib is then cut out in a V-form, and a square leading spar is




Fig. 7. This type of wing rib construction is very light and is also sufficiently strong.

cemented into each V. When the cement is hard, the protruding corner of the leading spar is rounded with sandpaper.

It must be remembered that all these spar arrangements can be used with any of the ribs shown, and the builder will do well to experiment with various combinations.

Figure 4 is a type of wing and rib construction that the writer feels should open new fields of experimentation. Because of its pointed nose effect, this cannot be classed as a Clark-Y rib, but its performance is remarkable, and the construction is of the lightest. The leading and trailing spars, as well as the top and bottom rib formers, are of strip bamboo, while the center spar is of 1/32-in. sheet balsa, its width being whatever the width of the rib is at its widest point. An effort to construct this design out of nothing but balsa would prove most interesting; such a design would have a promising future in wing construction.

The wing of a plane should be symmetrical in design from all points. Sharp, straight edges or blunt ends are as undesirable for speed as they are for appearance. This factor should be applied not only from leading to trailing edge, but also from wing tip to wing tip. For this reason, few wings end bluntly with the outer rib, the best designs are finished off in a graceful wing tip. Figures




Fig. 9. Another kind of perforated wing rib that is strong and not heavy.

Fig. 10. Variation of rib in Fig. 9 with different arrangement of spars.

1 and 2 show two popular types of wing tip finish. The first is the bamboo tip. Note that the ends of the leading and trailing spars are cut to match the angle of the bamboo at the point where they are cemented together, and that the center spar is tapered from the outer rib to the width of the bamboo at the point where it is cemented to it. When covered, the wing gives the appearance of a gradual slope to its wing tip.

Figure 2 gives the same general appearance, except that the wing has a pointed tip. The leading and trailing spars are tapered, as in the first case. Thread is used in place of the bamboo, and the center spar is tapered to meet it. This construction is far lighter, but not quite so strong, though repairs are easier to make. With the bamboo, the tip can be made round, semiround, as in Fig. 1, or any other desired shape simply by bending the bamboo but with thread the final form of the tip must take the appearance of straight lines.—EDWIN T. HAMILTON

The best and easiest ways of covering airplane motor wings will be described in a following article.

AUTOMATIC CONTROL FOR A FURNACE DAMPER

FULL automatic control of drafts on steam heating plants having a clock mechanism and pressure arm for opening and closing the check draft usually can be obtained by placing a link between the pressure balance control arm and the handle of the flue damper, as illustrated. This simple addition will cause the clock and pressure arm to close the flue damper at the same time that it shuts off the check draft and to open the damper when the draft is opened.

The link can be made from any piece of scrap metal stock and the pivots may be loose fitting rivets or nuts and bolts.

It may be necessary to fasten an extending arm on the handle of the flue damper if one does not already exist.—D. G. S.




Diagram showing how the link is connected between the damper and the pressure arms.

STRANGE as it may seem, there is no relation between japan drier and baking japan. The former is added in small quantities to hasten drying while the latter is baked on a surface to give a beautiful enamel finish.

The Stanley "Big Seven" Nail Hammers for 1931



Stanley-Atha No. 100
Plus "Chro-Moly"
Size 1 1/2—16 oz.

"The Architect of Nail Hammers." Chro-Molybdenum steel with our super heat treatment produces the "world's finest" hammer "Evertite" processed handle.



Stanley-Atha No. 31 1/2 F
Size 1 1/2—16 oz.

Super heat treated head. "Evertite" processed handle.



Stanley-Atha "Red Neck" No. 15
Size 1—16 oz.

A popular hammer with craftsmen. Super heat treated head. "Evertite" processed handle.



Stanley-Atha No. 31 1/2
Size 1 1/2—16 oz.

The greatest hammer value ever offered. Super heat treated head. "Evertite" processed handle.



Stanley-Atha No. 31 1/2 A
Size 1 1/2—16 oz.

A well balanced straight claw hammer for slipping work.



"Standard" No. 101 1/2
Size 1 1/2—16 oz.

"The Handy Man's Hammer"—a real "boy" for the occasional user.



"Defiance" No. 011 1/2
Size 1 1/2—16 oz.

A good hammer for the small odd jobs around the home.

**Greater Values
per dollar than has
ever been offered before**

Here are some of the reasons why you get more hammer per dollar in the Stanley line for 1931.

An improved hammer head—hard enough to stand severe pounding—tough enough to prevent breaking. This is made possible by a new Super Heat Treatment of the heads which brings out the full potential strength of the steel.

A handle that will stay permanently tight. An exclusive "Evertite" process of pre-shrinking the eye end of the handle together with patented wedges and a double tapered eye socket completes the job.

Well designed claws with proper bevels will grip and pull headless nails from the toughest wood.

Compare the design and balance of a Stanley-Atha hammer with any other. You'll appreciate why Stanley-Atha Nail Hammers are selected by most craftsmen.

See the 1931 Stanley-Atha Nail Hammers at your nearest hardware dealer's. Select the one that best fills your needs.



THE STANLEY RULE & LEVEL PLANT
New Britain, Conn.

STANLEY TOOLS

The Choice of the Trades

FREE AS A HAWK ON WING

Soar away—wherever fancy calls you. Swoop down to that little lake you've glimpsed from the highway. Wing your swift and easy way over roads and trails to new adventures—to new cities worth seeing, and new people worth meeting.

Free as a hawk you are, when you're riding a Harley-Davidson. All roads are yours. You breeze by car parades, and flit through traffic jams. You can ride as much and as far as you like, for Harley-Davidson cost-per-mile is next to nothing!

Name _____
Address _____
Room _____

USING OLD NEWSPAPERS INSTEAD OF KINDLING

OLD newspapers, being made from wood, are well adapted for use as kindling to start coal fires. The writer has used nothing except paper kindling for two years and has found it entirely satisfactory.

From four to six (or more after you have had a little practice) double sheets of newspaper are assembled and folded into fourths as shown at A. Next, the loose edges are lapped lengthwise to within 1½



Old newspapers, if rolled as shown in these diagrams, can be used to start coal fires.


or 2 in. of the folded edge, and the papers are rolled toward the folded edge as tightly as possible (steps B, C, and D). The cylinder thus formed is crimped by bending it away from the folded edge as at E, causing the tightly rolled tube to keep its shape. After one becomes accustomed to folding the paper, these kindlings may be formed as rapidly as splitting wood.

To start a fire, lay crumpled paper in the usual way and place from eight to twelve of the kindlings crisscross on top. When the paper rolls are aflame, they will readily ignite coal.—F. A. ST. JOHN

FILLING CORNER CRACKS

CORNER cracks in plaster walls are a common blemish in many homes. In addition to being unsightly, they are extremely hard to fill satisfactorily with trowel or putty knife. The best way is to use a coarse brush, such as a paste brush. The patching plaster is mixed to the consistency of a thick paste and is then brushed into the crack until it is completely filled. After drying a little, the excess plaster may be scraped off. The result will be a clean job that will last indefinitely if there is no further spreading or settling of the walls.—ROBERT ROAT

A GRAIN of salicylic acid added to a glue size tends to keep the mixture "sweet."



Ride a
HARLEY-DAVIDSON

MAIL THE COUPON


HARLEY-DAVIDSON MOTOR COMPANY Dept. P S Milwaukee, Wis.
Interested in your motorcycles. Send literature.

Name _____

Address _____

My age is ☐ 16-17 years, ☐ 18-20 years, ☐ 21 years and up,
☐ under 16 years. Check your age group.

DOCTOR MAKES PATTERNS AND BUILDS COMPLETE BENCH BAND SAW




The band saw has 12-in. wheels with a 1-in. face; they are 21 in. apart, center to center.

WHEN L. St. John Hely, M. D., of Richmond, Calif., wants a new machine for his home workshop, he designs and builds it himself. His latest achievement is the small band saw illustrated—an unusually efficient machine with 12-in. ball-bearing wheels turning 600 R.P.M.

The backing wheel and guide for the saw blade are adjustable. The table top and is also adjustable up and down since the quadrant is clamped on a block which slides vertically.

After making drawings for the saw, Dr. Hely prepared the patterns on other home-made machines and had them cast at a railroad foundry. He did all the machine work in his garage workshop except boring the holes in the wheels, which he had done in a machine shop.



The wheel guide rods are $\frac{1}{2}$ in. round steel, but the saw-blade guide rod is $\frac{1}{2}$ in. square.



EDWIN M. LOVE

*Distinguished
Craftsman and Designer*

Says

"Carborundum Stones Helped Me Build Better Stage Coach Models"

THE newest thing in home decoration is the Stage Coach Model. And now that workshop fans are turning to these attractive miniatures as enthusiastically as they did to ship models, suggestions coming from Edwin M. Love are well worth hearing. Mr. Love is one of the foremost coach model authorities in the country.

"In making coach models," he says, "as in every workshop project, good sharp tools are half the battle. I keep my chisels, knives, block plane, etc., and bench hooks keen edged and primed for action with Carborundum Brand Stones. Well sharpened tools do better work, give more service and last longer than those that are used after becoming dull."

The popularity of Carborundum Brand Stones with thousands of men, from amateur workshop enthusiasts to skilled carpenters and mechanics, checks with Mr. Love's statement about the necessity for constantly sharpened tools. Always have a Combination Stone at hand, ready to do its quick clean sharpening job just as soon as the slightest dullness or smallest nick is noticeable.

**FREE
36-PAGE
BOOKLET**

"ADVICE ON HOW TO SHARPEN
YOUR WORKING TOOLS" is full of
helpful, illustrated information every tool
user will appreciate.

THE CARBORUNDUM COMPANY
Niagara Falls, N. Y.

Please send me FREE, without any obligation,
your booklet, "Advice on How to Sharpen Your
Working Tools P. I."

Name _____

Address _____

Town and State _____

THE CARBORUNDUM COMPANY
NIAGARA FALLS, N. Y.

CANADIAN CARBORUNDUM CO., LTD.
NIAGARA FALLS, ONT.

APPROVED BY THE INSTITUTE OF STANDARDS
(Under the supervision of the U.S. Bureau of Standards)

Simplify!

Why fuss with old-fashioned, uncertain and wasteful glues? One glue—**CASCO**—does every gluing job better—easier—and assures permanent results.

TRY
CASCO
Waterproof
GLUE



SEND for

sample—and see for yourself that **CASCO** fills every gluing need. **CASCO** is an all-glue dry powder made from MILK. Mixes easily in cold water. No heating, no odor, no waste. Tremendously strong—Modern—Clean—Practical—Economical.



The
CASCO
FOLDER

describes the many uses of **CASCO**—as a Glue—as a Size—as a Binder. Sent with **CASCO** sample.

Hardware, paint and building supply dealers sell **CASCO** in 5 lb. cans, 1 lb. cans, 10 lb. cans, 40 lb. cans, 1 lb. cans. If not obtainable locally, order direct giving dealer's name.
Distributor—Special **CASCO** order of carton contains all sizes of testing tubs.
Manufacturers—Consult us on your gluing problems.

THE CASEIN MANUFACTURING CO.
OF AMERICA, INC.
205 East 42nd Street, New York



THE CASEIN MANUFACTURING CO.
OF AMERICA, INC.
205 East 42nd Street, New York

Enclosed find 10c (stamp only) for which send me your trial package of **CASCO** WATERPROOF GLUE and **CASCO** folder.

Name.....
Street.....
City..... State.....
Hardware, Paint or Building Supply Dealer's Name (Please include).....

PERNICIOUS ANEMIA CURE WINS \$10,000 AWARD

(Continued from page 31)

the importance of Dr. Minot's contribution, two facts should be remembered. First, Dr. Whipple did not apply his discovery to human beings. Secondly, he never claimed that the treatment would be effective in pernicious anemia. His dogs had secondary anemia, caused by bleeding. Pernicious anemia cannot be induced in any known laboratory manner. Its essential cause is entirely unknown. Moreover, secondary anemia, while dangerous, is seldom fatal. Pernicious anemia nearly always, or rather was, deadly. Until Dr. Minot perfected the treatment for human patients the average life of a pernicious anemia sufferer, from the time the symptoms first became obvious, was from two to three years.

For years Dr. Minot worked tirelessly upon his blood investigations, keeping scrupulous records of all cases that came to his attention and making microscopic examination of the blood of all of his patients. After finishing his internship at the Massachusetts General Hospital, he went to the Johns Hopkins Hospital in Baltimore, and for two years continued his studies there.

BACK again in Boston, he associated himself with Dr. James Homer Wright, distinguished pathologist. From him Dr. Minot learned something new about the probable cause of pernicious anemia. At the time, the generally accepted theory was that pernicious anemia resulted from poisons breaking up the red blood cells. Dr. Wright differed. The red corpuscles are made by the marrow in the bones. Dr. Wright held that pernicious anemia was caused by a tumor-like disease of the bone marrow, which prevented the blood cells from attaining their normal growth.

But what could be done about a tumor hidden in the bone marrow? Dr. Minot doggedly continued his studies. Practicing in association with Dr. Roger I. Lee, an experienced blood specialist, from 1914 until 1917 he tried the treatments then approved, among them operations to remove the spleen, and blood transfusions. In that three-year period, the two doctors had ninety-six pernicious anemia patients. Surgeons removed the spleens of nineteen of these sufferers. Forty-six of them were given seventy blood transfusions. In each case, the patient first improved, a condition known as a remission of the disease, and then relapsed again. This would occur two or three times, but finally every one of the sufferers died.

The turning point came in 1921, when Dr. Minot himself was taken seriously ill with diabetes. This was before the discovery of insulin, and he knew that the proper diet would be his only hope. Placing himself in the hands of an outstanding diabetes specialist, he followed his instructions to the letter. In fact, he became a diet enthusiast.

MEANWHILE, in 1922, insulin was discovered, and it saved Dr. Minot's life. Resuming his work with greater strength and energy than ever, he determined to try diets in pernicious anemia. He questioned all of his patients as to their eating habits, and found that only thirty percent of them ate normally. The majority of them, he discovered, had had an aversion to meat and green vegetables practically all their lives. In other words, their diet had been lacking almost entirely in protein.

About this time he came across a work entitled "The Newer Knowledge of Nutrition" by Dr. E. V. McCollum, the great vitamin expert. In this way, he learned for the first time that liver was rich in protein and in the vitamins that speed the growth of young animals. He also found that managers of zoological gardens (Continued on page 123)

MODERN STERLING HOME 797

Prices Never Lower

GET BOOK
"How to Buy a Home"
\$1.00

Insulated Weather Stripped Glass Double Hung Windows
\$1.00

Never before such value. Shows how to select a home, how to buy a home, how to finance a home, how to build a home, how to decorate a home, how to maintain a home, how to sell a home. Includes a complete directory of home builders, real estate agents, and home furnishings stores. Also includes a complete directory of home builders, real estate agents, and home furnishings stores. Also includes a complete directory of home builders, real estate agents, and home furnishings stores.

COLOR BOOK
"How to Buy a Home"
\$1.00

How to buy a home, how to finance a home, how to build a home, how to decorate a home, how to maintain a home, how to sell a home. Includes a complete directory of home builders, real estate agents, and home furnishings stores. Also includes a complete directory of home builders, real estate agents, and home furnishings stores.

WRIGLEY'S SPEARMINT
THE PERFECT GUM
MINT LEAF FLAVOR

Good and Good for You.

WORKING JIG SAW

For Saw Blades, Jigsaw Blades, Files

2000

Forms to Carry Lead Soldiers, Indians, Trappers,

Henry C. Schlerke, 1034-12nd St., Brooklyn, N. Y.

Rider Agents Wanted

Tires

Mead CYCLE COMPANY
DEPT. TEN CHICAGO

SAMPLES OF 33 RARE WOODS

MAN WOOD SERVICE CO.
28-28th St., Tel. 10, Chicago, Illinois

Build a CLOCK

FREE BOOK Shows How YOU Can Make Fine Clocks Night at Home

AMERICAN CROWN CLOCK COMPANY
1001 G Street, Philadelphia, Pa.

PERNICIOUS ANEMIA CURE WINS \$10,000 AWARD

(Continued from page 122)

who attempted to raise lion cubs on a diet of lean meat always lost them. The young animals contracted the bone disease known as rickets and invariably died. But if the cubs were fed liver, bones and fat, they grew into strong, healthy specimens.

If liver will strengthen the outside of the bones, Dr. M. reasoned, why not the marrow inside? Just then, the results of Dr. Whipple's experiments were announced and Dr. Minot began to feed his patients liver, prescribing about one quarter pound a day.

All through 1924 he secretly treated ten patients in that manner. The blood count of some of them had been as low as 2,000,000 red cells per cubic millimeter of blood. By 1925, they not only were all alive, but their counts ranged from 3,000,000 to more than 4,000,000, which is close to normal.

TOGETHER with an associate, Dr. William P. Murphy, Dr. M. not quietly continued the treatment increasing the liver dose to a half pound a day. Patients who were brought to the hospital dying from pernicious anemia, with the blood count down to one tenth of the normal and so ill that they could not eat at all, were fed liver in pulped form through stomach tubes.

Then, suddenly, in 1926, Dr. Minot, at a meeting of the Association of American Physicians, at Atlantic City, N. J., announced that forty-five pernicious anemia patients, treated by him and Dr. Murphy with the liver diet, had recovered.

Immediately thereafter, doctors in all parts of this country as well as all over Europe tried the new cure and found that Dr. Minot had not overstated its efficacy.

Since then, Dr. Minot and his associates have succeeded in separating the chemical in liver that cures pernicious anemia. Now, it may be taken in powdered form, dissolved in orange juice or other liquid. Recently, Dr. Whipple and his assistants have done the same thing so far as the chemical that fights secondary anemia is concerned.

In this way it has been possible to concentrate and purify chemical elements that represent only three percent of the entire liver weight, and yet contain eighty percent of the potency of the liver. This so-called liver fraction has been in use in many hospitals.

BORN in Boston, Mass., in 1885, Dr. Minot was graduated from the college of Harvard University in 1908 and from its Medical School in 1912. His Internship at the Massachusetts General Hospital lasted one year, after which he was connected with the Johns Hopkins Hospital in Baltimore, Md., until 1915. From then until the present, he has been connected in various capacities with the teaching staff of the Harvard Medical School and the medical staffs of the Massachusetts General Hospital and the Huntington Memorial Hospital in Boston, where he became chief of the medical laboratories in 1923. At present, he is professor of medicine at Harvard.

Dr. Whipple, born in Ashland, N. H., in 1878, was graduated from Yale University in 1900 and from the Johns Hopkins Medical School in 1905. From 1905 until 1907 he was connected with the Ancon Hospital in Panama, and in 1908 with the Bay View Hospital in Baltimore. After that, he served on the teaching staff of the Johns Hopkins Medical School until 1914, when he accepted the post of professor of research medicine and director of the Hooper Foundation for Medical Research at the University of California. In 1921 he was appointed dean and professor of pathology in the School of Medicine and Dentistry of the University of Rochester.



They're always looking for Bill when the crowd gathers

WHERE in the dence is Bill? It's like a funeral here. Gosh, if I could play an accordion like that boy, I'd charge you fellows for entertainment.

"Remember when he first came to college? What a 'wash out' we thought he was. He didn't go out for athletics or anything. But, (Hi. Boy, when he took out that accordion of his and started to play! He sure can make it talk and he says he's only played it for a couple of months. Lucky guy, he may not be able to play basketball—but he goes every place with the team and gets his expenses paid, too. Did you hear him play between quarters at the last game?"

"I wouldn't be at all surprised if he was voted the Most Popular Fellow in the class this year. He's a fine chap all right, but no one would ever have known it if it wasn't for that accordion of his."

Here's BILL NOW!



Nothing like an accordion to put you in the lime-light—in a class by yourself. The craze for this fascinating instrument is sweeping the country. Music dealers say they have

never seen such enthusiasm for a musical instrument before. On the radio, on the stage, in the dance orchestras, the accordion is now all the rage. All the live-wire college boys and girls are playing it. Just the thing to make you popular at parties. It's a cinch to learn. No teacher needed. The Free Instruction Book tells you the simplified way. And it's easy to own one—Hohner Accordions, the world's best, are priced as low as \$9.00.

Select the Instrument of Quality

Hohner Accordions are recognized by professional musicians as the finest instruments in their line in the world. Their total qualities, their accuracy and volume have given them a world-wide reputation, and they are guaranteed to give absolute satisfaction. You can make no mistake in buying a Hohner. Mail the coupon for FREE catalog giving full information about Hohner Accordions. Free Instruction Book with each instrument. Address: M. HOHNER, Inc., Dept. 207-B, 114 East 16th Street, New York, N. Y.

HOHNER ACCORDIONS


M. HOHNER, Inc., 114 E. 16th St.,
Dept. 207-B, New York

Please send me your catalog of Hohner
Accordions.

Name _____

Address _____

WHICH would you choose for a delicate JOB?



YOU never know how much "cheap" oils cost until you've used them on your delicate workshop equipment.


Then you learn how expensive they are. Heat and high speed breaks them down. Bearings and moving parts are bared to friction. And very soon repairs or replacements are necessary!

With 3-in-One Oil, all of your equipment is safe. This oil costs more to make—but less to use—for it does three different things to furnish complete protection.

Three-in-One cleans moving parts and bearings; works out old, gummy oil. It flows quickly and evenly to all friction points to provide lasting lubrication. It prevents rust and tarnish. Three-in-One is a special blend of animal, mineral and vegetable oils—so it does all these jobs at once, far better than any plain mineral oil can do them.

Handy cans and bottles, at good stores everywhere. Write for a free sample and "Dictionary of Uses."

THREE-IN-ONE OIL CO., DEPT. 303
130 William Street, New York
Factories: Rahway, N. J. - Montreal, Que.



3-in-One Oil

CLEANS - LUBRICATES - PREVENTS RUST

Cuts—and Short Cuts on A Motorized Jointer

By DONALD A. PRICE

WHILE the name of the jointer indicates its use in planing the edges of stock that is to be joined, its practical utility to the home craftsman is far more extensive.

Among its specific uses are: accurately truing up edges of boards for gluing up table tops and other wide pieces; planing the surfaces of boards of any width up to the capacity of the machine; planing bevels; cutting open and "dropped" or stopped chamfers; cutting rabbets for glass in picture frame moldings as well as shaping the face of the molding (providing it consists of plane surfaces); and in addition some "stunt" uses that simplify many cabinetmaking operations.

As in hand planing, the first operation in bringing a piece of work to size on the jointer is to prepare a true side and a square edge. Pressing the work

Fig. 1 After one side or face of a board has been planed, that side is pressed against the fence, and one edge is trued as at the right.



Fig. 2 Small, short, and thin work should be pushed through the jointer with the aid of a notched block.

Fig. 3 Cutting bevels with the fence slanting towards. This is the preferred method, as the tilted fence helps in holding down the work.



Accurate beveled joints are as easy to make with a bench jointer as plain square edges.

directly downwards on the table make successive light cuts until one side or face is planed true. Then run the work through to square up the edge, keeping the true side against the fence. This operation is shown in Fig. 1. Notice that there is

a safety guard on the machine and that it is being used.

Another safety precaution is to shift the hands holding the work as it is fed forward so that they are never over the knives or in danger of going into them if either hand should slip. Also, never make adjustments without first shutting off the power. Place a switch in a convenient place near the machine so that it can be readily shut off. It may be a "through" switch on the motor cord or, better yet, a "throw" switch mounted on the motor or the base.

When starting up the jointer—and this is a general rule for all machines—pull the belt over by hand to see that there is no interference before turning on the power. When running through work of small cross section or work that is extremely thin, use a notched block as shown in Fig. 2 to push it through.

The procedure in



cutting beveled edges is substantially the same as cutting a square edge except that the fence is tilted to the proper angle. Notice in Fig. 3 that the fence is set to bevel inwards instead of outwards. This always should be done when the construction of the machine will allow it, since the upward thrust of the cutters is then partially taken by the fence, making it easier to hold the work down. All edges which can be planed with the grain by means of this set-up should be run through the machine. Then, if a perfect finish must be had on the remaining edges, the fence can be set slanting outwards and the work turned end for end and run through in the opposite direction in order to cut with the grain.

THE set-up for rabbeting is shown in Fig. 5. The front table is dropped below the rear table the depth of the cut desired and the fence is set the width of the cut away from the end of the knives.

To cut an open chamfer, drop the front table to make a coarse cut and then set the fence at the 45° bevel as shown in Fig. 4. Feed slowly until the end of the piece is stopped by the block clamped in the rear table. If this does not give as long a chamfer as desired, an L-shaped piece or hook such as shown in Fig. 7 can be added to the rear table in order to allow the end of the piece to travel beyond the end of the table. This use of the stop will insure all chamfers being cut to the same length.

When a "drop" chamfer must be cut, lower the rear table down level with the front table. Set the tables in line by using a straightedge with a portion cut out to clear the knives. A block or a hook used as shown in Figs. 6 and 7 respectively is clamped firmly on the front table. The cut is started by slowly sliding the piece down the fence onto the machine, all the time pressing backwards to keep the end of the piece firmly against the stop on the front table. When the full depth of the cut is being taken, feed forward to a stop set on the rear table to give the desired length to the chamfer.



A CURVED taper such as at C, Fig. 8, can be cut by setting the table as shown in Fig. 10. The front table is dropped as low as possible and the rear table raised so that the head just starts to cut in position A of work. Feed forward keeping the foot of the leg always pressed down firmly on the front table and tilting up the top of the leg till the foot end is not less than 1/4 in. from the gap when the cut is stopped. This results in a gently increasing curve towards the end of the leg as shown at the bottom of Fig. 10. Cut the work off at X if a simple taper is desired, or finish the end as shown in dotted lines if a foot effect is called for.

A straight taper may be cut with exactly the same set-up as used in Fig. 10 for cutting a curved taper. The difference in procedure lies in keeping the cut pressed down on the rear table and guiding and gauging the cut entirely by this. You will find that the foot of the work lifts up slightly from the front table after the cut is started and that the cut will be straight. A few experiments will quickly show just how these taper cuts are made.

The modernistic leg pictured at B in

"Delta" Motor-Driven Units..the Modern Way of Woodworking

This is a motor-driven age! The woodworker of today no longer endures the tedious drudgery of handwork. He ENJOYS his work because he saves time and turns out better products by using these compact and efficient machines. No more are a priced as to be within the reach of a full or spare time wood worker. Delta Tools supply the modern way.



"DELTA" Band Saw for cutting of all shapes.

"DELTA" On Lath Work shop the Delta Tools Co. New, Circular Saw, Jointer

DELTA EFFICIENCY

Every Delta woodworking machine is built up to this standard—it must perform its work efficiently, quickly, and accurately. There are no hidden traps in Delta Tools, no outward, outward-looking operations, no bothersome disassemblies. Instead, there are thoughtful, practical designs, quality in workmanship and materials throughout even where it cannot be seen, and simplicity in basic constructional features. That's why wood workers everywhere say that Delta gives the most machine value for the dollar. That's why Delta owners are enthusiastic Delta boosters.

10 Day Trial—Easy Terms

Send coupon today for free illustrated literature describing the new 1931 "Delta" line. A complete 10-Day Trial Offer and Easy Payment Plan.

DELTA SPECIALTY COMPANY
Division of DELTA MFG. CO.
1001 47th Street, Dept. S-732, Minneapolis, Minn.

Delta Specialty Co. 1001 47th Street, Minneapolis, Minn. Dept. S-732

Selection: Please send the 1931 "Delta" literature and details of 10-day Trial Offer and Easy Payment Plan. Check boxes of particular interest.

☐ Band Saw ☐ Circular Saw ☐ Planer/Jointer
☐ Router Machine ☐ Jointer ☐ Shaping Cutter

Name _____ Age _____

"DELTA" COMBINATION JOINTER AND CIRCULAR SAW—Complete, an sturdy stand of convenient height. Jointer and Circular Saw can be operated separately or together without interference. This "DELTA" Outfit is furnished with or without motor. Both the Jointer and Circular Saw can be secured as separate, individual units if desired.

BURN YOUR NAME ON TOOLS
WITH THE
ARKOGRAF
Protect Your Tools From Theft. Write with Arkograf on the handle of your tools and the handle of your tools will be marked with a permanent, indelible mark. Complete Guide to the Arkograf is available. Write for it today. Arkograf is available. Write for it today. Arkograf is available. Write for it today.

BUILD YOUR OWN
AUTOMATIC ELECTRIC REFRIGERATOR
Write for the complete plan and instructions for building your own automatic electric refrigerator. The plan is complete and includes all the details of construction. Write for it today. The plan is complete and includes all the details of construction. Write for it today.

BURPEE'S SEEDS GROW
The Vegetables and Flowers you would like to see growing in your garden—read all about them in Burpee's Annual Garden Book. It describes the Burpee Quality Seeds, Bulbs, and Plants. Burpee's Annual will be mailed to you free. Write for your copy today.
W. Atlee Burpee Co.
294 Burpee Bldg., Philadelphia

EASY TO PLAY
ANTONE who has a time as long as you want to play. ANTONE who has a time as long as you want to play. ANTONE who has a time as long as you want to play. ANTONE who has a time as long as you want to play. ANTONE who has a time as long as you want to play.

New Model South Bend Lathes

20 Sizes and Types

SOUTH BEND LATHES are made in sizes 9" to 21" swing with 5' to 12' bed lengths and may be had with countershaft or motor drive, in bench, floor leg, tool room, and gap bed types. Easy payments, if desired—a small payment down and the balance in 12 monthly payments.


A few prominent users:

Westinghouse General Motors
Western Electric Nashua Corp.
General Electric A. S. Corporation



9" x 3 Junior Back-Geared, Screw Cutting, Precision Lathe, also made in 3 1/2' and 4' bed lengths.

Complete with countershaft and equipment. Weight, 375 lbs. Price **\$169**. Payments \$12.50 Down, Balance \$11.42 a Month for 12 Months.



10" x 5 Motor Driven Quick Change, Back-Geared, Screw Cutting, Precision Lathe, furnished in 6', 7', 10', 12' and 14' bed lengths.

Complete with reversing motor, reversing switch and regular lathe equipment. Weight, 3,240 pounds. Price **\$997**.

WRITE For These Books

"HOW TO RUN A LATHE"
28c postpaid

Contains 166 pages, more than 300 illustrations showing how to handle 100 different types of lathe jobs as presented in the modern machine shop. Sent postpaid for only 25 cents—cash or stamps of any country accepted.

AUTO MECHANICS SERVICE BOOK NO. 66
28c postpaid

This 96 page book, with 200 illustrations, describes correct and most practical way to do 60 automobile service jobs that come in the shop.

CATALOG NO. 91-A—FREE
This 104 page book illustrates, describes and prices the 96 different sizes and types of New Model South Bend Lathes. Send the Coupon now for your copy free.

SOUTH BEND LATHE WORKS

412 E. Madison St., South Bend, Ind. U. S. A.
In the U. S. for 2 Years—Established in 1899

SOUTH BEND LATHE WORKS

412 E. Madison St., South Bend, Indiana, U. S. A.

Gentlemen: Please send me books checked

- ☐ "How to Run a Lathe" (25c)
☐ Auto Mechanics Service Book (25c)
☐ Catalog No. 91-A (Free)

Name _____

Address _____

City _____ State _____

Fig. 4 (at right). An open chamfer is cut by dropping the front table to give a coarse cut and setting the fence at a 45° angle. A stop block is clamped to the rear table.

Fig. 5 (below). In rabbeting, the front table is dropped below the rear table to the depth of the desired cut. The fence gauges the width of the rabbet.




Fig. 6. To make a "drop" or stopped chamfer, the cut is started by sliding the piece slowly down the tilted fence.

turned end for end and a 1/4-in. cut taken from the bottom up to D, giving section F. The front table is raised to make the cut only 1/4 in. deep, and more is taken off the rib up to E, finally giving section G. When the 5/16 by 3/8 by 3/8 in. top piece is glued and bradded on, the leg is complete.

The dimensions are given merely for descriptive purposes. By changing the depth and width of the cuts, varying effects such as illustrated can be obtained. Another effect obtained by changing the finishing of the head is shown at A, in the photograph of Fig. 8, and at the extreme

Fig. 7. A set-up for "drop" chamfering which shows the use of a wooden block as a gage for starting each cut. **Fig. 8 (at right).** Examples of work.

the photograph of Fig. 8 and the drawing in Fig. 9, is made entirely on the jointer save for the block on the top, which is cut out separately and glued in place. A piece of wood 1 1/2 in. square is trued up. Then the jointer is set to cut a 1/4 by 1/2 in. rabbet, and the piece run through four times in one direction, when it will look like section A. It is now turned end for end and run through four times more to obtain section B.

The fence is now moved to the right side of the table and a 1 in. cut started at the top C of the leg. The piece is again




Fig. 9. By the skillful manipulation of a jointer, one can obtain many unusual and modern looking effects such as shown. Compare these with the samples A and B Fig. 8.

How to Install a Block Signal System on Your Model Railway

Where the special track contacts, lights, and switches should be placed—Problems of current control—Concluding article

By FREDERICK D. RYDER, JR.



Fig. 1. Once your control switches and signal lights are made, it is a simple matter to install the wiring.

AFTER you have completed the special block signal switches, the special signal lights, and the special track contacts as detailed in the two previous articles of this series (P. S. M., Dec. '30, p. 94; and Jan. '31, p. 86), you are ready to proceed with their installation on your own model railroad.

It makes no difference whether your railroad is "standard" or "O" gauge; the same work has to be done in the same way. In fact, the only difference will be in the number of sections of track included in each block.

The blocks should be evenly spaced around the track circuit. At first glance it would appear better to have the spacing

uneven because several trains of equal speed would be bound to stop in the blocks and thus give the system plenty to do. However, equal speed for several trains is never obtained. Even when all the locomotives are of the same type and each one hauls the same number of cars, slight differences in brush action will result in considerable variation in train speed.

Assuming that there is one train which operates at a slower speed than the rest, it would be natural to expect this train to run continuously while the others trail along with frequent stops in the blocks. Actually this doesn't happen. On my own railroad one of the four trains I operate is notably slower than the rest, yet it often happens that this train stops in the blocks because of the delay caused by the others starting up, one after another, after they have all stopped in blocks back of the slow train.

The first problem is to determine the positions where you want the block signal lights. Naturally, they should be at points where they will appear to best advantage and give the most realistic effect.

If the track circuit includes an up-and-down grade, one block and its signal light certainly should be located at the bottom of the grade unless the grade is so steep that it is necessary to have the trains moving at the bottom in order to climb properly. Do not locate a block in the middle of an up or a down grade. On the up grade it will cause needless wear on the locomotives in starting the trains from a standstill on the grade. On the down grade it will be difficult to make the trains stop

without having them coast past the block.

On my own model railroad, which is of "standard" gauge, the number of sections of track comprising a block run from six to nine sections.

The best way to determine how long to make the blocks on your own model railroad is to find out how far the trains will coast after the current is cut off at the points where you wish to install blocks. Make your tests with the fastest train you expect to operate. When you have determined the actual length of coast at each point, add a couple of sections for good measure so that there will be no chance of a train's coasting clear through a block to the live track at the far end of it.

After you have determined the location and length of each block, use a hack saw blade to saw through the third-rail pins at each end of each block. This will save taking up the track to remove the pins. Figure 3 shows a simple way to saw through a third-rail connecting pin by the aid of a hack saw blade held in a pair of pliers.

The block signal system works only with trains that run in one direction. It could, of course, be made to operate in both directions, but an interlocking system



Fig. 3. The third-rail connecting pin must be sawed through at each end of each block.

arranged in this way would be exceedingly complicated.

Locate the solenoid-operated switches at convenient points near the far ends of the blocks and place the block signal lights to the right of the track at about the same points. A special track contact should be placed in the section of track just beyond each block.

Now study the diagram of Fig. 2 (which is also shown pictorially in Fig. 1) and proceed with the wiring, using ordinary bell wire. Note that Fig. 2 shows only one block, but as all blocks are wired alike, you will have no trouble if you follow the diagram given.

You will note that one wire is marked "to track contact of next block." When the wiring is completed, you will find that two wires lead to each track contact. Consequently, when a locomotive passes over a track contact, it actually causes two solenoid magnets to operate. One acts to cut off the current from the block over which the train has just passed,





Fig. 2. The wiring diagram. While the connections for only one block are shown, every block is wired the same. The ground wire goes to the grounded running rails by way of a master switch.



Amazingly Easy Way to get into **ELECTRICITY**

Don't spend your life waiting for \$5 raises in a dull, hopeless job. Now... and forever... say good-bye to 25 and 35 dollars a week. Let me show you how to qualify for jobs leading to salaries of \$50, \$60 and up, a week, in Electricity—NOT by correspondence, but by an amazing way to teach, **RIGHT HERE IN THE GREAT COYNE SHOPS**. You become a practical expert in 90 days! Getting into Electricity is far easier than you imagine!

Learn Without Lessons in **90 DAYS** By Actual Work—in the Great Shops of Coyne


Lack of experience—age, or advanced education bars no one. I don't care if you don't know an armature from an air brake—I don't expect you to! I don't care if you're 16 years old or 48—it makes no difference! Don't let lack of money stop you. Most of the men at Coyne have no more money than you have.

EARN WHILE YOU LEARN

If you should need part-time work while at school to help pay expenses, I'll assist you to it. Then, in 12 brief weeks, in the great roaring shops of Coyne, I train you as you never dreamed you could be trained on a gigantic outlay of electrical apparatus... costing hundreds of thousands of dollars... real dynamos, engines, power plants, autos, switchboards, transmitting stations... everything from doorbells to farm power and lighting... full-sized... in full operation every day!

No Books—No Printed Lessons

No books, no baffling charts... all real actual work... right here in the great Coyne school... building



Prepare for Jobs Like These

Here are a few of hundreds of positions open to Coyne graduates. Our free shop placement bureau gives you lifetime employment service.

- Armature Dept. up to \$100 a Wk.
- Bobbin Dept. up to \$100 a Wk.
- Auto Electrician up to \$100 a Wk.
- Ignition Dept. up to \$100 a Wk.
- Maintenance Engineer up to \$100 a Wk.
- Service Station Foreman up to \$100 a Wk.
- Radio Expert up to \$100 a Wk.

real batteries... winding real armatures, operating real motors, dynamos and generators, wiring houses, etc., etc. That's a glimpse of how we make you a master practical electrician in 90 days, teaching you far more than the average ordinary electrician ever knows and fitting you to step into jobs leading to big pay immediately after graduation. Here, in this world-famous *Parent school*—and nowhere else in the world—can you get this training!

Jobs—Pay—Future

Don't worry about a job. Coyne training settles the job question for life. Demand for Coyne men often exceeds the supply. Our

employment bureau gives you a lifetime service. Two weeks after graduation, Clyde F. Hart got a position as electrician for the Great Western Railroad at over \$100 a week. That's not unusual. We can point to Coyne men making up to \$600 a month. \$60 a week is only the beginning of your opportunity. You can go into radio, battery, or automotive electrical business for yourself and make up to \$15,000 a year.

GET THE FACTS

Coyne is your one great chance to get into electricity. Every obstacle is removed. This school is 30 years old—Coyne training is tested—proven beyond all doubt—endorsed by many large electrical concerns. You can find out everything absolutely free. Simply mail the coupon and let me send you the big, free Coyne book of 150 photographs... facts... jobs... salaries... opportunities. Tell me how many men you know who are making big money and how we assist our graduates in the field. This does not obligate you. So act at once. Just mail coupon.



Get This FREE Book

Mr. H. C. LEWIS, President
COYNE ELECTRICAL SCHOOL, Dept. 21-73
500 S. Paulina St., Chicago, Ill.

Dear Mr. Lewis:

Without obligation send me your big free catalog and all details of your Free Employment Service, Radio, Aviation Electricity and Automotive Courses, and how I can earn while learning.

Name

Address

City State

COYNE ELECTRICAL SCHOOL

H. C. LEWIS, Pres. Established 1899

500 S. Paulina Street • Dept. 21-73 • Chicago, Illinois



Now in Our New Home

This is our new first-class modern home where it is installed thousands of dollars worth of the newest and most modern E. I. Equip. Every convenience arranged to make you happy and contented during your training.

a Big Job Open for Every Radio Trained Man

5000

Service Men Needed



ACTUAL PHOTOGRAPH OF STUDENTS WORKING IN SERVICE DEPT. OF COYNE RADIO SHOPS

LEARN RADIO-TELEVISION TALKING PICTURES in 8 WEEKS

By Actual Work ~~~ In the Great Shops of Coyne

Don't spend your life slaving away in some dull, hopeless job! Don't be satisfied to work for a mere \$20 or \$30 a week. Let me show you how to make **REAL MONEY IN RADIO**—THE FASTEST GROWING, BIGGEST MONEY-MAKING GAME ON EARTH!

THOUSANDS OF JOBS OPEN

Paying \$40, \$70 to \$200 a Week

Jobs as Designer, Inspector and Tester, paying \$5,000 to \$10,000 a year—as Radio Salesman and in Service and Installation Work, at \$45 to \$100 a week—as Operator or Manager of a Broadcasting Station, at \$1,000 to \$5,000 a year—as Wireless Operator on a Ship or Airplane, and Talking Picture or Sound Expert—**THOUSANDS OF JOBS PAYING \$40, \$70 and on UP TO \$200 A WEEK.**

No Books - No Lessons All Practical Work

Coyne is NOT a Correspondence School. We don't attempt to teach you from books or lessons. We train you on the finest outlay of Radio, Television and Sound equipment in any school—on scores of modern Radio Receivers, huge Broadcasting equipment, the very latest Television apparatus, Talking Picture and Sound Reproduction equipment, Code Practice equipment, etc. You don't need advanced education or previous experience. We give

you—right here in the Coyne Shops—all the actual practice and experience you'll need. And because we cut out all useless theory, you graduate as a Practical Radio Expert in 8 weeks' time.

TELEVISION Is on the Way!

And now Television is on the way! Soon there'll be a demand for **THOUSANDS OF TELEVISION EXPERTS!** The man who learns Television NOW can make a **FORTUNE** in this great new field. Get in on the ground-floor of this amazing new Radio development! Come to COYNE and learn Television on the very latest, newest Television equipment.

Talking Pictures A Great Field

Talking Pictures and Public Address Systems offer thousands of golden opportunities to the Trained Radio Man. Here is a great new field of Radio work that has just started to grow! Prepare NOW for these mar-

velous opportunities! Learn Radio Sound work at Coyne on actual Talking Picture and Sound Reproduction equipment.

EARN AS YOU LEARN

Don't worry about a job! Coyne Training settles the job question for life. We often have more calls for Coyne graduates than we can supply. **YOU GET FREE EMPLOYMENT SERVICE FOR LIFE.** And don't let lack of money stop you. If you need part-time work while at school to help pay living expenses, we will gladly help you get it. Many of our students pay nearly all of the expenses that way.

COYNE IS 31 YEARS OLD

Coyne Training is tested, proven beyond all doubt. You can find out everything absolutely free. How you can get a good Radio job or how you can go into business for yourself and earn from \$5,000 to \$15,000 a year. It costs **NOTHING** to investigate! Just MAIL THE COUPON for YOUR COPY OF MY BIG FREE BOOK!

H. C. Lewis, Pres. **Radio Division** Founded 1899
COYNE ELECTRICAL SCHOOL
500 S. Paulina Street Dept. 21-4H Chicago, Illinois

H. C. LEWIS, President
Radio Division, Coyne Electrical School
500 S. Paulina St., Dept. 21-4H Chicago, Ill.
Send me your Big Free Radio Book and all details of your Special Introductory Offer. This does not obligate me in any way.

Name

Address

City.....State

MEN WANTED 20 to 35 years old

RADIO

First Lesson Free!

Broadcasting
Television
"Talkies"
Manufacturing
Service
Sales
Auto-Radio
Aviation

See how easy to learn

See how quickly you can get ready for well-paid positions in fastest growing, most prosperous industry.

Big demand right now from employers for broadcast operators, technicians, inspectors, service men, disc jockeys, installers, and "trouble-shooters".

\$40 to \$75 a week—and more!

With free radio lesson we'll send you our amazing combined training and employment agreement—good for help in securing a beginner's job when you're only half way through. Guarantees you help in finding a position, satisfactory in salary, after you finish, or money refunded.

A World of Opportunities to Choose From

Rockefeller is building a \$500,000,000.00 "radio center" in New York. 20,000 movie theaters have gone "talkie". Auto-radio is selling like wild-fire. Midget sets are selling at rate of 10,000 a day! Aviation, television, servicing, sales—all these mean highly paid jobs and plenty of them. All you need to get one is the kind of training we give you, backed by a real placement service.



RADIO TESTER GIVEN

\$10.00 set analyzer and trouble-shooting guide. Part of our training without extra charge.

Lesson FREE! Mail Coupon

for free radio lesson and book of thrilling facts about this wonder-industry and how to "break in."

American School
Dept. R-248, Drexel Ave. &
58th St., Chicago

THE AMERICAN SCHOOL
Dept. R-248, Drexel Ave. & 58th St., Chicago
Please send without cost or obligation, free radio lesson and job ticket and radio booklet.

Name Age
St. No.
City State

8 Inches Off Waistline

"Reduced from 42 to 34 inches in 25 days. That's what the Director Diet did for me" says E. D. Lutz.

The "Director" banishes fat by a gentle vibrating massage-like action and causes it to be absorbed and dissipated. No dieting or exercises. Proven. A natural easy way to lose weight.

Sample Trial. Try the "Director" without making a penny. Write now for trial offer, duration, endorsements and letter from users.
LONDON & WARNER
366 N. Michigan Ave., Dept. E-61 Chicago, Ill.



CALLS SUN HUGE ELECTRIC LIGHT

(Continued from page 20)

the changing of matter into energy, a process which Dr. Robert A. Millikan and others declare is continually taking place in the universe. The sun is known to be consuming itself, without leaving any ash or products of combustion, at the amazing rate of four million tons every second, and it is probable that this self-consumption has been going on for millions of years.

This matter disappears out of the universe, and, according to Dr. Gunn's hypothesis, becomes energy in the form of heat and light through the medium of electric current.

THIS theory and the amazing results deducible from it have stimulated American astronomers to renewed effort to solve solar mysteries. Last fall a ninety-three-and-one-half-second eclipse which they observed on Tinian Island, a tiny ring-shaped bit of coral in the South Pacific, gave them a chance to study the sun while it was in process of staging a titanic eruption.

During this phenomenon they saw shooting tongues of incandescent gas streaming a hundred thousand miles beyond its surface, the farthest ever recorded, and, at one point, a glowing red dome, like a gigantic strawberry thrust itself into space. No one knows the cause of this unusual solar activity or its possible significance.

For two months, the members of an expedition, under the leadership of Commander C. H. J. Keppler, U. S. N., prepared their instruments for the split-second observations on the day of the eclipse. "Tin Can Island," known as Niutou on maps, derives its nickname from the fact that it is so inaccessible food and supplies are delivered to the inhabitants by throwing them overboard in tin cans and allowing them to be washed ashore. From this island it was believed the best view of the eclipse could be obtained.

In spite of the difficulties of landing their equipment, the party erected, besides the regular instruments, a giant, twin-lensed, 2,500-pound "Einstein camera" mounted on pillars of concrete. This novel steel instrument was used to check up on the theory of Professor Albert Einstein, famous German physicist, that the sun bends rays of light reaching the earth from stars near its edge.

THE photographs obtained with the "Einstein camera," the spectroscopes, and the other photographic equipment are being closely examined. Most of the final results of the expedition will not be known before two or three years of study. The spectroscopic photographs, made by Prof. Samuel A. Mitchell, of the University of Virginia, are expected to occupy his attention for the next fifteen years!

In spite of centuries of observation, most of the sun's secrets are hid. Only recently we learned that it does not, as formerly supposed, burn year in and year out with the same intensity but fluctuates in temperature. Only within the last few years have we discovered the baffling, paradoxical fact that when the sun is hottest, the earth is coldest. Only within the last few decades has the mysterious importance of sun spots become apparent. Only within the last century has the spectroscope begun to tell us what the sun is made of.

It is to the spectroscope that astronomy owes most of its intimate knowledge about the sun. Just as the eye might glimpse alternately a pool of cream and a lump of butter swirling in a churn, it picks out first one then another element in the gyrating mass of white-hot gas that forms the solar atmosphere. By analyzing the light that

reaches the earth, it identifies substances in the sun.

By use of the spectroscope in 1868, a new important chemical element was discovered in the sun seventeen years before it was found on earth. Sir Norman Lockyer, the British astronomer, who was the discoverer, named it "helium." In 1895 the Scottish chemist, Sir William Ramsay, isolated helium in his laboratory. Today, this valuable gas lifts the *Los Angeles* and other dirigibles and has found an important place in industry.

Of all the mysteries of the sun, none are more bewildering than the sun spots or "atomic cyclones" which periodically sweep its molten surface. These dark blotches on the face of the sun appear and disappear with the regularity of clockwork. They reach their maximum once every eleven years, the last period of greatest sun spot activity being in 1926. At present we are nearing the period of minimum sun spots.

THE exact nature of these dark blotches are still obscure. Recent researches show that they are "cold places" on the sun. Spectroscopic study of the light emitted by them proves that their material is some 2,000 degrees F. cooler than that of the surrounding body of the sun. As an explanation for this, Dr. Donald H. Menzel, of the Lick Observatory in California, suggests that the cyclonic whirl of the atoms at the spot acts as a titanic centrifugal pump sucking the gases upward from the hot interior and cooling them by expansion.

However, these "solar refrigerators" are hotter than anything we know on earth, being in the neighborhood of 5,000 degrees F. The center of the sun, according to Prof. A. S. Eddington, famous English astronomer, must at times run a temperature of not less than 40,000,000 degrees. When sun spots are most frequent, the brightness and heat of the sun increases. But, curiously enough, it has been discovered that during this period when the sun is hottest, the average temperature of the earth drops about two degrees. It is believed that during these periods the haziness and cloudiness of the earth's atmosphere is increased, thus forming a screen that keeps out some of the incoming heat rays.

In other ways, these "tornadoes on the sun" affect us more closely. Science has shown a close relationship exists between the waxing and waning of these spots and our crops and weather, our electric communications, and the number of "health rays" that reach us from the sun.

AT THE University of Iowa, Dr. C. C. Wylie studied the records of Iowa corn crops for fifty-five years, during which the sun had gone through eleven cycles of sun spots. He found that as the sun spots increased, the yield of corn decreased. The lower temperatures at the time of maximum sun spots is believed to play a leading part in producing this result.

The director of the Observatory of Bourges, France, L'Abbe Moreux, has amassed evidence over a period of years that indicates a close relationship between sun spots and the amount of rainfall, and Dr. S. Hanzlik, of the Meteorological Institute at Prague, Czechoslovakia, has found that the atmospheric pressure in the monsoon regions of the Orient varies with the number of spots on the sun. In Afghanistan, East Turkestan, and India the air pressure and the sun spots increase together, he reports.

Another interesting discovery of how these spots affect us was made in California. Records of the mean level of the sea in San Francisco harbor (Continued on page 137)

CALLS OUR SUN HUGE ELECTRIC LIGHT

(Continued from page 136)

showed that its maximum height and greatest drop occur in regular cycles of about eleven years, corresponding to the increase and decrease of spots on the sun.

Lloyd's, famous marine insurance company of London, is reported to have taken into consideration the effect of sun spots on the sea in granting maritime insurance. It has been found that disasters at sea are eighteen percent more numerous during the two years when the sun spots are most frequent than during the two years when they are least in evidence.

Flaring, brilliant northern lights and invisible "magnetic storms" that disrupt telephone and telegraph communication are other mysterious phenomena of the maximum sun spot period.

IN 1926, a giant sun spot, into which half a dozen planets the size of the earth could have been dropped, made its appearance. This spot was the direct cause of the most intense magnetic disturbance in the United States experienced in many years. On January 26, 1926, for more than an hour near noon telegraphic communication over the United States was almost completely paralyzed and transatlantic wireless messages were sent with difficulty.

It is possible that the secret of these magnetic storms lies in the fact that the whirling vortexes of the sun spots bombard the earth with electrons. It has been noted that the greatest magnetic disturbances occur when the sun spot faces the earth directly, just as the most light reaches an object from a revolving beacon when the beacon is turned so it is aimed directly at it.

The discoveries of science about sun spots have just begun. For every puzzle solved hundreds still remain. And these are but a small part of the perplexing problems offered by the sun. But behind all the many riddles in connection with it there is the super-mystery of how the sun functions, what keeps it going, and the nature of its unending storehouse of power. Does Dr. Lunn's theory suggest a possible solution of this hitherto baffling mystery?

MILLION-YEAR-OLD COAL CONTAINS LIVE GERMS

CAN seeds or germs live for centuries sealed up in mineral veins? Dr. C. B. Lipman, of the University of California, reports the discovery of live bacteria in lumps of coal millions of years old, adding to the long list of discoveries of "mummy wheat" and other simple forms of life discovered in mineral samples. Whether any of them existed underground when the minerals were formed, however, is doubted by scientists, who point out that it is almost impossible to keep live germs from minerals in which "mummified" ones have been found.


Germs are in and on everything we eat, breathe, and touch. Thus, in spite of all precautions, it is possible that live germs might find their way into laboratories on mineral samples, and might then be mistaken for organisms millions of years old.

Biologists say there is probably but one way in which suspended animation can be proved. That is by continued breeding of germs believed to be "mummified," and comparing them at all stages of development with other germs taken from minerals before they were disinfected. If the results show a form of life radically different from any that is known to exist at present, it can be stated positively that a case of suspended animation has been found.

If You Want a Job



or a
Hobby



that Pays
Well



Where You
can be Your
Own Boss



and Keep Your
Own Hours



learn
Illustrating

SEND for our free catalog "A Road To Bigger Things." Learn how former Federal School graduates now earn larger incomes. See the work and comments of the fifty famous artists who have contributed to the Federal Course in Illustrating.

Opportunities in drawing have never been better. Art is a vital part of today's business. Successful magazine and newspaper artists are making fine incomes. Advertisers and publishers are paying large sums annually to those who are trained in Modern Art. Think of the money paid to artists for the illustrations in this magazine alone. The Federal Course includes illustrating, cartooning, lettering, window card illustrating, etc.

TEST YOUR TALENT FREE

Why be content with a small income at routine work if art training may offer larger possibilities? Many people have a talent for art and do not realize it. That is why we enclose a test chart with our catalog. It finds out your ability. Fill out the coupon now. It may be the beginning of an art career which will enable you to earn a good income.

FEDERAL SCHOOL OF ILLUSTRATING
2141 Federal Schools Building * * Minneapolis, Minnesota



Federal School of Illustrating,
2141 Federal Schools Building,
Minneapolis, Minnesota.

Please send me free book "A Road To Bigger Things" and Standard Art Test.

Name _____

Age _____ Occupation _____

Address _____

RADIO PROGRAMS NOW RECORDED AT HOME

(Continued from page 83)

of the pick-up head you are using. Hooking the pick-up to your set is simple if you have an old set fitted with loudspeaker binding posts to which the loudspeaker cord tips are attached. Just connect the pick-up cord tips to the same posts. This will allow the loudspeaker to operate at the same time so you will know when to start and stop the recording.

If you have a modern set fitted with two power tubes in push-pull and a dynamic speaker, take out the two power tubes and wind the bare end of a small piece of wire several turns around the plate prong close to the base. The plate prong enters the right-hand one of the two smaller holes when you are looking down on the socket with the smaller holes farthest from you.

CONNECT these two wires to the pick-up cord tips and be sure that they do not short on the base or on any other metal part when you push the tubes back in place.

To record speech or music some kind of a microphone is necessary. Microphones sell at prices ranging from a few dollars to hundreds of dollars depending on the quality. The best and most expensive grades are, of course, used in the better class broadcasting and recording studios.

If you have no microphone you can use a pair of headphones. Keep the same set-up as for radio program recording and hook one of the headphone cord tips to the grid of the detector tube. The other should be connected to the metal frame or to ground. With battery sets, the prong is the one that enters the left-hand small hole as you look down on the socket with the two small holes away from you. In electric sets, the detector grid prong is the one that is spaced from the other four of the 227 tube.

Better results will be obtained if only one headphone is used, so short-circuit the other phone or disconnect it. A loudspeaker unit of the kind sold for attachment to the tone arm of the phonograph will give somewhat better results and a magnetic cone speaker will be better still. Because of its large area the cone speaker may cause feed-back howl, in which case it should be placed in another room with the door shut or else the loudspeaker on the set should be muffled by covering it with a blanket.

You will have a lot of fun experimenting with home recording, but don't expect too much in the way of fine tone quality. It cannot be had with such simple apparatus.

OLD CIRCUIT RETURNS

(Continued from page 84)

to understand why these two changes did the trick. The single control makes it impossible to tune the oscillator to the other interference or beat frequency. The single dial control always assures the correct frequency difference in the same direction.

The hashing together of stations that happen to operate on the proper frequency above and below the oscillator frequency has been eliminated by tuning ahead of the detector. An interfering station obviously would have to be exactly twice the intermediate frequency away from the desired station, or 250,000 cycles, and a station so far removed in frequency couldn't get by the sharply tuned detector circuit.

The selectivity of the superheterodyne will be discussed next month in POPULAR SCIENCE MONTHLY in an article dealing with the selectivity of modern radio receiving circuits.

Thousands

of BIG PAY Jobs

"The Radio industry is growing so rapidly that it can easily absorb thousands of men with training each year." - Martin F. Flanagan, Executive Secretary, Radio Manufacturers Association.



Martin F. Flanagan




J. E. Smith, President

"I am doubling and tripling the number of men by fitting them to big pay jobs created every year by Radio's continued amazing growth." - J. E. Smith, President, National Radio Institute.

Open to Radio

I Will Train You at Home to Be a Certified Radio-Trician



Send For This Big FREE Book



Producing stations sell thousands of jobs, paying from \$1000 to \$2000 a year.



Operating on ships gives world-wide travel, paying up to \$1000 a month and from \$40 to \$75 a month salary.



Many N. E. I. men make \$50 to \$100 a week selling and repairing Radio sets in their neighborhoods.

Mail the coupon below for my big, free book, "Rich Rewards in Radio." It gives full information on the many opportunities to earn \$40, \$60, \$75 and \$100 a week in this fast-growing industry. And it tells how you can learn quickly at home in your spare time, to fill a big-pay Radio job. My amazingly simple and inexpensive 30-60 home-study training is the correct lack of high-school education or Radio experience are no drawbacks.

Many N. E. I. Men Make \$50 to \$100 a Week

Many fellows who had no Radio experience before taking my training are now earning \$50 to \$100 a week. Your chances are even better because my course has been improved and the opportunities in Radio are growing greater every year. I train you for all branches of Radio—manufacturing, operating in broadcasting stations and on ships, selling and servicing sets for dealers or in business for yourself—and many other lines, including Television, Aircraft Radio and Talking Pictures. Moreover, N. E. I. training is the only training that enables you to be a **Certified RADIO-TRICIAN**.

Many Earn \$200 to \$1000 Extra While Learning

You stay right at home, hold your present job and learn in your spare time. I teach you to begin making money shortly after you enroll. My new 30-60 practical method makes this possible. I give you eight big laboratory outfits that teach you to build and service practically every type of receiving set made. G. W. Page, 1907 21st Ave., S. Nashville, Tenn., writes: "I picked up \$935 in my spare time while studying."

Television and Talking Pictures Included

My training not only gives you a thorough knowledge of Radio—all you need to get and hold a good job, but also, up to graduation, you may take any one of my new advanced courses, **WIRELESS TELEVISION**, **TALKING PICTURES**, **AVIATION**, **AIRCRAFT RADIO**, **REPAIRING**, **COMMUNICATIONS**, and **SHIP RADIO**. Six more Special Features: Public Address Systems and Advanced Radio Servicing and Maintenance. You won't be a "odd job" man when you finish my training. You'll know how to handle a job in any one of Radio's 23 different branches of opportunity.

Your Money Back If Not Satisfied

I back up my training with a signed agreement to refund every penny of your money if, after examination, you are not satisfied with the Lessons and Instruction Service I give you. My big free book tells all about my course, the many opportunities in Radio and how my Employment Department helps you get into Radio after you graduate. Mail the coupon for my book NOW! J. E. Smith, President, National Radio Institute, Dept. 10-P3, Washington, D. C.

Mail Today for FREE Book

J. E. SMITH, President
National Radio Institute, Dept. 10-P3
Washington, D. C.

Dear Mr. Smith: Send me your Free Book "Rich Rewards in Radio." I understand the plan and am under no obligation and that no salesman will call.

NAME

ADDRESS

CITY STATE



\$200 a Week

"Dear Mr. Smith, For the month of November I made \$75. In December over \$45. In January \$45. My earnings are falling under \$75 a week. Letter from graduate R. E. Williams, 126 W. 8th St., Norfolk, Va."

\$400 in Spare Time

"Dear Mr. Smith, I did not know a single thing about Radio before I enrolled, but I have made \$400 in my spare time." - MRS. L. L. Lutz, Jr., Tucson, Pa."



NEW DOGS FOR THE FROZEN NORTH

(Continued from page 140)

ever dog men of the North get together.

The drivers took the greatest care of their animals, and at every roadhouse or relay camp where they stopped for food and sleep it was "dog first," no driver thinking of himself until his team was fed, rubbed, and bedded. Little moccasins of Canton flannel were carried to be used on hard trails, and veils of black and green mosquito netting were placed over the dogs' eyes if the glare of sun on snow was too dazzling.

On short distances some of the dogs are remarkably fast, traveling at the rate of fifteen or sixteen miles an hour. Irish, one of the Adams and Darling team, an Irish setter with some husky blood, could go a mile in three minutes. Spot, a cross-breed pointer and husky, after leading a team for thirty miles, covered four miles in thirteen minutes and twenty-five seconds.

THE record for strength, endurance and speed combined was made by Seppala, a Siberian, in the famous serum dash of 1925, when it was necessary to send antitoxin serum from Nenana to Nome, a distance of 663 miles. By relays of teams, led by the wonder dogs Togo and Balto, this distance was covered during blizzards and at sixty degrees below zero in five and a half days, or an average of about 125 miles a day. A statue of Balto has been erected in Central Park, New York City, while the body of Togo, who was pensioned and died of old age at Mrs. Ricker's kennels, is in the Peabody Museum of Yale University.

The lead dog is selected regardless of age or sex. The leader usually is left to pick the track through unbroken snow, and will take a circuitous route, dodging anything in the way of mounds or hummocks that possibly might upset the sled. On a broken path, it will follow the previous tracks without a desire to deviate.

The studies told of the marvelous intelligence of certain leaders are a most beyond belief. A leader has certain privileges such as getting into the sled when the driver is not at the handlebar and reposing in comfort on the furs while the rest of the dogs lie in the snow. Occasionally bitter jealousy is felt by the others toward their leader and the utmost precaution is necessary to guard him from their attacks.

SOME leaders, however, through great strength and superior intelligence become more or less exempt from this pesting and their leadership is freely tolerated. Among these, Dubby, a magnificent specimen of the McKenzie River husky, brought down by "Scotty" Allan from the Kiondake region, was one of the most famous. Dubby lived to be twelve years old, but was poisoned in his ninth year, still in perfect condition and able to enjoy the rewards of his service.

He had to his credit a record of over 10,000 miles in harness and the stories told of his capacity are legion. Often he was driven loose, running ahead of the team instead of being hooked up with them, and he was so efficient as a manager that the loss of his pulling power was of small moment compared to his ability to find and keep the trail, and his capacity for doing many other clever and helpful things.

In the records of America's frozen North, epic stories have been written by the sturdy four-footed trail blazers. Without them, it would have taken fifty years longer to open up the great white empire of Alaska. Now, with science assisting sport to perpetuate the old breeds and originate new ones, they are writing new sagas in those sections of the United States where winter still is winter.

A BIGGER JOB—and YOU'RE THE MAN

Are you hunting a bigger job, or does the bigger job hunt you? Why waste years leading through routine work, when you can acquire in your spare time a comparatively few months' experience and specialized knowledge which bring promotion and salary increase? Thousands of men have increased their incomes by home-study business train-

ing under the LaSalle Problem Method. Let us show you how you can do just as well or better. The company will bring you complete information about our experience training in the business field you choose, together with details of our career and payment plan. Make your start toward that bigger job today.

Fund Yester! Through LaSalle!

LASALLE EXTENSION UNIVERSITY, Dept. 303-B, CHICAGO

17. If you are a member of the Chamber of Commerce, please indicate the advancement in the business field checked. Send also copy of Ten Year to the Editor of the all Wisconsin editions of

- | | | |
|---|--|---|
| <ul style="list-style-type: none"> ○ Business Management ○ Modern Salesmanship ○ Higher Arithmetic ○ Traffic Management ○ Railway Station Management ○ Law Dictes & L. B. ○ Commercial Law | <ul style="list-style-type: none"> ○ Industrial Management ○ Modern Foremanship ○ Personnel Management ○ Modern Business Correspondence ○ Export Bookkeeping ○ C. F. A. Counting ○ Railway Accounting | <ul style="list-style-type: none"> ○ Business English ○ Commercial Spanish ○ Effective Speaking ○ Bookkeeping and Finance ○ Telegraphy ○ Credit and Collection Correspondence |
|---|--|---|

XEROX

8. First & Number _____ Date _____ Page _____

SONG WRITERS

Advance Royalty Payments.
New Talking-Picture Song arrangements, etc., fully explained in our Free instruction book. *Words of Words or Music* let you say what you wish for free arrangement and advice. Post-approval license only. We write, compose, arrange music and secure Copyrights. Our modern method guarantees approval. Write Today—Hawman Associates, 1574 W. Broadway, New York, N. Y.



LAW Free Book

[illegible]

BLACKSTONE INSTITUTE, 36 Midway Ave.
192 N. 48th

ENGINEERING
ELECTRICAL • MECHANICAL • STRUCTURAL
AND ARCHITECTURE

1. **Answer the questions.** Write the answers in the spaces provided.
 2. **Read the text and answer the questions.** Write the answers in the spaces provided.
 3. **Write a short paragraph about the importance of the Internet in our lives.**
 4. **Write a short paragraph about the importance of the Internet in our lives.**
 5. **Write a short paragraph about the importance of the Internet in our lives.**
 6. **Write a short paragraph about the importance of the Internet in our lives.**
 7. **Write a short paragraph about the importance of the Internet in our lives.**
 8. **Write a short paragraph about the importance of the Internet in our lives.**
 9. **Write a short paragraph about the importance of the Internet in our lives.**
 10. **Write a short paragraph about the importance of the Internet in our lives.**

FINLAY ENGINEERING COLLEGE
1001-2nd Avenue S.W.
Edmonton, Alberta T6A 5K6

Wrestling Book FREE

[illegible]**20 WEEKLY Easy Meals**[illegible]

TRI-STATE COLLEGE

COLLEGE
 B.S. degree in 2 years
 in Architecture, Civil,
 Electrical, Mechanical,
 Mining, Metallurgical &
 Engineering. Students who
 hold B.S. can make up
 work. Tuition low. Catalog
 1958 College Street
 Aurora, Indiana

A definite program for getting ahead financially will be found on page four of this issue.

Aviation

Adventure
Big Pay..Thrills..Popularity

[illegible]**NEW LOW PRICES**[illegible]

At the right is a view of my drafting and specification office where a large staff of experienced assistants is in my constant employ.



All drawings and specifications are prepared in my offices.

My Offices
Just Across Street
From
U. S. Pat.
Office



Protect Your Ideas

Take the First Step Today—Action Counts

If you have a useful, practical, novel idea for any new article or for an improvement on an article, you should communicate with a competent Registered Patent Attorney AT ONCE. Every year thousands of applications for patents are filed in the U. S. Patent Office. Frequently there are numerous applications made for the same or substantially the same idea taken through the invention may have in different sections of the country and be entirely unknown to one another. In such a case the burden of proof rests upon the last application filed. Delays of even a few days in having the application accepted mean the loss of a patent. So lose no time. Get in touch with me at once by mailing the coupon below.

Prompt, Careful, Efficient Service

This large, experienced organization devotes its entire time and attention to patent and trademark cases. Our offices are directly across the street from the U. S. Patent Office. We understand the technical side of patent law. We know the rules and requirements of the Patent Office. We can proceed in the quickest and best ways in preparing an application for a patent covering your idea. Our success has been built on a strength in careful, efficient, satisfactory service to inventors and trade-mark owners located in every state in the Union.

Strict Secrecy Preserved—Write Me in Confidence

All communications, sketches, drawings, etc. are held in strictest confidence in a fire-proof, burglar-proof files which are accessible only to authorized members of my staff. Feel free to write me fully and frankly. It is probable that I can help you. At least I can. But FIRST clip the coupon and get my free book. Do THAT right now.

No Charge for Information On How to Proceed

The booklet shown here contains valuable information relating to patent procedure that every inventor should have. And with it I will send you my "Record of Invention" form on which you can sketch your idea and establish its date before a witness. Such evidence may later prove valuable to you. Simply mail the coupon and I will send you the booklet and the "Record of Invention" form, together with detailed information on how to proceed and the charges involved. Do this NOW. No need to lose a minute's time. The coupon will bring you complete information entirely without charge or obligation.


Clarence A. O'Brien

Registered Patent Attorney

Member of Bar of Supreme Court of the United States;
Court of Appeals, District of Columbia; Supreme Court,
District of Columbia, United States Court of Claims.

PRACTICE CONFINED EXCLUSIVELY TO
PATENTS, TRADEMARKS AND COPYRIGHTS

Inventors Write for these Free Books



Mail this Coupon Now

CLARENCE A. O'BRIEN

Registered Patent Attorney

881 Security Savings and Commercial
Bank Bldg., Washington, D. C.

—OR—

Suite 1106, Dept. B2, Woolworth Bldg.,
New York City

Please send me your free book, "How to Obtain a Patent" and your "Record of Invention" form without any cost or obligation on my part.

Name _____

Address _____

(Important: Write or Print Plainly and Address Only Received Text)

DESIGN YOUR HOUSE TO FIT ITS SITE

(Continued from page 74)

lights in this room, the entire interior illumination depending on movable floor and table lamps.

The kitchen, or "laboratory," is most compact, and was so placed that a pleasant view of the garden is obtained. The legs of the stove were removed and a cupboard for large cooking utensils placed beneath. The pot closet was built next to the stove, in which the equipment is hung against the wall instead of being piled on top of each other as in many kitchens.

Special attention was given to such small but comfort-making details as toe space beneath the counters, placing of the first shelf in the cupboard above the counter so low that the second shelf is reached easily, and a special shelf for flower bowl and clock. The sink is of acid-proof material set in small mosaic tile. Small shelves are provided in the cooling closet for spice boxes and similar containers, which are usually lost on a large shelf.

FOUNDATIONS, as well as all retaining walls, were reinforced with steel, the former with two 1/2-inch bars placed both at top and bottom. To prevent inroads by subterranean termites, all woodwork in the basement is kept at least six inches above grade, while numerous screen vents insure good ventilation throughout all the area beneath the house. Ground and woodwork under the building were treated with a patented preparation as a further preventive of insect attacks. The house is insured by a reliable anti-termite company, and is thoroughly inspected twice a year.

The exterior of this house is stucco, applied over heavy sixteen-gauge, one-inch mesh wire netting, outset from the sheathing by metal cleats. The roof is of split shakes, laid to weather a natural warm brown.

After the house was built it was decided to establish an office in the rear of the garden. The site selected is some five feet higher than the garden level. It was walled off and on it, in the manner shown by the accompanying sketch of the grounds, was erected a two-story, three-room office, of design that harmonizes with the house and with the general contour of the lot. Down stairs, this structure contains two rooms—an outer office for my secretary, where callers may wait, and an inner private office.

One of the accompanying photographs shows the interior of the private office and suggests its treatment. The woodwork is painted white, with touches of gold leaf on some of the cornice molds and around the fireplace. There is a wood dado on two sides of the room. Above this Madagascar grass cloth of cream color has been applied on wood backing. This facilitates the tacking of drawings on the wall, and also gives suitable background for some old William Blair maps, dated 1638, which are framed with glass on two sides so that the inscriptions on the backs of the prints may be read.

ON ONE side of this room a battery of casement windows, above low cupboards, overlooks a small, private *patio*. This *patio* is on two levels, due to inequalities of the ground, and contains a fountain, three or four trees, and about 100 potted plants. For furniture, there is a copy of an old bench at Mission San Juan Capistrano, a table, and a few stools.

In the second story of this building there is a large drafting room with accommodations for eight men at one time. Such a private office attached to a city home site is often convenient for a physician, attorney, architect or other professional man.

PATENTS TRADE-MARKS AND COPYRIGHTS



OUR OFFER: FOR PROTECTION OF YOUR INVENTION

YOUR FIRST STEP—The inventor should write for our blank form - **RECORD OF INVENTION**. A sketch and description should be made on this blank signed, witnessed, then returned to us. We also give our opinion as to whether the invention comes within the Patent Office definition of a patentable invention. This "Record of Invention" will serve as proof of conception. **There is no charge or obligation for this service.**

Write for Our Illustrated Guide Book HOW TO OBTAIN A PATENT

Contains full instructions regarding U. S. Patents and Trade Marks. Our Methods, Terms and 100 Mechanical Movements illustrated and described.

All Communications and Data Strictly Secret and Confidential

DELAYS ARE DANGEROUS IN PATENT MATTERS—IMPORTANT! To Avoid Delay!

YOU SHOULD HAVE YOUR CASE MADE SPECIAL IN OUR OFFICE to have correspondence secure, protection and early filing date in the Patent Office. To secure special preparation of your case send \$25.00 on account with model or sketch and description of invention. If the invention is not patentable we will return the cash cost of search.

Our Lawyers Practice in all U. S. Courts and Defend Clients in Suits

PAYMENT OF FEES IN INSTALLMENTS

We permit our clients to pay for their applications in three installments as the preparation of the application progresses in our office.

Highest References—Prompt Service—Reasonable Terms

-----WRITE TODAY-----

FREE COUPON

VICTOR J. EVANS & CO.

Registered Patent Attorneys Established 1888

MAIN OFFICES: 760 Ninth St., Washington, D. C.

BRANCH OFFICES: 1007 Westworth Bldg., New York City; 1640-42 Conway Bldg., Chicago, Ill.; 514 Empire Bldg., Pittsburgh, Pa.; 828 Fidelity Bldg., Philadelphia, Pa.; 1010 Hobart Bldg., San Francisco, Calif.

Continued. Please send me (FREE OF CHARGE) your books as described above.

Name _____

Address _____

Inventions Promoted

Patented or Unpatented. In business over 30 years. Send drawing and description or model, or write for information. Complete facilities. References.

ADAM FISHER MFG. CO.

183-D Ebright

St. Louis, Mo.

UNPATENTED IDEAS CAN BE SOLD

Write W. T. Evans
114 Bar Anz Bldg. Washington, D. C.

PATENTS

Trade Marks Copyrights Patents Inventions. Write for information.
ALBERT E. DIETERICH
Successor to Fred C. Dieterich & Co.
Formerly Director Patent Office
REGISTERED PATENT LAWYER AND SOLICITOR
681 A Dury Building
30 Years' Experience Washington, D. C.

PATENTS

TO THE MAN WITH AN IDEA

The inventor with a good idea should first have his idea patented. If you have an invention send us a sketch and description and we will give you our **OPINION** whether your invention comes within the Patent Office definition of a patentable invention. This "Record of Invention" will serve as proof of conception. **There is no charge or obligation for this service.**

IRVING L. McCATHAM, Patent Lawyer
Formerly with and successor to WICKES & BURE
700 International Bldg. Washington, D. C.
615 Park Bldg. New York City

TRADE-MARKS

PATENTS TRADE-MARKS

DO NOT LOSE YOUR RIGHTS TO PATENT PROTECTION

Before disclosing your invention to anyone send for blank form "EVIDENCE OF CONCEPTION" to be signed and witnessed.

LANCASTER ALLWINE & RUMEL
Registered Patent Attorneys
174 Dury Bldg. Washington, D. C.
Originators of Form "Evidence of Conception"

PATENTS SECURED TRADE-MARKS REGISTERED

PROTECTION—Write for Inventors and Trade-Mark Cases in connection with **PROPER PROTECTION**. You can be sure of reasonable terms. If you have an invention send us a sketch and description and we will give you our **OPINION** whether your invention comes within the Patent Office definition of a patentable invention. This "Record of Invention" will serve as proof of conception. **There is no charge or obligation for this service.**

WE ASSIST OUR CLIENTS TO SELL THEIR PATENTS

TERMS REASONABLE

BEST REFERENCES

-----WRITE TODAY-----
RANDOLPH & COMPANY, Patent Attorneys

Dept. 130 Washington, D. C.

Name _____

Address _____

...Here's the RADIO TRAINING

you've been
waiting for



Why envy the man who knows radio... who is able to assemble and repair fine sets... who knows the "why" and the "how," the theory and the practice of radio?

You, too, can learn about radio servicing, operating, radio telephony and telegraphy, broadcasting... radio in all its branches.

Learn at Home, in Your Spare Time

In order to make it easy for every man to study radio, RCA Institutes, Inc. is now training men in every branch of radio... So that men can get this training at home in their spare time, or at any of the resident schools throughout the country.

The RCA Institutes complete Home Laboratory Training Course gives you thorough and reliable radio training. You progress easily, step by step, and you receive with your training the complete RCA Institutes' Laboratory equipment—a modern outlay of apparatus furnished to every student, enabling you to solve radio problems. This is the logical way for you to acquire in your spare time the commercial knowledge and ability required by the radio industry.

Home Training Course by America's Oldest and Foremost Radio Training Organisation

This home training course and laboratory equipment are backed by more than twenty years' experience.

Send for this FREE BOOK Today!

Learn the facts about the radio industry... all about the opportunities in radio... about RCA Institutes and the staff of RCA Institutes instructors who train you. This book should be read by every ambitious man who wishes to train for the future. Forty pages of pictures and text. Describes in detail the training that has placed thousands of men in responsible positions in radio.



RCA INSTITUTES, Inc.

RCA INSTITUTES, Inc.
Dept. 972
15 Varick St., New York, N. Y.

Use Coupon: Please send me your FREE 48-page book which tells about the many opportunities in Radio and about our famous laboratory method of radio instruction at home.

Name _____

Address _____

Occupation _____

UNCLE SAM EXPOSES FAKE CURES

(Continued from page 3.)

reporting the case immediately to the Chief Post Office Inspector, Washington, D. C.

Some companies have mulcted the public out of more than a million and a half dollars before their owners were brought to justice, largely because those on the "sucker list" were ashamed to admit that they had been "taken in." One of the quickest captures made stopped a promoter from selling a fake curative when the total sum he had received amounted to only two dollars and fifty cents.

SOME of the devices are relatively inexpensive—as, for example, a "Vacuum Fat Remover," which consisted of a rubber cup to be pressed down over the fatty tissue to "suck off the superfluous weight by means of a vacuum." It sold for about a dollar. But that was a dollar too much, as the outfit was worthless. However, the higher the price, the better the fake device seems to sell.

One man was so anxious to get an apparatus guaranteed to restore his youth in ten days that he couldn't wait to send the price, \$1,000, by mail. He telegraphed it. And he has been writing almost daily letters to Post Office officials ever since trying to get his money back.

It should be noted that the Post Office Department can make no guarantee to get money back that has been sent to crooked promoters. All it can do in most cases is to stop the criminal from fleecing others.

One of the devices that sold at a fancy price was an "Infra-Red Ray Hair Restoring Skullcap." It was a small black bonnet with a tiny electric heating coil, covered with asbestos, in the top. When the electrical connection was plugged in, the coil warmed the top of the wearer's head. According to the advertisements, the cap gave off penetrating infra-red rays that entered the scalp, stimulated the roots of the hair, and made thick and beautiful locks spring out of heads formerly as bare as a billiard ball.

In fact, these rays were said to be so penetrating that they reached down to the wearer's jaws and would stop a toothache as well as grow hair! Tests at the laboratory showed that a hot water bottle would give off just as many "infra-red rays" as the magic bonnet.

NOT all of the work of this fraud-busting laboratory concerns mechanical devices. Making a careful chemical analysis of powders, pills, and liquids, for which wonder-working powers are claimed, is another important phase of the work.

A few weeks ago, a test was made of some powder that was being advertised as able to cure a whole catalogue of human ills. Three pinches of the powder were to be placed in the shoes of the user every morning. The result would be that fevers, inflammations, infections, and microbes would be "drawn off through the feet" during the day. A chemical analysis of the compound showed that it contained nothing but common baking soda and sulphur.

Another chemical analysis revealed that a "sure cure for pyorrhea" was simply sheep dip, such as is used on farms to kill ticks on the animals, done up in a glossy package.

Not many years ago, a promoter actually sold eye drops that were purveyed to cure howlegs and flat feet. The afflicted person was to put a drop of the liquid in his eye twice a day and watch results—if he could notice any.

The eyes are a favorite point of attack for the crook who is mulcting the public with his fake curatives. When the chemists of the

Collaborative Investigations laboratory examined, not long ago, one compound that was guaranteed to cure cross-eyes, they found that its formula read like a cake recipe. It was concocted of strained honey, egg yolks, distilled water, and unsalted butter. The purchaser was supposed to put one "or more" drops of this mess in his eyes three times a day.

There are three different branches to the attack made by the Government on the sellers of such worthless nostrums. The Post Office Department prevents the convicted crook from using the mails, the Food and Drug Bureau has control over the labels placed on bottles and boxes, and the Federal Trade Commission sees that the advertising contains no fraudulent claims. But even so the criminals sometimes rob thousands before they are caught.

ONE of their best bats is the testimonial given by a "benefited user." How unreliable such testimonials are is revealed by the fact that the Post Office investigators discovered in one case that seventy-five percent of the people who testified that a tuberculosis cure had restored them to health had died of tuberculosis. And the promoter, who later died of the same disease, kept on using the testimonials for ten years after the people who gave them were dead!

One of the most recent of these "guaranteed cures" for tuberculosis, by means of which a heartless promoter fleeced thousands of unfortunate invalids, came in the shape of little cones of incense. They were to be burned over an alcohol lamp in the bedroom before retiring for the night. The windows were to be left closed so the "curative" fumes would be breathed during sleep. A chemical examination of the cones showed they were made of charcoal, a little sulphur, and a slight amount of eucalyptus oil to give the smoke a pleasing smell.

However, sick people are not the only ones fleeced by fraudulent claims. A year or so ago, thousands of city dwellers bought a miniature churn that would turn one pound of butter into two. The laboratory test showed that all it did was to produce an adulterated and comparatively worthless product in place of the good butter.

While city people were buying the fake churn, farmers were purchasing a miraculous "sex determiner" which would tell them whether an egg would hatch into a hen or a rooster. This device consisted of a red peg, either of wood or iron, which was suspended from a metal bar by a silk thread. When an egg was placed underneath, the peg was supposed to swing to one side or the other. If it swung to the right, that meant a rooster; if it swung to the left, it indicated a pullet.

WHEN the device was held over things that had no sex at all, such as rubber dolls and celluloid fish, in the laboratory, it acted just the same as it did when held over an egg. The result depended largely on the steadiness of the nerves of the holder and the air currents in the room, and not on any magical powers of the red peg.

But what probably caps the climax in the way of impossible claims was one investigated by the laboratory on the complaint of poultry growers who had bought a "red-hot pepper compound, guaranteed to rid chickens of lice." The promoter declared that if the powder was mixed with the chicken feed it would cause the hens to "sweat off all the lice and mites." That was one time when the laboratory didn't have to make any chemical analysis, because the workers knew what some of the poultrymen didn't know—that chickens don't have sweat glands!

HEAT YOUR CAR BUT DON'T BURN IT

(Continued from page 86)

and circulates the air through the cast-iron radiator by a small electric fan. This one," he went on as he opened the second package, "is the same idea, using hot water. It's got a fan, too. The only difference is that the exhaust gas heater gets hot a lot quicker. I find that doctors and others who have to make a lot of short trips with long waits like the exhaust type pretty well because they get heat quick. Salesmen that make long trips are much more likely to pick the hot water job."

"But I don't see how you can get enough heat from the hot water system," Green objected. "The motor runs so cold there isn't any real heat in the water."

"If it does," Gus retorted, "that's your fault for not covering up part of the radiator. Of course the kind of anti freeze you use makes a difference. You can't run the motor at summer temperature if you use alcohol, so the exhaust gas heater would have the edge on the water job if you keep the motor cold to save alcohol. If you use glycerin or green ethylene glycol, you keep the motor as near the boiling point as you please."

"How about ventilation with those two?" Green asked.

"Leave one of the windows open," Gus explained. "The fan keeps the air circulating so the draft isn't so bad. This one," he said opening the third package, "takes care of the ventilation too. This funnel-shaped opening is fastened right back of the engine fan and the fan forces a stream of fresh cold air through the heater and then through the opening in the fixture which fastens over a hole cut in the dash."

"Of course the cold air is heated so it's good and warm by the time it comes out the hole in the dash. This particular job uses the hot water for heat."

"Seems to me," Green broke in, "I've seen the same thing worked out as a cover for the exhaust manifold. Why isn't that simpler?"

"It is if you don't mind the hot engine smell," he explained. "Then, too, any leak in an exhaust gasket will fill the car with gas."

"Why don't somebody invent an electric heater that you could hook up to the battery like the rest of the electrical equipment of the car?" Green suggested.

"Would the heat from a dinky little electric toaster be enough to warm your car?" Gus countered. "It takes two hundred and fifty watts of current to run a toaster and your generator produces only eighty watts, and most of that has to be used to charge the storage battery. Also, what would be the use of burning more gasoline to drive a bigger generator just so you could operate an electric heater when you have a lot of heat going to waste already?"

"I'm wrong again," Green laughed. "Well, I guess you'd better put in a hot water heater. After what just happened, my wife would feel safer."

THERE was a rapid snap in the air next morning as Green and his wife set out. They passed the Model Garage just as Gus was opening up for the day.

"I wanted to thank you, Mr. Wilson," chirped up Mrs. Green as they stopped, "for selling my husband that ducky little fixture with the door that lets the heat in from the engine compartment. That's much better than that awful thing he installed."

Green slyly winked, Gus smilingly acknowledged her thanks, and the car drove on.



The "Ideal" Lawnmower Sharpener

A wonderfully simple all metal machine that has been making the mower sharp in minutes. It's the only sharpener that makes a few sharp edges and proved to sharpen the blade in a few seconds. It's the only sharpener that makes a few sharp edges and proved to sharpen the blade in a few seconds. It's the only sharpener that makes a few sharp edges and proved to sharpen the blade in a few seconds.

Hundreds of dull mowers in your locality

Are you one of them? If so, you need this sharpener. It's the only sharpener that makes a few sharp edges and proved to sharpen the blade in a few seconds. It's the only sharpener that makes a few sharp edges and proved to sharpen the blade in a few seconds.

C. S. Coburn, North Little Rock, Ark. This sharpener is the only one that makes a few sharp edges and proved to sharpen the blade in a few seconds. It's the only sharpener that makes a few sharp edges and proved to sharpen the blade in a few seconds.

FREE book tells how others do it!

THIS MAN IS MAKING \$4 to \$6 AN HOUR

SHARPENING LAWNMOWERS IN SPARE TIME WITH THE "IDEAL" LAWNMOWER SHARPENER

Man, Why Don't You Do That? You've got the chance the same chance as W. T. Moore, Twin Falls, Idaho, who made \$100 net profit in 90 days. He made more than Walter Weaver, Moline, Ill., who made \$100 in 4 months. The same chance as hundreds of others who have trapped rich rewards with this efficient lawnmower sharpener.

Use Your Spare Time If you work at a trade you do it all day long and earn \$4 to \$6 an hour evenings and weekends. E. W. Allen, Moline, Ill., says: "I have a spare time job. I bought an 'Ideal' Sharpener in which I have a good over 3,000 lawnmowers. In the last few weeks I worked at my trade machine in 10 hours a day. I also ground 97 mowers which netted me \$114.30 clear gain."

You Make Money Right Away Clean it up. It's no water. We have an exclusive right to sell in your locality. That's close to \$200 in 10 days. That's close to \$200 in 10 days. That's close to \$200 in 10 days.

Our Free Book Tells You How Others have made thousands of dollars with this 'Ideal' sharpener. Send for the book today. It's free.

SEND THIS AND MAIL TODAY

THE FATE-ROOT-HEATH CO.

632-944 Bell St., Plymouth, Ohio, U.S.A.

Send me the book but not the book. I can make my spare time worth \$4 to \$6 per hour.

Name _____

Address _____

City _____ State _____

Electrical Engineering

Training for men of all ages. This is a course in Theoretical and Practical Electrical Engineering. It covers all the latest developments in the industry. It is a course in Theoretical and Practical Electrical Engineering. It covers all the latest developments in the industry.

BLISS ELECTRICAL SCHOOL 182 Takoma Ave., Washington, D. C.

Don't Envy The Plumber BE ONE!

The world demands modern Plumbing and Skilled Trained Mechanics to do the job. We train you quick. Learn in 8 to 12 weeks. No money down. We'll pay you while you learn. Investigate today. Write for our free booklet.

Write— UNIVERSAL PLUMBING SCHOOL 2321 T Street Ave. Norman City, Mo.



RAILWAY POSTAL CLERKS

MANY OTHER U. S. GOVERNMENT POSITIONS \$1700 to \$3400 a Year

MEN - BOYS - 18 to 45 Steady Work Rapid Advancement Long Vacation With Pay Mail Coupon Today Act at Once

FRANKLIN INSTITUTE

Dept. T28, Rochester, N. Y.

Send for our valuable free booklet. It tells you how to get the job done. It tells you how to get the job done. It tells you how to get the job done.

Railway Postal Clerk \$1800-\$2700 Post Office Clerk \$1700-\$2300 City Mail Carrier \$1700-\$2100 Rural Mail Carrier \$1200-\$1800 Customs Inspector \$2100 up

This One



KZ39-SNL-KDX5

If it Climbs *this HILL* it will climb anything


GOOD, ordinary gasoline is in the tank, and yet the engine is "knocking" as if it were on the steepest hill in the world. It is.

Those rollers under the rear wheels are harder to climb than Pikes Peak. The dynamometer shows their resistance is equal to a 20% grade.

But switch the gas feed from ordinary gasoline to Ethyl Gasoline. The knocking stops, the wheels begin to roll faster, and the driver shifts back to high.

What is the difference? A gallon of good gasoline was used for fuel at first. Another gallon of identical gasoline *plus* a teaspoonful of Ethyl fluid was used for the second test.


These few drops of Ethyl fluid



The mounds under the wheels are braked to tax pulling power more than the steepest hill in the world.



This isn't a dynamo in the left of the picture; it is a dynamometer which measures the pull on the rollers under the wheels of the car.



The active ingredient in Ethyl fluid is lead.

prevent the uneven explosions of gasoline that cause power-waste, "knock" and over-heating. They control combustion so Ethyl Gasoline delivers its power to the pistons with smoothly increasing pressure.

This test does *more* than prove that Ethyl Gasoline prevents "knocking" under strain. It proves that the greater power Ethyl Gasoline gives

on any kind of road is not only greater engine power, but greater rear-wheel power.

Try Ethyl Gasoline in your car. See how it increases power, gives you quick get-away and sends you zooming up hills in high. You will find pumps everywhere marked with the Ethyl emblem. Ethyl Gasoline Corporation, Chrysler Building, New York City.



ETHYL GASOLINE



John Kunst using radius gages on current work in his shop.

Showing the application to the work of the **LUFKIN** new style radius gage.



Where Inventors' Dreams Come True

WHIO would think of leaving a place like Budapest to find romance? John Kunst left his old world foundry and came to America 26 years ago. Now he owns a shop where the singing of belts and lathes is music to inventors who watch their dreams turn into perfect working models in the skilled hands of the craftsmen employed by the John Kunst Co., at 43 Murray St., New York City.

"We have filled over 150,000 orders" says John Kunst, "orders for everything from simple patterns to complete working models of big and intricate machines."

These comparatively tiny working models must run and demonstrate the application of new discoveries or principles. They must be made with hair line precision. "In this fine work we use Lufkin Radius Gages—they are the handiest and safest" said Mr. Kunst. "You don't need to have a whole bunch of gages in your hand interfering with the work." Lufkin Radius Gages are made so that each gage is a separate unit, for convenient and accurate application to the work. Each gage has five forms, 3 radius and 2 fillet, and the straight sides are at 90° for checking location of radius.

Here is a scientific tool that is **NEW** in design and far more practical in actual work than the old type gages. Lufkin precision tools are the result of painstaking research to put every modern convenience into the hands of the skilled craftsmen of today.

*For accuracy, improved design and construction,
finer finish and balance—demand*

LUFKIN PRECISION TOOLS

THE LUFKIN RULE CO., SAGINAW, MICH.

106 LAFAYETTE STREET, NEW YORK, and WINDSOR, ONTARIO

Send for this FREE CATALOG

112 pages containing valuable tables of decimal equivalents of number and letter size drills, U. S. Standards for Wire Gages, double depth of threads, weight of iron and steel, metric system, etc. Also illustrations and descriptions of the complete line of Lufkin Precision Tools, including Micrometers, Calipers, Dividers, Combination Squares, Steel Rules, Depth, Thickness, Surface, Screw Pitch and Radius Gages, and practically every other fine tool the shop requires.

THE LUFKIN RULE CO., Dept. "W",
Saginaw, Mich., U. S. A.
Please send me Lufkin Catalog No. 6

Name _____

Street _____

City _____

State _____

No. 77 A
16 Gages
1/32 to 1/8



View No. 1—Work being checked on a piece of glass.

View No. 2—Gage used for determining radius of inside corners.



View No. 3—Gage used for determining radius of outside corners.



View No. 4—Shows gage used on concave surface of 1/2 circle or less.



View No. 5—Checks 1/2 of a circumference.



"A DISTINCT CONTRIBUTION"



Says

**AUGUST
HECKSCHER**

Noted Philanthropist

Chairman of the Heckscher Foundation for Children; President Child Welfare Committee of America

Director:
Empire Trust Company
Crucible Steel Company

"The most laudable service that any industry can render is the attempt to benefit its patrons. That is the cardinal principle of philanthropy. And so, interested as I always am in modern developments, I consider that your use of the Ultra Violet Ray in your Toasting of LUCKY STRIKE is a distinct contribution of which the public will whole-heartedly approve."

August Heckscher

Everyone knows that sunshine mellows — that's why TOASTING includes the use of the Ultra Violet Ray. LUCKY STRIKE — the finest cigarette you ever smoked, made of the finest tobaccos — the Cream of the Crop — THEN — "IT'S TOASTED." Everyone knows that heat purifies and so TOASTING removes harmful irritants that cause throat irritation and coughing. No wonder 20,679 physicians have stated LUCKIES to be less irritating!

"It's toasted"

Your Throat Protection — against irritation — against cough



Consistent with its policy of laying the facts before the public, The American Tobacco Company has invited Mr. August Heckscher to review the reports of the distinguished men who have witnessed LUCKY STRIKE'S famous Toasting Process. The statement of Mr. Heckscher appears on this page.

© 1938, The American Tobacco Co., Inc.